



IMfinity[®] Motors for explosive atmospheres (ATEX)



3-phase induction motors
Variable speed and fixed speed
IE3 Premium efficiency
Frame size 80 to 355
Power rating 0.75 to 400 kW

ATEX GAS – Zones 1 & 2
ATEX DUST – Zones 21 & 22

LEROY-SOMER™

Nidec
All for dreams

ATEX Gas, Zones 1 and 2 - ATEX Dust, Zones 21 and 22

Contents

GENERAL INFORMATION

| | |
|---|----|
| Introduction..... | 5 |
| Quality commitment..... | 6 |
| Certification..... | 7 |
| Definition of atmospheres and zones..... | 8 |
| Temperature classes..... | 9 |
| Classification of common gases..... | 10 |
| Dust explosive atmospheres..... | 11 |
| Classification of dust groups..... | 11 |
| Dust ignition temperatures..... | 11 |
| Types of protection for equipment..... | 12 |
| Equipment certification..... | 13 |
| Equipment marking..... | 13 |
| Benefits of the IECEx system..... | 14 |
| Directive and standards relating to motor efficiency..... | 15 |
| Standards and approvals..... | 17 |

ENVIRONMENT

| | |
|--|----|
| IP (Ingress Protection) definitions..... | 19 |
| Conditions of use..... | 20 |
| VIK execution..... | 20 |
| Impregnation and enhanced protection..... | 21 |
| Heating..... | 22 |
| External finish..... | 23 |
| Interference suppression and protection of people..... | 24 |

CONSTRUCTION

| | |
|---|----|
| Mounting arrangements and operating position..... | 25 |
| Mains connection..... | 26 |
| Radial loads..... | 27 |
| Cooling..... | 28 |
| Motor connections..... | 31 |
| Bearings and bearing life..... | 32 |
| Lubrication and maintenance of bearings..... | 33 |

OPERATION

| | |
|--|----|
| Duty cycle definitions..... | 34 |
| Supply voltage..... | 37 |
| Insulation class - Temperature rise and thermal reserve..... | 39 |
| Starting times and starting current..... | 40 |
| Power - Torque - Efficiency - Power Factor (Cos φ)..... | 41 |
| Noise level..... | 44 |
| Weighted noise level [dB(A)]..... | 45 |
| Vibrations..... | 46 |
| Optimised performance..... | 48 |
| Starting methods for induction motors..... | 49 |
| Braking..... | 50 |
| Operation with speed drive..... | 52 |

ATEX GAS - ZONE 1

| | |
|------------------------------|----|
| FLSD series - Cast iron..... | 56 |
|------------------------------|----|

GENERAL INFORMATION

| | |
|---------------------------------|----|
| Designation..... | 56 |
| Identification and marking..... | 57 |
| Description..... | 59 |

ELECTRICAL CHARACTERISTICS

| | |
|-------------------------------|----|
| IE3 powered by the mains..... | 61 |
| IE3 powered by the drive..... | 63 |

MECHANICAL CHARACTERISTICS

| | |
|---|----|
| Shaft ends (extensions)..... | 66 |
| Foot mounted IM 1001 (IM B3)..... | 67 |
| Foot and flange mounted IM 2001 (IM B35)..... | 71 |
| Flange mounted IM 3001 (IM B5), IM 3011 (IM V1)..... | 75 |
| Foot and face mounted IM 2101 (IM B34)..... | 76 |
| Face mounted IM 3601 (IM B14)..... | 77 |
| Terminal box..... | 78 |
| Bearings and lubrication..... | 79 |
| Axial loads..... | 81 |
| Radial loads..... | 84 |
| Terminal box connection..... | 90 |

OPTIONAL FEATURES

| | |
|-------|----|
| | 93 |
|-------|----|

HANDLING

| | |
|------------------------------------|----|
| Position of the lifting rings..... | 95 |
|------------------------------------|----|

ATEX Gas, Zones 1 and 2 - ATEX Dust, Zones 21 and 22 Contents

ATEX GAS - ZONE 2

| | |
|--------------------------------------|----|
| FLSN series - Cast iron | 96 |
|--------------------------------------|----|

GENERAL INFORMATION

| | |
|---------------------------------|----|
| Designation..... | 96 |
| Identification and marking..... | 97 |
| Description..... | 99 |

ELECTRICAL CHARACTERISTICS

| | |
|--------------------------------------|-----|
| FLSN - IE3 powered by the mains..... | 100 |
| FLSN - IE3 powered by the drive..... | 102 |

MECHANICAL CHARACTERISTICS

| | |
|---|-----|
| Shaft ends (extensions)..... | 103 |
| Foot mounted IM 1001 (IM B3)..... | 104 |
| Foot and face mounted IM 2001 (IM B35)..... | 105 |
| Face mounted IM 3001 (IM B5), IM 3011 (IM V1)..... | 106 |
| Foot and face mounted IM 2101 (IM B34)..... | 107 |
| Flange mounted IM 3601 (IM B14)..... | 108 |
| Bearings and lubrication..... | 109 |
| Axial loads..... | 111 |
| Radial loads..... | 114 |
| Terminal box connection..... | 119 |

| | |
|---------------------------------|-----|
| OPTIONAL EQUIPMENT | 120 |
|---------------------------------|-----|

HANDLING

| | |
|------------------------------------|-----|
| Position of the lifting rings..... | 124 |
|------------------------------------|-----|

ATEX GAS - ZONE 2

| | |
|-------------------------------------|-----|
| LSN series - Aluminium | 125 |
|-------------------------------------|-----|

GENERAL INFORMATION

| | |
|---------------------------------|-----|
| Designation..... | 125 |
| Identification and marking..... | 126 |
| Description..... | 128 |

ELECTRICAL CHARACTERISTICS

| | |
|-------------------------------------|-----|
| LSN - IE3 powered by the mains..... | 129 |
| LSN - IE3 powered by the drive..... | 131 |

MECHANICAL CHARACTERISTICS

| | |
|---|-----|
| Shaft ends (extensions)..... | 132 |
| Foot mounted IM 1001 (IM B3)..... | 133 |
| Foot and face mounted IM 2001 (IM B35)..... | 134 |
| Face mounted IM 3001 (IM B5), IM 3011 (IM V1)..... | 134 |
| Foot and face mounted IM 2101 (IM B34)..... | 136 |
| Flange mounted IM 3601 (IM B14)..... | 137 |
| Bearings and lubrication..... | 138 |
| Axial loads..... | 139 |
| Radial loads..... | 144 |
| Terminal box connection..... | 151 |

| | |
|---------------------------------|-----|
| OPTIONAL EQUIPMENT | 152 |
|---------------------------------|-----|

HANDLING

| | |
|------------------------------------|-----|
| Position of the lifting rings..... | 156 |
|------------------------------------|-----|

ATEX Gas, Zones 1 and 2 - ATEX Dust, Zones 21 and 22

Contents

ATEX DUST- ZONES 21 & 22

FLSPX & FLSES series - Cast iron 157

GENERAL INFORMATION

Designation..... 157

Identification and marking 159

Description..... 161

ELECTRICAL CHARACTERISTICS

FLSPX / FLSES - IE3 powered by the mains..... 162

FLSPX / FLSES - IE3 powered by the drive 166

MECHANICAL CHARACTERISTICS

Shaft ends (extensions) 168

Foot mounted IM 1001 (IM B3)..... 169

Foot and face mounted IM 2001
(IM B35)..... 170

Face mounted IM 3001 (IM B5),
IM 3011 (IM V1)..... 171

Foot and face mounted IM 2101
(IM B34) 173

Flange mounted IM 3601 (IM B14)..... 174

Bearings and lubrication 175

Axial loads 178

Radial loads 182

OPTIONAL EQUIPMENT 187

HANDLING

Position of the lifting rings 191

ATEX DUST- ZONES 21 & 22

LSPX & LSES series - Aluminium 192

GENERAL INFORMATION

Designation..... 192

Identification and marking 194

Description..... 196

ELECTRICAL CHARACTERISTICS

LSPX / LSES - IE3 powered by the mains 197

LSPX / LSES - IE3 powered by the drive 199

MECHANICAL CHARACTERISTICS

Shaft ends (extensions) 200

Foot mounted IM 1001 (IM B3)..... 201

Foot and face mounted IM 2001
(IM B35)..... 202

Face mounted IM 3001 (IM B5),
IM 3011 (IM V1)..... 203

Foot and face mounted IM 2101
(IM B34) 204

Flange mounted IM 3601 (IM B14)..... 205

Bearings and lubrication 206

Axial loads 209

Radial loads 212

Mains connection 219

OPTIONAL EQUIPMENT 220

HANDLING

Position of the lifting rings 224

APPENDIX 225

Configurator..... 225

Product availability 225

IMfinity® ATEX 3-phase induction motors - IE3 efficiency class

ATEX Gas, Zones 1 and 2 - ATEX Dust, Zones 21 and 22

General information

Introduction

Nidec Leroy-Somer describes in this catalogue the Premium efficiency induction motors of its new IMfinity® generation for use in explosive gas and dust atmospheres (ATEX).

These motors have been designed to incorporate the latest European standards, and can satisfy most industrial requirements.

They stand out as benchmark products in the Nidec Leroy-Somer range for ATEX applications.

Other motors, ranging in power from 0.045 to 2200 kW and with particular designs, are included in the Nidec Leroy-Somer motor programme.

| | |
|--|--|
| <p>ATEX GAS motors - Zone 1</p>  | <p>FLSD series</p> <p>  II 2 G Ex $\begin{matrix} \text{db} \\ \text{or} \\ \text{db eb} \end{matrix}$ II $\begin{matrix} \text{B} \\ \text{or} \\ \text{C} \end{matrix}$ $\begin{matrix} \text{T4} \\ \text{or} \\ \text{T5} \\ \text{or} \\ \text{T6} \end{matrix}$ Gb </p> <p>Premium Efficiency</p> <p>IE3 powered by the mains IE3 powered by the drive</p> |
| <p>ATEX GAS motors - Zone 2</p>  | <p>FLSN / LSN series</p> <p>  II 3 G Ex ec II C T3 Gc </p> <p>Premium Efficiency</p> <p>IE3 cast iron or aluminium on mains IE3 cast iron or aluminium on drive</p> |
| <p>ATEX DUST motors - Zone 21</p>  | <p>FLSPX / LSPX series</p> <p>  II 2 D Ex tb III C T125°C Db </p> <p>Premium Efficiency</p> <p>IE3 cast iron or aluminium on mains IE3 cast iron or aluminium on drive</p> |
| <p>ATEX DUST motors - Zone 22</p>  | <p>FLSES / LSES series</p> <p>  II 3 D Ex tc III B T125°C Dc </p> <p>Premium Efficiency</p> <p>IE3 cast iron or aluminium on mains IE3 cast iron or aluminium on drive</p> |

The Nidec Leroy-Somer quality management system is based on:

- controlling processes from as early as the initial sales offering up until delivery to the customer, including design, manufacturing launch and production
 - a total quality policy based on the continuous improvement of operational processes, involving all departments in the company in order to guarantee customer satisfaction in terms of delivery times, conformity and cost
 - indicators used to monitor process performance
 - corrective actions and advancements with tools such as FMECA, QFD, MAVP, MSP/MSQ and Hoshin type improvement workshops on flows, process re-engineering, plus Lean Manufacturing and Lean Office
 - annual surveys, opinion polls and regular visits to customers in order to ascertain and detect their expectations
- personnel trained in and taking part in analyses and actions for continuous improvement of our processes
 - the motors in this catalogue which have been studied to measure the impact of their life cycle on the environment

certified by the following bodies: LCIE, DNV, INERIS, EFECTIS, UL, BSRIA, TUV, EAC, which check the technical performance of the products against the various standards or recommendations.

Nidec Leroy-Somer has entrusted the certification of its expertise to various international organisations.

Certification is granted by independent professional auditors, and recognises the high standards of the **company's quality assurance procedures**. All activities resulting in the final version of the products have therefore received official certification **ISO 9001: 2015 from the DNV**. Similarly, our environmental approach has enabled us to obtain ISO 14001: 2015 certification.

Products for particular applications or those designed to operate in specific environments are also approved or



ISO 9001 : 2015




General information Certification

The ATEX motors presented in this catalogue comply with the national and/or international standards that govern the construction of this type of equipment.

CE type-examination certificates are drawn up by notified bodies in accordance with the European ATEX Directive No. 2014/34/EU.

The certificates issued by the organisations mentioned below are obligatorily recognised in all EU Member States.

They allow CE marking or the distinctive EU mark to be affixed to the certified equipment.



ATMOSPHERES WITH EXPLOSIVE RISK AND EUROPEAN DIRECTIVES

An explosive risk zone is anywhere in which an explosive or potentially explosive atmosphere may be present, and where the explosive character may be permanent, intermittent or accidental. An explosive atmosphere is one in which a mixture of air and flammable substances (in the form of combustible gases, vapours, mists or dust) exists permanently. A potentially explosive atmosphere is one which is liable to become explosive as a result of particular or accidental local conditions.

In areas with an explosive risk, electrical installations must be limited to what is essential for operational requirements.

Two European Directives govern the equipment and protection of workers in these areas.

Directive 2014/34/EU

This Directive harmonises the essential safety requirements that must be met by equipment and protective systems intended for use in (potentially) explosive atmospheres, in compliance with the free movement of goods within the European Union.

Directive 1999/92/EC

This Directive concerns the protection of workers by stipulating the minimum requirements for the health and safety of workers liable to be exposed to the risk of explosive atmospheres.


In particular, it imposes the following obligations on a site operator:

- to define the zones in which explosive atmospheres may occur and to characterise them;
- to choose electrical equipment suited to the previously defined zones;
- to provide the appropriate conditions for the installation, operation and maintenance of this equipment.

DEFINITION OF EXPLOSION-RISK ZONES

The IEC 60079-10-1 and -2 standards define the danger zones according to the risk of explosive atmospheres occurring there, as illustrated in the following diagram:

| | | |
|--|--|--|
| <p>Zone 0 (gas) and 20 (dust)</p> <p>A location in which an explosive atmosphere is present continuously or for long periods. Only electrical control and measuring equipment may be installed there, and therefore no electric motors.</p> | <p>Zone 1 (gas) and 21 (dust)</p> <p>A location in which an explosive atmosphere is present occasionally or intermittently.</p> | <p>Zone 2 (gas) and 22 (dust)</p> <p>A location in which an explosive atmosphere is accidentally present and only under abnormal operating circumstances.</p> |
|--|--|--|



Determining the suitability of equipment (its type of protection) for a zone and its application is the responsibility of the operator.

Electrical equipment installed in locations where there is a risk of explosion is classified, according to standard 60079-0, into three groups of equipment:

- **Group I:** Firedamp mines - This group concerns only firedamp (methane) in mines.
- **Group II:** Explosive gas atmospheres - The gases present are classified into three subdivisions A, B or C depending on the severity of the risks.
- **Group III:** Explosive dust atmospheres - Different types of dust are classified into three subdivisions A, B or C depending on their properties.

| Directive 2014/34/UE equipment classification | | | | | IEC60079-0 equipment classification Equipment Protection Level | | | | | Zones |
|--|------------|------------------------------|------------------|------------------|--|--------------------|------------------------------|------------------|------------------|----------|
| Use | ATEX Group | Category | Protection level | If ATEX presence | Use | Equipment group | EPL | Protection level | If ATEX presence | 60079-10 |
| Firedamp mines | I | M1 All firedamp content | Very high | Power on | Firedamp mines | I | Ma All firedamp content | Very high | Power on | |
| | | M2 Within a certain value | High | Power off | | | Mb Within a certain value | High | Power off | |
| Surface Industries | II | 1G | Very high | Power on | Gas explosive atmospheres | II A B C | Ga | Very high | Power on | 0 |
| | | 2G | High | | | | Gb | High | | 1 |
| | | 3G | Normal | | | | Gc | Reinforced | | 2 |
| | | 1D | Very high | | | | Da | Very high | | 20 IP6X |
| | | 2D | High | | | | Db | High | | 21 IP6X |
| | | 3D | Normal | | | | Dc | Reinforced | | 22 IP5X |
| | | | | | Dust explosive atmospheres | III A B C | | | | |

- I : Methane
- IIA : Propane
- IIIB : Ethylene
- IIIC : Hydrogen, Acetylene
- IIIA : combustible airborne particles
- IIIB : non-conductive dust (electrical resistivity >10³Ω.m)
- IIIC : conductive dust

CLASSIFICATION OF GAS EQUIPMENT GROUPS

Gases are classified into three subdivisions according to the risks following an explosion. These risks increase from subdivision A to subdivision C. **Equipment certified for use in the presence of a type C gas can therefore be used in the presence of type A and B gases.**

TEMPERATURE CLASSES

The temperature class is based on the maximum temperature rise of the equipment and the ambient operating temperature. The maximum surface temperature of an electrical appliance must always be lower than the ignition temperature of the gas mixture in which it will be used.

In order to select the different appliances according to their surface temperature, **six temperature classes** have been created:

| Temperature class | T1 | T2 | T3 | T4 | T5 | T6 |
|---|----------|----------|----------|----------|----------|---------|
| Ignition temperature | > 450 °C | > 300 °C | > 200 °C | > 135 °C | > 100 °C | > 85 °C |
| Max. permissible surface temperature of the equipment | 450 °C | 300 °C | 200 °C | 135 °C | 100 °C | 85 °C |

IMfinity® ATEX 3-phase induction motors - IE3 efficiency class
ATEX Gas, Zones 1 and 2 - ATEX Dust, Zones 21 and 22
General information
Classification of common gases

| Gas | Ignition temperature °C | Temperature class of the equipment. | Explosion group |
|--|-------------------------|-------------------------------------|-----------------|
| Acetaldehyde | 140 | T4 | IIA |
| Acetic acid | 464 | T1 | IIA |
| Acetic anhydride | 316 | T2 | IIA |
| Acetone | 465 | T1 | IIA |
| Acetylene | 305 | T2 | IIC |
| Ammonia | 630 | T1 | IIA |
| Amyl acetate | 380 | T2 | IIA |
| Benzene (pure) | 498 | T1 | IIA |
| Butane n | 365 | T2 | IIA |
| Butanol n | 343 | T2 | IIA |
| Carbon disulfide | 95 | T6 | IIC |
| Carbon monoxide | 605 | T1 | IIB |
| Cyclohexanone | 420 | T2 | IIA |
| Dichloroethylene | 460 | T1 | IIA |
| Dichloromethane | 625 | T1 | IIA |
| Diesel DIN 51601/04.78 | 220 to 300 | T3 | IIA |
| Diethyl ether | 180 | T4 | IIB |
| Ethane | 472 | T2 - T1 | IIA |
| Ethyl acetate | 427 | T2 | IIA |
| Ethyl alcohol | 425 | T2 | IIA - IIB |
| Ethyl chloride | 510 | T1 | IIA |
| Ethylene | 425 | T2 | IIB |
| Ethylene glycol | 235 | T3 | IIB |
| Ethylene oxide | 440 | T2 | IIB |
| Fuel oil EL DIN 51 603 part 1/12.81 | 220 to 300 | T3 | IIA |
| Fuel oil L DIN 51 603 part 2/10.76 | 220 to 300 | T3 | IIA |
| Fuel oils M and S DIN 51 603 part 2/10.76 | 220 to 300 | T3 | IIA |
| Hexane n | 225 | T3 | IIA |
| Hydrogen | 560 | T1 | IIC |
| Hydrogen sulphide | 270 | T3 | IIB |
| Kerosene (or fuel-oil No. 1) | 220 to 300 | T3 | IIA |
| Mains gas | 560 | T1 | IIB |
| Methane | 537 | T1 | IIA |
| Methanol | 385 | T2 | IIA |
| Naphthalene | 520 | T1 | IIA |
| Oleic acid | 360 | T2 | IIB |
| Phenol | 595 | T1 | IIA |
| Propane | 450 | T2 | IIA |
| Propylene alcohol | 405 | T2 | IIB |
| Special spirits with initial boiling point > 135 °C | 220 to 300 | T3 | IIA |
| Spirits for motors with initial boiling point < 135 °C | 220 to 300 | T3 | IIA |
| Tetralin (tetrahydronaphthalene) | 425 | T2 | IIB |
| Toluene | 482 | T1 | IIA |

Values for guidance only

IMfinity® ATEX 3-phase induction motors - IE3 efficiency class

ATEX Gas, Zones 1 and 2 - ATEX Dust, Zones 21 and 22

General information

Dust explosive atmospheres

CLASSIFICATION OF DUST EQUIPMENT GROUPS

Dusts are classified into three groups according to their characteristics:

| Group | Dust type | Size | Resistivity |
|-------|--------------------------------|----------|-----------------------|
| IIIA | Combustible airborne particles | > 500 µm | - |
| IIIB | Non-conductive dusts | ≤ 500 µm | > 10 ³ Ω.m |
| IIIC | Conductive dusts | ≤ 500 µm | ≤ 10 ³ Ω.m |

DUST IGNITION TEMPERATURES

Combustible dusts are dangerous because they can generate an explosive atmosphere when dispersed in the air (dust cloud). Furthermore, a layer of combustible dust can ignite and act as a source of ignition in an explosive atmosphere.

| Material (granulometry) | Aluminium (10 µm) | Wheat (37 µm) | Wood (60 µm) | Sugar (30 µm) | Paint pigment (52 µm) | Maize (28 µm) | Polyethylene (72 µm) |
|--|----------------------|------------------|-----------------|------------------|-----------------------------|------------------|-------------------------|
| Minimum ignition temperature of a dust cloud | 560 °C | 510 °C | 500 °C | 490 °C | 470 °C | 440 °C | 440 °C |
| Minimum ignition temperature of a 5 mm layer | 430 °C | 300 °C | 310 °C | 480 °C | 450 °C | 280 °C | (fusion) |

The maximum surface temperature of the equipment must be at all times:

- < layer ignition T° -75°C

- < 2/3 cloud ignition T°

All ATEX dust or ATEX gas-dust motors offered in this catalogue are qualified and marked for temperature class T 125°C.

TYPE OF PROTECTION FOR ELECTRICAL EQUIPMENT

European standards define, depending on the type of protection chosen, the design rules specific to electrical equipment for use in explosive atmospheres.

These types of protection are each covered by a specific standard supplementing standard IEC 60079-0 (general rules) and are symbolised by a lower case letter. The following distinctions apply:

- db: flameproof enclosures
- eb: increased safety
- ec: non-sparking
- p: pressurized enclosure
- q: powder filling
- o: oil immersion
- i: intrinsic safety
- m: encapsulation
- t: protection by enclosure

TYPE OF PROTECTION FOR MOTORS IN EXPLOSIVE GAS ATMOSPHERES

Electric motors protected by "db" flameproof enclosure (EN 60079-1)

The requirements they must satisfy include the following:

- withstanding an internal explosion of the air/gas mixture without damage or permanent deformation of the enclosure,
- ensuring that ignition inside the enclosure cannot be transmitted to the surrounding explosive atmosphere,
- presenting a surface temperature lower than the external ignition temperature of the gas.

These three conditions require:

- highly robust construction of the enclosure,
- minimum seal lengths and smaller gaps so that the explosion of the air/gas mixture inside the enclosure is not transmitted to the surrounding explosive atmosphere (bearing / casing sockets, shaft passages, etc.),
- limited temperature rise, taking into account unfavourable operating conditions (voltage limits), and guaranteeing, depending on the ambient temperature, a surface temperature lower than the temperature class imposed by the nature of the gas present.


Electric motors protected by "eb" increased safety enclosure (EN 60079-7)

The "eb" protection type concerns equipment which, in normal operation, does not produce arcs, sparks or hot spots; this excludes in particular all rotating machines with commutator.

This requires, among other things, in terms of their design:

- special precautions in order to avoid any arcing or sparks: minimum air gaps and creepage distances between live elements and earthings, absence of mechanical friction, insulation, minimum distances in ventilation systems, specific fan materials, etc.
- temperature at any point on the motor (including the stator and rotor) below the ignition temperature of the gas. This temperature must take into account a locked rotor time as defined in EN 60079-7.

In the event of rotor failure and jamming, a control device must be able to disconnect the motor from the power supply within a time $t < t_E$.



- $T^\circ\text{C}$ = Internal temperature at the hottest spot
- Marked temp = Temperature limit (slightly below the rated temperature class)
- Temp. at P_N = Temperature at nominal rating
- Ambient temperature = Highest permissible ambient temperature
- t_s = time in seconds
- t_E = locked rotor time
- (A) = temperature rise in normal service
- (B) = temperature rise in locked rotor test

Electric motors with "ec" non-sparking protection (EN 60079-7)

The "ec" protection type concerns equipment that does not generate sparks, arcs or hot spots and operates in an exceptionally explosive atmosphere.

(Only usable in zone 2).

This requires in terms of equipment design:

- precautions to avoid any arcing or sparking: minimum air gaps and creepage distances between live elements and earthings.
- temperature at any point on the motor (including the stator and rotor) below the ignition temperature of the gas. However, any jamming of the rotor falls outside this requirement.

TYPE OF PROTECTION BY TB OR TC ENCLOSURE FOR MOTORS IN EXPLOSIVE DUST ATMOSPHERES

Type of protection "t" by enclosure prevents the risk of explosion by:

- the non-penetration of dust into the motor thanks to its "IP" Protection Index which must be at least:
 - IP 65 for motors installed in zone 21 and/or exposed to conductive dusts (Ex tb).
 - IP 55 for motors installed in zone 22 (Ex tc) (non-conductive dusts).
- the maximum surface temperature of the motor never exceeding under any circumstances the temperature class indicated on the nameplate.
- no production of sparks or arcs outside the engine.

For equipment installed in the European Union, the 2014/34/EU ATEX Directive governs the means of demonstrating compliance with the various standards for equipment intended for use in explosive zones. As a minimum, electrical equipment suitable for use in zones 0 or 20 and 1 or 21 must always be certified by a notified body with the necessary approvals.

Outside Europe, some countries accept the local use of components approved in accordance with the rules in force in the EU.

In order to facilitate the circulation of electrical equipment used in explosive atmospheres and to simplify the acquisition of any local certifications, the International Electrotechnical Commission has for some years been proposing **voluntary IECEx certification**, which is increasingly recognised in many countries outside Europe as well as by major international clients. **Some of the motor ranges in this catalogue have IECEx certification.**

In North America and particularly in the USA, the regulation to be taken into consideration is the NEC (National Electrical Code) for the installation and certification rules. Unfortunately, there is no mutual recognition between EN/IEC and NEC standards. For installations outside North America, it is often the case that American firms based in Europe, Asia or Africa invite tenders with reference to the NEC.

| | NEC 500 | Types of product | GENELEC |
|-------------|------------------|---------------------------|----------------------------------|
| | Class I | Gas | Group I (mines) and II (surface) |
| | Class II | Dust | Group III |
| | Class III | Airborne fibres and dusts | |
| | Division (DIV) 1 | Gas and dusts | Zone 0, 1 or 21 |
| | Division (DIV) 2 | | Zone 2 or 22 |
| Gas | Group A | Acetylene | IIC |
| | Group B | Hydrogen | IIC |
| | Group C | Ethylene | IIB |
| | Group D | Propane | IIA |
| Dust | Group E | Conductive dusts | IIIC |
| | Group F | Coal dust | IIIB |
| | Group D | Non-conductive dusts | IIIB |

Equipment marking

Two types of markings must appear on electrical equipment operating in explosive gas and/or dust atmospheres:

- Markings as per ATEX Directive 2014/34/EU, with the logo , indication of the group and category of the equipment, and the symbol G, D or GD.
- IEC markings (standard 60079-0) with indication of the type of protection, equipment group, temperature class and EPL (Equipment Protection Level).

| Motor type | | | | |
|---|---|---|---|--|
| FLSD | (F)LSN | (F)LSPX | (F)LS/(F)LSES zone 22 | |
|  |  |  |  | ATEX marking |
| II | II | II | II | Equipment group |
| 2 ; 3 | 3 | 2 ; 3 | 3 | Equipment category |
| G , GD | G , GD | D | D | Gas or (Gas and Dust) (Gas, GasDust, Dust) |
| Ex | Ex | Ex | Ex | Explosion protection |
| db, db eb | ec | tb | tc | Type of protection |
| II A, B, C | II A, B, C | III A, B, C | III A, B | Equipment group |
| T4, T5 T6 | T3 | T125°C | T125°C | Temperature class |
| Gb | Gc | Db | Dc | Equipment Protection Level |

| | |
|--|-------------------------|
| ATEX marking | Protection type marking |
|  II 2 G | Ex db IIB T4 Gb |
|  II 2 D | Ex tb IIIC T125°C Db |

THE IECEx SYSTEM

This is an international certification system for verifying compliance with IEC standards concerning the safety of equipment, service facilities and personnel in explosive atmospheres.

Created in September 1999, this system aims to facilitate the circulation of electrical equipment and services used in explosive atmospheres, while maintaining the necessary level of safety (source: www.iecex.com).

It is a system that provides the internationally recognised means of proving that products and services comply with IEC standards.

The voluntary and international aspects of the IECEx system differentiate it from certification under ATEX, for example, which is compulsory and only applies in the European Union.

The IECEx system includes global certification programmes for both service facilities and equipment.

IECEx certification comprises:

- product testing,
- assessment of control, quality and testing procedures,
- audits of industrial plants, routine monitoring and inspections.

Also, IECEx has produced a comprehensive set of operational documents and procedures to develop a single internationally standardised approach to Ex certification.

The approach includes:

- A standardised method for obtaining IECEx certification.
- A unique set of operational procedures, and test procedures that are always applied in the same way.
- Single-source technical and operational assistance to maintain operations.
- Test procedures that are assessed and controlled on a centralised basis.

IECEx CERTIFICATION

A manufacturer who needs to have equipment certified under the IECEx system must apply to an IECEx competent body in any Member State. To date, there are 30 IECEx Member States.

The body conducts or coordinates the certification activities.

An assessment of the manufacturer's quality system is carried out by the body itself and the auditor then publishes an IECEx Quality Assessment Report (QAR).

Type testing of products is carried out on behalf of the body by an authorised laboratory.

In addition to its assessment work, the laboratory draws up an IECEx Test Report (ExTR).

The ExTR is then submitted to the body for approval.

Based on the QAR and ExTR, the body then publishes the Certificate of Conformity (CoC).

The CoC certifies that the equipment in question is in conformity with the IEC standards in force.

Once published by the body, the ExTR and QAR are registered on the IECEx website.

This confirms that an ExTR and QAR exist for the product.

IECEx CERTIFIED MOTORS

For IECEx certified motors, the certification number is indicated on their nameplate, e.g., "IECEx INE 10.0012X". In this case, "INE" signifies that the IECEx certificate has been published by INERIS, an approved certification body in France.

Furthermore, the certificates are published in electronic form and are publicly available on the IECEx website. They can therefore be consulted and printed at any time from the internet.

IECEx certification is particularly useful for certain markets.

In Australia, New Zealand and Singapore, for example, IECEx certificates are accepted, while not all IEC certificates are accepted.

Other countries, such as Russia, China and Korea, may accept the ExTR as a basis for their national certification.

IECEx marking was introduced in 2008 and certifies that a motor has been approved by a certification body of a Member State and can therefore be placed on the market without further testing.

Nidec Leroy-Somer offers IECEx certification on a wide range of its low-voltage ATEX motors, such as:

- **FLSD series (Ex db and Ex db eb flameproof motors).**
- **FLSN series in cast iron (Ex ec non-sparking motors) and LSN series in aluminium.**
- **FLSPX zone 21 and FLSES zone 22 series in cast iron, Ex t anti-dust motors.**

BENEFITS OF THE IECEx SYSTEM FOR CUSTOMERS

A significant advantage of IECEx is the availability of manufacturers' certificates on the IECEx website.

Customers can therefore confirm the validity of IECEx certificates at any time, unlike ATEX, for example. This increases the customer's confidence that the motor vendor is obliged to maintain the necessary quality systems.

There have been a number of changes to the standards and new standards created in recent years. They mainly concern motor efficiency and their scope includes measurement methods and motor classification.

Regulations are gradually being implemented, both nationally and internationally, in many countries in order to promote the use of high-efficiency motors (Europe, USA, Canada, Brazil, Australia, New Zealand, Korea, China, Israel, etc.).

The new generation of Premium efficiency three-phase induction motors responds to changes in the standards as well as the latest demands of system integrators and users.

STANDARD IEC 60034-30-1 (MARCH 2014)

This defines the principle to be adopted and brings global harmonisation to energy efficiency classes for electric motors throughout the world.

Motors concerned

Single-speed, single-phase and three phase cage induction or permanent magnet motors, on a sinusoidal mains supply.

Sphere of application:

- U_n from 50 to 1000 V
- P_n from 0.12 to 1000 kW
- 2, 4, 6 and 8 poles
- Continuous duty at rated power without exceeding the specified insulation class. Generally known as S1 duty.
- 50 and 60 Hz frequency
- On the mains
- Marked for an ambient temperature between -20°C and +60°C
- Marked for an altitude up to 4000 m

Motors not concerned

- Motors with frequency inverter when the motor cannot be tested without one.
- Brake motors when the brake forms an integral part of the motor and can neither be removed nor supplied by a separate source when being tested.
- Motors which are fully integrated in a machine and cannot be tested separately (such as rotor/stator).

STANDARD FOR MEASURING THE EFFICIENCY OF ELECTRIC MOTORS: IEC 60034-2-1 (JUNE 2014)

This concerns asynchronous induction motors:

- Single-phase and three-phase with power ratings of 1 kW or less. The preferred method is the D.O.L. method.
- Three-phase motors with power ratings above 1 kW. The preferred method is the summation of losses method with the total of additional losses measured.

Notes:

- The standard for efficiency measurement is very similar to the IEEE 112-B method used in North America.
- Since the measurement method is different, this means that, for the same motor, the rated value will be different (usually lower) with IEC 60034-2-1 than with the previous IEC 60034-2.

Example of a 22 kW 4P LSES motor:

- according to IEC 60034-2, the efficiency is 92.6%
- according to IEC 60034-2-1, the efficiency is 92.3%

ERP (ENERGY RELATED PRODUCT) DIRECTIVE 2009/125/EC (21 OCTOBER 2009)

This establishes a framework for setting the eco-design requirements to be applied to "energy-consuming products". These products are grouped into lots. Motors come under lot 11 of the eco-design programme, as do pumps, fans and circulating pumps.

DECREE IMPLEMENTING EUROPEAN ERP (ENERGY RELATED PRODUCT) DIRECTIVE EU/2019/1781 + EU/4/2014

This is based on standard IEC 60034-30-1 for defining efficiency classes. It specifies the efficiency levels to be attained for machines sold in the European market and outlines the timetable for their implementation.

| Classes of efficiency | Level of efficiency |
|-----------------------|---------------------|
| IE1 | Standard |
| IE2 | High |
| IE3 | Premium |
| IE4 | Super Premium |

This standard only defines efficiency classes and their conditions. It is then up to each country to define the efficiency classes and the exact scope of application.

Motors concerned: 3-phase motors from 0.75 to 1000 kW with 2, 4, 6 and 8 poles; duty S1, S3 \geq 80%, S6 \geq 80%.

Obligation to place Premium efficiency motors on the market:

- Class IE3 from 1st January 2015 for power ratings from 7.5 to 375 kW.
- Class IE3 from 1st January 2017 for power ratings from 0.75 to 375 kW.
- Class IE3 from July 2021 for power ratings from 375 to 1000 kW.

Motors not concerned:

- Motors designed to operate when fully immersed in liquid.
- Motors which are fully integrated in another product (rotor/stator).
- Motors with duty other than continuous duty.
- Motors designed to operate in the following conditions:
 - altitude > 4000 m
 - ambient air temperature > 60°C
 - maximum operating temperature > 400°C
 - ambient air temperature < -30°C or < 0°C for air-cooled motors
 - cooling water temperature at product entry < 0°C or > 32°C
 - "Ex eb" increased safety motors as per directive ATEX 2014/34/EU
 - brake motors

IMfinity® ATEX 3-phase induction motors - IE3 efficiency class

ATEX Gas, Zones 1 and 2 - ATEX Dust, Zones 21 and 22

General information

Standards and approvals

Motors comply with the standards quoted in this catalogue

LIST OF STANDARDS QUOTED IN THIS DOCUMENT

| Reference | | International standards |
|---------------------------|-------------|--|
| IEC 60034-1 | EN 60034-1 | Electrical rotating machines: ratings and operating characteristics. |
| IEC 60034-2 | | Electrical rotating machines: methods for determining losses and efficiency from tests (additional losses added as a fixed percentage) |
| IEC 60034-2-1 | | Electrical rotating machines: methods for determining losses and efficiency from tests (measured additional losses) |
| IEC 60034-5 | EN 60034-5 | Electrical rotating machines: classification of degrees of protection provided by rotating machine enclosures |
| IEC 60034-6 | EN 60034-6 | Electrical rotating machines (except traction): cooling methods. |
| IEC 60034-7 | EN 60034-7 | Electrical rotating machines (except traction): symbols for mounting positions and assembly layouts. |
| IEC 60034-8 | | Electrical rotating machines: terminal markings and direction of rotation. |
| IEC 60034-9 | EN 60034-9 | Electrical rotating machines: noise limits. |
| IEC 60034-12 | EN 60034-12 | Starting performance of single-speed three-phase cage induction motors for supply voltages up to and including 660 V. |
| IEC 60034-14 | EN 60034-14 | Electrical rotating machines: mechanical vibration of certain machines with frame sizes 56 mm and higher. Measurement, evaluation and limits of vibrational intensity |
| IEC 60034-17 | | Cage induction motors when fed from converters - Application guide |
| IEC 60034-30-1 | | Electrical rotating machines: efficiency classes for single-speed three-phase cage induction motors (IE code) |
| IEC 60038 | | IEC standard voltages |
| IEC 60072-1 | | Dimensions and output powers for electrical rotating machines: between 56 and 400 frame size and flanges of between 55 and 1080. |
| IEC 60085 | | Evaluation and thermal classification of electrical insulation. |
| IEC 60721-2-1 | | Classification of natural environment conditions. Temperature and humidity. |
| IEC 60892 | | Effects of an imbalance in the voltage system on the characteristics of three-phase squirrel-cage induction motors. |
| IEC 61000-2-10/11 and 2-2 | | Electromagnetic compatibility (EMC): environment. |
| IEC guide 106 | | Guidelines on the specification of environmental conditions for the determination of operating characteristics of equipment. |
| ISO 281 | | Bearings - Basic dynamic loadings and nominal bearing life. |
| ISO 1680 | EN 21680 | Acoustics - Test code for measuring airborne noise emitted by electrical rotating machines: a method for establishing an expert opinion for free field conditions over a reflective surface. |
| ISO 8821 | | Mechanical vibration - Balancing. Conventions on shaft keys and related parts. |
| | EN 50102 | Degree of protection provided by electrical housings against extreme mechanical impacts. |
| ISO 12944-2 | | Corrosion protection |
| IEC 60079-0 | EN 60079-0 | Electrical equipment for explosive atmospheres: general rules |
| IEC 60079-1 | EN 60079-1 | Electrical equipment for explosive atmospheres: flameproof enclosures "d" |
| IEC 60079-15 | EN 60079-15 | Electrical equipment for explosive atmospheres: non-sparking "n" |
| IEC 60079-31 | EN 60079-31 | Electrical equipment for use in the presence of combustible dust. |

IMfinity® ATEX 3-phase induction motors - IE3 efficiency class

ATEX Gas, Zones 1 and 2 - ATEX Dust, Zones 21 and 22

General information

Standards and approvals

MAIN PRODUCT MARKINGS WORLDWIDE

There are lots of special markings throughout the world. They mainly concern product conformance with current user safety standards in different countries. Some markings or labels only concern energy regulations. The same country can therefore have two markings: one for safety and one for energy.



This marking is mandatory throughout the European Union. It means that the product is in conformity with all the relevant directives. If the product is not in conformity with a relevant directive, it cannot be CE rated and cannot therefore bear the **CE** mark.



In **Canada and the United States**: The **CSA** mark accompanied by the letters C and US means that the product is approved for the US and Canadian markets, in accordance with the relevant American and Canadian standards. If a product has characteristics applicable to more than one type of product (e.g., electrical equipment incorporating fuel combustion), the mark indicates conformance with all the relevant standards.



This marking only applies to finished products such as complete machines. A motor is just a component and is not therefore affected by this marking.

Note: c CSA us and c UL us mean the same thing but one is delivered by the CSA and the other by the UL.



The **c UL us mark**, which is optional, indicates conformance with Canadian requirements and those of the United States. UL encourages manufacturers distributing products bearing the UL Recognized Component Mark for both countries to use this combined mark.

For Canada at least c UR us or c CSA us is required. Both are also possible.

Components covered by the UL "Recognized Component Mark" programme are designed to be installed in another device, system or end product. They should be installed in the factory, not in the field and it is possible that their performance capability will be restricted and will limit their use. When a complete product or system containing UL Recognized components is assessed, the end product assessment process can be rationalised.



Canada: energy efficiency conformity logo (optional).



USA: energy efficiency conformity logo (optional).



USA and Canada: EISA conformity logo (optional).



This marking is mandatory for the Chinese market. It indicates that the product conforms to the regulations currently in force (safety of users). The electric motors concerned are rated ≤ 1.1 kW.



The EAC mark replaces the GOST mark. It is the equivalent of the CE mark for the European Union market. This new mark covers regulations for Russia, Kazakhstan and Belarus. All products marketed in these three countries must bear this marking.

Other markings concern specific applications, such as ATEX for example.

IMfinity® ATEX 3-phase induction motors - IE3 efficiency class
ATEX Gas, Zones 1 and 2 - ATEX Dust, Zones 21 and 22
General information
Standards and approvals

CERTIFICATION OF NIDEC LEROY-SOMER MOTORS (versions derived from standard design)

| Country | Initials | Certification No. | Application |
|---------|----------------|--------------------------------|---|
| CANADA | CSA | LR 57 008 166,631 | Standard adapted range (see section "Supply voltage") Complete motors |
| USA | UL or FU | E 68554 SA 6704 E 206450 | Impregnation systems Stator / rotor assemblies for sealed units Complete motors |
| FRANCE | LCIE INERIS | - | Sealing, shocks, safety |

For approved special products, see the relevant documents.

IP (INGRESS PROTECTION) RATING OF ELECTRICAL EQUIPMENT ENCLOSURES

In accordance with IEC 60034-5 - EN 60034-5 (IP) - IEC 62262 (IK)

| 1 st digit: protection against solid materials | | | 2 nd digit protection against liquids | | | 3 rd digit mechanical protection | | |
|---|--------------|---|--|-------|--|---|-------|-----------------------|
| IP | Tests | Definition | IP | Tests | Definition | IK | Tests | Definition |
| 0 | | No protection | 0 | | No protection | 00 | | No protection |
| 1 | Ø 50 mm | Protected against solid objects larger than 50 mm (e.g. accidental contact with the hand) | 1 | | Protected against water drops falling vertically (condensation) | 01 | | Impact energy: 0.15 J |
| 2 | Ø 12 mm | Protected against solid objects larger than 12 mm (e.g. a finger) | 2 | | Protected against water drops falling at up to 15° from the vertical | 02 | | Impact energy: 0.20 J |
| 3 | Ø 2.5 mm | Protected against solid objects larger than 2.5 mm (e.g. tools, wires) | 3 | | Protected against rain falling at up to 60° from the vertical | 03 | | Impact energy: 0.37 J |
| 4 | Ø 1 mm | Protected against solid objects larger than 1 mm (e.g. thin tools, small wires) | 4 | | Protected against projected water from all directions | 04 | | Impact energy: 0.50 J |
| 5 | Ø 1 mm | Protected against dust (no deposits of harmful material) | 5 | | Protected against jets of water from all directions from a hose | 05 | | Impact energy: 0.70 J |
| 6 | Ø 1 mm | Protected against any dust penetration | 6 | | Protected against projected water comparable to big waves | 06 | | Impact energy: 1 J |
| | | | 7 | | Protected against the effects of immersion between 0.15 and 1 m | 07 | | Impact energy: 2 J |
| | | | 8 | | Protected against prolonged effects of immersion under pressure | 08 | | Impact energy: 5 J |
| | | | | | | 09 | | Impact energy: 10 J |
| | | | | | | 10 | | Impact energy: 20 J |

Example:

Example of an IP 55 machine

IP : Protection rating

5. : Machine protected against dust and accidental contact.
 Test result: no ingress of dust in harmful quantities, no risk of direct contact with rotating parts. The test will last for 2 hours.

.5 : Machine protected against jets of water from all directions from hoses with a flow rate of 12.5 l/min at 0.3 bar at 3 m distance from the machine.
 The test will last for 3 minutes.
 Test result: no damage from water projected onto the machine.

IMfinity® ATEX 3-phase induction motors - IE3 efficiency class

ATEX Gas, Zones 1 and 2 - ATEX Dust, Zones 21 and 22

General information

Operating conditions

NORMAL OPERATING CONDITIONS

a - Motors can operate in the following normal conditions:

- ambient temperature within the range -16°C to +40°C,
- altitude less than 1000 m,
- atmospheric pressure: 1050 hPa (mbar).

The EN 60079-0 standard concerning electrical equipment for explosive atmospheres extends the ambient temperature range T_a from -20 to +40°C as standard. In this case, no additional marking is required on the certified or approved equipment.

Temperatures outside this range can be considered when certifying the equipment. Additional marking must then be provided. These extensions require special consultation.


b - FLSD motors are designed to operate in environments with a relative humidity of up to 95% at 40°C.

POWER CORRECTION

The power ratings of our motors are given for continuous duty (S1) at rated voltage and frequency, at 1000 m maximum altitude and 40°C maximum ambient temperature as standard.

By downgrading their rated power, it is possible to use our ATEX motors in temperature conditions above 40°C (60°C) and at altitudes higher than 1000 m.

Correction coefficients table*




* For FLSD Ex db eb IIB or IIC T4 motors and (F)LSN Ex ec II T3 motors.
Not applicable to FLSD T5 or T6 motors (please contact us).

HARSH ENVIRONMENTS

Certain conditions of use require finishes suited to the environment: very dusty, damp or aggressive environments.

The essential criteria for anti-corrosion protection are based on suitable components meeting the requirements of the ATEX Directive (fastenings, plates, cover), metal cable glands, protection of the active parts (stator and rotor), special paints.



VIK EXECUTION

ATEX motors of the type Exdb eb IIC T4 Gb and Ex ec IIC T3 Gc can be produced in compliance with the VIK recommendations issued by German heavy industry, which apply to equipment used in explosive atmospheres.

The main characteristics to be satisfied by motors manufactured according to this recommendation are as follows:

- Finish suited to corrosive atmospheres (paint, screws, etc.).
- Two stainless steel nameplates, including one inside the terminal box.
- For flameproof and non-sparking motors, IE3 efficiency level is required.

- Drip cover if motor placed in vertical position with shaft end downwards.
- Marking with the VIK logo.
- Captive screws for fixing terminal box covers.
- Corrosion-resistant earth terminal secured to the housing with a caliper.
- Winding PTC sensors.
- Flat grease nipples (M10 x 1) as per DIN 3404.

IMfinity® ATEX 3-phase induction motors - IE3 efficiency class

ATEX Gas, Zones 1 and 2 - ATEX Dust, Zones 21 and 22

General information

Impregnation and enhanced protection

NORMAL ATMOSPHERIC PRESSURE (750 MM HG)

The selection table below enables selection of the construction method best suited for operation in environments where the temperature and relative humidity vary widely.

The symbols used refer to permutations of components, materials, impregnation methods and finishes (varnish or paint).

The protection of the winding is generally described by the term "tropicalization".

T: Tropicalization

TC: Complete Tropicalization

For high humidity environments, we recommend that the windings are pre-heated (see next page).

INFLUENCE OF ATMOSPHERIC PRESSURE

As atmospheric pressure decreases, air particles rarefy and the environment becomes increasingly conductive.

- P > 550 mm Hg:

standard impregnation according to previous table - Possible derating or forced ventilation.

- P > 200 mm Hg:

Coating of bearings - Flying leads up to a zone at P ~ 750 mm Hg - Derating to take account of insufficient ventilation - Forced ventilation.

- P < 200 mm Hg: Special manufacture based on specification.

In all cases, these problems should be resolved by a special contract worked out on the basis of a specification.

| Ambient temperature | Relative humidity | | Influence on construction |
|-----------------------------|--|-----------------------|--|
| | RH ≤ 95% | RH > 95% ¹ | |
| θ < - 40 °C | ask for quotation | ask for quotation |  <p>Increasing derating</p> |
| - 16°C to + 50°C | T Standard | TC Standard | |
| -40°C to +50°C ² | T1 | TC1 | |
| -16°C to +65°C ² | T2 | TC2 | |
| +65°C to +90°C ² | T3 | TC3 | |
| θ > +90 °C | ask for quotation | ask for quotation | |
| Plate mark | T | TC | |
| Influence on construction |  <p>Increased protection of windings</p> | | |

1. Atmosphere without high levels of condensation

2. For motors with frame size ≥ 280 mm and IP23 motors with frame size ≥ 315 mm: ask for quotation

 Standard construction

IMfinity® ATEX 3-phase induction motors - IE3 efficiency class

ATEX Gas, Zones 1 and 2 - ATEX Dust, Zones 21 and 22

Environment Heaters

SPACE HEATERS

Severe climatic conditions, e.g. $T_{amb} < -40^{\circ}\text{C}$, $\text{RH} > 95\%$ etc, may require the use of space heaters (fitted to one or two winding end coils) which serve to maintain the average temperature of the motor, provide trouble-free starting, and/or eliminate problems caused by condensation (loss of insulation).

The heater supply wires are brought out to a terminal block in the motor terminal box.

The heaters must be switched off while the motor is running.

DC SUPPLY INJECTION HEATING

An alternative to the use of space heaters is to inject direct current into two of the phases wired in series from a DC voltage source. This method can only be used on motors of less than 10 kW.

This is easily calculated: if R is the resistance of the windings in series, the DC voltage will be given by the equation (Ohm's law):

$$U_{(V)} = \sqrt{P_{(W)} \cdot R_{(\Omega)}}$$

Resistance should be measured with a micro-ohmmeter.

AC INJECTION HEATING

A single-phase AC voltage (from 10 to 15% of the rated voltage) can be used between 2 phases placed in series. This method can be used on the entire motor range.

See the mechanical and electrical options pages for each motor family to find the space heater values.



IMfinity® ATEX 3-phase induction motors - IE3 efficiency class

ATEX Gas, Zones 1 and 2 - ATEX Dust, Zones 21 and 22

Environment

Paint finish

Surface protection is defined in the ISO 12944 standard. This standard defines the planned service life of a paint system until the first major application of maintenance paint. Durability is not a guarantee.

The EN ISO 12944 standard comprises 8 sections. Part 2 covers the classification of the environments.

Nidec Leroy-Somer motors are protected with a range of surface finishes.

The surfaces receive appropriate special treatments, as shown below.

PREPARATION OF SURFACES

| Surfaces | Parts | Surface treatment |
|-----------------|--|---|
| Cast iron | Endshields | Shot blasting + Primer |
| Steel | Accessories | Phosphatization + Primer |
| | Terminal boxes - Fan covers | Electrostatic painting or Epoxy powder |
| Aluminium alloy | Housings - Terminal boxes | Shot blasting |
| Polymer | Fan covers - Terminal boxes Ventilation grilles | None, but must be free from grease, casting-mould coatings and dust which would affect paint adhesion |

CLASSIFICATION OF ENVIRONMENTS

Nidec Leroy-Somer paint systems according to the categories.

| Atmospheric corrosivity categories | Corrosion protection as per ISO 12944 -2 | Durability class | ISO 6270 | ISO 9227 | Equivalent system Nidec Leroy-Somer | Description of system |
|------------------------------------|--|------------------|--|------------------------|-------------------------------------|---|
| | | | Equivalent water condensation No. of hours | Salt mist No. of hours | | |
| Others | - | - | | | Non-painted | No coating except for cast iron parts |
| | | - | | | Primary | 1 primary coat / Ph-Zn Pu |
| Medium | C3 | Limited | 48 | 120 | C3L | 1 polyurethane coat |
| | | Medium | 120 | 240 | | |
| | | High | 240 | 480 | | |
| | | Very high | 480 | 720 | | |
| High | C4 | Limited | 120 | 240 | | |
| | | Medium | 240 | 480 | C4M | 1 primary coat / Ph-Zn Pu 1 polyurethane coat |
| | | | | | C4M-EP* | 1 primary coat / Ph-Zn Pu 1 epoxy coat |
| | | High | 480 | 720 | | |
| | | Very high | 720 | 1440 | | |
| | | Very high | C5 | Limited | 240 | 480 |
| Medium | 480 | | | 720 | C5M | 1 primary coat / Ph-Zn Pu 1 Ph-Zn Pu intermediate coat 1 polyester / acrylic coat |
| | | | | | | |
| High | 720 | | | 1440 | | |
| Very high | - | - | | | | |

C3L limited for all versions

The Ia system applies to the group of moderate climates and the IIa system to the group of general climates, as defined in standard IEC 60721.2.1.

Standard paint colour references:

RAL 2004 ATEX GAS

RAL 1007 ATEX DUST ZONES 21

RAL 6000 ATEX DUST ZONES 22

IMfinity® ATEX 3-phase induction motors - IE3 efficiency class

ATEX Gas, Zones 1 and 2 - ATEX Dust, Zones 21 and 22

Environment

Interference suppression and protection of people

AIRBORNE INTERFERENCE

EMISSION

For standard motors, the enclosure acts as an electromagnetic screen, reducing electromagnetic emissions measured at 0.25 metres from the motor to approximately 5 gauss (5×10^{-4} T). However, electromagnetic emissions may be noticeably reduced by a special construction of aluminium alloy end shields and a stainless steel shaft.

IMMUNITY

The construction of motor enclosures (especially finned aluminium alloy frames) isolates external electromagnetic sources to the extent that any field penetrating the enclosure and magnetic circuit will be too weak to interfere with the operation of the motor.

POWER SUPPLY INTERFERENCE

The use of electronic systems for starting, variable speed control or power supply can create harmonics on the supply lines which may interfere with the operation of machines. These phenomena are taken into account in determining the machine dimensions, which act as quenching chokes in this respect.

The CISPR 11 standard, currently undergoing study, will define the permissible rejection and immunity rates.

Three-phase squirrel cage machines do not in themselves produce interference of this type. Mains connection equipment (contactors) may, however, need interference protection.

APPLICATION OF DIRECTIVE 2014/30/EU CONCERNING ELECTROMAGNETIC COMPATIBILITY (EMC)

a - for motors only

According to amendment 1 of IEC 60034-1, induction motors are not transmitters and do not produce interference (via carried or airborne signals) and therefore conform inherently to the essential requirements of the EMC directives.

b - for motors supplied by inverters (at fixed or variable frequency)

In this case, the motor is only a sub-assembly of a device which the system builder must ensure conforms to the essential requirements of the EMC directives.

APPLICATION OF LOW VOLTAGE DIRECTIVE 2014/35/EU

All motors are subject to this directive. The main requirements concern the protection of people, animals and property against risks caused by operation of the motors (see the commissioning and maintenance manual for precautions to be taken).

APPLICATION OF MACHINERY DIRECTIVE 2006/42/EC

All motors are designed to be integrated in a device subject to the machinery directive.

PRODUCT MARKING

The fact that motors comply with the essential requirements of the Directives is shown by the **CE** mark on their nameplates and/or packaging and documentation.














IMfinity® ATEX 3-phase induction motors - IE3 efficiency class

ATEX Gas, Zones 1 and 2 - ATEX Dust, Zones 21 and 22

Construction

Mounting arrangements and operating positions

MOUNTINGS AND POSITIONS (AS PER STANDARD IEC 60034-7)

| | | |
|--|---|--|
| Foot mounted motors <ul style="list-style-type: none"> • all frame sizes | IM 1001 (IM B3) - Horizontal shaft - Feet on floor  | IM 1071 (IM B8) - Horizontal shaft - Feet on top  |
| | IM 1051 (IM B6) - Horizontal shaft - Wall mounted with feet on left when viewed from drive end  | IM 1011 (IM V5) - Vertical shaft downwards - Feet on wall  |
| | IM 1061 (IM B7) - Horizontal shaft - Wall mounted with feet on right when viewed from drive end  | IM 1031 (IM V6) - Vertical shaft upwards - Feet on wall  |
| (FF) flange mounted motors <ul style="list-style-type: none"> • all frame sizes (except IM 3001, which is limited to frame size 225 mm) | IM 3001 (IM B5) - Horizontal shaft  | IM 2001 (IM B35) - Horizontal shaft - Feet on floor  |
| | IM 3011 (IM V1) - Vertical shaft downwards  | IM 2011 (IM V15) - Vertical shaft downwards - Feet on wall  |
| | IM 3031 (IM V3) - Vertical shaft upwards  | IM 2031 (IM V36) - Vertical shaft upwards - Feet on wall  |
| (FT) face mounted motors <ul style="list-style-type: none"> • all frame sizes ≤ 132 mm | IM 3601 (IM B14) - Horizontal shaft  | IM 2101 (IM B34) - Horizontal shaft - Feet on floor  |
| | IM 3611 (IM V18) - Vertical shaft downwards  | IM 2111 (IM V58) - Vertical shaft downwards - Feet on wall  |
| | IM 3631 (IM V19) - Vertical shaft upwards  | IM 2131 (IM V69) - Vertical shaft upwards - Feet on wall  |
| Motors without drive end shield Warning: The protection (IP) specified on the IM B9 and IM B15 motor nameplates is provided by the customer when the motor is assembled. | IM 9101 (IM B9) - Threaded tie rods - Horizontal shaft  | IM 1201 (IM B15) - Foot-mounted and threaded rods - Horizontal shaft  |

| Frame height (mm) | Mounting positions | | | | | | | | | | | |
|-------------------|--------------------|---------|---------|---------|---------|---------|---------|---------|---------|---------|---------|---------|
| | IM 1001 | IM 1051 | IM 1061 | IM 1071 | IM 1011 | IM 1031 | IM 3001 | IM 3011 | IM 3031 | IM 2001 | IM 2011 | IM 2031 |
| ≤ 200 | ● | ● | ● | ● | ● | ● | ● | ● | ● | ● | ● | ● |
| 225 and 250 | ● | ● | ● | ● | ● | ● | ■ | ● | ● | ● | ● | ● |
| ≥ 280 | ● | ■ | ■ | ■ | ■ | ■ | ■ | ● | ● | ● | ● | ■ |

● : possible positions

■ : please contact us, specifying the coupling method and the axial and radial loads if applicable


TERMINAL BOX

Placed as standard on the top of the motor near the drive end, it is fitted with plugs or a removable undrilled support plate.


The standard position of the plug is on the right, seen from the drive end but, owing to the symmetrical construction of the box, it can usually be placed in any of the 4 directions, as shown in the table below.

If required, the terminal box may be fitted in a different position (on the left or right as seen from the drive end, and at the front or rear of the motor housing).

Terminal box positions in relation to the drive end (motor in IM 1001 position)



Plug positions in relation to the drive end



Position 2 not recommended (impossible on standard flange mounted (FF) motor)

FLYING LEADS

According to specification, motors can be supplied with flying leads using single-core cables (as an option, the cables can be protected by a sheath) or multicore cables.

Please state cable characteristics (cross-section, length, number of conductors), connection method (flying leads or on a terminal block) and the drill hole position.

WIRING DIAGRAMS

All standard motors are supplied with a wiring diagram in the terminal box.

The diagrams normally used are shown opposite.

On the following pages are outline diagrams with internal and external connections.

EARTH TERMINAL

This is situated inside the terminal box. Consisting of a threaded stud with a hexagonal nut, it is used to connect cables with cross-sections at least as large as the cross-section of the phase conductors.

The earth terminal is indicated by the symbol: \equiv in the terminal box moulding. A second earth terminal is installed on the motor.

In the VIK version, for Ex db eb IIC T4 Gb and Ex ec IIC T3 Gc motors, an earth terminal is always fixed to the housing by means of a caliper.


| Position of the terminal box | A | B | D |
|-----------------------------------|---|---|---|
| LSN - LSES - LSPX | ● | ■ | ■ |
| FLSN - FLSES - FLSPX 80 to 225 MT | ● | - | - |
| FLSN - FLSES - FLSPX 225M to 355 | ● | ■ | ■ |
| FLSD 80 to 280 | ● | - | - |
| FLSD 315 | ● | ■ | ■ |

● : standard
 ■ : please contact us
 - : not available

| Cable gland position | 1 | 2* | 3 | 4 |
|-----------------------------|---|----|---|---|
| FLSD-(F)LSN-(F)LSES-(F)LSPX | ◆ | * | * | * |

* not recommended (impossible on (FF) flange mounted motors and on the FLSES 355LK/400/450)

◆ : standard
 * : possible by simply turning round the terminal box



Construction

Radial loads

PERMISSIBLE RADIAL LOAD ON THE MAIN DRIVE SHAFT

In pulley and belt couplings, the drive shaft carrying the pulley is subjected to a radial force F_{pr} applied at a distance X (mm) from the shoulder of the drive shaft (length E).

Radial force acting on the drive end: F_{pr}

The radial force F_{pr} expressed in daN applied to the drive end is found by the formula:

$$F_{pr} = 1.91 \cdot 10^6 \frac{P_N \cdot k}{D \cdot N_N} \pm P_P$$

where:

P_N = rated motor power (kW)

D = external diameter of the drive pulley (mm)

N_N = rated motor speed (min^{-1})

k = factor depending on the type of transmission

P_P = weight of the pulley (daN)

The weight of the pulley is positive when it acts in the same direction as the tension force in the belt (and negative when it acts in the opposite direction).

Range of values for factor k (*)

- toothed belts: $k = 1$ to 1.5

- V-belts: $k = 2$ to 2.5

- flat belts

• with tensioner: $k = 2.5$ to 3

• without tensioner: $k = 3$ to 4

(*) A more accurate figure as factor k can be obtained from the transmission suppliers.

Permissible radial force on the drive shaft

The charts on the following pages indicate, for each type of motor, the radial force F_R at a distance X permissible on the drive end shaft extension, for a bearing life L_{10h} of 25,000 hours.


Note: For frame sizes ≥ 315 M, the selection charts are applicable for a motor installed with the shaft horizontal.

Change in bearing life depending on the radial load factor


For a radial load F_{pr} ($F_{pr} \neq F_R$), applied at distance X , the bearing life L_{10h} changes, as a rough estimate, in the ratio k_R ($k_R = F_{pr}/F_R$) as shown in the

chart below, for standard fitting arrangements.

If the load factor k_R is greater than 1.05, you should consult our technical department, stating mounting position and direction of force before opting for a special fitting arrangement.




Change in bearing life L_{10h} depending on the radial load factor k_R for standard fitting arrangements.



Construction Cooling mode

Designation system for the IC (International Cooling) coded cooling method in the IEC 60034-6 standard.

The standard allows for two designations (general formula and simplified formula) as shown in the example opposite.



NB: The letter A may be omitted if this will not lead to confusion. This contracted formula becomes the simplified formula.

Simplified formula: IC 411.

Circuit layout

| Characteristic number | Abbreviated designation | Description |
|----------------------------|---|--|
| 0 ⁽¹⁾ | Free circulation | The coolant enters and leaves the machine freely. It is taken from and returned to the fluid round the machine. |
| 1 ⁽¹⁾ | Machine with one intake pipe | The coolant is taken up elsewhere than from the fluid round the machine, brought into the machine through an intake pipe and emptied into the fluid round the machine. |
| 2 ⁽¹⁾ | Machine with one outlet pipe | The coolant is taken up from the fluid round the machine, brought away from the machine by an outlet pipe and does not go back into the fluid round the machine. |
| 3 ⁽¹⁾ | Machine with two pipes (intake and outlet) | The coolant is taken up elsewhere than from the fluid round the machine, brought to the machine through an intake pipe, then taken away from the machine through an outlet pipe and does not go back into the fluid round the machine. |
| 4 | Surface-cooled machine using the fluid around the machine | The primary coolant circulates in a closed circuit, transferring its heat to a secondary coolant (the one surrounding the machine) through the machine casing. The casing surface is either smooth or finned to improve heat transmission. |
| 5 ⁽²⁾ | Integrated heat exchanger (using the surrounding environment) | The primary coolant circulates in a closed circuit, transferring its heat to a secondary coolant (the one surrounding the machine) in an integral heat exchanger inside the machine. |
| 6 ⁽²⁾ | Machine-mounted heat exchanger (using the surrounding environment) | The primary coolant circulates in a closed circuit, transferring its heat to a secondary coolant (the one surrounding the machine) in a heat exchanger that forms an independent unit, mounted on the machine. |
| 7 ⁽²⁾ | Integrated heat exchanger (not using the surrounding environment) | The primary coolant circulates in a closed circuit, transferring its heat to a secondary coolant (which is not the one round the machine) in an integral heat exchanger inside the machine. |
| 8 ⁽²⁾ | Machine-mounted heat exchanger (not using the surrounding environment) | The primary coolant circulates in a closed circuit, transferring its heat to a secondary coolant (which is not the one round the machine) in a heat exchanger that forms an independent unit, mounted on the machine. |
| 9 ⁽²⁾⁽³⁾ | Separate heat exchanger (may or may not be using the surrounding environment) | The primary coolant circulates in a closed circuit, transferring its heat to the secondary fluid in a heat exchanger that forms an independent unit, away from the machine. |

Coolant

| Characteristic letter | Type of fluid |
|-----------------------|--|
| A | Air |
| F | Freon |
| H | Hydrogen |
| N | Nitrogen |
| C | Carbon dioxide |
| W | Water |
| U | Oil |
| S | Any other fluid (must be identified separately) |
| Y | The fluid has not yet been selected (used temporarily) |

Mode of circulation

| Characteristic number | Abbreviated designation | Description |
|-------------------------|--|---|
| 0 | Free circulation | The circulation of the coolant is due only to differences in temperature. Ventilation caused by the rotor is negligible. |
| 1 | Self-circulation | The circulation of the coolant depends on the rotational speed of the main machine, and is caused by the action of the rotor alone, or a device mounted directly on it. |
| 2, 3, 4 | | Not yet defined. |
| 5 ⁽⁴⁾ | Built-in and independent device | The coolant is circulated by a built-in device which is powered independently of the rotational speed of the main machine. |
| 6 ⁽⁴⁾ | Independent device mounted on the machine | The coolant is circulated by a device mounted on the machine which is powered independently of the rotational speed of the main machine. |
| 7 ⁽⁴⁾ | Entirely separate and independent device or using the pressure of the coolant circulation system | The coolant is circulated by a separate electrical or mechanical device, independent of and not mounted on the machine, or by the pressure in the coolant circulation system. |
| 8 ⁽⁴⁾ | Relative displacement | The circulation of the coolant is produced by the relative movement between the machine and the coolant, either by displacement of the machine in relation to the coolant, or by the flow of the surrounding coolant. |
| 9 | All other devices | The coolant is circulated using a method other than those defined above: it must be described in full. |

(1) Filters or labyrinth seals for dust removal or noise protection can be fitted inside the casing or in the ducting. The first characteristic numbers 0 to 3 also apply to machines in which the coolant is taken up at the outlet of a water-cooler designed to lower the temperature of the ambient air or recirculated through a water-cooler so as not to increase the ambient temperature.

(2) The nature of the heat exchanger elements is not specified (smooth or finned tubes, corrugated surfaces, etc).

(3) A separate heat exchanger can be installed near to or at a distance from the machine. A secondary gas coolant may or may not be the surrounding environment.

(4) Use of such a device does not exclude the ventilating action of the rotor or the existence of an additional fan mounted directly on the rotor.

Construction Cooling mode

MOTOR VENTILATION

In compliance with IEC 60034-6, the motors in this catalogue are cooled using method IC 411, i.e.: "surface-cooled machine using the ambient air circulating round the machine".

Cooling is achieved by a fan mounted at the non-drive end of the motor, inside a fan cover which acts as a safety guard (check according to IEC 600 34-5). The fan draws the air through the grille in the cover and blows it along the housing fins, giving an identical heat balance in either direction of rotation (except for LSES 2-pole motors of frame size 315 mm).

NB: Obstruction, even accidental, of the fan cover grille (grille clogged or placed against a wall) seriously impairs motor cooling.

We recommend a minimum distance of 1/3 of the frame size between the end of the fan cover and any possible obstacle (wall, machine, etc).


Variable speed motor cooling (ventilation)

Special precautions need to be taken when standard induction motors are being used with variable speed, powered by an inverter or voltage controller.

During prolonged operation at low speed, cooling efficiency is greatly

diminished. It is therefore advisable to install a forced ventilation unit that will produce a constant flow of air at any motor speed.

In prolonged operation at high speed, the fan may make excessive noise. It is again advisable to install a forced ventilation unit.



NON-VENTILATED APPLICATIONS IN CONTINUOUS DUTY

Motors can be supplied without fans. Dimensions will depend on the application.

These motors shall be subject to special qualification.

IC 418 COOLING






If they are placed in the air flow from a fan, these motors are capable of supplying their rated power if the speed of the air between the housing fins and the overall flow rate of the air between the fins comply with the data in the table opposite.

| Type LSES/FLSES | 2 poles | | 4 poles | | 6 poles | |
|-----------------|-----------------------------|-----------|-----------------------------|-----------|-----------------------------|-----------|
| | flow rate m ³ /h | speed m/s | flow rate m ³ /h | speed m/s | flow rate m ³ /h | speed m/s |
| 80 | 120 | | 60 | 4 | 40 | 2.5 |
| 90 | 200 | 11.5 | 75 | 5.5 | 60 | 3.5 |
| 100 | 300 | 15 | 130 | 7.5 | 95 | 5 |
| 112 | 460 | 18 | 200 | 9 | 140 | 6 |
| 132 | 570 | 21 | 300 | 10.5 | 220 | 7 |
| 160 | 1000 | 21 | 600 | 12.5 | 420 | 9 |
| 180 | 1200 | 21 | 900 | 16 | 600 | 10 |
| 200 | 1800 | 23 | 1200 | 16 | 750 | 10 |
| 225 | 2000 | 24 | 1500 | 18 | 1700 | 13 |
| 250 | 3000 | 25 | 2600 | 20 | 1700 | 13 |
| 280 | 3000 | 25 | 2600 | 20 | 2000 | 15 |
| 315 | 5000 | 25 | 2600 | 20 | 2000 | 15 |
| 355 | 5200 | 25 | 2800 | 20 | 2200 | 15 |
| 400 | 5500 | 25 | 3000 | 20 | 2600 | 15 |
| 450 | 6000 | 25 | 3200 | 20 | 2600 | 15 |

These air flows are valid for normal operating conditions as described in the "Environmental limitations" section.

IMfinity® ATEX 3-phase induction motors - IE3 efficiency class
ATEX Gas, Zones 1 and 2 - ATEX Dust, Zones 21 and 22
Construction
Cooling mode

STANDARD CODES

| | | |
|-------------------------|--|---|
| <p>IC 410</p> | <p>Enclosed machine, surface-cooled by natural convection and radiation. No external fan.</p> |  |
| <p>IC 411</p> | <p>Enclosed machine. Smooth or finned ventilated casing. External shaft-mounted fan.</p> |  |
| <p>IC 416 A*</p> | <p>Enclosed machine. Smooth or finned enclosed casing. External motorized axial (A) fan supplied with the machine.</p> |  |
| <p>IC 416 R*</p> | <p>Enclosed machine. Smooth or finned enclosed casing. External motorized radial (R) fan supplied with the machine.</p> |  |
| <p>IC 418</p> | <p>Enclosed machine. Smooth or finned casing. No external fan. Ventilation provided by air flow coming from the driven system.</p> |  |

* Features not within manufacturer's standard range.

IMfinity® ATEX 3-phase induction motors - IE3 efficiency class

ATEX Gas, Zones 1 and 2 - ATEX Dust, Zones 21 and 22

Construction

Motor connections

SINGLE-SPEED MOTORS

| Voltages and connection | Internal wiring diagrams | Winding outline diagrams | External connection diagrams | |
|---|--------------------------|--------------------------|------------------------------|----------------|
| | | | D.O.L. starting | Y / Δ starting |
| Single voltage type motors (3 TERMINALS) | | | | |
| - Voltage: U - Connection: Y internal e.g. 400 V/Y | | | | |
| - Voltage: U - Connection: internal Δ e.g. 400 V / Δ | | | | |
| Dual-voltage motors with Y, Δ connections (6 TERMINALS) | | | | |
| - Voltage: U - Connection: Δ (at the lower voltage) e.g. 230 V / Δ | | | | |
| - Voltage: $U \sqrt{3}$ - Connection: Y (at the higher voltage) e.g. 400 V/Y | | | | |
| Dual-voltage motors with series-parallel connections (9 TERMINALS) | | | | |
| - Voltage: U - Connection: YY (at the lower voltage) e.g. 230 V / YY | | | | |
| - Voltage: 2 U - Connection: Y (series-star at the higher voltage) e.g. 460 V/Y | | | | |

IMfinity® ATEX 3-phase induction motors - IE3 efficiency class

ATEX Gas, Zones 1 and 2 - ATEX Dust, Zones 21 and 22

Construction

Bearings and bearing life

DEFINITIONS

LOAD RATINGS

Static load rating C_0 :

This is the load for which permanent deformation at point of contact between a bearing race and the ball (or roller) with the heaviest load reaches 0.01% of the diameter of the ball (or roller).

Dynamic load rating C :

This is the load (constant in intensity and direction) for which the nominal service life of the bearing will reach 1 million revolutions.

The static load rating C_0 and dynamic load rating C are obtained for each bearing by following the method in ISO 281.

SERVICE LIFE

The service life of a bearing is the number of revolutions (or number of operating hours at a constant speed) that the bearing can accomplish before the first signs of fatigue (spalling) begin to appear on a ring, ball or roller.

Nominal service life L_{10h}

According to the ISO recommendations, the nominal service life is the length of time achieved or exceeded by 90% of apparently identical bearings operating under the conditions specified by the manufacturer.

Note: The majority of bearings last much longer than the nominal service life; the average service life achieved or exceeded by 50% of bearings is around 5 times longer than the nominal service life.

DETERMINATION OF NOMINAL SERVICE LIFE

Constant load and speed of rotation

The nominal service life of a bearing expressed in operating hours L_{10h} , the dynamic load rating C expressed in daN and the applied loads (radial load F_r and axial load F_a) are related by the following equation:

$$L_{10h} = \frac{1000000}{60 \cdot N} \cdot \left(\frac{C}{P}\right)^p$$

where N = speed of rotation (min^{-1})

P ($P = X F_r + Y F_a$): equivalent dynamic load (F_r, F_a, P in daN)

p : exponent which is a function of the contact between the races and balls (or rollers)

$p = 3$ for ball bearings


$p = 10/3$ for roller bearings

The formulae that give Equivalent Dynamic Load (values of factors X and Y) for different types of bearing may be obtained from the various manufacturers.

Variable load and speed of rotation

For bearings with periodically variable load and speed, the nominal service life is established using the equation:

$$L_{10h} = \frac{1000000}{60 \cdot N_m} \cdot \left(\frac{C}{P_m}\right)^p$$



N_m : average speed of rotation

$$N_m = N_1 \cdot \frac{q_1}{100} + N_2 \cdot \frac{q_2}{100} + \dots (\text{min}^{-1})$$

P_m : average equivalent dynamic load

$$P_m = P \sqrt{P_1^p \cdot \left(\frac{N_1}{N_m}\right) \cdot \frac{q_1}{100} + P_2^p \cdot \left(\frac{N_2}{N_m}\right) \cdot \frac{q_2}{100} + \dots (\text{daN})}$$

with q_1, q_2, \dots as %

Nominal service life L_{10h} is applicable to bearings made of bearing steel and normal operating conditions (lubricant film present, no contamination, correctly fitted, etc.).

Situations and data differing from these conditions will lead to either a reduction or an increase in service life compared to the nominal service life.

Corrected nominal service life

If the ISO recommendations (DIN ISO 281) are used, improvements to bearing steel, manufacturing processes and the effects of operating conditions may be integrated in the nominal service life calculation.

The theoretical pre-fatigue service life L_{nah} is thus calculated using the formula:

$$L_{nah} = a_1 a_2 a_3 L_{10h}$$

where:

a_1 : failure probability factor.

a_2 : factor for the characteristics and tempering of the steel.

a_3 : factor for the operating conditions (lubricant quality, temperature, speed of rotation, etc).

ROLE OF THE LUBRICANT

The principal role of the lubricant is to avoid direct contact between the metal parts in motion: balls or rollers, slip-rings, cages, etc. It also protects the bearing against wear and corrosion.

The quantity of lubricant needed by a bearing is normally quite small. There should be enough to provide good lubrication without undesirable overheating. As well as lubrication itself and the operating temperature, the amount of lubricant should be judged by considerations such as sealing and heat dissipation.

The lubricating power of a grease or an oil lessens with time owing to mechanical constraints and straight forward ageing. Used or contaminated lubricants should therefore be replaced or topped up with new lubricant at regular intervals.

Bearings can be lubricated with grease, oil or, in certain cases, with a solid lubricant.

LUBRICATION WITH GREASE

A lubricating grease can be defined as a product of semi-fluid consistency obtained by the dispersion of a thickening agent in a lubricating fluid and which may contain several additives to give it particular properties.

| Composition of a grease |
|-------------------------|
| Base oil: 85 to 97% |
| Thickener: 3 to 15% |
| Additives: 0 to 12% |

THE BASE OIL PROVIDES THE LUBRICATION

The oil making up the grease **is of prime importance**. It is the oil that lubricates the moving parts by coating them with a protective film which prevents direct contact. The thickness of the lubricating film is directly linked to the viscosity of the oil, and the viscosity itself depends on temperature. The two main oil types used in the composition of grease are mineral oils and synthetic oils. Mineral oils are suitable for normal applications in a range of temperatures from -30°C to +150°C.

Synthetic oils have the advantage of being effective in severe conditions (extreme variations of temperature, harsh chemical environments, etc.).

THE THICKENER GIVES THE GREASE CONSISTENCY

The more thickener a grease contains, the "harder" it will be. Grease consistency varies with the temperature. In falling temperatures, the grease hardens progressively, and the opposite happens when temperatures rise.

The consistency of a grease can be quantified using the NLGI (National Lubricating Grease Institute) classification. There are 9 NLGI grades, from 000 for the softest greases up to 6 for the hardest. Consistency is expressed by the depth to which a cone sinks into a grease maintained at 25°C.

If we only consider the chemical nature of the thickener, lubricating greases fall into three major categories:

- **Conventional greases with a metallic soap base** (calcium, sodium, aluminium, lithium). Lithium soaps have several advantages over other metallic soaps: a high melting point (180° to 200°), good mechanical stability and good water resistant properties.

- **Greases with a complex soap base.** The main advantage of this type of soap is a very high melting point (over 250°C).

- **Soapless greases.** The thickener is an inorganic compound, such as clay. Their main property is the absence of a melting point, which makes them practically non-liquefying.

ADDITIVES IMPROVE SOME GREASE PROPERTIES

Additives fall into two types, depending on whether or not they are soluble in the base oil.

The most common insoluble additives – graphite, molybdenum disulphide, talc, mica, etc. – improve the friction characteristics between metal surfaces. They are therefore used in applications where heavy pressure occurs.

The soluble additives are the same as those used in lubricating oils: antioxidants, anti-rust agents, etc.

LUBRICATION TYPE

The bearings are lubricated with a polyurea soap-based grease.

DUTY CYCLES

(as per IEC 60034-1)

The typical duty cycles are described below:

1 - Continuous duty - Type S1

Operation at constant load of sufficient duration for thermal equilibrium to be reached (see figure 1).

2 - Short-time duty - Type S2

Operation at constant load during a given time, less than that required for thermal equilibrium to be reached, followed by a rest and de-energized period of sufficient duration to re-establish machine temperatures within 2 K of the coolant (see figure 2).

3 - Intermittent periodic duty - Type S3

A sequence of identical duty cycles, each consisting of a period of operation at constant load and a rest and de-energized period (see figure 3). Here, the cycle is such that the starting current does not significantly affect the temperature rise.

4 - Intermittent periodic duty with starting - Type S4

A sequence of identical duty cycles, each consisting of a significant starting period, a period of operation at constant load and a rest and de-energized period (see figure 4).

5 - Intermittent periodic duty with electrical braking - Type S5

A sequence of periodic duty cycles, each consisting of a starting period, a period of operation at constant load, a period of rapid electrical braking and a rest and de-energized period (see figure 5).

6 - Periodic continuous duty with intermittent load - Type S6

A sequence of identical duty cycles, each consisting of a period of operation at constant load and a period of operation at no load. There is no rest and de-energized period (see figure 6).

7 - Periodic continuous duty with electrical braking - Type S7

A sequence of identical duty cycles, each consisting of a starting period, a period of operation at constant load and a period of electrical braking. There is no rest and de-energized period (see figure 7).

8 - Periodic continuous duty with related changes of load and speed - Type S8

A sequence of identical duty cycles, each consisting of a period of operation at constant load corresponding to a predetermined rotation speed, followed by one or more periods of operation at

other constant loads corresponding to different rotation speeds (in induction motors, this can be done by changing the number of poles). There is no rest and de-energized period (see figure 8).

9 - Duty with non-periodic variations in load and speed - Type S9

This is a duty in which the load and speed generally vary non-periodically within the permissible operating range. This duty frequently includes applied overloads which may be much higher than the full load or loads (see figure 9).


Note: For this type of duty, the appropriate full load values must be used as the basis for calculating overload.

10 - Operation at discrete constant loads - Type S10

This duty consists of a maximum of 4 discrete load values (or equivalent loads), each value being applied for sufficient time for the machine to reach thermal equilibrium. The minimum load during a load cycle may be zero (no-load operation or rest and de-energized period) (see figure 10).


NB: only S1 duty type is affected by IEC 60034-30-1

Fig. 1. - Continuous duty. Type S1.




N = operation at constant load
 T_{max} = maximum temperature attained

Fig. 2. - Short-time duty. Type S2.



N = operation at constant load
 T_{max} = maximum temperature attained

Fig. 3. - Intermittent periodic duty. Type S3.



N = operation at constant load
 R = rest
 T_{max} = maximum temperature attained
 Running factor (%) = $\frac{N}{N + R} \cdot 100$


IMfinity® ATEX 3-phase induction motors - IE3 efficiency class

ATEX Gas, Zones 1 and 2 - ATEX Dust, Zones 21 and 22

Operation

Duty cycle - Definitions


Fig. 4. - Intermittent periodic duty with starting. Type S4.



D = starting
 N = operation at constant load
 R = rest
 T_{max} = maximum temperature attained during cycle

$$\text{Operating factor (\%)} = \frac{D + N}{N + R + D} \cdot 100$$


Fig. 5. - Intermittent periodic duty with electrical braking. Type S5.



D = starting
 N = operation at constant load
 F = electrical braking
 R = rest
 T_{max} = maximum temperature attained during cycle

$$\text{Operating factor (\%)} = \frac{D + N + F}{D + N + F + R} \cdot 100$$


Fig. 6. - Periodic continuous duty with intermittent load. Type S6.



N = operation at constant load
 V = no-load operation
 T_{max} = maximum temperature attained during cycle

$$\text{Operating factor (\%)} = \frac{N}{N + V} \cdot 100$$


Fig. 7. - Periodic continuous duty with electrical braking. Type S7.



D = starting
 N = operation at constant load
 F = electrical braking
 T_{max} = maximum temperature attained during cycle

Operating factor = 1

Fig. 8. - Periodic continuous duty with related changes of load and speed. Type S8.



$F_1 F_2$ = electric braking
 D = starting
 $N_1 N_2 N_3$ = operation at constant loads
 T_{max} = maximum temperature attained during cycle

$$\text{Operating factor} = \frac{D + N_1}{D + N_1 + F_1 + N_2 + F_2 + N_3} \cdot 100 \%$$

$$\frac{F_1 + N_2}{D + N_1 + F_1 + N_2 + F_2 + N_3} \cdot 100 \%$$

$$\frac{F_2 + N_3}{D + N_1 + F_1 + N_2 + F_2 + N_3} \cdot 100 \%$$


IMfinity® ATEX 3-phase induction motors - IE3 efficiency class

ATEX Gas, Zones 1 and 2 - ATEX Dust, Zones 21 and 22

Operation


Duty cycle - Definitions

Fig. 9. - Duty with non-periodic variations in load and speed. Type S9.



- D = starting
- L = operation at variable loads
- F = electrical braking
- R = rest
- S = operation at overload
- C_p = full load
- T_{max} = maximum temperature attained

Fig. 10 - Duty at discrete constant loads. Type S10.



- L = load
- N = rated power for type S1 duty
- $p = p / \frac{L}{N}$ = reduced load
- t = time
- T_p = total cycle time
- t_i = discrete period within a cycle
- $\Delta t_i = t_i / T_p$ = relative duration of period within a cycle
- P_u = electrical losses
- H_N = temperature at rated power for type S1 duty
- ΔH_i = increase or decrease in temperature rise during the i'th period of the cycle

Power is determined according to duty cycle. See "Operation" section, § "Power - Torque - Efficiency - Power Factor (Cos ϕ)".

For duty ratings between S3 and S8 inclusive, the default cycle is 10 minutes unless otherwise indicated.

IMfinity® ATEX 3-phase induction motors - IE3 efficiency class

ATEX Gas, Zones 1 and 2 - ATEX Dust, Zones 21 and 22

Operation

Supply voltage

REGULATIONS AND STANDARDS

The IEC 60038 standard gives the European reference voltage as 230/400V three-phase and 230 V single-phase, with a tolerance of $\pm 10\%$.

The IEC 60034-1 standard states $\pm 2\%$ tolerance for the frequency.

All other voltages and frequencies are available on request.

- For motors of frame size ≤ 160 mm, maximum operating voltage: 700V
- For motors of frame size ≥ 180 mm, maximum operating voltage: 1000 V

EFFECTS ON MOTOR PERFORMANCE

VOLTAGE RANGE

The characteristics of motors will of course vary with a corresponding variation in voltage of $\pm 10\%$ around the rated value.

An approximation of these variations is given in the table below.

| | Voltage variation as a % | | | | |
|-------------------------------------|--------------------------|-------|----|-------|--------|
| | UN-10% | UN-5% | UN | UN+5% | UN+10% |
| Torque curve | 0.81 | 0.90 | 1 | 1.10 | 1.21 |
| Slip | 1.23 | 1.11 | 1 | 0.91 | 0.83 |
| Rated current | 1.10 | 1.05 | 1 | 0.98 | 0.98 |
| Rated efficiency | 0.97 | 0.98 | 1 | 1.00 | 0.98 |
| Rated power factor (cos φ) | 1.03 | 1.02 | 1 | 0.97 | 0.94 |
| Starting current | 0.90 | 0.95 | 1 | 1.05 | 1.10 |
| Nominal temperature rise | 1.18 | 1.05* | 1 | 1* | 1.10 |
| P (Watt) no-load | 0.85 | 0.92 | 1 | 1.12 | 1.25 |
| Q (reactive VA) no-load | 0.81 | 0.9 | 1 | 1.1 | 1.21 |

* According to standard IEC 60034-1, the additional temperature rise must not exceed 10 K within $\pm 5\%$ of UN.

IMfinity® ATEX 3-phase induction motors - IE3 efficiency class

ATEX Gas, Zones 1 and 2 - ATEX Dust, Zones 21 and 22

Operation

Supply voltage

SIMULTANEOUS VARIATION OF VOLTAGE AND FREQUENCY

Within the tolerances defined in guide 106 of the IEC (see § D2.1), machine input and performance are unaffected if the variations are of the same polarity and the voltage/frequency ratio U/f remains constant.

If this is not the case, variations in performance are significant and require the machine specification to be changed.

Variation in main motor parameters (approx.) within the limits defined in IEC Guide 106.

| U/f | P_u | M | N | $\cos \varphi$ | Efficiency |
|----------|--|--------------------------------------|------------------|--|----------------------|
| Constant | $P_u \frac{f'}{f}$ | M | $N \frac{f'}{f}$ | $\cos \varphi$ unchanged | Efficiency unchanged |
| Variable | $P_u \left(\frac{U'/U}{f'/f}\right)^2$ | $M \left(\frac{U'/U}{f'/f}\right)^2$ | $N \frac{f'}{f}$ | Dependent on the machine saturation status | |

M = minimum and maximum values of starting torque.

USE OF 400 V - 50 HZ MOTORS ON 460 V - 60 HZ SUPPLIES

For a rated power at 60 Hz equal to the rated power at 50 Hz, the main characteristics are modified according to the following variations:

- Efficiency increases by 0.5 - 1.5%
- Power factor decreases by 0.5 to 1.5%
- Rated current decreases by 0 to 5%
- IS/IN increases by around 10%
- Slip and rated torque MN, MD / MN, MM / MN remain more or less constant.

USE ON SUPPLIES WITH U' VOLTAGES DIFFERENT FROM THE VOLTAGES IN THE CHARACTERISTICS TABLES

In this case, the machine windings should be adjusted.

As a result, only the current values will be changed and become:

$$I' = I_{400V} \times \frac{400}{U'}$$

PHASE VOLTAGE IMBALANCE

The phase imbalance for voltage is calculated as follows:


$$\text{Phase voltage imbalance as a \%} = 100 \times \frac{\text{maximum difference in voltage compared to the average voltage value}}{\text{average voltage value}}$$

The effect on motor performance is summarized in the table opposite.

When this imbalance is known before the motor is purchased it is advisable, in order to establish the type of motor

required, to apply the derating specified in standard IEC 60892, illustrated on the graph opposite.

| Percentage imbalance | 0 | 2 | 3.5 | 5 |
|---------------------------|-----|------|------|-------|
| Stator current | 100 | 101 | 104 | 107.5 |
| Increase in losses as a % | 0 | 4 | 12.5 | 25 |
| Temperature rise | 1 | 1.05 | 1.14 | 1.28 |




PHASE CURRENT IMBALANCE

Voltage imbalances induce current imbalances. Natural lack of symmetry due to manufacture also induces current imbalances.

The chart opposite shows the ratios in which the negative phase component is equal to 5% (and 3%) of the positive phase components in three-phase current supplies without zero components (neutral absent or not connected).

Inside the curve, the negative phase component is lower than 5% (and 3%).



IMfinity® ATEX 3-phase induction motors - IE3 efficiency class

ATEX Gas, Zones 1 and 2 - ATEX Dust, Zones 21 and 22

Operation

Supply voltage

INSULATION CLASS

The machines in this catalogue have been designed with a class F insulation system for the windings.

Class F allows for temperature rises of 105 K (measured by the resistance variation method) and maximum temperatures at the hot spots in the machine of 155°C (Ref. IEC 60085 and IEC 60034-1).

Complete impregnation with tropicalized varnish of thermal class 180°C gives protection against attacks from the environment, such as: 90% relative humidity, interference, etc.

For special constructions, the winding is class H and impregnated with special varnishes which enable it to operate in conditions of high temperatures with relative air humidity of up to 100%.

The insulation of the windings is monitored in two ways:

a - Dielectric inspection which involves checking the leakage current, at an applied voltage of $(2U + 1000)$ V, in conditions complying with standard IEC 60034-1 (systematic test).

b - Monitoring the insulation resistance between the windings and between the windings and the earth (sampling test) at a DC voltage of 500 V or 1000 V.

TEMPERATURE RISE AND THERMAL RESERVE

Nidec Leroy-Somer motors are built to have a maximum winding temperature rise of 80 K under normal operating conditions (ambient temperature 40°C, altitude below 1000 m, rated voltage and frequency, rated load).

The result is a thermal reserve linked to the following factors:

- a difference of 25 K between the nominal temperature rise (U_n, F_n, P_n) and the permissible temperature rise (105 K) for class F insulation;
- a difference of 10°C minimum at the voltage limits.

In IEC 60034-1 and 60034-2, temperature rise ($\Delta\theta$), is calculated using the winding resistance variation method, with the formula:


$$\Delta T = \frac{R_2 - R_1}{R_1} (235 + T_1) + (T_1 - T_2)$$

R_1 : cold resistance measured at ambient temperature T_1

R_2 : stabilized hot resistance measured at ambient temperature T_2

235: coefficient for a copper winding (for an aluminium winding, the coefficient is 225)

Temperature rise (ΔT^*) and maximum temperatures at hot spots (T_{max}) for insulation classes (IEC 60034-1).



- T_{max} overheating at hot spots
- Temperature rise
- Ambient temperature



IMfinity® ATEX 3-phase induction motors - IE3 efficiency class

ATEX Gas, Zones 1 and 2 - ATEX Dust, Zones 21 and 22

Operation


Starting times and starting current

PERMISSIBLE STARTING TIMES AND LOCKED ROTOR TIMES

The calculated starting times must remain within the limits of the graph opposite which defines maximum starting times in relation to the current surge.

Three successive cold starts and two consecutive hot starts are allowed with return to stop between each start.

Permissible motor starting time as a function of the ratio I_D/I_N .



Note: For IP55 motors with frame size ≥ 355 LD, 2 successive cold starts and 1 hot start are allowed (after thermal stabilisation at rated power). A stop of at least 15 minutes must be observed between each successive start.



DEFINITIONS

The useful power (P_u) at the motor shaft is linked to the torque (M) by the equation:

$$P_u = M \cdot \omega$$

where P_u in W, M in N.m, ω in rad/s and where ω is expressed as a function of the speed of rotation in min^{-1} by the equation:

$$\omega = 2\pi \cdot N / 60$$

The active power (P) drawn from the mains is expressed as a function of the

apparent power (S) and the reactive power (Q) by the equation:

$$S = \sqrt{P^2 + Q^2}$$

(S in VA, P in W and Q in VAR)

The power P is linked to the output power P_u by the equation:

$$P = \frac{P_u}{\eta}$$

where η is the efficiency of the machine.

The output power P_u at the motor shaft is expressed as a function of the phase-to-phase mains voltage (U in Volts), of the absorbed line current (I in Amps) by the equation:


$$P_u = U \cdot I \cdot \sqrt{3} \cdot \cos\phi \cdot \eta$$

where $\cos\phi$ is the power factor found from the ratio:

$$\cos\phi = \frac{P}{S}$$

EFFICIENCY

In accordance with the agreements signed at the Rio and Buenos Aires international conferences, **the new generation of motors with aluminium or cast iron casing** has been designed to improve efficiency in order to reduce atmospheric pollution (carbon dioxide). The improved efficiency of low voltage industrial motors (representing around 50% of installed power in industry) has had a large impact on energy consumption.



Advantages of improvement in efficiency

| Motor characteristics | Effects on the motor | Customer benefits |
|--|--|---|
| Increase in efficiency and in power factor | - | Lower operating costs Longer service life (x2 or 3) Better return on investment |
| Noise reduction | - | Improved working conditions |
| Vibration reduction | - | Quiet operation and longer service life of equipment being driven |
| Temperature reduction | Longer service life of fragile components (insulation system components, greased bearings) | Reduced number of operating incidents and reduced maintenance costs |
| | Increased capability of instantaneous or extended overloads | Wider field of applications (voltages, altitude, ambient temperature, etc.) |

INFLUENCE OF LOAD ON EFFICIENCY AND COS φ

See the selection data.

Overrating motors in a number of applications causes them to operate at about 3/4 load, resulting in optimum motor efficiency.

IMfinity® ATEX 3-phase induction motors - IE3 efficiency class

ATEX Gas, Zones 1 and 2 - ATEX Dust, Zones 21 and 22

Operation

Power - Torque - Cos φ

RATED POWER P_N IN RELATION TO DUTY CYCLE

GENERAL RULES FOR STANDARD MOTORS

$$P_n = \sqrt{\frac{n \times t_d \times [I_D/I_n \times P]^2 + (3600 - n \times t_d)P^2 \times \text{fdm}}{3600}}$$

Iterative calculation where:

- t_{d(s)} starting time achieved with motor rated P_(w)
- n number of (equivalent) starts per hour
- fdm (OF) operating factor (decimal)
- I_D/I_n current demand for motor rated P
- P_{u(w)} motor output power during the duty cycle using OF (in decimal), operating factor
- P_(w) motor rated power selected for the calculation

Note: n and OF are defined in section D4.6.2.

Sp = specification

| | |
|-----|---|
| S1 | OF = 1; n ≤ 6 |
| S2 | n = 1 operating life determined by specification (Sp) |
| S3 | OF according to Sp; n = 0 (no effect of starting on temperature rise) |
| S4 | OF according to Sp; n according to Sp; t _d , P _u , P according to Sp (replace n with 4n in the above formula) |
| S5 | OF according to Sp; n = n starts + 3 n brakings = 4 n; t _d , P _u , P as per Sp (replace n with 4n in the above formula) |
| S6 | $P = \sqrt{\frac{\sum n_i (P_i^2 \cdot t_i)}{\sum n_i t_i}}$ |
| S7 | same formula as S5 but OF = 1 |
| S8 | at high speed, same formula as in S1 at low speed, same formula as in S5 |
| S9 | S8 duty formula after complete description of cycle with OF on each speed |
| S10 | same formula as S6 |

In addition, see the warning regarding precautions to be taken. Variations in voltage and/or frequency greater than standard should also be taken into account. The application should also be taken into account (general at constant torque, centrifugal at quadratic torque, etc.).

DETERMINATION OF THE POWER IN INTERMITTENT DUTY CYCLES FOR ADAPTED MOTORS

RMS POWER IN INTERMITTENT DUTY

This is the rated power absorbed by the driven machine, usually defined by the manufacturer.

If the power absorbed by the machine varies during a cycle, the rms power P is calculated using the equation:

$$P = \sqrt{\frac{\sum n_i (P_i^2 \cdot t_i)}{\sum n_i t_i}} = \sqrt{\frac{P_1^2 \cdot t_1 + P_2^2 \cdot t_2 + \dots + P_n^2 \cdot t_n}{t_1 + t_2 + \dots + t_n}}$$

if, during the working time the absorbed power is:

P1 for period t1

P2 for period t2

Pn for period tn

Power values lower than 0.5 PN are replaced by 0.5 PN in the calculation of rms power P (no-load operation is a special case).

Additionally, it is also necessary to check that for a particular motor of power PN:

- the actual starting time is at most equal to 5 seconds,
- the maximum output of the cycle does not exceed twice the rated output power P,
- there is still sufficient accelerating torque during the starting period.

Load factor (FC)

Expressed as a percentage, this is the ratio of the period of operating time with a load during the cycle to the total powered-up time during the cycle.

Operating factor (fdm / OF)

Expressed as a percentage, this is the ratio of the motor powered-up time during the cycle to the total cycle time, provided that the total cycle time is less than 10 minutes.

Starting class

Class: $n = nD + k \cdot nF + k' \cdot ni$

nD: number of complete starts per hour;

nF: number of electrical braking operations per hour.

“Electrical braking” means any braking directly involving the stator winding or the rotor winding:

- Regenerative braking (with frequency drive, multipole motor, etc).
- Reverse-current braking (the most commonly used).
- DC injection braking.

ni: number of pulses (incomplete starts up to a third of maximum speed) per hour.

k and k' are constants determined as follows:

| | k | k' |
|-----------------------|---|-----|
| Cage induction motors | 3 | 0.5 |

- Reversing the direction of rotation involves braking (usually electrical) and starting.
- Braking with Nidec Leroy-Somer electro-mechanical brakes, as with any other brakes that are independent of the motor, does not constitute electrical braking in the sense described above.

CALCULATING DERATING

- Input criteria (load)
 - RMS power during the cycle = P
 - Moment of inertia related to the speed of the motor: $J_{c/m}$
 - Operating factor = OF (fdm)
 - Class of starts per hour = n
 - Resistive torque during starting = M_r
 - Engine speed = N

- Selection in catalogue
 - Motor rated power = P_n
 - Starting current Id, cosφ
 - Moment of rotor inertia J_m
 - Average starting torque M_{mot}
 - Efficiency at P_n (ηP_n) and at $P(\eta P)$

Calculations

- Starting time:

$$t_d = \frac{\pi}{30} \cdot N \cdot \frac{(J_e + J_r)}{M_{mot} - M_r}$$

- Cumulative starting time per hour: $n \times t_d$

- Energy to be dissipated per hour during starts = sum of the energy dissipated in the rotor (= inertia acceleration energy) and the energy dissipated in the stator during the cumulative starting time per hour:

$$E_d = \frac{1}{2} (J_e + J_r) \left(\frac{\pi \cdot N}{30} \right)^2 \times n + n \times t_d \sqrt{3} U_d \cos \phi_d$$

- Energy to be dissipated during operation

$$E_f = P \cdot (1 - \eta P) \cdot [(OF) \times 3600 - n \times t_d]$$

- Energy that the motor can dissipate at rated power with the Operating Factor for Intermittent Duty.

$$E_m = (OF) \cdot 3600 \cdot P_n \cdot (1 - \eta P_n)$$

- (The heat dissipated when the motor is at rest can be ignored).


Dimensioning is correct if the following relationship is verified =

$$E_m \geq E_d + E_f$$

If the sum of $E_d + E_f$ is lower than $0.75 E_m$, check whether a motor with the next lowest power rating would be more suitable.

EQUIVALENT THERMAL CONSTANT

The equivalent thermal constant enables the machine cooling time to be predetermined.



$$\text{Thermal constant} = \frac{T}{\ln 2} = 1.44 T$$

Cooling curve $\Delta\theta = f(t)$

where:

$\Delta\theta$ = temperature rise in S1 duty

T = time taken to go from the nominal temperature rise to half its value

t = time

ln = natural logarithm

TRANSIENT OVERLOAD AFTER OPERATING IN TYPE S1 DUTY CYCLE

At rated voltage and frequency, the motors can withstand an overload of:
 1.20 for an OF = 50 %
 1.40 for an OF = 10 %

However, it is necessary to ensure that the maximum torque is much greater than 1.5 times the rated torque corresponding to the overload.

NOISE EMITTED BY ROTATING MACHINES

In a compressible medium, the mechanical vibrations of an elastic body create pressure waves which are characterized by their amplitude and frequency. The pressure waves constitute an audible noise if they have a frequency of between 16 Hz and 16000 Hz.

Noise is measured by a microphone linked to a frequency analyser. Measurements are taken in an anechoic chamber on machines at no-load, and a sound pressure level L_p or a sound power level L_w can then be established. Measurement can also be carried out in situ on machines which may be on-load, using an acoustic intensity meter which can differentiate between sound sources and identify the sound emissions from the machine.

The concept of noise is linked to hearing. The auditory sensation is determined by integrating weighted frequency components with isosonic curves (giving a sensation of constant sound level) according to their intensity.

The weighting is carried out on sound meters using filters whose bandwidth takes into account, to a certain extent, the physiology of the human ear:

Filter A: used for low and medium noise levels. High attenuation, narrow bandwidth.

Filter B: used for very high noise levels. Wide bandwidth.

Filter C: very low attenuation over the whole of the audible frequency range.

Filter A is used most frequently for sound levels emitted by rotating machinery. It is this filter which has been used to establish the standardized characteristics.

A few basic definitions:

The unit of reference is the bel, and the sub-multiple decibel dB is used here.

Sound pressure level in dB


$$L_p = 20 \log_{10} \left(\frac{P}{P_0} \right) \quad p_0 = 2 \cdot 10^{-5} \text{ Pa}$$

Sound power level in dB

$$L_w = 10 \log_{10} \left(\frac{P}{P_0} \right) \quad p_0 = 10^{-12} \text{ W}$$


Sound intensity level in dB

$$L_w = 10 \log_{10} \left(\frac{I}{I_0} \right) \quad I_0 = 10^{-12} \text{ W/m}^2$$



CORRECTION OF MEASUREMENTS

For differences of less than 10 dB between 2 sound sources or where there is background noise, corrections can be made by addition or subtraction using the rules below.




Addition of levels

If L_1 and L_2 are the separately measured levels ($L_2 \geq L_1$), the resulting sound level L_R will be obtained by the formula:

$$L_R = L_2 + \Delta L$$

ΔL is found by using the curve above.



Subtraction of levels*

This is most commonly used to eliminate background noise from measurements taken in a "noisy" environment.

If L is the measured level and L_f the background noise level, the actual sound level L_R will be obtained by the calculation:

$$L_R = L - \Delta L$$

ΔL is found by using the curve above.

*This method is the one normally used for measuring sound power and pressure levels. It is also an integral part of sound intensity measurement.

IMfinity® ATEX 3-phase induction motors - IE3 efficiency class

ATEX Gas, Zones 1 and 2 - ATEX Dust, Zones 21 and 22

Operation

Weighted sound level [dB(A)]

Under IEC 60034-9, the guaranteed values are given for a machine operating at no-load under normal supply conditions (IEC 60034-1), in the actual operating position, or sometimes in the direction of rotation as specified in the design.

This being the case, standardized sound power level limits are shown for the values obtained for the machines described in this catalogue. (Measurements were taken in conformity with standard ISO 1680).

Expressed as sound power level (L_w) according to the standard, the level of sound is also shown as sound pressure level (L_p) in the selection data. The maximum standard tolerance for all these values is + 3 dB(A).



For VIK version motors, this +3dB(A) tolerance is not accepted.



The noise levels of the motors in this catalogue are indicated in the selection tables.

VIBRATION LEVELS - BALANCING

Inaccuracies due to construction (magnetic, mechanical and air-flow) lead to sinusoidal (or pseudo sinusoidal) vibrations over a wide range of frequencies. Other sources of vibrations disturb operation: bad fastening of the frame, incorrect coupling, bushing misalignment, etc.


We shall first of all look at the vibrations emitted at the operating frequency, corresponding to an unbalanced load, whose amplitude swamps all other frequencies and on which the dynamic balancing of the mass in rotation has a decisive effect.

Under standard ISO 8821, rotating machines can be balanced with or without a key or with a half-key on the shaft extension.

Standard ISO 8821 requires the balancing method to be marked on the shaft extension as follows:

- Half-key balancing: letter H
- Full key balancing: letter F
- No-key balancing: letter N

The machines in this catalogue are in vibration class level A - level B is available on request.



Measuring system for suspended machines

Measuring system for machines on flexible mountings

The measurement points quoted in the standards are indicated in the drawings above.

At each point, the results should be lower than those given in the tables below for each balancing class and only the highest value is to be taken as the "vibration level".

MEASURED MAGNITUDE

The vibration speed can be chosen as the variable to be measured. This is the speed at which the machine moves either side of its static position. It is measured in mm/s.

As the vibratory movements are complex and non-harmonic, it is the root mean square (rms) value of the speed of vibration which is used to express the vibration level.




Measured are the vibratory displacement amplitude (in μm) or vibratory acceleration (in m/s^2).

If the vibratory displacement is measured against frequency, the measured value decreases with the frequency: high frequency vibrations cannot be measured.

If the vibratory acceleration is measured, the measured value increases with the frequency: low-frequency vibrations (unbalanced loads) cannot be measured here.

The rms speed of vibration is the variable chosen by the standards.

However, if preferred, the table of vibration amplitudes may still be used (for measuring sinusoidal and similar vibrations).



IMfinity® ATEX 3-phase induction motors - IE3 efficiency class

ATEX Gas, Zones 1 and 2 - ATEX Dust, Zones 21 and 22

Operation

Vibration

MAXIMUM VIBRATION MAGNITUDE LIMITS (RMS VALUES) IN TERMS OF DISPLACEMENT, SPEED AND ACCELERATION FOR A FRAME SIZE H (IEC 60034-14)

| Vibration level | Frame size H (mm) | | | | | | | | |
|-----------------|--------------------|---------------|----------------------------------|--------------------|---------------|----------------------------------|--------------------|---------------|----------------------------------|
| | 56 ≤ H ≤ 132 | | | 132 < H ≤ 280 | | | H > 280 | | |
| | Displacement μm | Speed mm/s | Acceleration m/s ² | Displacement μm | Speed mm/s | Acceleration m/s ² | Displacement μm | Speed mm/s | Acceleration m/s ² |
| A | 25 | 1.6 | 2.5 | 35 | 2.2 | 3.5 | 45 | 2.8 | 4.4 |
| B | 11 | 0.7 | 1.1 | 18 | 1.1 | 1.7 | 29 | 1.8 | 2.8 |

For large machines and special requirements with regard to vibration, balancing can be carried out *in situ* (finished assembly). Prior consultation is essential, as the machine dimensions may be modified by the necessary addition of balancing disks mounted on the shaft extensions.










THERMAL PROTECTION

Motors are protected by a manual or automatic overcurrent relay, placed between the isolating switch and the motor. This relay can in turn be protected by fuses.

These protection devices provide total protection of the motor against non-transient overloads. If a shorter reaction time is required, if you want to detect transient overloads, or if you wish to monitor temperature rises at "hot spots" in the motor or at strategic points in the installation for maintenance purposes, it would be advisable to install heat sensors

at sensitive points. The various types are shown in the table below, with a description of each. It must be emphasized that under no circumstances can these sensors be used to carry out direct regulation of the motor operating cycles.

BUILT-IN INDIRECT THERMAL PROTECTION

| Type | Operating principle | Operating curve | Breaker rating (A) | Protection provided | Mounting Number of devices* |
|--|---|---|------------------------------------|---|---|
| Normally open thermal protection PTO | Bimetallic strip, indirectly heated, with normally open (NO) contact  |  | 2.5 A at 250 V with cos ϕ 0.4 | general surveillance for non-transient overloads | Mounted in control circuit 2 in series |
| Normally closed thermal protection PTF | Bimetallic strip, indirectly heated, with normally closed (Nc) contact  |  | 2.5 A at 250 V with cos ϕ 0.4 | general surveillance for non-transient overloads | Mounted in control circuit 2 in parallel |
| Positive temperature coefficient thermistor PTC | Non-linear variable resistor, indirectly heated  |  | 0 | general surveillance for transient overloads | Mounted with associated relay in control circuit 3 in series |
| Thermocouples T ($T < 150^{\circ}\text{C}$) Constantan Copper K ($T < 1000^{\circ}\text{C}$) Copper-nickel | Peltier effect |  | 0 | continuous surveillance of hot spots at regular intervals | Mounted in control panels with associated reading equipment (or recorder) 1 per hot spot |
| Platinum temperature sensor PT 100 | Non-linear variable resistor, indirectly heated |  | 0 | continuous high-precision surveillance of key hot spots | Mounted in control panels with associated reading equipment (or recorder) 1 per hot spot |
| Temperature sensor PT 1000 | Resistance depending on the winding temperature |  | 0 | continuous high-precision surveillance of key hot spots | Mounted in control panels with associated reading equipment (or recorder) 1 per hot spot |

- NRT: nominal running temperature.

- The NRTs are chosen according to the position of the sensor in the motor and the temperature rise class.

* The number of devices relates to the winding protection.

FITTING THE VARIOUS THERMAL PROTECTIONS

- PTO or PTF, in the control circuits.
- PTC, with relay, in the control circuits.
- PT 100 or thermocouples, with associated reading equipment or recorder, in the installation control panel for continuous surveillance.

ALARM AND EARLY WARNING

All protective equipment can be backed up by another type of protection (with different NRTs): the first device will then act as an early warning (light or sound signals given without shutting down the power circuits), and the second device will be the alarm (shutting down the power circuits).

BUILT-IN DIRECT THERMAL PROTECTIONS

For low rated currents, bimetallic strip-type protection can be used. The line current passes through the strip, which shuts down or restores the supply circuit as necessary. The design of this type of protection allows for manual or automatic reset.

The two essential parameters for starting squirrel cage synchronous motors are:

- starting torque,
- starting current.

These two parameters and the resistive torque determine the starting time.

These three characteristics arise from the construction of cage induction motors. Depending on the driven load, it may be necessary to adjust these values to avoid torque surges on the load or current surges in the supply. There are essentially five different types of supply, which are:

- D.O.L. starting,
- star/delta starting,
- soft starting with auto-transformer,
- soft starting with resistors,
- electronic starting.

The tables on the next few pages give the electrical outline diagrams, the effect on the characteristic curves, and a comparison of the respective advantages of each mode.

MOTORS WITH ASSOCIATED ELECTRONICS

Electronic starting modes control the voltage at the motor terminals throughout the entire starting phase, giving very gradual smooth starting:

DIGISTART D2 ELECTRONIC STARTER

This simple, compact electronic starter enables three-phase induction motors to be started smoothly by controlling their acceleration. It incorporates motor protection.



- **18 to 200 A range**

- **Integrated by-pass:** ease of wiring.
- **Simplicity and speed of setup.**

All settings configured with just seven selector switches.

- **Flexibility**

- Mains supply voltages
200 - 440 VAC & 200 - 575 VAC

- **Starting and stopping modes:**

- Current limit.
- Current ramp.
- Deceleration control.
- Communication.
- Modbus RTU, DeviceNet, Profibus, Ethernet/IP, Profinet, Modbus TCP, USB, display console.
- Management of pumping functions.

DIGISTART D3 ELECTRONIC STARTER

Using the latest electronic control technologies to manage transient phases, the DIGISTART D3 range combines simplicity and user-friendliness while offering the user a high-performance, communicating electronic starter, and can achieve substantial energy savings.



- Range from 23 to 1600A / 400V or 690V
- Integrated bypass up to 1000 A:
- Compact design: Up to 60% space saving.
- Energy saving.
- Reduced installation costs.

- **Advanced control**

- Starting and stopping adapt to the load automatically.
- Automatic parameter optimisation by gradually learning the types of start.
- Special deceleration curve for pumping applications which derives from more than 15 years of Nidec Leroy-Somer's experience and expertise.

- **High availability**

- Able to operate with only two power components operational.
- Protection devices can be disabled to implement forced run mode (smoke extraction, fire pump, etc.).

- **Total protection**

- Continuous thermal modelling for maximum motor protection (even in the event of a power cut).
- Trips on configurable power thresholds.
- Control of phase current imbalance.
- Monitoring of motor temperatures and the environment with PTC or PT 100.

- **Other features**

- Installation trips in the event of an earth fault.
- Connection to "Δ" motor (6-wire).
- Starter size at least one rating lower.
- Automatic detection of motor connection.
- Ideal for replacing Y/Δ starters.

- **Communication**

Modbus RTU, DeviceNet, Profibus, Ethernet/IP, Profinet, Modbus TCP, USB.

- **Simplicity of setup**

- 3 parameter-setting levels.
- Preset configurations for pumps, fans, compressors, etc.
- Standard: access to the main parameters.
- Advanced menu: access to all data.
- Storage.
- Time-stamped log of trips.
- Energy consumption and operating conditions.
- Latest modifications.
- Simulate operation by forcing control.
- Display the state of the inputs / outputs
- Counters: running time, number of starts, etc.

- **Starting on variable speed drive**

One of the advantages of variable speed drives is that loads can be started without a current surge on the mains supply, since starting is always performed with no voltage or frequency at the motor terminals.

Operation Braking

OVERVIEW

The braking torque equals the torque developed by the motor increased by the resistant torque of the driven machine.

$$C_f = C_m + C_r$$

C_f = braking torque

C_m = motor torque

C_r = resistive torque

Braking time, i.e.: the time required for an induction motor to change from speed N to stop, is calculated by the formula:


$$T_f = \frac{\Pi \cdot J \cdot N}{30 \cdot C_f(\text{moy})}$$

T_f (in s) = braking time

J (in kgm^2) = moment of inertia

N (in min^{-1}) = speed of rotation

C_f (av) (in N.m) = average braking torque during the time period



Curves $I = f(N)$, $C_m = f(N)$, $C_r = f(N)$, in the motor's starting and braking zones.

I = current absorbed

C = torque value

C_f = braking torque

C_r = resistive torque

C_m = motor torque

N = speed of rotation

g = slip

N_s = synchronous speed

AB = reverse current braking

BC = starting, acceleration

DC = regenerative braking

EF = reversal

REVERSE-CURRENT BRAKING

This method of braking is obtained by reversing two of the phases.

In general, an isolator disconnects the motor from the supply at the time the speed changes to $N=0$.

In cage induction motors, the average braking torque is generally greater than the starting torque.

Braking torque varies in different types of machine, as it depends on the rotor cage construction.

This method of braking involves a large amount of absorbed current, more or less constant and slightly higher than the starting current.

Thermal stresses during braking are three times higher than during acceleration.

Accurate calculations are required for repetitive braking.

Note: The direction of rotation of a motor is changed by reverse-current braking and restarting.

Thermically, one reversal is the equivalent of 4 starts. Care must therefore be taken when choosing a machine.

DC INJECTION BRAKING

Operating stability can be a problem when reverse-current braking is used, due to the flattening out of the braking torque curve in the speed interval $(0, -N_s)$.


There is no such problem with DC injection braking: this can be used on both cage induction and slip-ring motors. With this braking method, the induction motor is connected to the mains and braking occurs when the AC voltage is cut off and DC voltage is applied to the stator.

There are four different ways of connecting the windings to the DC voltage.

The DC voltage applied to the stator is usually supplied by a rectifier plugged into the mains.

Thermal stresses are approximately three times lower than for reverse-current braking.

The shape of the braking torque curve in the speed interval $(0, -N_s)$ is similar to that of the curve $T_m = f(N)$ and is obtained by changing the abscissa variable to $N_f = N_s - N$.



Motor winding connections for DC voltage

The braking current is calculated using the formula:

$$I_f = k1_i \times I_d \sqrt{\frac{C_f - C_b}{k2 - C_d}}$$

The values of k1 according to the 4 connections are:

$$k1_a = 1.225 \quad k1_c = 2.12$$

$$k1_b = 1.41 \quad k1_d = 2.45$$

The braking torque can be found by:

$$C_f = \frac{\pi \cdot J \cdot N}{30 \cdot T_f}$$

In the formulae above:

If (in A) = direct current for braking

Id (in A) = starting current in the phase
 = $\frac{1}{\sqrt{3}}$ Id as per catalogue (for Δ connection)

Cf (in N.m) = average braking torque during the time period (Ns, N)

Cfe (in N.m) = average external braking torque

Cd (in N.m) = starting torque

J (in kgm²) = total moment of inertia at motor shaft

N (in min⁻¹) = speed of rotation

Tf (in s) = braking time

k1i = numerical factors for connections a, b, c and d in the diagram

k2 = numerical factors taking account of the average braking torque (k2 = 1.7)

The DC voltage to be applied to the windings is calculated by:

$$U_f = k3_i \cdot k4 \cdot I_f \cdot R1$$

k3 values for the four diagrams are as follows:

$$k3_a = 2 \quad k3_b = 1.5$$

$$k3_c = 0.66 \quad k3_d = 0.5$$

Uf (in V) = DC voltage for braking

If (in A) = direct current for braking

R1 (in Ω) = stator phase resistance at 20°C

k3i = numerical factors for diagrams a, b, c and d

k4 = numerical factor taking account of the temperature rise in the motor (k4 = 1.3)

MECHANICAL BRAKING

Electromechanical brakes (DC or AC field excitation) can be fitted at the non-drive end of the motor.

For further details, see our “Brake motors” catalogue.

DECELERATION BRAKES

For safety reasons, deceleration brakes are fitted at the rear (non-drive end) of motors used on hazardous machines (for example, where cutting tools may come into contact with the operator).

The range of brakes is determined by its braking torques:

2.5 - 4 - 8 - 16 - 32 - 60 N.m

The appropriate brake is selected in the factory according to the number of motor poles, the driven inertia, the number of brakings per hour and the required braking time.



IMfinity® ATEX 3-phase induction motors - IE3 efficiency class

ATEX Gas, Zones 1 and 2 - ATEX Dust, Zones 21 and 22

Operation

Operation with speed drive

APPLICATIONS AND CHOICE OF SOLUTIONS

In principle, there are three typical types of load. It is essential to determine the speed range and the application torque (or power) in order to select the drive system:

Centrifugal machines

The torque varies as the square of the speed (or cube of the power). The torque required for acceleration is low (about 20% of rated torque). The starting torque is low.

- Sizing: depends on the power or torque at maximum speed.
- Drive selected for normal duty.

Typical applications: ventilation, pumping, etc.

Applications with constant torque

The torque remains constant throughout the speed range. The torque required for acceleration may be high, depending on the machine (higher than the rated torque).

- Sizing: depends on the torque required over the entire speed range.
- Drive selected for heavy duty.

Typical machines: extruders, crushers, gantries, presses, etc.

Applications with constant power

The torque decreases as the speed increases. The torque required for acceleration is no more than the rated torque. The starting torque is at its maximum.

- Sizing: depends on the torque required at minimum speed and the range of operating speeds.
- Drive selected for heavy duty.
- An encoder feedback is advisable for improved regulation.


Typical machines: winders, machine tool spindles, etc.

4-QUADRANT MACHINES

These applications have a torque/speed operating type as described opposite, but the load becomes a driving load in certain stages of the cycle.

- Sizing: see above depending on the load.
- In the case of repetitive braking, install a reinforced insulation system (RIS).
- Drive selection: to dissipate the power from a driving load, it is possible to use a braking resistor, or to send power back to the grid. In the latter case, a regenerative or 4-quadrant drive should be used.

Typical machines: centrifuges, travelling cranes, presses, machine tool spindles, etc.



CHOICE OF INVERTER / MOTOR COMBINATION


The curve below expresses the output torque of a 50 Hz motor (2, 4 or 6 poles) supplied by a drive.

For a frequency inverter with power P_N operating at constant power P within a determined range of speeds, it is possible to optimise the choice of motor and its number of poles to give a maximum amount of torque.

Example: the Unidrive M400-034-00056A-3.5 T drive can supply the following motors:

- LSSES 90 - 2 p - 2.2 kW - 7.1 N.m*
- LSSES 100 - 4 p - 2.2 kW - 14.6 N.m*
- LSSES 112 - 6 p - 2.2 kW - 21.9 N.m*

The choice of the motor and speed drive combination will therefore depend on the application.



USING THE MOTOR AT CONSTANT TORQUE FROM 0 TO 87 HZ

Using motors with a Δ connection in conjunction with a frequency inverter increases the constant torque range from 50 to 87 Hz, which can increase the power by the same ratio.

The size of the frequency inverter is determined by the current value at 230 V and programmed with a voltage/frequency ratio of 400 V, 87 Hz.

Example of selection with 4 poles:



- For constant torque of 195 Nm from 750 to 2600 min⁻¹:
- > selection: 30 kW 4P LSES motor + 100 A drive

Example of selection with 2 poles:

- For constant power of 4 kW from 3000 to 5200 min⁻¹:
- > selection: 3 kW 2P LSES motor + 11 A drive

CAUTION: Max. mechanical speed by frame size to be complied with.

**Characteristics of motors on drives
230V Δ connection 400 V 50 Hz supply**



MOTORS USED WITH VARIABLE SPEED DRIVE

GENERAL

Drive control by a frequency inverter can in fact result in an increase in the machine temperature rise, due to a significantly lower supply voltage than on the mains, additional losses related to the wave form produced by the drive (PWM) and the reduction in speed of the cooling fan.

Standard IEC 60034-17 describes numerous good practices for all types of electric motor, however since this is Nidec Leroy-Somers' area of specialist expertise, we describe the best ways to deal with variable speed in the section below.

The homologation conditions of our safety motors allow them to operate on frequency drives on condition that the required precautions are taken to ensure that under all circumstances there is compliance with the temperature class marked on the nameplate.

Consequently a reduction must generally be made in the rated power of the motor. Derating tables have been produced by our design bureau based on under-load tests on platforms, and on the requirements of IEC 60034-17. Depending on the application, the desired speed range and the torque profile of the driven machine, Nidec Leroy-Somer will select the most suitable safety motor. The drive, if of a type not designed for operation in an explosive zone, must be located in a non-explosive zone.

The specific instructions given in the specific instruction manuals must be followed if a drive is used. In particular the following minimum requirements must be observed:

- Check that the drive switching frequency is 3kHz minimum.
- Check that the motor has a second nameplate indicating the maximum characteristics and performance levels of the motor during its use at variable speed.
- The reference voltage, usually 400V 50Hz, is given on the motor nameplate. The drive must deliver a constant voltage/frequency ratio.

- Programme the maximum current value as well as the min and max frequency values shown on the second nameplate of the motor into the drive.
- Connect all the temperature sensors present on the motor (windings and, if relevant, bearing housings) to safety devices which are independent of those used for operation under normal conditions.

NAMEPLATES ON MOTORS OPERATING WITH VARIABLE SPEED DRIVES

The performance levels of motors operating using variable speed drives, shown on the speed drive nameplate, are values obtained with PWM supplies, with 360V at the motor terminals, in continuous operation:

That is, for the following two cases:

- * **400V rated voltage before drive + drive voltage drop of 40V.**
- * **Rated voltage -10% + drive with no voltage drop.**

Please contact us for other cases.

Some applications require special construction specifications:

- Do not use a motor for lifting that is not rated S3 or S4.
- Do not use the motor with a different duty type from that on the nameplate and in particular not in lifting applications.

In certain cases, the use of forced ventilation (where the fan is driven by an auxiliary motor whose type has been certified) may prove necessary. For small motors (frame height less than 160), the standard self-ventilated cooling mode (IC411) is nevertheless to be preferred.

A device for measuring the actual speed of the motor, using an incremental or absolute encoder which is ATEX certified, may also be installed at the rear of most of our safety motors.

ATEX motors supplied through a frequency inverter are equipped with thermal protective devices in the winding. These must operate independently of measuring and control devices required for operation. Our derating tables are based on a drive supply whose switching frequency is equal to or greater than 3 kHz.

The nameplates of our motors indicate the T/Tn ratio (see electrical characteristics tables for each series).

For use of the motor with a drive with voltage drop and continuous operation (1h min) in the 45-50 Hz frequency range, use T/Tn = 95%.

MOTOR ADAPTATION

A motor is always characterised by the following parameters depending on the design:

- temperature class
- voltage range
- frequency range
- thermal reserve

CHANGE IN MOTOR BEHAVIOUR

The above parameters are subject to change when the power is supplied by the drive, due to the following phenomena:

- voltage drops in the drive components,
- current increase in proportion with the decrease in voltage,
- difference in motor power supply according to the type of control (flux vector or U/f).

The main consequence is an increase in the motor current, which leads to higher copper losses and therefore a higher winding temperature (even at 50 Hz).

Reducing the speed leads to a reduction in air flow and hence a reduction in cooling efficiency, and as a result the motor temperature rise will increase again. Conversely, during prolonged operation at high speed, as the noise emitted by

the ventilation can become troublesome for the environment, the use of forced ventilation is recommended.

Above the synchronous speed, the iron losses increase and hence cause further temperature rise in the motor.

The control mode influences the heating of the motor according to its type:

- A U/f ratio gives the fundamental voltage maximum at 50 Hz but requires more current at low speed to obtain a high starting torque and therefore generates a temperature rise at low speed when the motor is poorly ventilated.

- Flux vector control requires less current at low speed while providing significant torque but regulates the voltage at 50 Hz and causes a voltage drop at the motor terminals, therefore requiring more current at the same power.

Consequences for the motor

Recap: Nidec Leroy-Somer recommends the connection of PTC sensors, monitored by the drive, to protect the motor as much as possible.

CONSEQUENCES OF SUPPLY FROM DRIVES

Supplying the motor from a variable speed drive with a diode rectifier induces a voltage drop (~5%).

Some PWM techniques can be used to limit this voltage drop (~2%), to the detriment of the machine temperature rise (injection of harmonics of orders 5 and 7).

The non-sinusoidal signal (PWM) provided by the drive generates voltage peaks at the winding terminals due to the significant voltage variations relating to switching of the IGBTs (also called dV/dt). Repeated overvoltages can eventually damage the windings depending on their value and/or the motor design.

The value of the voltage peaks is proportional to the supply voltage. This value can exceed the limit voltage for the windings which is related to the wire grade, the impregnation type and the insulation that may or may not be present in the slot bottoms or between phases.

Another reason for attaining high voltage values is when regeneration phenomena occur in the case of a driving load, hence the need to prioritise freewheel stops or stops that follow the longest permissible ramp.

WINDING INSULATION AND RECOMMENDATIONS RELATING TO THE MECHANISM OF ROTATION

The insulation systems used for Nidec Leroy-Somer motors and recommendations for protection systems on the mechanisms of rotation are indicated in our good practice guide ref. 5626.

EXTREME OPERATING CONDITIONS AND OTHER POINTS

MOTOR CONNECTIONS

Nidec Leroy-Somer does not recommend any specific connections for applications operating with a single motor on a single drive.

TRANSIENT OVERLOADS

Drives are designed to withstand transient overload. When the overload values are too high, the system will automatically shut down. Nidec Leroy-Somer motors are designed to withstand these overloads, however in the event of very repetitive operation we still recommend use of a temperature sensor in the winding of the motor.

STARTING TORQUE AND CURRENT

Thanks to advances in control electronics, the torque available when the motor is switched on can be adjusted to a value between the rated torque and the variable speed drive breakdown torque. The starting current will be directly related to the torque (120 or 180%).

ADJUSTING THE SWITCHING FREQUENCY

The variable speed drive switching frequency has an impact on losses in the motor and the drive, on the acoustic noise and the torque ripple.

A low switching frequency has an adverse effect on temperature rise in motors.

Nidec Leroy-Somer recommends a variable speed drive switching frequency of at least 3 kHz.

In addition, a high switching frequency optimises the acoustic noise and torque ripple level.

OPERATION AT SPEEDS HIGHER THAN THOSE ASSIGNED BY THE MAINS FREQUENCIES

(speed higher than 3600 min^{-1}) can be risky:

- the cage may be damaged,
- bearing life may be impaired,
- there may be increased vibration,
- etc.

When high-speed motors are used, they often need to be adapted, and an in-depth mechanical and electrical design study is needed.

CHOICE OF MOTOR

There are two possibilities:

a - The frequency inverter is not supplied by Nidec Leroy-Somer

All the motors in this catalogue can be used with a frequency inverter. Depending on the application, motors will need to be derated by around 10% compared to the motor operating curves in order to guarantee that motors will not be damaged.

b - The frequency inverter is supplied by Nidec Leroy-Somer


As these two ranges have been specifically designed for use in combination, excellent performance is guaranteed, in accordance with the curves on the previous pages.

GOOD WIRING PRACTICES AND TYPICAL MOTOR DRIVE CONNECTIONS


The wiring and connection rules for Nidec Leroy-Somer motors are indicated in our good practice guide, ref. 5626.

IMfinity® ATEX 3-phase induction motors - IE3 efficiency class
ATEX GAS motors - Zone 1
FLSD series
General information - Designation

| | | | | | | | | | |
|---|---|---|---|----|-------------------|----|--------------|----------------------------|----|
| ATEX GAS motors - Zone 1 | FLSD series | | | | | | | | |
|  | II | 2 | G | Ex | db or db eb | II | B or C | T4 or T5 or T6 | Gb |
| | Premium Efficiency IE3 powered by the mains IE3 powered by the drive | | | | | | | | |



The complete motor **reference** described below will enable you to **order** the desired equipment.
 The selection method consists of following the terms in the designation.



NAMEPLATES

The nameplate identifies the motors, indicates the main performance and shows compatibility of the motor

concerned with the main standards and regulations concerning them. All motors in this catalogue with power between 0.75 and 400 kW are fitted with

two information plates: one indicating the motor's performance when supplied from the mains, and the other the motor's performance when supplied from a drive.

DEFINITION OF SYMBOLS USED ON NAMEPLATES

☉ Legal mark of conformity of product to the requirements of European Directives

SPECIFIC MARKING: ATEX  **IECEX**

II 2G or II 2G and II 2D: ATEX/IECEX marking

Ex db or db(eb): "flameproof enclosure" protection type.

II B or II Cv: "gas" equipment group

T4: "gas" temperature class

Gb: "gas" EPL level

Ex tb: "dust" protection type (option)

IIIC: "dust" equipment group (if tb)

T125°C: max. surface temperature (if tb)

Db: "dust" EPL level

0080: INERIS Notified Body

INERIS ... X: ATEX attestation number

IECEX INE...: IECEX certificate No.

| Zone | ATEX/IECEX marking | Gas protection mode marking | Dust protection mode marking (if tb) | Min. protection rating |
|------------------|--|--|--|------------------------|
| / |  I M2 | Ex db I Mb | | IP55 |
| 1 & 2 |  II 2 G | Ex db IIB T4 Gb (1) Ex db IIC T4 Gb (1) Ex db IIB T5 Gb (1) Ex db IIC T5 Gb (1) Ex db IIB T6 Gb (1) Ex db IIC T6 Gb (1) | | IP55 |
| 1 & 21 2 & 22 |  II 2D | Ex db IIB T4 Gb (1) Ex db IIC T4 Gb (1) Ex db IIB T5 Gb (1) Ex db IIC T5 Gb (1) Ex db IIB T6 Gb (1) Ex db IIC T6 Gb (1) | Ex tb IIIC T125°C Db Ex tb IIIC T125°C Db Ex tb IIIC T100°C Db Ex tb IIIC T100°C Db Ex tb IIIC T85°C Db Ex tb IIIC T85°C Db | IP65 |

(1): or Ex db eb

MOTOR SYMBOLS

MOT 3 ~: three-phase AC motor

FLSD: motor type

280: frame size

M: housing symbol

4: 4 poles

B3: operating position

No.: Serial number

2017: year of construction

IM: operating position symbol

°C: maximum ambient temperature

Ins. cl.: winding insulation class

S: standard operating duty

%: operating duty

d/h: number of starts per hour

SF: duty factor

IE %: efficiency level and efficiency, at rated load and voltage

2/4: efficiency at 2/4 load

3/4: efficiency at 3/4 load

kg: weight

DE: drive end bearing

NDE: non drive end bearing

g: quantity of grease to be added per bearing at each re-lubrication (in g)

h: interval in hours between re-lubrication

IP: protection rating

IK: shock resistance

m: maximum operating altitude

V: supply voltage

Hz: supply frequency

min⁻¹: speed of rotation (rpm)

kW: rated power

A: rated current

cos: power factor

%: efficiency at 4/4 load

Δ: delta coupling

∧: star coupling

POLYREX EM 103: bearing grease reference

Insulated bearing: NDE: isolated non drive end bearing

Manufactured by CEB: equipment manufacturer

EAC Ex: equipment for explosive atmospheres certified for Eurasia

cURus E68554: insulation system class F homologated for USA and Canada

 : vibration level code

 : balancing mode code

 : starting requirements code

279 E: plate reference

IMfinity® ATEX 3-phase induction motors - IE3 efficiency class

ATEX GAS motors - Zone 1

FLSD series - Cast iron

General information - Identification and marking

Inverter settings PWM: characteristics for setting the PWM drive enabling compliance with the motor temperature class

Motor performance valid for 400 V - 50 Hz at inverter input: motor performance valid for 400V - 50Hz at drive input

Duty S9: performances given for S9 duty

Min.Fsw: minimum switching frequency of the drive in kHz

Nmax: admissible maximum motor speed in min⁻¹ (rpm)

PTC 140°C: PTC sensor type - temperature limit = 140°C

IVIC: pulse voltage insulation class code

CAST IRON MOTOR NAMEPLATES - FLSD ZONE 1

Mains supply plate

MOT. 3~ FLSD 280 M4 B3
N° E0777501EC01 2017 645 kg 0080
IE3
 DE 6316 C3 13 g 18500 h IP 55 1000 m
 NDE 6314 C3 10 g 18500 h IK 08 IM 1001
 40°C

| V | Hz | min ⁻¹ | kW | A | cos φ | % |
|-------|----|-------------------|-----|-----|-------|------|
| Δ 400 | 50 | 1485 | 90 | 166 | 0,83 | 94,9 |
| Δ 415 | | | | 96 | | |
| Δ 415 | | 1485 | | 163 | 0,81 | 95,1 |
| Δ 460 | 60 | 1785 | 104 | 164 | 0,84 | 95 |

 POLYREX EM 103 PTC 140°C
 II 2 G - Ex db IIB T4 Gb EAC : 1Ex db IIB T4 Gb X
 Manufactured by CEB - F90500 BEAUCOURT
 INERIS 19ATEX0031X IECEx INE 19.0055X
 279 E

Drive supply plate

MOT. 3~ FLSD 280 M4 B3
N° E0777501EC01 0080
IE3
 Inverter settings PWM

| V | Hz | min ⁻¹ | kW | A | cos φ |
|-------|----|-------------------|----|-----|-------|
| Δ 400 | 50 | 1485 | 90 | 166 | 0,83 |

 Motor performance valid for : 400 V - 50 Hz at inverter input

| Hz | 10 | 17 | 25 | 50 | 60 | 87 |
|-------|----|----|----|-----|-----|----|
| T/Tn% | 87 | 92 | 98 | 100 | 100 | 57 |

 Duty S9 Min. Fsw : 3 kHz Nmax : 2610 min⁻¹
 PTC 140°C
 280 E
IVIC C

3~2P FLSD90SL
IP55 IK08 T
IE3
 Ta40°C Ins.Cl.F S1 1000m 33kg 84.2%
 IEC Ex
 INERIS 10 ATEX 0025X IECEx INE10.0012X
 II 2 G Ex db IIB T4 Gb
 DE: 6205 ZZ C3
 NDE: 6205 ZZ C3

| V | Hz | min-1 | kW | cosψ | A |
|-------|----|-------|------|------|------|
| Δ 230 | 50 | 2890 | 1.50 | 0.85 | 5.20 |
| Δ 400 | 50 | 2890 | 1.50 | 0.85 | 3.00 |
| Δ 415 | 50 | 2900 | 1.50 | 0.83 | 2.95 |
| Δ 460 | 60 | 3505 | 1.50 | 0.83 | 2.65 |

 PTC 150°C

3~2P FLSD90SL
IP55 IK08 T
IE3
 Ta40°C Ins.Cl.F S9 1000m 33kg
 IEC Ex
 INERIS 10 ATEX 0025X IECEx INE10.0012X
 II 2 G Ex db IIB T4 Gb
 DE: 6205 ZZ C3
 NDE: 6205 ZZ C3
 Inverter settings

| V | Hz | min-1 | kW | cosψ | A |
|-------|----|-------|------|------|------|
| Δ 400 | 50 | 2870 | 1.50 | 0.87 | 3.25 |

 Motor performance

| Hz | 10 | 17 | 25 | 50 | 87 | min.Fsw (kHz) |
|-------|-----|-----|-----|-----|----|---------------|
| T/Tn% | 100 | 100 | 100 | 100 | 57 | 3 |

 PTC 150°C
IVIC C

The motor enclosure is designed in such a way that no internal explosion can be transmitted to the explosive atmosphere around the motor.

This enclosure must withstand, without being damaged, any pressure levels caused by an internal explosion.

The shape, length and gap of the assembly joints, at shaft passages, cable entries, etc., are designed to render hot gases on the outside non-hazardous.

In addition, the external temperature of the motor enclosure must not exceed the ignition temperature of the explosive atmosphere present in the installation zone.

No mechanism outside the motor enclosure (e.g., fan) must be a potential source of sparks, arcing or dangerous overheating.

The Ex db motors from Nidec Leroy-Somer are certified to comply with Directive 2014/34/EU and the IECEx system regulations.

Lastly, Ex db or Ex db eb motors can also be used for applications in Ex t zone 21 dusty atmospheres.

The following definitions are therefore possible:

- Ex tb IIIB T125°C Db, IP65 for zone 21 + Ex db or Ex db eb, IIB or IIC T4 Gb
- Ex tb IIIC T125°C Db, IP65 for zone 21 + Ex db or Ex db eb, IIB or IIC T4 Gb

Since the ingress of dust is prevented, only the external temperature class is important for both applications: T4 (=135°C) for gas and T125°C for dust

| Designations | Materials | Comments |
|-----------------------------|---|---|
| Finned housing | Cast iron | - with integral feet , or without feet • 4, 6 or 8 securing holes for frames with feet • lifting rings for frame size ≥ 90 - external earth terminal |
| Stator | Insulated low-carbon magnetic steel laminations Electroplated enamelled copper | - low carbon content guarantees long-term lamination pack stability - semi-enclosed slots - class F insulation - 1 set of PTC sensors in the windings from FLSD 80 to FLSD 315 |
| Rotor | Insulated low-carbon magnetic steel laminations Aluminium (A5L) or copper | - squirrel cage with sloping bars - rotor cage pressure die-cast in aluminum (or alloys for special applications) or copper-soldered - assembly by hot shrinking on the shaft or by keying - class A rotor balanced dynamically, 1/2 key |
| Shaft | Steel | - for frame size ≤ 132: • tapped at drive end • closed keyway - for frame size ≥ 160: • tapped at drive end • open keyway |
| End shields | Cast iron | |
| Bearings and lubrication | | - regreasable bearings from frame size 160 - bearing preloaded at the rear from 80 to 280 and preloaded at the front from 315 S |
| Labyrinth seal Lip seals | Technopolymer or steel Synthetic rubber | - gasket or labyrinth seal at the front and rear for frame sizes 80 to 132 and 315 - decompression grooves for frame sizes 160 to 280 and 315 |
| Fan | Composite material up to and including 280 Metallic from 315, and in IIIC | - bi-directional: straight blades |
| Fan cover | Steel plate | - fitted with a drip cover (option) |
| Terminal box | Cast iron | - "db" type in standard version and "eb" type as an option (see below) - equipped with one or more ISO drill holes with plug or cable gland - directional: 4 positions - indoor earth terminal - terminal block |

IMfinity® ATEX 3-phase induction motors - IE3 efficiency class

ATEX GAS motors - Zone 1

FLSD series - Cast iron

General information - Description

CORROBLOC FINISH

The Corrobloc finish is a top coat for the basic cast iron motor described above. In addition to the basic construction its special finishes resist corrosion in particularly harsh environments. and these qualities are enhanced with age.

| Designations | Materials | Comments |
|---------------------|-----------------------------------|---|
| Stator - Rotor | | - protection and anti-corrosion for frame sizes 80 to 132 |
| Nameplate | Stainless steel | - nameplate: indelible marking |
| Fastenings | Steel with anti-corrosion coating | - stainless steel screws from FLSD 160 on |
| Terminal box | Body and cover made of cast-iron | |
| Cable gland or plug | Brass | - Ex protection mode identical to the terminal box |
| Paint finish | | - C4M system (see Paint section) |

INCREASED SAFETY TERMINAL BOX VERSION Ex db eb, IIB or IIC

These motors have a "db" type flameproof casing and an "eb" increased safety type terminal box.

| | | |
|--------------|-----------|---|
| Terminal box | Cast iron | <ul style="list-style-type: none"> - "eb" type increased safety - "db" type separation between motor enclosure and "eb" type terminal box - safety block |
|--------------|-----------|---|

VERSIONS Ex db IIC and Ex db eb IIC


Available up to frame size 315 included.



Flameproof motor - "db" terminal box



Flameproof motor - "eb" terminal box



| Type | Gas group | Rated power P _n kW | Rated torque M _n N.m | Starting torque/ Rated torque M _d /M _n | Maximum torque/ Rated torque M _m /M _n | Starting current/ Rated current I _d /I _n | Moment of inertia J kg.m ² | Weight IM B3 kg | Noise LP db(A) | 400V 50Hz | | | | | | | |
|----------------|-----------|-------------------------------------|---------------------------------------|--|---|--|---|-----------------------|----------------------|---------------------------------------|--------------------------------------|-------------------------------------|----------|------|--------------|--------------|------|
| | | | | | | | | | | Rated speed N min ⁻¹ | Rated current I _n A | Efficiency IEC 60034-2-1 2007 | | | Power factor | | |
| | | | | | | | | | | | | 4/4 | η 3/4 | 2/4 | 4/4 | Cos φ 3/4 | 2/4 |
| 2 poles | | | | | | | | | | | | | | | | | |
| FLSD 80 L | IIB-IIC | 0.75 | 2.5 | 3.1 | 3.5 | 7.6 | 0.00096 | 25 | 59 | 2885 | 1.6 | 82.6 | 82.7 | 80.5 | 0.82 | 0.75 | 0.62 |
| FLSD 90 SL | IIB-IIC | 1.1 | 3.7 | 2.6 | 3.2 | 6.85 | 0.00203 | 28 | 59 | 2885 | 2.2 | 85.6 | 86.6 | 85.9 | 0.85 | 0.79 | 0.68 |
| FLSD 90 SL | IIB-IIC | 1.5 | 5 | 2.9 | 3 | 7 | 0.00225 | 30 | 68 | 2890 | 3 | 85.1 | 86.1 | 85.4 | 0.85 | 0.79 | 0.68 |
| FLSD 90 LU | IIB-IIC | 2.2 | 7.3 | 3.5 | 3.6 | 8.2 | 0.00294 | 36 | 70 | 2895 | 4.3 | 87.0 | 88.2 | 88.1 | 0.86 | 0.80 | 0.70 |
| FLSD 100 L | IIB-IIC | 3 | 9.9 | 3.2 | 3.6 | 8.1 | 0.00370 | 40 | 66 | 2895 | 5.8 | 87.1 | 88.1 | 87.8 | 0.86 | 0.81 | 0.70 |
| FLSD 112 MG | IIB-IIC | 4 | 13.1 | 2.5 | 3 | 7.25 | 0.00944 | 50 | 70 | 2920 | 7.3 | 88.5 | 89.5 | 89.4 | 0.89 | 0.85 | 0.77 |
| FLSD 132 SM | IIB-IIC | 5.5 | 17.9 | 2 | 2.8 | 6.4 | 0.00993 | 73 | 67 | 2935 | 10.3 | 90.0 | 90.8 | 90.4 | 0.86 | 0.82 | 0.73 |
| FLSD 132 SM | IIB-IIC | 7.5 | 24.4 | 2.1 | 2.9 | 6.95 | 0.01120 | 86 | 67 | 2940 | 13.8 | 91.2 | 92.0 | 91.8 | 0.86 | 0.82 | 0.75 |
| FLSD 132 M | IIB-IIC | 9 | 29.2 | 2.5 | 3.2 | 7.55 | 0.01222 | 96 | 67 | 2940 | 16.8 | 91.3 | 92.0 | 91.7 | 0.85 | 0.80 | 0.72 |
| FLSD 160 MA | IIB-IIC | 11 | 35.6 | 2.7 | 3.2 | 7.51 | 0.041 | 170 | 68 | 2954 | 20.1 | 91.2 | 91.4 | 90.7 | 0.87 | 0.84 | 0.76 |
| FLSD 160 MB | IIB-IIC | 15 | 48.7 | 2.8 | 3.1 | 7.54 | 0.048 | 181 | 68 | 2951 | 26.7 | 91.9 | 92.7 | 92.5 | 0.89 | 0.87 | 0.81 |
| FLSD 160 L | IIB-IIC | 18.5 | 59.9 | 2.7 | 3.3 | 7.84 | 0.055 | 190 | 68 | 2950 | 32.6 | 92.4 | 92.9 | 92.9 | 0.88 | 0.86 | 0.79 |
| FLSD 180 M | IIB-IIC | 22 | 71.4 | 2.5 | 3.2 | 7.66 | 0.070 | 258 | 69 | 2955 | 38.5 | 93.4 | 94.0 | 93.9 | 0.89 | 0.87 | 0.81 |
| FLSD 200 LA | IIB-IIC | 30 | 97.1 | 2.2 | 3 | 7.35 | 0.141 | 344 | 77 | 2954 | 54.1 | 93.4 | 93.6 | 93.1 | 0.86 | 0.82 | 0.75 |
| FLSD 200 LB | IIB-IIC | 37 | 121.2 | 2.1 | 3 | 7.04 | 0.141 | 350 | 76 | 2945 | 65.2 | 93.7 | 93.9 | 93.9 | 0.88 | 0.86 | 0.80 |
| FLSD 225 MR | IIB-IIC | 45 | 145.9 | 2.4 | 3 | 7.69 | 0.164 | 376 | 76 | 2948 | 78.6 | 94.0 | 94.6 | 94.6 | 0.88 | 0.86 | 0.79 |
| FLSD 250 M | IIB-IIC | 55 | 177.8 | 1.9 | 2.6 | 6.92 | 0.356 | 572 | 80 | 2970 | 93.9 | 94.7 | 95.0 | 94.6 | 0.90 | 0.88 | 0.83 |
| FLSD 280 S | IIB-IIC | 75 | 243 | 2 | 2.3 | 6.03 | 0.564 | 744 | 80 | 2963 | 125 | 95.0 | 95.5 | 95.6 | 0.91 | 0.90 | 0.88 |
| FLSD 280 M | IIB-IIC | 90 | 291 | 2.5 | 2.8 | 7.73 | 0.564 | 744 | 80 | 2968 | 150 | 95.3 | 95.6 | 95.5 | 0.91 | 0.90 | 0.85 |
| FLSD 315 S | IIB | 110 | 354 | 2.1 | 2.6 | 6.58 | 1.24 | 1290 | 79 | 2975 | 184 | 95.9 | 96.0 | 95.5 | 0.90 | 0.89 | 0.85 |
| FLSD 315 S | IIC | 110 | 352 | 2.2 | 2.4 | 7.09 | 1.51 | 1398 | 79 | 2981 | 182 | 96.5 | 96.2 | 95.4 | 0.90 | 0.89 | 0.86 |
| FLSD 315 M | IIB | 132 | 424 | 2.1 | 2.5 | 6.71 | 1.29 | 1295 | 79 | 2975 | 221 | 96.0 | 96.1 | 95.6 | 0.90 | 0.90 | 0.89 |
| FLSD 315 M | IIC | 132 | 424 | 1.8 | 2.0 | 5.8 | 1.51 | 1398 | 79 | 2975 | 219 | 96.2 | 96.2 | 95.6 | 0.90 | 0.90 | 0.89 |
| FLSD 315 LA | IIB | 160 | 516 | 2.1 | 2.8 | 6.64 | 1.39 | 1330 | 79 | 2972 | 268 | 96.4 | 96.5 | 96.1 | 0.90 | 0.89 | 0.84 |
| FLSD 315 LA | IIC | 160 | 513 | 2 | 2.1 | 6.69 | 1.51 | 1398 | 79 | 2976 | 266 | 96.3 | 96.3 | 95.7 | 0.90 | 0.90 | 0.87 |
| FLSD 315 LB | IIB-IIC | 200 | 645 | 2.3 | 2.3 | 7.28 | 1.51 | 1398 | 79 | 2976 | 335 | 96.3 | 96.6 | 96.4 | 0.90 | 0.89 | 0.84 |

| | | | | | | | | | | | | | | | | | |
|-------------------------|---------|------|-------|-----|-----|------|---------|------|----|------|-------|------|------|------|-------|-------|-------|
| 4 poles | | | | | | | | | | | | | | | | | |
| FLSD 90 SL ¹ | IIB-IIC | 0.75 | 5 | 2.2 | 2.9 | 6.45 | 0.00338 | 28 | 51 | 1452 | 1.7 | 83.8 | 84.4 | 83.1 | 0.79 | 0.71 | 0.58 |
| FLSD 90 SL | IIB-IIC | 1.1 | 7.3 | 2.5 | 3.1 | 6.75 | 0.00421 | 34 | 49 | 1450 | 2.3 | 84.9 | 85.8 | 85.0 | 0.81 | 0.74 | 0.61 |
| FLSD 90 LU | IIB-IIC | 1.5 | 9.9 | 2.9 | 3.6 | 7.35 | 0.00526 | 37 | 51 | 1454 | 3.3 | 85.4 | 85.8 | 84.1 | 0.78 | 0.70 | 0.56 |
| FLSD 100 LG | IIB-IIC | 2.2 | 14.4 | 2.7 | 2.7 | 6.92 | 0.01155 | 49 | 50 | 1460 | 4.4 | 89.6 | 90.0 | 89.1 | 0.81 | 0.75 | 0.63 |
| FLSD 100 LG | IIB-IIC | 3 | 19.6 | 2.5 | 3.3 | 7.27 | 0.01155 | 49 | 50 | 1462 | 6 | 88.7 | 89.3 | 88.7 | 0.82 | 0.76 | 0.64 |
| FLSD 112 MU | IIB-IIC | 4 | 26.2 | 2.7 | 3 | 6.6 | 0.01431 | 54 | 50 | 1458 | 8.1 | 88.8 | 89.5 | 88.9 | 0.80 | 0.75 | 0.64 |
| FLSD 132 SM | IIB-IIC | 5.5 | 35.9 | 2.9 | 3.7 | 8.35 | 0.02304 | 85 | 60 | 1462 | 10.5 | 90.1 | 90.7 | 90.2 | 0.84 | 0.78 | 0.67 |
| FLSD 132 MU | IIB-IIC | 7.5 | 49.1 | 3 | 3.4 | 8.1 | 0.02960 | 100 | 62 | 1458 | 13.8 | 90.4 | 91.5 | 91.9 | 0.87 | 0.82 | 0.73 |
| FLSD 160 M | IIB-IIC | 11 | 72.3 | 2.1 | 3.4 | 7.96 | 0.070 | 180 | 58 | 1470 | 20.7 | 91.6 | 92.4 | 92.4 | 0.85 | 0.80 | 0.69 |
| FLSD 160 L | IIB-IIC | 15 | 99.2 | 2.3 | 3.3 | 7.94 | 0.097 | 199 | 58 | 1468 | 27.9 | 92.1 | 92.6 | 92.7 | 0.86 | 0.81 | 0.71 |
| FLSD 180 M | IIB-IIC | 18.5 | 120.1 | 2.9 | 3.1 | 7.4 | 0.132 | 248 | 63 | 1472 | 34.7 | 92.6 | 92.6 | 92.0 | 0.83 | 0.79 | 0.70 |
| FLSD 180 L | IIB-IIC | 22 | 142.8 | 2.8 | 3.2 | 7.31 | 0.149 | 260 | 63 | 1472 | 41.3 | 93.0 | 93.2 | 93.0 | 0.83 | 0.79 | 0.69 |
| FLSD 200 L | IIB-IIC | 30 | 193.9 | 3 | 2.8 | 7.21 | 0.259 | 369 | 64 | 1478 | 55.7 | 93.6 | 94.0 | 93.6 | 0.83 | 0.79 | 0.69 |
| FLSD 225 SK | IIB-IIC | 37 | 239.4 | 2 | 2.6 | 6.76 | 0.571 | 519 | 65 | 1483 | 68.3 | 94.1 | 94.6 | 94.4 | 0.84 | 0.80 | 0.71 |
| FLSD 225 MK | IIB-IIC | 45 | 290 | 2 | 2.5 | 6.84 | 0.63 | 537 | 65 | 1484 | 82.4 | 94.2 | 94.6 | 94.6 | 0.84 | 0.80 | 0.73 |
| FLSD 250 M | IIB-IIC | 55 | 355 | 2.2 | 2.8 | 7.39 | 0.73 | 608 | 69 | 1484 | 100.6 | 94.6 | 95.0 | 94.9 | 0.84 | 0.80 | 0.72 |
| FLSD 280 S | IIB-IIC | 75 | 485 | 2.4 | 2.9 | 7.85 | 0.89 | 729 | 70 | 1484 | 138 | 95.0 | 95.0 | 94.5 | 0.83 | 0.78 | 0.68 |
| FLSD 280 M | IIB-IIC | 90 | 581 | 2.4 | 2.8 | 7.7 | 1.02 | 765 | 70 | 1483 | 166 | 95.2 | 95.2 | 94.4 | 0.83 | 0.79 | 0.70 |
| FLSD 315 S | IIB | 110 | 708 | 2 | 2.5 | 6.85 | 2.27 | 1289 | 71 | 1486 | 191 | 95.7 | 95.6 | 95.0 | 0.87 | 0.85 | 0.78 |
| FLSD 315 S | IIC | 110 | 708 | 2.4 | 2.2 | 6.2 | 3.03 | 1446 | 71 | 1483 | 188 | 96.0 | 96.2 | 95.9 | 0.88 | 0.87 | 0.83 |
| FLSD 315 M | IIB | 132 | 852 | 2.8 | 2.8 | 6.72 | 2.27 | 1289 | 71 | 1487 | 235 | 95.9 | 95.9 | 95.6 | 0.85 | 0.82 | 0.76 |
| FLSD 315 M | IIC | 132 | 849 | 2.5 | 2.4 | 6.6 | 3.03 | 1446 | 71 | 1484 | 226 | 96.0 | 96.2 | 95.8 | 0.88 | 0.87 | 0.82 |
| FLSD 315 LA | IIB | 160 | 1032 | 2.3 | 2.5 | 6.44 | 2.62 | 1357 | 71 | 1484 | 279 | 96.0 | 96.3 | 96.1 | 0.87 | 0.848 | 0.78 |
| FLSD 315 LA | IIC | 160 | 1029 | 2.7 | 2.6 | 7.2 | 3.03 | 1446 | 71 | 1485 | 273 | 96.0 | 96.1 | 95.7 | 0.88 | 0.857 | 0.793 |
| FLSD 315 LB | IIB-IIC | 200 | 1288 | 2.9 | 2.5 | 7.59 | 3.03 | 1446 | 71 | 1485 | 355 | 96.0 | 96.3 | 96.1 | 0.846 | 0.811 | 0.72 |

| | | | | | | | | | | | | | | | | | |
|-------------------------|---------|------|-------|-----|-----|------|---------|------|----|-----|------|------|------|------|------|------|------|
| 6 poles | | | | | | | | | | | | | | | | | |
| FLSD 90 SL ¹ | IIB-IIC | 0.75 | 7.6 | 1.9 | 2.3 | 4.45 | 0.00380 | 29 | 40 | 950 | 1.9 | 79.1 | 80.1 | 78.3 | 0.72 | 0.63 | 0.49 |
| FLSD 90 LU | IIB-IIC | 1.1 | 11 | 2.3 | 2.6 | 4.8 | 0.00520 | 35 | 57 | 954 | 2.8 | 81.7 | 82.3 | 80.3 | 0.71 | 0.62 | 0.48 |
| FLSD 100 LG | IIB-IIC | 1.5 | 14.8 | 2.4 | 2.8 | 5.65 | 0.01526 | 46 | 47 | 966 | 3.6 | 83.8 | 84.4 | 82.9 | 0.72 | 0.63 | 0.50 |
| FLSD 112 MU | IIB-IIC | 2.2 | 21.7 | 2.4 | 2.9 | 5.6 | 0.01901 | 53 | 45 | 968 | 5.4 | 84.5 | 85.1 | 83.5 | 0.70 | 0.62 | 0.49 |
| FLSD 132 SM | IIB-IIC | 3 | 29.5 | 2.7 | 3.1 | 6.4 | 0.02546 | 82 | 50 | 972 | 6.8 | 87.3 | 87.7 | 86.3 | 0.73 | 0.66 | 0.53 |
| FLSD 132 M | IIB-IIC | 4 | 39.4 | 2.4 | 2.9 | 6.25 | 0.03046 | 89 | 54 | 970 | 9.2 | 86.9 | 87.0 | 85.8 | 0.72 | 0.65 | 0.53 |
| FLSD 132 MU | IIB-IIC | 5.5 | 54.4 | 2.5 | 2.9 | 6.3 | 0.03723 | 98 | 55 | 966 | 11.7 | 88.3 | 89.0 | 88.7 | 0.77 | 0.71 | 0.59 |
| FLSD 160 M | IIB-IIC | 7.5 | 73.6 | 2 | 3.1 | 6.4 | 0.118 | 188 | 55 | 978 | 16 | 89.1 | 89.1 | 87.5 | 0.76 | 0.69 | 0.57 |
| FLSD 160 LK | IIB-IIC | 11 | 108 | 2.3 | 2.9 | 6.77 | 0.211 | 240 | 55 | 976 | 21.4 | 90.3 | 90.5 | 90.3 | 0.83 | 0.78 | 0.68 |
| FLSD 180 L | IIB-IIC | 15 | 146.6 | 2.7 | 3.2 | 7.1 | 0.250 | 272 | 58 | 977 | 30.7 | 91.2 | 91.2 | 90.4 | 0.78 | 0.72 | 0.59 |
| FLSD 200 LA | IIB-IIC | 18.5 | 181.7 | 2.6 | 3 | 7.26 | 0.300 | 348 | 58 | 978 | 36.4 | 91.8 | 92.4 | 92.0 | 0.80 | 0.75 | 0.65 |
| FLSD 200 LB | IIB-IIC | 22 | 214.6 | 2.6 | 3 | 7.1 | 0.346 | 369 | 58 | 980 | 44.7 | 92.2 | 92.1 | 91.3 | 0.77 | 0.72 | 0.60 |
| FLSD 225 MK | IIB-IIC | 30 | 291.8 | 2.3 | 2.5 | 6.52 | 0.760 | 504 | 64 | 985 | 55.3 | 93.0 | 93.4 | 93.0 | 0.84 | 0.81 | 0.71 |
| FLSD 250 M | IIB-IIC | 37 | 358.9 | 2.7 | 2.8 | 7.52 | 0.937 | 590 | 64 | 986 | 67.9 | 93.3 | 93.6 | 93.3 | 0.85 | 0.81 | 0.72 |
| FLSD 280 S | IIB-IIC | 45 | 436 | 2.8 | 2.7 | 7.22 | 1.36 | 751 | 60 | 986 | 79 | 94.4 | 94.8 | 94.8 | 0.87 | 0.84 | 0.76 |
| FLSD 280 M | IIB-IIC | 55 | 534 | 2.8 | 2.6 | 7.12 | 1.36 | 751 | 60 | 986 | 98 | 94.3 | 94.8 | 94.7 | 0.86 | 0.82 | 0.74 |
| FLSD 315 S | IIB | 75 | 727 | 2.0 | 2.1 | 7.03 | 2.67 | 1255 | 70 | 991 | 138 | 95.0 | 95.3 | 95.0 | 0.83 | 0.80 | 0.73 |
| FLSD 315 S | IIC | 75 | 724 | 2.4 | 1.9 | 5.8 | 2.67 | 1255 | 70 | 989 | 137 | 95.9 | 96.0 | 95.7 | 0.82 | 0.82 | 0.78 |
| FLSD 315 M | IIB | 90 | 869 | 2.7 | | | | | | | | | | | | | |

IMfinity® ATEX 3-phase induction motors - IE3 efficiency class

ATEX GAS motors - Zone 1
FLSD series - Cast iron - IE3

Electrical characteristics - Mains supply



II 2 G Ex db or db eb II B or C T4 Gb




| Type | Rated power | 415V 50Hz | | | | 460V 60Hz | | | |
|----------------|----------------------|-------------------------------------|---------------------|------------|--------------|-------------------------------------|---------------------|------------|--------------|
| | | Rated speed | Rated current | Efficiency | Power factor | Rated speed | Rated current | Efficiency | Power factor |
| | P _n kW | N _n min ⁻¹ | I _n A | η 4/4 | Cos φ 4/4 | N _n min ⁻¹ | I _n A | η 4/4 | Cos φ 4/4 |
| 2 poles | | | | | | | | | |
| FLSD 80 L | 0.75 | 2895 | 1.6 | 83.0 | 0.79 | 3505 | 1.4 | 83.7 | 0.79 |
| FLSD 90 SL | 1.1 | 2895 | 2.15 | 85.9 | 0.83 | 3505 | 1.95 | 84.8 | 0.83 |
| FLSD 90 SL | 1.5 | 2900 | 2.95 | 85.3 | 0.83 | 3505 | 2.65 | 86.0 | 0.83 |
| FLSD 90 LU | 2.2 | 2905 | 4.15 | 87.5 | 0.85 | 3510 | 3.7 | 88.2 | 0.85 |
| FLSD 100 L | 3 | 2910 | 5.6 | 87.5 | 0.85 | - | - | - | - |
| FLSD 112 MG | 4 | 2930 | 7.15 | 89.0 | 0.88 | 3535 | 6.4 | 89.9 | 0.88 |
| FLSD 132 SM | 5.5 | 2940 | 9.9 | 90.5 | 0.85 | 3545 | 9 | 90.8 | 0.85 |
| FLSD 132 SM | 7.5 | 2945 | 13.5 | 91.5 | 0.85 | 3550 | 12 | 92.2 | 0.85 |
| FLSD 132 M | 9 | 2950 | 16.3 | 91.4 | 0.84 | 3554 | 14.6 | 92.3 | 0.84 |
| FLSD 160 MA | 11 | 2958 | 19.52 | 91.5 | 0.86 | 3559 | 17 | 91.9 | 0.86 |
| FLSD 160 MB | 15 | 2954 | 25.69 | 92.5 | 0.88 | 3557 | 22.59 | 92.7 | 0.89 |
| FLSD 160 L | 18.5 | 2954 | 32.04 | 92.5 | 0.87 | 3553 | 27.86 | 92.9 | 0.88 |
| FLSD 180 M | 22 | 2960 | 36.8 | 93.6 | 0.89 | 3561 | 32.6 | 94.1 | 0.89 |
| FLSD 200 LA | 30 | 2959 | 53.08 | 93.6 | 0.84 | 3560 | 46.44 | 93.8 | 0.86 |
| FLSD 200 LB | 37 | 2951 | 62.7 | 93.8 | 0.88 | 3553 | 55.4 | 93.8 | 0.88 |
| FLSD 225 MR | 45 | 2954 | 76.86 | 94.1 | 0.87 | 3556 | 67.3 | 94.4 | 0.88 |
| FLSD 250 M | 55 | 2971 | 91.3 | 94.5 | 0.89 | 3572 | 81.29 | 94.1 | 0.89 |
| FLSD 280 S | 75 | 2967 | 121 | 95.2 | 0.91 | 3566 | 107 | 95.4 | 0.92 |
| FLSD 280 M | 90 | 2972 | 145 | 95.6 | 0.91 | 3574 | 128 | 95.3 | 0.91 |
| FLSD 315 S | 110 | 2979 | 179 | 96.0 | 0.90 | 3581 | 158 | 95.4 | 0.90 |
| FLSD 315 S | 110 | 2983 | 175 | 96.6 | 0.90 | 3584 | 159 | 96.3 | 0.90 |
| FLSD 315 M | 132 | 2976 | 214 | 96.0 | 0.90 | 3580 | 194 | 95.7 | 0.90 |
| FLSD 315 M | 132 | 2978 | 211 | 96.4 | 0.90 | 3580 | 190 | 96.2 | 0.90 |
| FLSD 315 LA | 160 | 2975 | 258 | 96.2 | 0.89 | 3575 | 232 | 96.2 | 0.90 |
| FLSD 315 LA | 160 | 2978 | 256 | 96.4 | 0.90 | 3580 | 230 | 96.3 | 0.90 |
| FLSD 315 LB | 200 | 2978 | 323 | 96.5 | 0.89 | 3582 | 290 | 96.4 | 0.90 |

| | | | | | | | | | |
|----------------|------|------|------|------|------|------|------|------|------|
| 4 poles | | | | | | | | | |
| FLSD 90 SL | 0.75 | 1454 | 1.6 | 84.0 | 0.78 | 1762 | 1.5 | 85.7 | 0.76 |
| FLSD 90 SL | 1.1 | 1454 | 2.3 | 84.9 | 0.79 | 1758 | 2.1 | 86.5 | 0.78 |
| FLSD 90 LU | 1.5 | 1456 | 3.2 | 85.6 | 0.76 | 1762 | 2.9 | 86.9 | 0.75 |
| FLSD 100 LG | 2.2 | 1470 | 4.3 | 89.8 | 0.79 | 1770 | 3.9 | 90.6 | 0.79 |
| FLSD 100 LG | 3 | 1462 | 6 | 88.8 | 0.79 | 1768 | 5.2 | 89.9 | 0.80 |
| FLSD 112 MU | 4 | 1462 | 8.1 | 89.4 | 0.78 | 1764 | 7.7 | 85.5 | 0.77 |
| FLSD 132 SM | 5.5 | 1466 | 10.3 | 90.2 | 0.82 | 1768 | 9.2 | 91.7 | 0.82 |
| FLSD 132 MU | 7.5 | 1462 | 13.5 | 90.9 | 0.85 | 1766 | 12.1 | 91.8 | 0.85 |
| FLSD 160 M | 11 | 1473 | 20.2 | 92.0 | 0.83 | 1775 | 17.8 | 92.5 | 0.83 |
| FLSD 160 L | 15 | 1471 | 26.9 | 92.2 | 0.84 | 1773 | 24.2 | 93.0 | 0.84 |
| FLSD 180 M | 18.5 | 1474 | 33.8 | 92.8 | 0.82 | 1775 | 30.1 | 93.6 | 0.83 |
| FLSD 180 L | 22 | 1475 | 40.5 | 93.1 | 0.81 | 1774 | 35.7 | 93.6 | 0.83 |
| FLSD 200 L | 30 | 1480 | 54.8 | 93.7 | 0.82 | 1781 | 47.9 | 94.1 | 0.82 |
| FLSD 225 SK | 37 | 1485 | 66.7 | 94.2 | 0.83 | 1787 | 59.7 | 94.5 | 0.83 |
| FLSD 225 MK | 45 | 1484 | 80.4 | 94.3 | 0.83 | 1785 | 71.8 | 95.0 | 0.83 |
| FLSD 250 M | 55 | 1485 | 97.7 | 94.8 | 0.83 | 1787 | 87.4 | 95.4 | 0.83 |
| FLSD 280 S | 75 | 1486 | 135 | 95.1 | 0.82 | 1787 | 121 | 95.4 | 0.82 |
| FLSD 280 M | 90 | 1484 | 161 | 95.3 | 0.82 | 1787 | 144 | 95.4 | 0.82 |
| FLSD 315 S | 110 | 1486 | 186 | 95.7 | 0.86 | 1788 | 166 | 95.8 | 0.87 |
| FLSD 315 S | 110 | 1485 | 181 | 96.1 | 0.88 | 1785 | 164 | 96.1 | 0.88 |
| FLSD 315 M | 132 | 1487 | 230 | 95.8 | 0.84 | 1789 | 203 | 96.2 | 0.85 |
| FLSD 315 M | 132 | 1485 | 218 | 96.2 | 0.88 | 1786 | 197 | 96.2 | 0.88 |
| FLSD 315 LA | 160 | 1486 | 270 | 95.9 | 0.86 | 1788 | 248 | 96.3 | 0.89 |
| FLSD 315 LA | 160 | 1486 | 265 | 96.1 | 0.87 | 1787 | 238 | 96.3 | 0.88 |
| FLSD 315 LB | 200 | 1487 | 350 | 96.1 | 0.83 | 1788 | 310 | 96.3 | 0.84 |

| | | | | | | | | | |
|----------------|------|-----|------|------|------|------|------|------|------|
| 6 poles | | | | | | | | | |
| FLSD 90 SL | 0.75 | 956 | 1.9 | 79.4 | 0.69 | - | - | - | - |
| FLSD 90 LU | 1.1 | 958 | 2.8 | 81.7 | 0.68 | - | - | - | - |
| FLSD 100 LG | 1.5 | 970 | 3.6 | 84.1 | 0.69 | - | - | - | - |
| FLSD 112 MU | 2.2 | 972 | 5.3 | 84.6 | 0.68 | - | - | - | - |
| FLSD 132 SM | 3 | 974 | 6.8 | 86.8 | 0.71 | - | - | - | - |
| FLSD 132 M | 4 | 972 | 9.2 | 87.0 | 0.70 | - | - | - | - |
| FLSD 132 MU | 5.5 | 970 | 11.5 | 88.5 | 0.75 | - | - | - | - |
| FLSD 160 M | 7.5 | 980 | 15.8 | 89.4 | 0.74 | 1181 | 14 | 91.0 | 0.74 |
| FLSD 160 LK | 11 | 978 | 20.9 | 90.4 | 0.81 | 1179 | 18.6 | 91.7 | 0.81 |
| FLSD 180 L | 15 | 979 | 30.1 | 91.3 | 0.76 | 1181 | 26.6 | 91.7 | 0.76 |
| FLSD 200 LA | 18.5 | 980 | 35.8 | 92.0 | 0.79 | 1181 | 31.6 | 93.0 | 0.79 |
| FLSD 200 LB | 22 | 983 | 44 | 92.3 | 0.75 | 1183 | 39.1 | 93.0 | 0.76 |
| FLSD 225 MK | 30 | 987 | 54.5 | 93.0 | 0.83 | 1187 | 47.9 | 94.1 | 0.84 |
| FLSD 250 M | 37 | 987 | 66.2 | 93.4 | 0.83 | 1188 | 58.5 | 94.1 | 0.84 |
| FLSD 280 S | 45 | 987 | 77 | 94.6 | 0.86 | 1187 | 68 | 94.6 | 0.86 |
| FLSD 280 M | 55 | 986 | 96 | 94.5 | 0.85 | 1187 | 85 | 94.8 | 0.85 |
| FLSD 315 S | 75 | 992 | 134 | 94.8 | 0.82 | 1192 | 118 | 95.1 | 0.83 |
| FLSD 315 S | 75 | 990 | 132 | 96.0 | 0.82 | 1190 | 119 | 96.1 | 0.82 |
| FLSD 315 M | 90 | 992 | 161 | 95.1 | 0.82 | 1193 | 141 | 95.3 | 0.83 |
| FLSD 315 M | 90 | 990 | 160 | 95.4 | 0.82 | 1190 | 144 | 95.6 | 0.82 |
| FLSD 315 LA | 110 | 990 | 200 | 95.5 | 0.81 | 1190 | 176 | 95.8 | 0.82 |
| FLSD 315 LB | 132 | 993 | 240 | 95.7 | 0.80 | 1193 | 214 | 95.9 | 0.81 |

For temperature classes T5 and T6, please contact us.




| Type | 400V 50Hz | | | | % Rated torque M_n at | | | | | 400V 87Hz Δ^1 | | | | Maximum mechanical speed ² |
|----------------|-------------|-------------------------|---------------|----------------|-------------------------|--------|--------|--------|--------|----------------------|-------------------------|---------------|----------------|---------------------------------------|
| | Rated power | Rated speed | Rated current | Power factor | 10Hz | 17Hz | 25Hz | 50Hz | 87Hz | Rated power | Rated speed | Rated current | Power factor | |
| | P_n kW | N_n min ⁻¹ | I_n A | Cos ϕ 4/4 | | | | | | P_n kW | N_n min ⁻¹ | I_n A | Cos ϕ 4/4 | |
| 2 poles | | | | | | | | | | | | | | |
| FLSD 80 L | 0.75 | 2870 | 1.75 | 0.84 | 2.33 | 2.5 | 2.5 | 2.5 | 1.43 | - | - | - | - | 7200 |
| FLSD 90 SL | 1.1 | 2870 | 2.35 | 0.86 | 3.39 | 3.65 | 3.65 | 3.65 | 2.08 | - | - | - | - | 7200 |
| FLSD 90 SL | 1.5 | 2870 | 3.25 | 0.87 | 4.6 | 4.95 | 4.95 | 4.95 | 2.82 | - | - | - | - | 7200 |
| FLSD 90 LU | 2.2 | 2875 | 4.6 | 0.89 | 6.74 | 7.25 | 7.25 | 7.25 | 4.13 | - | - | - | - | 7200 |
| FLSD 100 L | 3 | 2875 | 6.15 | 0.88 | 9.21 | 9.9 | 9.9 | 9.9 | 5.64 | - | - | - | - | 7200 |
| FLSD 112 MG | 4 | 2910 | 7.95 | 0.91 | 12.18 | 13.1 | 13.1 | 13.1 | 7.47 | - | - | - | - | 7200 |
| FLSD 132 SM | 5.5 | 2930 | 14.9 | 0.88 | 22.69 | 24.4 | 24.4 | 24.4 | 13.91 | - | - | - | - | 6700 |
| FLSD 132 SM | 7.5 | 2930 | 14.9 | 0.88 | 22.69 | 24.4 | 24.4 | 24.4 | 13.91 | - | - | - | - | 6700 |
| FLSD 132 M | 9 | 2935 | 17.9 | 0.87 | 27.16 | 29.2 | 29.2 | 29.2 | 16.64 | - | - | - | - | 5220 |
| FLSD 160 MA | 11 | 2949 | 22.5 | 0.89 | 35.6 | 35.6 | 35.6 | 35.6 | - | - | - | - | - | 3600 |
| FLSD 160 MB | 15 | 2943 | 30.1 | 0.90 | 48.7 | 48.7 | 48.7 | 48.7 | - | - | - | - | - | 3600 |
| FLSD 160 L | 18.5 | 2941 | 37 | 0.90 | 59.9 | 59.9 | 59.9 | 59.9 | - | - | - | - | - | 3600 |
| FLSD 180 M | 22 | 2952 | 43.1 | 0.90 | 71.4 | 71.4 | 71.4 | 71.4 | - | - | - | - | - | 3600 |
| FLSD 200 LA | 30 | 2946 | 59.9 | 0.88 | 97.1 | 97.1 | 97.1 | 97.1 | - | - | - | - | - | 3600 |
| FLSD 200 LB | 37 | 2923 | 73.6 | 0.89 | 110.3 | 113.9 | 118.8 | 121.2 | - | - | - | - | - | 3600 |
| FLSD 225 MR | 45 | 2942 | 88.3 | 0.90 | 140.1 | 140.1 | 140.1 | 140.1 | - | - | - | - | - | 3600 |
| FLSD 250 M | 55 | 2963 | 106.3 | 0.90 | 165.4 | 165.4 | 165.4 | 165.4 | - | - | - | - | - | 3600 |
| FLSD 280 S | 75 | 2949 | 143.3 | 0.91 | 213.5 | 228.0 | 242.6 | 242.6 | - | - | - | - | - | 3600 |
| FLSD 280 M | 90 | 2961 | 168.9 | 0.92 | 258.6 | 273.2 | 290.6 | 290.6 | - | - | - | - | - | 3600 |
| FLSD 315 S | 110 | 2966 | 207 | 0.90 | 353.6 | 353.6 | 353.6 | 353.6 | - | - | - | - | - | 3600 |
| FLSD 315 M | 132 | 2966 | 249.3 | 0.90 | 403.2 | 415.9 | 424.4 | 424.4 | - | - | - | - | - | 3600 |
| FLSD 315 LA | 160 | 2967 | 299.7 | 0.90 | 490.4 | 505.9 | 516.2 | 516.2 | - | - | - | - | - | 3600 |
| FLSD 315 LB | 200 | 2966 | 375.6 | 0.90 | 566.7 | 573.2 | 586 | 586 | - | - | - | - | - | 3600 |
| 4 poles | | | | | | | | | | | | | | |
| FLSD 90 SL | 0.75 | 1445 | 1.75 | 0.82 | 4.6 | 4.95 | 4.95 | 4.95 | 2.82 | - | - | - | - | 7200 |
| FLSD 90 SL | 1.1 | 1440 | 2.5 | 0.83 | 6.74 | 7.25 | 7.25 | 7.25 | 4.13 | - | - | - | - | 7200 |
| FLSD 90 LU | 1.5 | 1445 | 3.45 | 0.81 | 9.16 | 9.85 | 9.85 | 9.85 | 5.61 | - | - | - | - | 7200 |
| FLSD 100 LG | 2.2 | 1435 | 4.9 | 0.79 | 14.4 | 14.4 | 14.4 | 14.4 | 8.33 | - | - | - | - | 7200 |
| FLSD 100 LG | 3 | 1456 | 6.4 | 0.84 | 16.41 | 19.6 | 19.6 | 19.6 | 11.17 | - | - | - | - | 7200 |
| FLSD 112 MU | 4 | 1450 | 8.5 | 0.83 | 21.93 | 26.2 | 26.2 | 26.2 | 14.93 | - | - | - | - | 7200 |
| FLSD 132 SM | 5.5 | 1456 | 11.2 | 0.86 | 33.39 | 35.9 | 35.9 | 35.9 | 20.46 | - | - | - | - | 6700 |
| FLSD 132 MU | 7.5 | 1460 | 13.8 | 0.86 | 49.1 | 49.1 | 49.1 | 49.1 | 28.22 | - | - | - | - | 6700 |
| FLSD 160 M | 11 | 1462 | 22.8 | 0.88 | 72.3 | 72.3 | 72.3 | 72.3 | 54.2 | - | - | - | - | 2610 |
| FLSD 160 L | 15 | 1456 | 31 | 0.88 | 99.2 | 99.2 | 99.2 | 99.2 | 65.5 | - | - | - | - | 2610 |
| FLSD 180 M | 18.5 | 1463 | 38.4 | 0.86 | 120.1 | 120.1 | 120.1 | 120.1 | 68.46 | - | - | - | - | 2610 |
| FLSD 180 L | 22 | 1467 | 45.9 | 0.86 | 142.8 | 142.8 | 142.8 | 142.8 | 81.4 | - | - | - | - | 2610 |
| FLSD 200 L | 30 | 1471 | 61.2 | 0.86 | 193.7 | 193.7 | 193.7 | 193.7 | 110.41 | - | - | - | - | 2610 |
| FLSD 225 SK | 37 | 1483 | 75.9 | 0.85 | 239 | 239 | 239 | 239 | 136.23 | - | - | - | - | 2610 |
| FLSD 225 MK | 45 | 1481 | 92.1 | 0.86 | 278.5 | 281.4 | 287.2 | 287.2 | 163.7 | - | - | - | - | 2610 |
| FLSD 250 M | 55 | 1482 | 110.8 | 0.86 | 354.9 | 354.9 | 354.9 | 354.9 | 202.29 | - | - | - | - | 2610 |
| FLSD 280 S | 75 | 1481 | 151.2 | 0.86 | 436.1 | 460.4 | 484.6 | 484.6 | 276.22 | - | - | - | - | 2610 |
| FLSD 280 M | 90 | 1478 | 181.4 | 0.86 | 505.2 | 528.4 | 551.7 | 551.7 | 314.47 | - | - | - | - | 2610 |
| FLSD 315 S | 110 | 1483 | 212.3 | 0.88 | 679.7 | 693.8 | 708.0 | 708.0 | 403.56 | - | - | - | - | 2610 |
| FLSD 315 M | 132 | 1482 | 256.2 | 0.88 | 818 | 835.1 | 852.1 | 852.1 | 485.7 | - | - | - | - | 2610 |
| FLSD 315 LA | 160 | 1478 | 309.6 | 0.88 | 897.8 | 959.7 | 1011.3 | 1011.3 | 576.44 | - | - | - | - | 2610 |
| FLSD 315 LB | 200 | 1483 | 388.9 | 0.87 | 1069 | 1146.2 | 1223.5 | 1223.5 | 697.4 | - | - | - | - | 2610 |
| 6 poles | | | | | | | | | | | | | | |
| FLSD 90 SL | 0.75 | 945 | 2.05 | 0.75 | 7.02 | 7.55 | 7.55 | 7.55 | 4.30 | - | - | - | - | 7200 |
| FLSD 90 LU | 1.1 | 945 | 2.85 | 0.74 | 10.23 | 11 | 11 | 11 | 6.27 | - | - | - | - | 7200 |
| FLSD 100 LG | 1.5 | 962 | 3.8 | 0.74 | 13.08 | 14.8 | 14.8 | 14.8 | 8.44 | - | - | - | - | 7200 |
| FLSD 112 MU | 2.2 | 962 | 5.65 | 0.74 | 19.17 | 21.7 | 21.7 | 21.7 | 12.37 | - | - | - | - | 7200 |
| FLSD 132 SM | 3 | 970 | 7.1 | 0.76 | 27.44 | 29.5 | 29.5 | 29.5 | 16.82 | - | - | - | - | 6700 |
| FLSD 132 M | 4 | 966 | 9.7 | 0.75 | 36.64 | 39.4 | 39.4 | 39.4 | 22.46 | - | - | - | - | 6700 |
| FLSD 132 MU | 5.5 | 962 | 12.5 | 0.79 | 50.59 | 54.4 | 54.4 | 54.4 | 31.01 | - | - | - | - | 6700 |
| FLSD 160 M | 7.5 | 976 | 17.2 | 0.81 | 73.6 | 73.6 | 73.6 | 73.6 | 41.95 | - | - | - | - | 1740 |
| FLSD 160 LK | 11 | 973 | 24.3 | 0.85 | 108 | 108 | 108 | 108 | 61.56 | - | - | - | - | 1740 |
| FLSD 180 L | 15 | 976 | 33.7 | 0.82 | 146.6 | 146.6 | 146.6 | 146.6 | 83.56 | - | - | - | - | 1740 |
| FLSD 200 LA | 18.5 | 972 | 40.1 | 0.83 | 181.7 | 181.7 | 181.7 | 181.7 | 103.57 | - | - | - | - | 1740 |
| FLSD 200 LB | 22 | 978 | 48.4 | 0.82 | 214.6 | 214.6 | 214.6 | 214.6 | 122.32 | - | - | - | - | 1740 |
| FLSD 225 MK | 30 | 985 | 61.5 | 0.87 | 291.8 | 291.8 | 291.8 | 291.8 | 166.33 | - | - | - | - | 1740 |
| FLSD 250 M | 37 | 985 | 75 | 0.87 | 358.9 | 358.9 | 358.9 | 358.9 | 204.57 | - | - | - | - | 1740 |
| FLSD 280 S | 45 | 984 | 85.9 | 0.88 | 436.2 | 436.2 | 436.2 | 436.2 | 248.63 | - | - | - | - | 1740 |
| FLSD 280 M | 55 | 984 | 109.6 | 0.88 | 502.1 | 518.1 | 534.1 | 534.1 | 304.44 | - | - | - | - | 1740 |
| FLSD 315 S | 75 | 990 | 154.5 | 0.84 | 727 | 727 | 727 | 727 | 414.39 | - | - | - | - | 1740 |
| FLSD 315 M | 90 | 990 | 184 | 0.84 | 869 | 869 | 869 | 869 | 495.33 | - | - | - | - | 1740 |
| FLSD 315 LA | 110 | 987 | 227.9 | 0.83 | 1023.4 | 1044.7 | 1066 | 1066 | 607.62 | - | - | - | - | 1740 |
| FLSD 315 LB | 132 | 990 | 270.2 | 0.83 | 1251 | 1263.7 | 1276.5 | 1276.5 | 727.61 | - | - | - | - | 1740 |



| Gas | Rated power | 415V 50Hz | | | | 460V 60Hz | | | |
|----------------|-------------------|----------------------------------|------------------|------------|--------------|----------------------------------|------------------|------------|--------------|
| | | Rated speed | Rated current | Efficiency | Power factor | Rated speed | Rated current | Efficiency | Power factor |
| | P _n kW | N _n min ⁻¹ | I _n A | η 4/4 | Cos φ 4/4 | N _n min ⁻¹ | I _n A | η 4/4 | Cos φ 4/4 |
| 2 poles | | | | | | | | | |
| FLSD 80 L | 0.75 | 2895 | 1.6 | 83.0 | 0.79 | 3505 | 1.4 | 83.7 | 0.79 |
| FLSD 90 SL | 1.1 | 2895 | 2.2 | 85.9 | 0.83 | 3505 | 2 | 84.8 | 0.83 |
| FLSD 90 SL | 1.5 | 2900 | 3 | 85.3 | 0.83 | 3505 | 2.7 | 86.0 | 0.83 |
| FLSD 90 LU | 2.2 | 2905 | 4.2 | 87.5 | 0.85 | 3510 | 3.7 | 88.2 | 0.85 |
| FLSD 100 L | 3 | 2910 | 5.6 | 87.5 | 0.85 | - | - | - | - |
| FLSD 112 MG | 4 | 2930 | 7.2 | 89.0 | 0.88 | 3535 | 6.4 | 89.9 | 0.88 |
| FLSD 132 SM | 5.5 | 2940 | 9.9 | 90.5 | 0.85 | 3545 | 9 | 90.8 | 0.85 |
| FLSD 132 SM | 7.5 | 2945 | 13.5 | 91.5 | 0.85 | 3550 | 12 | 92.2 | 0.85 |
| FLSD 132 M | 9 | 2950 | 16.3 | 91.4 | 0.84 | 3554 | 14.6 | 92.3 | 0.84 |
| FLSD 160 MA | 11 | 2958 | 19.5 | 91.5 | 0.86 | 3559 | 17 | 91.9 | 0.86 |
| FLSD 160 MB | 15 | 2954 | 25.7 | 92.5 | 0.88 | 3557 | 22.6 | 92.7 | 0.89 |
| FLSD 160 L | 18.5 | 2954 | 32 | 92.5 | 0.87 | 3553 | 27.9 | 92.9 | 0.88 |
| FLSD 180 M | 22 | 2960 | 36.8 | 93.6 | 0.89 | 3561 | 32.6 | 94.1 | 0.89 |
| FLSD 200 LA | 30 | 2959 | 53.1 | 93.6 | 0.84 | 3560 | 46.4 | 93.8 | 0.86 |
| FLSD 200 LB | 37 | 2951 | 62.7 | 93.8 | 0.88 | 3553 | 55.4 | 93.8 | 0.88 |
| FLSD 225 MR | 45 | 2954 | 76.9 | 94.1 | 0.87 | 3556 | 67.3 | 94.4 | 0.88 |
| FLSD 250 M | 55 | 2972 | 90.7 | 94.9 | 0.89 | 3574 | 80 | 94.7 | 0.89 |
| FLSD 280 S | 75 | 2967 | 121 | 95.2 | 0.91 | 3566 | 107 | 95.4 | 0.92 |
| FLSD 280 M | 90 | 2972 | 145 | 95.6 | 0.91 | 3574 | 128 | 95.3 | 0.91 |
| FLSD 315 S | 110 | 2983 | 175 | 96.6 | 0.90 | 3584 | 159 | 96.3 | 0.90 |
| FLSD 315 M | 132 | 2978 | 211 | 96.4 | 0.90 | 3580 | 190 | 96.2 | 0.90 |
| FLSD 315 LA | 160 | 2978 | 256 | 96.4 | 0.90 | 3580 | 230 | 96.3 | 0.90 |
| FLSD 315 LB | 200 | 2978 | 323 | 96.5 | 0.89 | 3582 | 290 | 96.4 | 0.90 |
| 4 poles | | | | | | | | | |
| FLSD 90 SL | 0.75 | 1454 | 1.6 | 84.0 | 0.78 | 1762 | 1.5 | 85.7 | 0.76 |
| FLSD 90 SL | 1.1 | 1454 | 2.3 | 84.9 | 0.79 | 1758 | 2.1 | 86.5 | 0.78 |
| FLSD 90 LU | 1.5 | 1456 | 3.2 | 85.6 | 0.76 | 1762 | 2.9 | 86.9 | 0.75 |
| FLSD 100 LG | 2.2 | 1470 | 4.3 | 89.8 | 0.79 | 1770 | 3.9 | 90.6 | 0.79 |
| FLSD 100 LG | 3 | 1462 | 6 | 88.8 | 0.79 | 1768 | 5.2 | 89.9 | 0.80 |
| FLSD 112 MU | 4 | 1462 | 8.1 | 89.4 | 0.78 | 1764 | 7.7 | 85.5 | 0.77 |
| FLSD 132 SM | 5.5 | 1466 | 10.3 | 90.2 | 0.82 | 1768 | 9.2 | 91.7 | 0.82 |
| FLSD 132 MU | 7.5 | 1462 | 13.5 | 90.9 | 0.85 | 1766 | 12.1 | 91.8 | 0.85 |
| FLSD 160 M | 11 | 1473 | 20.2 | 92.0 | 0.83 | 1775 | 17.8 | 92.5 | 0.83 |
| FLSD 160 L | 15 | 1471 | 26.9 | 92.2 | 0.84 | 1773 | 24.2 | 93.0 | 0.84 |
| FLSD 180 M | 18.5 | 1474 | 33.8 | 92.8 | 0.82 | 1775 | 30.1 | 93.6 | 0.83 |
| FLSD 180 L | 22 | 1475 | 40.5 | 93.1 | 0.81 | 1774 | 35.7 | 93.6 | 0.83 |
| FLSD 200 L | 30 | 1480 | 54.8 | 93.7 | 0.82 | 1781 | 47.9 | 94.1 | 0.82 |
| FLSD 225 SK | 37 | 1485 | 66.7 | 94.2 | 0.83 | 1787 | 59.7 | 94.5 | 0.83 |
| FLSD 225 MK | 45 | 1484 | 80.4 | 94.3 | 0.83 | 1785 | 71.8 | 95.0 | 0.83 |
| FLSD 250 M | 55 | 1485 | 97.7 | 94.8 | 0.83 | 1787 | 87.4 | 95.4 | 0.83 |
| FLSD 280 S | 75 | 1486 | 135 | 95.1 | 0.82 | 1787 | 121 | 95.4 | 0.82 |
| FLSD 280 M | 90 | 1484 | 161 | 95.3 | 0.82 | 1787 | 144 | 95.4 | 0.82 |
| FLSD 315 S | 110 | 1485 | 181 | 96.1 | 0.88 | 1785 | 164 | 96.1 | 0.88 |
| FLSD 315 M | 132 | 1485 | 218 | 96.2 | 0.88 | 1786 | 197 | 96.2 | 0.88 |
| FLSD 315 LA | 160 | 1486 | 265 | 96.1 | 0.87 | 1787 | 238 | 96.3 | 0.88 |
| FLSD 315 LB | 200 | 1487 | 350 | 96.1 | 0.83 | 1788 | 310 | 96.3 | 0.84 |
| 6 poles | | | | | | | | | |
| FLSD 90 SL | 0.75 | 956 | 1.9 | 79.4 | 0.69 | - | - | - | - |
| FLSD 90 LU | 1.1 | 958 | 2.8 | 81.7 | 0.68 | - | - | - | - |
| FLSD 100 LG | 1.5 | 970 | 3.6 | 84.1 | 0.69 | - | - | - | - |
| FLSD 112 MU | 2.2 | 972 | 5.3 | 84.6 | 0.68 | - | - | - | - |
| FLSD 132 SM | 3 | 974 | 6.8 | 86.8 | 0.71 | - | - | - | - |
| FLSD 132 M | 4 | 972 | 9.2 | 87.0 | 0.70 | - | - | - | - |
| FLSD 132 MU | 5.5 | 970 | 11.5 | 88.5 | 0.75 | - | - | - | - |
| FLSD 160 M | 7.5 | 980 | 15.8 | 89.4 | 0.74 | 1181 | 14 | 91.0 | 0.74 |
| FLSD 160 LK | 11 | 978 | 20.9 | 90.4 | 0.81 | 1179 | 18.6 | 91.7 | 0.81 |
| FLSD 180 L | 15 | 979 | 30.1 | 91.3 | 0.76 | 1181 | 26.6 | 91.7 | 0.76 |
| FLSD 200 LA | 18.5 | 980 | 35.8 | 92.0 | 0.79 | 1181 | 31.6 | 93.0 | 0.79 |
| FLSD 200 LB | 22 | 983 | 44 | 92.3 | 0.75 | 1183 | 39.1 | 93.0 | 0.76 |
| FLSD 225 MK | 30 | 987 | 54.5 | 93.0 | 0.83 | 1187 | 47.9 | 94.1 | 0.84 |
| FLSD 250 M | 37 | 987 | 66.2 | 93.4 | 0.83 | 1188 | 58.5 | 94.1 | 0.84 |
| FLSD 280 S | 45 | 987 | 76.9 | 94.6 | 0.86 | 1187 | 68 | 94.6 | 0.86 |
| FLSD 280 M | 55 | 986 | 96.1 | 94.46 | 0.85 | 1187 | 85 | 94.8 | 0.85 |
| FLSD 315 S | 75 | 990 | 131.7 | 95.98 | 0.82 | 1190 | 119 | 96.1 | 0.82 |
| FLSD 315 M | 90 | 989 | 160.1 | 95.41 | 0.82 | 1190 | 144 | 95.6 | 0.82 |
| FLSD 315 LA | 110 | 990 | 200 | 95.50 | 0.81 | 1190 | 176 | 95.8 | 0.82 |
| FLSD 315 LB | 132 | 993 | 240.1 | 95.72 | 0.80 | 1193 | 214 | 95.9 | 0.81 |

Dimensions in millimetres





| Type | Main shaft end | | | | | | | | | | | | | |
|------------------|----------------|----|------|------|-----|-----|----|---------|----|------|------|-----|-----|----|
| | 4 and 6 poles | | | | | | | 2 poles | | | | | | |
| | F | GD | D | G | E | O | p | F | GD | D | G | E | O | p |
| FLSD 80 L | - | - | - | - | - | - | - | 6 | 6 | 19j6 | 15.5 | 40 | 6 | 16 |
| FLSD 90 LU/SL | 8 | 7 | 24j6 | 20 | 50 | M8 | 19 | 8 | 7 | 24j6 | 20 | 50 | 8 | 19 |
| FLSD 100 L | - | - | - | - | - | - | - | 8 | 7 | 28j6 | 24 | 60 | 10 | 22 |
| FLSD 100 LG | 8 | 7 | 28j6 | 24 | 60 | M10 | 22 | - | - | - | - | - | - | - |
| FLSD 112 MG | - | - | - | - | - | - | - | 8 | 7 | 28j6 | 24 | 60 | 10 | 22 |
| FLSD 112 MU | 8 | 7 | 28j6 | 24 | 60 | M10 | 22 | - | - | - | - | - | - | - |
| FLSD 132 M | 10 | 8 | 38k6 | 33 | 80 | M12 | 28 | 10 | 8 | 38k6 | 33 | 80 | M12 | 28 |
| FLSD 132 MU | 10 | 8 | 38k6 | 33 | 80 | M12 | 28 | - | - | - | - | - | - | - |
| FLSD 132 SM | 10 | 8 | 38k6 | 33 | 80 | M12 | 28 | 10 | 8 | 38k6 | 33 | 80 | M12 | 28 |
| FLSD 160 L | 12 | 8 | 42k6 | 37 | 110 | M16 | 36 | 12 | 8 | 42k6 | 37 | 110 | M16 | 36 |
| FLSD 160 LK/M | 12 | 8 | 42k6 | 37 | 110 | M16 | 36 | - | - | - | - | - | - | - |
| FLSD 160 MA/MB | - | - | - | - | - | - | - | 12 | 8 | 42k6 | 37 | 110 | M16 | 36 |
| FLSD 180 L | 14 | 9 | 48k6 | 42.5 | 110 | M16 | 36 | - | - | - | - | - | - | - |
| FLSD 180 M | 14 | 9 | 48k6 | 42.5 | 110 | M16 | 36 | 14 | 9 | 48k6 | 42.5 | 110 | M16 | 36 |
| FLSD 200 L/LA/LB | 16 | 10 | 55m6 | 49 | 110 | M20 | 42 | 16 | 10 | 55m6 | 49 | 110 | M20 | 42 |
| FLSD 225 MK/SK | 18 | 11 | 60m6 | 53 | 140 | M20 | 42 | - | - | - | - | - | - | - |
| FLSD 225 MR | - | - | - | - | - | - | - | 16 | 10 | 55m6 | 49 | 110 | M20 | 42 |
| FLSD 250 M | 18 | 11 | 65m6 | 58 | 140 | M20 | 42 | 18 | 11 | 60m6 | 53 | 140 | M20 | 42 |
| FLSD 280 M/S | 20 | 12 | 75m6 | 67.5 | 140 | M20 | 42 | 18 | 11 | 65m6 | 58 | 140 | M20 | 42 |
| FLSD 315 LA/LB | 25 | 14 | 90m6 | 81 | 170 | M24 | 50 | 20 | 12 | 70m6 | 62.5 | 140 | M20 | 42 |
| FLSD 315 M/S | 22 | 14 | 80m6 | 71 | 170 | M20 | 42 | 18 | 11 | 65m6 | 58 | 140 | M20 | 42 |

| Type | Secondary shaft ends | | | | | | | | | | | | | |
|------------------|----------------------|----|------|------|-----|-----|----|---------|----|------|------|-----|-----|----|
| | 4 and 6 poles | | | | | | | 2 poles | | | | | | |
| | FA | GF | DA | GB | EA | OA | pA | FA | GF | DA | GB | EA | OA | pA |
| FLSD 80 L | - | - | - | - | - | - | - | 5 | 5 | 14j6 | 11 | 30 | M5 | 15 |
| FLSD 90 LU/SL | 6 | 6 | 19j6 | 15.5 | 40 | M6 | 16 | 6 | 6 | 19j6 | 15.5 | 40 | M6 | 16 |
| FLSD 100 L | - | - | - | - | - | - | - | 8 | 7 | 24j6 | 20 | 50 | M8 | 19 |
| FLSD 100 LG | 8 | 7 | 24j6 | 20 | 50 | M8 | 19 | - | - | - | - | - | - | - |
| FLSD 112 MG | - | - | - | - | - | - | - | 8 | 7 | 24j6 | 20 | 50 | M8 | 19 |
| FLSD 112 MU | 8 | 7 | 24j6 | 20 | 50 | M8 | 19 | - | - | - | - | - | - | - |
| FLSD 132 M | 8 | 7 | 28j6 | 24 | 60 | M10 | 22 | 8 | 7 | 28j6 | 24 | 60 | M10 | 22 |
| FLSD 132 MU | 8 | 7 | 28j6 | 24 | 60 | M10 | 22 | - | - | - | - | - | - | - |
| FLSD 132 SM | 8 | 7 | 28j6 | 24 | 60 | M10 | 22 | 8 | 7 | 28j6 | 24 | 60 | M10 | 22 |
| FLSD 160 L | 12 | 8 | 42k6 | 37 | 110 | M16 | 36 | 12 | 8 | 42k6 | 37 | 110 | M16 | 36 |
| FLSD 160 LK/M | 12 | 8 | 42k6 | 37 | 110 | M16 | 36 | - | - | - | - | - | - | - |
| FLSD 160 MA/MB | - | - | - | - | - | - | - | 12 | 8 | 42k6 | 37 | 110 | M16 | 36 |
| FLSD 180 L | 14 | 9 | 48k6 | 42.5 | 110 | M16 | 36 | - | - | - | - | - | - | - |
| FLSD 180 M | 14 | 9 | 48k6 | 42.5 | 110 | M16 | 36 | 14 | 9 | 48k6 | 42.5 | 110 | M16 | 36 |
| FLSD 200 L/LA/LB | 16 | 10 | 55m6 | 49 | 110 | M20 | 42 | 16 | 10 | 55m6 | 49 | 110 | M20 | 42 |
| FLSD 225 MK/SK | 18 | 11 | 60m6 | 53 | 140 | M20 | 42 | - | - | - | - | - | - | - |
| FLSD 225 MR | - | - | - | - | - | - | - | 16 | 10 | 55m6 | 49 | 110 | M20 | 42 |
| FLSD 250 M | 18 | 11 | 60m6 | 53 | 140 | M20 | 42 | 18 | 11 | 60m6 | 53 | 140 | M20 | 42 |
| FLSD 280 M/S | 18 | 11 | 60m6 | 53 | 140 | M20 | 42 | 18 | 11 | 60m6 | 53 | 140 | M20 | 42 |
| FLSD 315 LA/LB | 20 | 12 | 70m6 | 63.5 | 140 | M20 | 42 | 20 | 12 | 70m6 | 63.5 | 140 | M20 | 42 |
| FLSD 315 M/S | 20 | 12 | 70m6 | 63.5 | 140 | M20 | 42 | 18 | 11 | 65m6 | 58 | 140 | M20 | 42 |

Ex db IIB T4 Gb

Dimensions in millimetres



| Type | Main dimensions | | | | | | | | | | | | | | | | | | | |
|---------------------|-----------------|-----|-----|-----|-----|----|-----|------|----|-----|-----|-----|------|------|-----|-----|-----|-----|------|--|
| | A | AB | B | BB | C | x | AA | K | HA | H | AC* | HD | LB | LJ | J | I | II | AD | AD1 | |
| FLSD 80 L | 125 | 157 | 100 | 133 | 56 | 10 | 34 | 10 | 10 | 80 | 173 | 283 | 259 | 26 | 142 | 80 | 77 | - | - | |
| FLSD 90 LU | 140 | 170 | 125 | 155 | 56 | 10 | 33 | 12 | 10 | 90 | 196 | 306 | 324 | 32 | 142 | 80 | 77 | 135 | 41 | |
| FLSD 90 SL | 140 | 170 | 100 | 155 | 56 | 10 | 33 | 12 | 10 | 90 | 196 | 306 | 297 | 32 | 142 | 80 | 77 | 135 | 41 | |
| FLSD 100 L | 160 | 196 | 140 | 201 | 63 | 18 | 40 | 12 | 13 | 100 | 209 | 316 | 345 | 32 | 142 | 80 | 77 | 135 | 41 | |
| FLSD 100 LG | 160 | 196 | 140 | 200 | 63 | 10 | 38 | 12 | 13 | 100 | 231 | 325 | 347 | 33 | 142 | 80 | 77 | 148 | 34.5 | |
| FLSD 112 MG | 190 | 230 | 140 | 186 | 70 | 14 | 48 | 12 | 12 | 112 | 231 | 337 | 346 | 33 | 142 | 80 | 77 | 148 | 34.5 | |
| FLSD 112 MU | 190 | 230 | 140 | 186 | 70 | 14 | 48 | 12 | 12 | 112 | 231 | 337 | 387 | 33 | 142 | 80 | 77 | 148 | 34.5 | |
| FLSD 132 M | 216 | 255 | 178 | 243 | 89 | 15 | 63 | 12 | 16 | 132 | 272 | 371 | 462 | 55.5 | 142 | 80 | 77 | 173 | 35 | |
| FLSD 132 MU | 216 | 255 | 178 | 243 | 89 | 15 | 63 | 12 | 16 | 132 | 272 | 371 | 506 | 55.5 | 142 | 80 | 77 | 173 | 35 | |
| FLSD 132 SM | 216 | 255 | 140 | 243 | 89 | 15 | 63 | 12 | 16 | 132 | 272 | 371 | 462 | 55.5 | 142 | 80 | 77 | 173 | 35 | |
| FLSD 160 L | 254 | 302 | 254 | 295 | 108 | 20 | 70 | 14.5 | 22 | 160 | 309 | 481 | 596 | 30 | 242 | 134 | 145 | 214 | 52 | |
| FLSD 160 LK | 254 | 302 | 254 | 295 | 108 | 20 | 70 | 14.5 | 22 | 160 | 309 | 503 | 657 | 51 | 242 | 134 | 145 | 214 | 52 | |
| FLSD 160 M | 254 | 302 | 210 | 295 | 108 | 20 | 70 | 14.5 | 22 | 160 | 309 | 481 | 596 | 30 | 242 | 134 | 145 | 214 | 52 | |
| FLSD 160 MA | 254 | 302 | 210 | 295 | 108 | 20 | 70 | 14.5 | 22 | 160 | 309 | 481 | 596 | 30 | 242 | 134 | 145 | 214 | 52 | |
| FLSD 160 MB | 254 | 302 | 210 | 295 | 108 | 20 | 70 | 14.5 | 22 | 160 | 309 | 481 | 596 | 30 | 242 | 134 | 145 | 214 | 52 | |
| FLSD 180 L | 279 | 330 | 279 | 335 | 121 | 28 | 75 | 14.5 | 22 | 180 | 347 | 523 | 653 | 51 | 242 | 134 | 145 | 230 | 52 | |
| FLSD 180 M | 279 | 330 | 241 | 335 | 121 | 28 | 75 | 14.5 | 22 | 180 | 347 | 523 | 653 | 51 | 242 | 134 | 145 | 230 | 52 | |
| FLSD 200 L/LA/LB | 318 | 377 | 305 | 370 | 133 | 32 | 81 | 18.5 | 22 | 200 | 384 | 563 | 776 | 54 | 242 | 134 | 145 | 265 | 49 | |
| FLSD 225 MK 4 poles | 356 | 428 | 311 | 428 | 149 | 32 | 80 | 18.5 | 28 | 225 | 384 | 641 | 830 | 90.5 | 242 | 134 | 145 | 265 | 49 | |
| FLSD 225 MK 6 poles | 356 | 428 | 311 | 428 | 149 | 32 | 80 | 18.5 | 28 | 225 | 384 | 688 | 830 | 51.5 | 320 | 180 | 190 | 265 | 49 | |
| FLSD 225 MR | 356 | 445 | 311 | 400 | 149 | 44 | 90 | 18.5 | 30 | 225 | 384 | 588 | 776 | 54 | 242 | 134 | 145 | 265 | 49 | |
| FLSD 225 SK | 356 | 428 | 286 | 428 | 149 | 32 | 80 | 18.5 | 28 | 225 | 384 | 641 | 830 | 90.5 | 242 | 134 | 145 | 265 | 49 | |
| FLSD 250 M | 406 | 476 | 349 | 435 | 168 | 41 | 80 | 24 | 25 | 250 | 481 | 713 | 880 | 79 | 320 | 180 | 190 | 309 | 49 | |
| FLSD 280 M | 457 | 529 | 368 | 499 | 190 | 40 | 85 | 24 | 25 | 280 | 481 | 743 | 1030 | 49 | 320 | 180 | 190 | 322 | 49 | |
| FLSD 280 S | 457 | 529 | 419 | 499 | 190 | 40 | 85 | 24 | 25 | 280 | 481 | 743 | 1030 | 49 | 320 | 180 | 190 | 322 | 49 | |
| FLSD 315 LA/LB | 508 | 600 | 508 | 598 | 216 | 45 | 100 | 27 | 38 | 315 | 624 | 893 | 1252 | 70 | 336 | 217 | 268 | - | - | |
| FLSD 315 M | 508 | 600 | 457 | 598 | 216 | 45 | 100 | 27 | 38 | 315 | 624 | 893 | 1252 | 70 | 336 | 217 | 268 | - | - | |
| FLSD 315 S | 508 | 600 | 406 | 598 | 216 | 45 | 100 | 27 | 38 | 315 | 624 | 893 | 1252 | 70 | 336 | 217 | 268 | - | - | |

* AC: housing diameter without lifting rings

IMfinity® ATEX 3-phase induction motors - IE3 efficiency class



ATEX GAS motors - Zone 1

FLSD series - Cast iron - Mechanical characteristics

Foot mounted IM 1001 (IMB3)

Ex db eb IIB T4 Gb

Dimensions in millimetres




| Type | Main dimensions | | | | | | | | | | | | | | | | | | |
|---------------------|-----------------|-----|-----|-----|-----|----|-----|------|----|-----|-----|-------|------|------|-----|-----|-----|-----|------|
| | A | AB | B | BB | C | x | AA | K | HA | H | AC* | HD | LB | LJ | J | I | II | AD | AD1 |
| FLSD 80 L | 125 | 157 | 100 | 133 | 50 | 10 | 34 | 10 | 10 | 80 | 173 | 269.5 | 259 | 29 | 136 | 68 | 68 | - | - |
| FLSD 90 LU | 140 | 170 | 125 | 155 | 56 | 10 | 33 | 12 | 10 | 90 | 196 | 292.5 | 324 | 35 | 136 | 68 | 68 | 135 | 41 |
| FLSD 90 SL | 140 | 170 | 100 | 155 | 56 | 10 | 33 | 12 | 10 | 90 | 196 | 292.5 | 297 | 35 | 136 | 68 | 68 | 135 | 41 |
| FLSD 100 L | 160 | 196 | 140 | 201 | 63 | 18 | 40 | 12 | 13 | 100 | 209 | 302.5 | 345 | 35 | 136 | 68 | 68 | 135 | 41 |
| FLSD 100 LG | 160 | 196 | 140 | 200 | 63 | 10 | 38 | 12 | 13 | 100 | 231 | 311.5 | 347 | 36 | 136 | 68 | 68 | 148 | 34.5 |
| FLSD 112 MG | 190 | 230 | 140 | 186 | 70 | 14 | 48 | 12 | 12 | 112 | 231 | 323.5 | 346 | 36 | 136 | 68 | 68 | 148 | 34.5 |
| FLSD 112 MU | 190 | 230 | 140 | 186 | 70 | 14 | 48 | 12 | 12 | 112 | 231 | 323.5 | 387 | 33 | 136 | 68 | 68 | 148 | 34.5 |
| FLSD 132 M | 216 | 255 | 178 | 243 | 89 | 15 | 63 | 12 | 16 | 132 | 272 | 357.5 | 462 | 58.5 | 136 | 68 | 68 | 173 | 35 |
| FLSD 132 MU | 216 | 255 | 178 | 243 | 89 | 15 | 63 | 12 | 16 | 132 | 272 | 357.5 | 506 | 58.5 | 136 | 68 | 68 | 173 | 35 |
| FLSD 132 SM | 216 | 255 | 140 | 243 | 89 | 15 | 63 | 12 | 16 | 132 | 272 | 357.5 | 462 | 58.5 | 136 | 68 | 68 | 173 | 35 |
| FLSD 160 L | 254 | 302 | 254 | 295 | 108 | 20 | 70 | 14.5 | 22 | 160 | 309 | 465 | 596 | 28 | 246 | 126 | 147 | 214 | 52 |
| FLSD 160 LK | 254 | 302 | 254 | 295 | 108 | 20 | 70 | 14.5 | 22 | 160 | 309 | 487 | 657 | 49 | 246 | 126 | 147 | 214 | 52 |
| FLSD 160 M | 254 | 302 | 210 | 295 | 108 | 20 | 70 | 14.5 | 22 | 160 | 309 | 465 | 596 | 28 | 246 | 126 | 147 | 214 | 52 |
| FLSD 160 MA | 254 | 302 | 210 | 295 | 108 | 20 | 70 | 14.5 | 22 | 160 | 309 | 465 | 596 | 28 | 246 | 126 | 147 | 214 | 52 |
| FLSD 160 MB | 254 | 302 | 210 | 295 | 108 | 20 | 70 | 14.5 | 22 | 160 | 309 | 465 | 596 | 28 | 246 | 126 | 147 | 214 | 52 |
| FLSD 180 L | 279 | 330 | 279 | 335 | 121 | 28 | 75 | 14.5 | 22 | 180 | 347 | 507 | 653 | 49 | 246 | 126 | 147 | 230 | 52 |
| FLSD 180 M | 279 | 330 | 241 | 335 | 121 | 28 | 75 | 14.5 | 22 | 180 | 347 | 507 | 653 | 49 | 246 | 126 | 147 | 230 | 52 |
| FLSD 200 L/LA/LB | 318 | 377 | 305 | 370 | 133 | 32 | 81 | 18.5 | 22 | 200 | 384 | 547 | 776 | 52 | 246 | 126 | 147 | 265 | 49 |
| FLSD 225 MK 4 poles | 356 | 428 | 311 | 428 | 149 | 32 | 80 | 18.5 | 28 | 225 | 384 | 625 | 830 | 88.5 | 246 | 126 | 147 | 265 | 49 |
| FLSD 225 MK 6 poles | 356 | 428 | 311 | 428 | 149 | 32 | 80 | 18.5 | 28 | 225 | 384 | 665 | 830 | 35.5 | 352 | 175 | 210 | 265 | 49 |
| FLSD 225 MR | 356 | 445 | 311 | 400 | 149 | 44 | 90 | 18.5 | 30 | 225 | 384 | 572 | 776 | 52 | 246 | 126 | 147 | 265 | 49 |
| FLSD 225 SK | 356 | 428 | 286 | 428 | 149 | 32 | 80 | 18.5 | 28 | 225 | 384 | 625 | 830 | 88.5 | 246 | 126 | 147 | 265 | 49 |
| FLSD 250 M | 406 | 476 | 349 | 435 | 168 | 41 | 80 | 24 | 25 | 250 | 481 | 690 | 880 | 63 | 352 | 175 | 210 | 309 | 49 |
| FLSD 280 M | 457 | 529 | 368 | 499 | 190 | 40 | 85 | 24 | 25 | 280 | 481 | 720 | 1030 | 33 | 352 | 175 | 210 | 322 | 49 |
| FLSD 280 S | 457 | 529 | 419 | 499 | 190 | 40 | 85 | 24 | 25 | 280 | 481 | 720 | 1030 | 33 | 352 | 175 | 210 | 322 | 49 |
| FLSD 315 LA/LB | 508 | 600 | 508 | 598 | 216 | 45 | 100 | 27 | 38 | 315 | 624 | 940 | 1252 | 85 | 400 | 231 | 339 | - | - |
| FLSD 315 M | 508 | 600 | 457 | 598 | 216 | 45 | 100 | 27 | 38 | 315 | 624 | 940 | 1252 | 85 | 400 | 231 | 339 | - | - |
| FLSD 315 S | 508 | 600 | 406 | 598 | 216 | 45 | 100 | 27 | 38 | 315 | 624 | 940 | 1252 | 85 | 400 | 231 | 339 | - | - |

* AC: housing diameter without lifting rings

Ex db IIC T4 Gb

Dimensions in millimetres



| Type | Main dimensions | | | | | | | | | | | | | | | | | | |
|---------------------|-----------------|-----|-----|-----|-----|----|-----|------|----|-----|-----|-----|------|------|-----|-----|-----|-----|------|
| | A | AB | B | BB | C | x | AA | K | HA | H | AC* | HD | LB | LJ | J | I | II | AD | AD1 |
| FLSD 80 L | 125 | 157 | 100 | 133 | 50 | 10 | 34 | 10 | 10 | 80 | 173 | 283 | 259 | 26 | 142 | 80 | 77 | - | - |
| FLSD 90 LU | 140 | 170 | 125 | 155 | 56 | 10 | 33 | 12 | 10 | 90 | 196 | 306 | 324 | 32 | 142 | 80 | 77 | 135 | 41 |
| FLSD 90 SL | 140 | 170 | 100 | 155 | 56 | 10 | 33 | 12 | 10 | 90 | 196 | 306 | 297 | 32 | 142 | 80 | 77 | 135 | 41 |
| FLSD 100 L | 160 | 196 | 140 | 201 | 63 | 18 | 40 | 12 | 13 | 100 | 209 | 316 | 345 | 32 | 142 | 80 | 77 | 135 | 41 |
| FLSD 100 LG | 160 | 196 | 140 | 200 | 63 | 10 | 38 | 12 | 13 | 100 | 231 | 325 | 347 | 33 | 142 | 80 | 77 | 148 | 34.5 |
| FLSD 112 MG | 190 | 230 | 140 | 186 | 70 | 14 | 48 | 12 | 12 | 112 | 231 | 337 | 346 | 33 | 142 | 80 | 77 | 148 | 34.5 |
| FLSD 112 MU | 190 | 230 | 140 | 186 | 70 | 14 | 48 | 12 | 12 | 112 | 231 | 337 | 387 | 33 | 142 | 80 | 77 | 148 | 34.5 |
| FLSD 132 M | 216 | 255 | 178 | 243 | 89 | 15 | 63 | 12 | 16 | 132 | 272 | 371 | 462 | 55.5 | 142 | 80 | 77 | 173 | 35 |
| FLSD 132 MU | 216 | 255 | 178 | 243 | 89 | 15 | 63 | 12 | 16 | 132 | 272 | 371 | 506 | 55.5 | 142 | 80 | 77 | 173 | 35 |
| FLSD 132 SM | 216 | 255 | 140 | 243 | 89 | 15 | 63 | 12 | 16 | 132 | 272 | 371 | 462 | 55.5 | 142 | 80 | 77 | 173 | 35 |
| FLSD 160 L | 254 | 302 | 254 | 295 | 108 | 20 | 70 | 14.5 | 22 | 160 | 309 | 518 | 596 | 30 | 242 | 134 | 145 | 214 | 52 |
| FLSD 160 LK | 254 | 302 | 254 | 295 | 108 | 20 | 70 | 14.5 | 22 | 160 | 309 | 540 | 657 | 51 | 242 | 134 | 145 | 214 | 52 |
| FLSD 160 M | 254 | 302 | 210 | 295 | 108 | 20 | 70 | 14.5 | 22 | 160 | 309 | 518 | 596 | 30 | 242 | 134 | 145 | 214 | 52 |
| FLSD 160 MA | 254 | 302 | 210 | 295 | 108 | 20 | 70 | 14.5 | 22 | 160 | 309 | 518 | 596 | 30 | 242 | 134 | 145 | 214 | 52 |
| FLSD 160 MB | 254 | 302 | 210 | 295 | 108 | 20 | 70 | 14.5 | 22 | 160 | 309 | 518 | 596 | 30 | 242 | 134 | 145 | 214 | 52 |
| FLSD 180 L | 279 | 330 | 279 | 335 | 121 | 28 | 75 | 14.5 | 22 | 180 | 347 | 523 | 653 | 51 | 242 | 134 | 145 | 230 | 52 |
| FLSD 180 M | 279 | 330 | 241 | 335 | 121 | 28 | 75 | 14.5 | 22 | 180 | 347 | 523 | 653 | 51 | 242 | 134 | 145 | 230 | 52 |
| FLSD 200 L/LA/LB | 318 | 377 | 305 | 370 | 133 | 32 | 81 | 18.5 | 22 | 200 | 384 | 563 | 776 | 54 | 242 | 134 | 145 | 265 | 49 |
| FLSD 225 MK 4 poles | 356 | 428 | 311 | 428 | 149 | 32 | 80 | 18.5 | 28 | 225 | 384 | 641 | 830 | 90.5 | 242 | 134 | 145 | 265 | 49 |
| FLSD 225 MK 6 poles | 356 | 428 | 311 | 428 | 149 | 32 | 80 | 18.5 | 28 | 225 | 384 | 710 | 830 | 48.5 | 326 | 185 | 195 | 265 | 49 |
| FLSD 225 MR | 356 | 445 | 311 | 400 | 149 | 44 | 90 | 18.5 | 30 | 225 | 384 | 588 | 776 | 54 | 242 | 134 | 145 | 265 | 49 |
| FLSD 225 SK | 356 | 428 | 286 | 428 | 149 | 32 | 80 | 18.5 | 28 | 225 | 384 | 641 | 830 | 90.5 | 242 | 134 | 145 | 265 | 49 |
| FLSD 250 M | 406 | 476 | 349 | 435 | 168 | 41 | 80 | 24 | 25 | 250 | 481 | 735 | 880 | 76 | 326 | 185 | 195 | 309 | 49 |
| FLSD 280 M | 457 | 529 | 368 | 499 | 190 | 40 | 85 | 24 | 25 | 280 | 481 | 765 | 1030 | 46 | 326 | 185 | 195 | 322 | 49 |
| FLSD 280 S | 457 | 529 | 419 | 499 | 190 | 40 | 85 | 24 | 25 | 280 | 481 | 765 | 1030 | 46 | 326 | 185 | 195 | 322 | 49 |
| FLSD 315 LA/LB | 508 | 600 | 508 | 598 | 216 | 45 | 100 | 27 | 38 | 315 | 624 | 893 | 1252 | 70 | 336 | 217 | 268 | - | - |
| FLSD 315 M | 508 | 600 | 457 | 598 | 216 | 45 | 100 | 27 | 38 | 315 | 624 | 893 | 1252 | 70 | 336 | 217 | 268 | - | - |
| FLSD 315 S | 508 | 600 | 406 | 598 | 216 | 45 | 100 | 27 | 38 | 315 | 624 | 893 | 1252 | 70 | 336 | 217 | 268 | - | - |

* AC: housing diameter without lifting rings

IMfinity® ATEX 3-phase induction motors - IE3 efficiency class


ATEX GAS motors - Zone 1

FLSD series - Cast iron - Mechanical characteristics

Foot mounted IM 1001 (IMB3)

Ex db eb IIC T4 Gb

Dimensions in millimetres




| Type | Main dimensions | | | | | | | | | | | | | | | | | | |
|---------------------|-----------------|-----|-----|-----|-----|----|-----|------|----|-----|-----|-------|------|------|-----|-----|-----|-----|------|
| | A | AB | B | BB | C | x | AA | K | HA | H | AC* | HD | LB | LJ | J | I | II | AD | AD1 |
| FLSD 80 L | 125 | 157 | 100 | 133 | 50 | 10 | 34 | 10 | 10 | 80 | 173 | 269.5 | 259 | 29 | 136 | 68 | 68 | - | - |
| FLSD 90 LU | 140 | 170 | 125 | 155 | 56 | 10 | 33 | 12 | 10 | 90 | 196 | 292.5 | 324 | 35 | 136 | 68 | 68 | 135 | 41 |
| FLSD 90 SL | 140 | 170 | 100 | 155 | 56 | 10 | 33 | 12 | 10 | 90 | 196 | 292.5 | 297 | 35 | 136 | 68 | 68 | 135 | 41 |
| FLSD 100 L | 160 | 196 | 140 | 201 | 63 | 18 | 40 | 12 | 13 | 100 | 209 | 302.5 | 345 | 35 | 136 | 68 | 68 | 135 | 41 |
| FLSD 100 LG | 160 | 196 | 140 | 200 | 63 | 10 | 38 | 12 | 13 | 100 | 231 | 311.5 | 347 | 36 | 136 | 68 | 68 | 148 | 34.5 |
| FLSD 112 MG | 190 | 230 | 140 | 186 | 70 | 14 | 48 | 12 | 12 | 112 | 231 | 323.5 | 346 | 36 | 136 | 68 | 68 | 148 | 34.5 |
| FLSD 112 MU | 190 | 230 | 140 | 186 | 70 | 14 | 48 | 12 | 12 | 112 | 231 | 323.5 | 387 | 36 | 136 | 68 | 68 | 148 | 34.5 |
| FLSD 132 M | 216 | 255 | 178 | 243 | 89 | 15 | 63 | 12 | 16 | 132 | 272 | 357.5 | 462 | 58.5 | 136 | 68 | 68 | 173 | 35 |
| FLSD 132 MU | 216 | 255 | 178 | 243 | 89 | 15 | 63 | 12 | 16 | 132 | 272 | 357.5 | 506 | 58.5 | 136 | 68 | 68 | 173 | 35 |
| FLSD 132 SM | 216 | 255 | 140 | 243 | 89 | 15 | 63 | 12 | 16 | 132 | 272 | 357.5 | 462 | 58.5 | 136 | 68 | 68 | 173 | 35 |
| FLSD 160 L | 254 | 302 | 254 | 295 | 108 | 20 | 70 | 14.5 | 22 | 160 | 309 | 465 | 596 | 28 | 246 | 126 | 147 | 214 | 52 |
| FLSD 160 LK | 254 | 302 | 254 | 295 | 108 | 20 | 70 | 14.5 | 22 | 160 | 309 | 487 | 657 | 49 | 246 | 126 | 147 | 214 | 52 |
| FLSD 160 M | 254 | 302 | 210 | 295 | 108 | 20 | 70 | 14.5 | 22 | 160 | 309 | 465 | 596 | 28 | 246 | 126 | 147 | 214 | 52 |
| FLSD 160 MA | 254 | 302 | 210 | 295 | 108 | 20 | 70 | 14.5 | 22 | 160 | 309 | 465 | 596 | 28 | 246 | 126 | 147 | 214 | 52 |
| FLSD 160 MB | 254 | 302 | 210 | 295 | 108 | 20 | 70 | 14.5 | 22 | 160 | 309 | 465 | 596 | 28 | 246 | 126 | 147 | 214 | 52 |
| FLSD 180 L | 279 | 330 | 279 | 335 | 121 | 28 | 75 | 14.5 | 22 | 180 | 347 | 507 | 653 | 49 | 246 | 126 | 147 | 230 | 52 |
| FLSD 180 M | 279 | 330 | 241 | 335 | 121 | 28 | 75 | 14.5 | 22 | 180 | 347 | 507 | 653 | 49 | 246 | 126 | 147 | 230 | 52 |
| FLSD 200 L/LA/LB | 318 | 377 | 305 | 370 | 133 | 32 | 81 | 18.5 | 22 | 200 | 384 | 547 | 776 | 52 | 246 | 126 | 147 | 265 | 49 |
| FLSD 225 MK 4 poles | 356 | 428 | 311 | 428 | 149 | 32 | 80 | 18.5 | 28 | 225 | 384 | 625 | 830 | 88.5 | 246 | 126 | 147 | 265 | 49 |
| FLSD 225 MK 6 poles | 356 | 428 | 311 | 428 | 149 | 32 | 80 | 18.5 | 28 | 225 | 384 | 665 | 830 | 35.5 | 352 | 175 | 210 | 265 | 49 |
| FLSD 225 MR | 356 | 445 | 311 | 400 | 149 | 44 | 90 | 18.5 | 30 | 225 | 384 | 572 | 776 | 52 | 246 | 126 | 147 | 265 | 49 |
| FLSD 225 SK | 356 | 428 | 286 | 428 | 149 | 32 | 80 | 18.5 | 28 | 225 | 384 | 625 | 830 | 88.5 | 246 | 126 | 147 | 265 | 49 |
| FLSD 250 M | 406 | 476 | 349 | 435 | 168 | 41 | 80 | 24 | 25 | 250 | 481 | 690 | 880 | 63 | 352 | 175 | 210 | 309 | 49 |
| FLSD 280 M | 457 | 529 | 368 | 499 | 190 | 40 | 85 | 24 | 25 | 280 | 481 | 720 | 1030 | 33 | 352 | 175 | 210 | 322 | 49 |
| FLSD 280 S | 457 | 529 | 419 | 499 | 190 | 40 | 85 | 24 | 25 | 280 | 481 | 720 | 1030 | 33 | 352 | 175 | 210 | 322 | 49 |
| FLSD 315 LA/LB | 508 | 600 | 508 | 598 | 216 | 45 | 100 | 27 | 38 | 315 | 624 | 940 | 1252 | 85 | 400 | 231 | 339 | - | - |
| FLSD 315 M | 508 | 600 | 457 | 598 | 216 | 45 | 100 | 27 | 38 | 315 | 624 | 940 | 1252 | 85 | 400 | 231 | 339 | - | - |
| FLSD 315 S | 508 | 600 | 406 | 598 | 216 | 45 | 100 | 27 | 38 | 315 | 624 | 940 | 1252 | 85 | 400 | 231 | 339 | - | - |

* AC: housing diameter without lifting rings

Ex db IIB T4 Gb

Dimensions in millimetres



| Type | Main dimensions | | | | | | | | | | | | | | | | | | | |
|---------------------|-----------------|-----|-----|-----|-----|----|-----|------|----|-----|-----|-----|------|------|-----|-----|-----|-----|------|-------|
| | A | AB | B | BB | C | x | AA | K | HA | H | AC* | HD | LB | LJ | J | I | II | AD | AD1 | Symb |
| FLSD 80 L | 125 | 157 | 100 | 133 | 50 | 10 | 34 | 10 | 10 | 80 | 173 | 283 | 259 | 26 | 142 | 80 | 77 | - | - | FF165 |
| FLSD 90 LU | 140 | 170 | 125 | 155 | 56 | 10 | 33 | 12 | 10 | 90 | 196 | 306 | 324 | 32 | 142 | 80 | 77 | 135 | 41 | FF165 |
| FLSD 90 SL | 140 | 170 | 100 | 155 | 56 | 10 | 33 | 12 | 10 | 90 | 196 | 306 | 297 | 32 | 142 | 80 | 77 | 135 | 41 | FF165 |
| FLSD 100 L | 160 | 196 | 140 | 201 | 63 | 18 | 40 | 12 | 13 | 100 | 209 | 316 | 345 | 32 | 142 | 80 | 77 | 135 | 41 | FF215 |
| FLSD 100 LG | 160 | 196 | 140 | 200 | 63 | 10 | 38 | 12 | 13 | 100 | 231 | 325 | 347 | 33 | 142 | 80 | 77 | 148 | 34.5 | FF215 |
| FLSD 112 MG | 190 | 230 | 140 | 186 | 70 | 14 | 48 | 12 | 12 | 112 | 231 | 337 | 346 | 33 | 142 | 80 | 77 | 148 | 34.5 | FF215 |
| FLSD 112 MU | 190 | 230 | 140 | 186 | 70 | 14 | 48 | 12 | 12 | 112 | 231 | 337 | 387 | 33 | 142 | 80 | 77 | 148 | 34.5 | FF215 |
| FLSD 132 M | 216 | 255 | 178 | 243 | 89 | 15 | 63 | 12 | 16 | 132 | 272 | 371 | 462 | 55.5 | 142 | 80 | 77 | 173 | 35 | FF265 |
| FLSD 132 MU | 216 | 255 | 178 | 243 | 89 | 15 | 63 | 12 | 16 | 132 | 272 | 371 | 506 | 55.5 | 142 | 80 | 77 | 173 | 35 | FF265 |
| FLSD 132 SM | 216 | 255 | 140 | 243 | 89 | 15 | 63 | 12 | 16 | 132 | 272 | 371 | 462 | 55.5 | 142 | 80 | 77 | 173 | 35 | FF265 |
| FLSD 160 L | 254 | 302 | 254 | 295 | 108 | 20 | 70 | 14.5 | 22 | 160 | 309 | 481 | 596 | 30 | 242 | 134 | 145 | 214 | 52 | FF300 |
| FLSD 160 LK | 254 | 302 | 254 | 295 | 108 | 20 | 70 | 14.5 | 22 | 160 | 309 | 503 | 657 | 51 | 242 | 134 | 145 | 214 | 52 | FF300 |
| FLSD 160 M | 254 | 302 | 210 | 295 | 108 | 20 | 70 | 14.5 | 22 | 160 | 309 | 481 | 596 | 30 | 242 | 134 | 145 | 214 | 52 | FF300 |
| FLSD 160 MA | 254 | 302 | 210 | 295 | 108 | 20 | 70 | 14.5 | 22 | 160 | 309 | 481 | 596 | 30 | 242 | 134 | 145 | 214 | 52 | FF300 |
| FLSD 160 MB | 254 | 302 | 210 | 295 | 108 | 20 | 70 | 14.5 | 22 | 160 | 309 | 481 | 596 | 30 | 242 | 134 | 145 | 214 | 52 | FF300 |
| FLSD 180 L | 279 | 330 | 279 | 335 | 121 | 28 | 75 | 14.5 | 22 | 180 | 347 | 523 | 653 | 51 | 242 | 134 | 145 | 230 | 52 | FF300 |
| FLSD 180 M | 279 | 330 | 241 | 335 | 121 | 28 | 75 | 14.5 | 22 | 180 | 347 | 523 | 653 | 51 | 242 | 134 | 145 | 230 | 52 | FF300 |
| FLSD 200 L/LA/LB | 318 | 377 | 305 | 370 | 133 | 32 | 81 | 18.5 | 22 | 200 | 384 | 563 | 776 | 54 | 242 | 134 | 145 | 265 | 49 | FF350 |
| FLSD 225 MK 4 poles | 356 | 428 | 311 | 428 | 149 | 32 | 80 | 18.5 | 28 | 225 | 384 | 641 | 830 | 90.5 | 242 | 134 | 145 | 265 | 49 | FF400 |
| FLSD 225 MK 6 poles | 356 | 428 | 311 | 428 | 149 | 32 | 80 | 18.5 | 28 | 225 | 384 | 688 | 830 | 51.5 | 320 | 180 | 190 | 265 | 49 | FF400 |
| FLSD 225 MR | 356 | 445 | 311 | 400 | 149 | 44 | 90 | 18.5 | 30 | 225 | 384 | 588 | 776 | 54 | 242 | 134 | 145 | 265 | 49 | FF400 |
| FLSD 225 SK | 356 | 428 | 286 | 428 | 149 | 32 | 80 | 18.5 | 28 | 225 | 384 | 641 | 830 | 90.5 | 242 | 134 | 145 | 265 | 49 | FF400 |
| FLSD 250 M | 406 | 476 | 349 | 435 | 168 | 41 | 80 | 24 | 25 | 250 | 481 | 713 | 880 | 79 | 320 | 180 | 190 | 309 | 49 | FF500 |
| FLSD 280 M | 457 | 529 | 368 | 499 | 190 | 40 | 85 | 24 | 25 | 280 | 481 | 743 | 1030 | 49 | 320 | 180 | 190 | 322 | 49 | FF500 |
| FLSD 280 S | 457 | 529 | 419 | 499 | 190 | 40 | 85 | 24 | 25 | 280 | 481 | 743 | 1030 | 49 | 320 | 180 | 190 | 322 | 49 | FF500 |
| FLSD 315 LA/LB | 508 | 600 | 508 | 598 | 216 | 45 | 100 | 27 | 38 | 315 | 624 | 893 | 1252 | 70 | 336 | 217 | 268 | - | - | FF600 |
| FLSD 315 M | 508 | 600 | 457 | 598 | 216 | 45 | 100 | 27 | 38 | 315 | 624 | 893 | 1252 | 70 | 336 | 217 | 268 | - | - | FF600 |
| FLSD 315 S | 508 | 600 | 406 | 598 | 216 | 45 | 100 | 27 | 38 | 315 | 624 | 893 | 1252 | 70 | 336 | 217 | 268 | - | - | FF600 |

* AC: housing diameter without lifting rings

IMfinity® ATEX 3-phase induction motors - IE3 efficiency class


ATEX GAS motors - Zone 1

FLSD series - Cast iron - Mechanical characteristics

Foot and flange mounted IM 2001 (IM B35)

Ex db eb IIB T4 Gb

Dimensions in millimetres




| Type | Main dimensions | | | | | | | | | | | | | | | | | | | Symb |
|---------------------|-----------------|-----|-----|-----|-----|----|-----|------|----|-----|-----|-------|------|------|-----|-----|-----|-----|------|-------|
| | A | AB | B | BB | C | x | AA | K | HA | H | AC* | HD | LB | LJ | J | I | II | AD | AD1 | |
| FLSD 80 L | 125 | 157 | 100 | 133 | 50 | 10 | 34 | 10 | 10 | 80 | 173 | 269.5 | 259 | 29 | 136 | 68 | 68 | - | - | FF165 |
| FLSD 90 LU | 140 | 170 | 125 | 155 | 56 | 10 | 33 | 12 | 10 | 90 | 196 | 292.5 | 324 | 35 | 136 | 68 | 68 | 135 | 41 | FF165 |
| FLSD 90 SL | 140 | 170 | 100 | 155 | 56 | 10 | 33 | 12 | 10 | 90 | 196 | 292.5 | 297 | 35 | 136 | 68 | 68 | 135 | 41 | FF165 |
| FLSD 100 L | 160 | 196 | 140 | 201 | 63 | 18 | 40 | 12 | 13 | 100 | 209 | 302.5 | 345 | 35 | 136 | 68 | 68 | 135 | 41 | FF215 |
| FLSD 100 LG | 160 | 196 | 140 | 200 | 63 | 10 | 38 | 12 | 13 | 100 | 231 | 311.5 | 347 | 36 | 136 | 68 | 68 | 148 | 34.5 | FF215 |
| FLSD 112 MG | 190 | 230 | 140 | 186 | 70 | 14 | 48 | 12 | 12 | 112 | 231 | 323.5 | 346 | 36 | 136 | 68 | 68 | 148 | 34.5 | FF215 |
| FLSD 112 MU | 190 | 230 | 140 | 186 | 70 | 14 | 48 | 12 | 12 | 112 | 231 | 323.5 | 387 | 33 | 136 | 68 | 68 | 148 | 34.5 | FF215 |
| FLSD 132 M | 216 | 255 | 178 | 243 | 89 | 15 | 63 | 12 | 16 | 132 | 272 | 357.5 | 462 | 58.5 | 136 | 68 | 68 | 173 | 35 | FF265 |
| FLSD 132 MU | 216 | 255 | 178 | 243 | 89 | 15 | 63 | 12 | 16 | 132 | 272 | 357.5 | 506 | 58.5 | 136 | 68 | 68 | 173 | 35 | FF265 |
| FLSD 132 SM | 216 | 255 | 140 | 243 | 89 | 15 | 63 | 12 | 16 | 132 | 272 | 357.5 | 462 | 58.5 | 136 | 68 | 68 | 173 | 35 | FF265 |
| FLSD 160 L | 254 | 302 | 254 | 295 | 108 | 20 | 70 | 14.5 | 22 | 160 | 309 | 465 | 596 | 28 | 246 | 126 | 147 | 214 | 52 | FF300 |
| FLSD 160 LK | 254 | 302 | 254 | 295 | 108 | 20 | 70 | 14.5 | 22 | 160 | 309 | 487 | 657 | 49 | 246 | 126 | 147 | 214 | 52 | FF300 |
| FLSD 160 M | 254 | 302 | 210 | 295 | 108 | 20 | 70 | 14.5 | 22 | 160 | 309 | 465 | 596 | 28 | 246 | 126 | 147 | 214 | 52 | FF300 |
| FLSD 160 MA | 254 | 302 | 210 | 295 | 108 | 20 | 70 | 14.5 | 22 | 160 | 309 | 465 | 596 | 28 | 246 | 126 | 147 | 214 | 52 | FF300 |
| FLSD 160 MB | 254 | 302 | 210 | 295 | 108 | 20 | 70 | 14.5 | 22 | 160 | 309 | 465 | 596 | 28 | 246 | 126 | 147 | 214 | 52 | FF300 |
| FLSD 180 L | 279 | 330 | 279 | 335 | 121 | 28 | 75 | 14.5 | 22 | 180 | 347 | 507 | 653 | 49 | 246 | 126 | 147 | 230 | 52 | FF300 |
| FLSD 180 M | 279 | 330 | 241 | 335 | 121 | 28 | 75 | 14.5 | 22 | 180 | 347 | 507 | 653 | 49 | 246 | 126 | 147 | 230 | 52 | FF300 |
| FLSD 200 L/LA/LB | 318 | 377 | 305 | 370 | 133 | 32 | 81 | 18.5 | 22 | 200 | 384 | 547 | 776 | 52 | 246 | 126 | 147 | 265 | 49 | FF350 |
| FLSD 225 MK 4 poles | 356 | 428 | 311 | 428 | 149 | 32 | 80 | 18.5 | 28 | 225 | 384 | 625 | 830 | 88.5 | 246 | 126 | 147 | 265 | 49 | FF400 |
| FLSD 225 MK 6 poles | 356 | 428 | 311 | 428 | 149 | 32 | 80 | 18.5 | 28 | 225 | 384 | 665 | 830 | 35.5 | 352 | 175 | 210 | 265 | 49 | FF400 |
| FLSD 225 MR | 356 | 445 | 311 | 400 | 149 | 44 | 90 | 18.5 | 30 | 225 | 384 | 572 | 776 | 52 | 246 | 126 | 147 | 265 | 49 | FF400 |
| FLSD 225 SK | 356 | 428 | 286 | 428 | 149 | 32 | 80 | 18.5 | 28 | 225 | 384 | 625 | 830 | 88.5 | 246 | 126 | 147 | 265 | 49 | FF400 |
| FLSD 250 M | 406 | 476 | 349 | 435 | 168 | 41 | 80 | 24 | 25 | 250 | 481 | 690 | 880 | 63 | 352 | 175 | 210 | 309 | 49 | FF500 |
| FLSD 280 M | 457 | 529 | 368 | 499 | 190 | 40 | 85 | 24 | 25 | 280 | 481 | 720 | 1030 | 33 | 352 | 175 | 210 | 322 | 49 | FF500 |
| FLSD 280 S | 457 | 529 | 419 | 499 | 190 | 40 | 85 | 24 | 25 | 280 | 481 | 720 | 1030 | 33 | 352 | 175 | 210 | 322 | 49 | FF500 |
| FLSD 315 LA/LB | 508 | 600 | 508 | 598 | 216 | 45 | 100 | 27 | 38 | 315 | 624 | 940 | 1252 | 85 | 400 | 231 | 339 | - | - | FF600 |
| FLSD 315 M | 508 | 600 | 457 | 598 | 216 | 45 | 100 | 27 | 38 | 315 | 624 | 940 | 1252 | 85 | 400 | 231 | 339 | - | - | FF600 |
| FLSD 315 S | 508 | 600 | 406 | 598 | 216 | 45 | 100 | 27 | 38 | 315 | 624 | 940 | 1252 | 85 | 400 | 231 | 339 | - | - | FF600 |

* AC: housing diameter without lifting rings

Ex db IIC T4 Gb

Dimensions in millimetres



| Type | Main dimensions | | | | | | | | | | | | | | | | | | | |
|---------------------|-----------------|-----|-----|-----|-----|----|-----|------|----|-----|-----|-----|------|------|-----|-----|-----|-----|------|-------|
| | A | AB | B | BB | C | x | AA | K | HA | H | AC* | HD | LB | LJ | J | I | II | AD | AD1 | Symb |
| FLSD 80 L | 125 | 157 | 100 | 133 | 50 | 10 | 34 | 10 | 10 | 80 | 173 | 283 | 259 | 26 | 142 | 80 | 77 | - | - | FF165 |
| FLSD 90 LU | 140 | 170 | 125 | 155 | 56 | 10 | 33 | 12 | 10 | 90 | 196 | 306 | 324 | 32 | 142 | 80 | 77 | 135 | 41 | FF165 |
| FLSD 90 SL | 140 | 170 | 100 | 155 | 56 | 10 | 33 | 12 | 10 | 90 | 196 | 306 | 297 | 32 | 142 | 80 | 77 | 135 | 41 | FF165 |
| FLSD 100 L | 160 | 196 | 140 | 201 | 63 | 18 | 40 | 12 | 13 | 100 | 209 | 316 | 345 | 32 | 142 | 80 | 77 | 135 | 41 | FF215 |
| FLSD 100 LG | 160 | 196 | 140 | 200 | 63 | 10 | 38 | 12 | 13 | 100 | 231 | 325 | 347 | 33 | 142 | 80 | 77 | 148 | 34.5 | FF215 |
| FLSD 112 MG | 190 | 230 | 140 | 186 | 70 | 14 | 48 | 12 | 12 | 112 | 231 | 337 | 346 | 33 | 142 | 80 | 77 | 148 | 34.5 | FF215 |
| FLSD 112 MU | 190 | 230 | 140 | 186 | 70 | 14 | 48 | 12 | 12 | 112 | 231 | 337 | 387 | 33 | 142 | 80 | 77 | 148 | 34.5 | FF215 |
| FLSD 132 M | 216 | 255 | 178 | 243 | 89 | 15 | 63 | 12 | 16 | 132 | 272 | 371 | 462 | 55.5 | 142 | 80 | 77 | 173 | 35 | FF265 |
| FLSD 132 MU | 216 | 255 | 178 | 243 | 89 | 15 | 63 | 12 | 16 | 132 | 272 | 371 | 506 | 55.5 | 142 | 80 | 77 | 173 | 35 | FF265 |
| FLSD 132 SM | 216 | 255 | 140 | 243 | 89 | 15 | 63 | 12 | 16 | 132 | 272 | 371 | 462 | 55.5 | 142 | 80 | 77 | 173 | 35 | FF265 |
| FLSD 160 L | 254 | 302 | 254 | 295 | 108 | 20 | 70 | 14.5 | 22 | 160 | 309 | 518 | 596 | 30 | 242 | 134 | 145 | 214 | 52 | FF300 |
| FLSD 160 LK | 254 | 302 | 254 | 295 | 108 | 20 | 70 | 14.5 | 22 | 160 | 309 | 540 | 657 | 51 | 242 | 134 | 145 | 214 | 52 | FF300 |
| FLSD 160 M | 254 | 302 | 210 | 295 | 108 | 20 | 70 | 14.5 | 22 | 160 | 309 | 518 | 596 | 30 | 242 | 134 | 145 | 214 | 52 | FF300 |
| FLSD 160 MA | 254 | 302 | 210 | 295 | 108 | 20 | 70 | 14.5 | 22 | 160 | 309 | 518 | 596 | 30 | 242 | 134 | 145 | 214 | 52 | FF300 |
| FLSD 160 MB | 254 | 302 | 210 | 295 | 108 | 20 | 70 | 14.5 | 22 | 160 | 309 | 518 | 596 | 30 | 242 | 134 | 145 | 214 | 52 | FF300 |
| FLSD 180 L | 279 | 330 | 279 | 335 | 121 | 28 | 75 | 14.5 | 22 | 180 | 347 | 560 | 653 | 51 | 242 | 134 | 145 | 230 | 52 | FF300 |
| FLSD 180 M | 279 | 330 | 241 | 335 | 121 | 28 | 75 | 14.5 | 22 | 180 | 347 | 560 | 653 | 51 | 242 | 134 | 145 | 230 | 52 | FF300 |
| FLSD 200 L/LA/LB | 318 | 377 | 305 | 370 | 133 | 32 | 81 | 18.5 | 22 | 200 | 384 | 600 | 776 | 54 | 242 | 134 | 145 | 265 | 49 | FF350 |
| FLSD 225 MK 4 poles | 356 | 428 | 311 | 428 | 149 | 32 | 80 | 18.5 | 28 | 225 | 384 | 678 | 830 | 90.5 | 242 | 134 | 145 | 265 | 49 | FF400 |
| FLSD 225 MK 6 poles | 356 | 428 | 311 | 428 | 149 | 32 | 80 | 18.5 | 28 | 225 | 384 | 710 | 830 | 48.5 | 326 | 185 | 195 | 265 | 49 | FF400 |
| FLSD 225 MR | 356 | 445 | 311 | 400 | 149 | 44 | 90 | 18.5 | 30 | 225 | 384 | 625 | 776 | 54 | 242 | 134 | 145 | 265 | 49 | FF400 |
| FLSD 225 SK | 356 | 428 | 286 | 428 | 149 | 32 | 80 | 18.5 | 28 | 225 | 384 | 678 | 830 | 90.5 | 242 | 134 | 145 | 265 | 49 | FF400 |
| FLSD 250 M | 406 | 476 | 349 | 435 | 168 | 41 | 80 | 24 | 25 | 250 | 481 | 735 | 880 | 76 | 326 | 185 | 195 | 309 | 49 | FF500 |
| FLSD 280 M | 457 | 529 | 368 | 499 | 190 | 40 | 85 | 24 | 25 | 280 | 481 | 765 | 1030 | 46 | 326 | 185 | 195 | 322 | 49 | FF500 |
| FLSD 280 S | 457 | 529 | 419 | 499 | 190 | 40 | 85 | 24 | 25 | 280 | 481 | 765 | 1030 | 46 | 326 | 185 | 195 | 322 | 49 | FF500 |
| FLSD 315 LA/LB | 508 | 600 | 508 | 598 | 216 | 45 | 100 | 27 | 38 | 315 | 624 | 893 | 1252 | 70 | 336 | 217 | 268 | - | - | FF600 |
| FLSD 315 M | 508 | 600 | 457 | 598 | 216 | 45 | 100 | 27 | 38 | 315 | 624 | 893 | 1252 | 70 | 336 | 217 | 268 | - | - | FF600 |
| FLSD 315 S | 508 | 600 | 406 | 598 | 216 | 45 | 100 | 27 | 38 | 315 | 624 | 893 | 1252 | 70 | 336 | 217 | 268 | - | - | FF600 |

* AC: housing diameter without lifting rings

IMfinity® ATEX 3-phase induction motors - IE3 efficiency class


ATEX GAS motors - Zone 1

FLSD series - Cast iron - Mechanical characteristics

Foot and flange mounted IM 2001 (IM B35)

Ex db eb IIC T4 Gb


Dimensions in millimetres



| Type | Main dimensions | | | | | | | | | | | | | | | | | | | Symb |
|---------------------|-----------------|-----|-----|-----|-----|----|-----|------|----|-----|-----|-------|------|------|-----|-----|-----|-----|------|-------|
| | A | AB | B | BB | C | x | AA | K | HA | H | AC* | HD | LB | LJ | J | I | II | AD | AD1 | |
| FLSD 80 L | 125 | 157 | 100 | 133 | 50 | 10 | 34 | 10 | 10 | 80 | 173 | 269.5 | 259 | 29 | 136 | 68 | 68 | - | - | FF165 |
| FLSD 90 LU | 140 | 170 | 125 | 155 | 56 | 10 | 33 | 12 | 10 | 90 | 196 | 292.5 | 324 | 35 | 136 | 68 | 68 | 135 | 41 | FF165 |
| FLSD 90 SL | 140 | 170 | 100 | 155 | 56 | 10 | 33 | 12 | 10 | 90 | 196 | 292.5 | 297 | 35 | 136 | 68 | 68 | 135 | 41 | FF165 |
| FLSD 100 L | 160 | 196 | 140 | 201 | 63 | 18 | 40 | 12 | 13 | 100 | 209 | 302.5 | 345 | 35 | 136 | 68 | 68 | 135 | 41 | FF215 |
| FLSD 100 LG | 160 | 196 | 140 | 200 | 63 | 10 | 38 | 12 | 13 | 100 | 231 | 311.5 | 347 | 36 | 136 | 68 | 68 | 148 | 34.5 | FF215 |
| FLSD 112 MG | 190 | 230 | 140 | 186 | 70 | 14 | 48 | 12 | 12 | 112 | 231 | 323.5 | 346 | 36 | 136 | 68 | 68 | 148 | 34.5 | FF215 |
| FLSD 112 MU | 190 | 230 | 140 | 186 | 70 | 14 | 48 | 12 | 12 | 112 | 231 | 323.5 | 387 | 36 | 136 | 68 | 68 | 148 | 34.5 | FF215 |
| FLSD 132 M | 216 | 255 | 178 | 243 | 89 | 15 | 63 | 12 | 16 | 132 | 272 | 357.5 | 462 | 58.5 | 136 | 68 | 68 | 173 | 35 | FF265 |
| FLSD 132 MU | 216 | 255 | 178 | 243 | 89 | 15 | 63 | 12 | 16 | 132 | 272 | 357.5 | 506 | 58.5 | 136 | 68 | 68 | 173 | 35 | FF265 |
| FLSD 132 SM | 216 | 255 | 140 | 243 | 89 | 15 | 63 | 12 | 16 | 132 | 272 | 357.5 | 462 | 58.5 | 136 | 68 | 68 | 173 | 35 | FF265 |
| FLSD 160 L | 254 | 302 | 254 | 295 | 108 | 20 | 70 | 14.5 | 22 | 160 | 309 | 465 | 596 | 28 | 246 | 126 | 147 | 214 | 52 | FF300 |
| FLSD 160 LK | 254 | 302 | 254 | 295 | 108 | 20 | 70 | 14.5 | 22 | 160 | 309 | 487 | 657 | 49 | 246 | 126 | 147 | 214 | 52 | FF300 |
| FLSD 160 M | 254 | 302 | 210 | 295 | 108 | 20 | 70 | 14.5 | 22 | 160 | 309 | 465 | 596 | 28 | 246 | 126 | 147 | 214 | 52 | FF300 |
| FLSD 160 MA | 254 | 302 | 210 | 295 | 108 | 20 | 70 | 14.5 | 22 | 160 | 309 | 465 | 596 | 28 | 246 | 126 | 147 | 214 | 52 | FF300 |
| FLSD 160 MB | 254 | 302 | 210 | 295 | 108 | 20 | 70 | 14.5 | 22 | 160 | 309 | 465 | 596 | 28 | 246 | 126 | 147 | 214 | 52 | FF300 |
| FLSD 180 L | 279 | 330 | 279 | 335 | 121 | 28 | 75 | 14.5 | 22 | 180 | 347 | 507 | 653 | 49 | 246 | 126 | 147 | 230 | 52 | FF300 |
| FLSD 180 M | 279 | 330 | 241 | 335 | 121 | 28 | 75 | 14.5 | 22 | 180 | 347 | 507 | 653 | 49 | 246 | 126 | 147 | 230 | 52 | FF300 |
| FLSD 200 L/LA/LB | 318 | 377 | 305 | 370 | 133 | 32 | 81 | 18.5 | 22 | 200 | 384 | 547 | 776 | 52 | 246 | 126 | 147 | 265 | 49 | FF350 |
| FLSD 225 MK 4 poles | 356 | 428 | 311 | 428 | 149 | 32 | 80 | 18.5 | 28 | 225 | 384 | 625 | 830 | 88.5 | 246 | 126 | 147 | 265 | 49 | FF400 |
| FLSD 225 MK 6 poles | 356 | 428 | 311 | 428 | 149 | 32 | 80 | 18.5 | 28 | 225 | 384 | 665 | 830 | 35.5 | 352 | 175 | 210 | 265 | 49 | FF400 |
| FLSD 225 MR | 356 | 445 | 311 | 400 | 149 | 44 | 90 | 18.5 | 30 | 225 | 384 | 572 | 776 | 52 | 246 | 126 | 147 | 265 | 49 | FF400 |
| FLSD 225 SK | 356 | 428 | 286 | 428 | 149 | 32 | 80 | 18.5 | 28 | 225 | 384 | 625 | 830 | 88.5 | 246 | 126 | 147 | 265 | 49 | FF400 |
| FLSD 250 M | 406 | 476 | 349 | 435 | 168 | 41 | 80 | 24 | 25 | 250 | 481 | 690 | 880 | 63 | 352 | 175 | 210 | 309 | 49 | FF500 |
| FLSD 280 M | 457 | 529 | 368 | 499 | 190 | 40 | 85 | 24 | 25 | 280 | 481 | 720 | 1030 | 33 | 352 | 175 | 210 | 322 | 49 | FF500 |
| FLSD 280 S | 457 | 529 | 419 | 499 | 190 | 40 | 85 | 24 | 25 | 280 | 481 | 720 | 1030 | 33 | 352 | 175 | 210 | 322 | 49 | FF500 |
| FLSD 315 LA/LB | 508 | 600 | 508 | 598 | 216 | 45 | 100 | 27 | 38 | 315 | 624 | 940 | 1252 | 85 | 400 | 231 | 339 | - | - | FF600 |
| FLSD 315 M | 508 | 600 | 457 | 598 | 216 | 45 | 100 | 27 | 38 | 315 | 624 | 940 | 1252 | 85 | 400 | 231 | 339 | - | - | FF600 |
| FLSD 315 S | 508 | 600 | 406 | 598 | 216 | 45 | 100 | 27 | 38 | 315 | 624 | 940 | 1252 | 85 | 400 | 231 | 339 | - | - | FF600 |

* AC: housing diameter without lifting rings

Dimensions in millimetres



| Symbol IEC | Flange dimensions | | | | | | | |
|------------|-------------------|-----|-----|-----|---|------|------|------|
| | M | N | D | T | n | α° | S | LA |
| FF 165 | 165 | 130 | 200 | 3.5 | 4 | 45 | 12 | 10 |
| FF 165 | 165 | 130 | 200 | 3.5 | 4 | 45 | 12 | 10 |
| FF 165 | 165 | 130 | 200 | 3.5 | 4 | 45 | 12 | 10 |
| FF 215 | 215 | 180 | 250 | 4 | 4 | 45 | 14.5 | 10 |
| FF 215 | 215 | 180 | 250 | 4 | 4 | 45 | 14.5 | 13 |
| FF 215 | 215 | 180 | 250 | 4 | 4 | 45 | 14.5 | 13 |
| FF 215 | 215 | 180 | 250 | 4 | 4 | 45 | 14.5 | 13 |
| FF 265 | 265 | 230 | 300 | 4 | 4 | 45 | 14.5 | 13.5 |
| FF 265 | 265 | 230 | 300 | 4 | 4 | 45 | 14.5 | 13.5 |
| FF 265 | 265 | 230 | 300 | 4 | 4 | 45 | 14.5 | 13.5 |
| FF 300 | 300 | 250 | 350 | 5 | 4 | 45 | 18.5 | 15 |
| FF 300 | 300 | 250 | 350 | 5 | 4 | 45 | 18.5 | 15 |
| FF 300 | 300 | 250 | 350 | 5 | 4 | 45 | 18.5 | 15 |
| FF 300 | 300 | 250 | 350 | 5 | 4 | 45 | 18.5 | 15 |
| FF 300 | 300 | 250 | 350 | 5 | 4 | 45 | 18.5 | 15 |
| FF 300 | 300 | 250 | 350 | 5 | 4 | 45 | 18.5 | 15 |
| FF 300 | 300 | 250 | 350 | 5 | 4 | 45 | 18.5 | 15 |
| FF 300 | 300 | 250 | 350 | 5 | 4 | 45 | 18.5 | 15 |
| FF 350 | 350 | 300 | 400 | 5 | 4 | 45 | 18.5 | 15 |
| FF 400 | 400 | 350 | 450 | 5 | 8 | 22.5 | 18.5 | 16 |
| FF 400 | 400 | 350 | 450 | 5 | 8 | 22.5 | 18.5 | 16 |
| FF 400 | 400 | 350 | 450 | 5 | 8 | 22.5 | 18.5 | 16 |
| FF 400 | 400 | 350 | 450 | 5 | 8 | 22.5 | 18.5 | 16 |
| FF 500 | 500 | 450 | 550 | 5 | 8 | 22.5 | 18.5 | 18 |
| FF 500 | 500 | 450 | 550 | 5 | 8 | 22.5 | 18.5 | 18 |
| FF 500 | 500 | 450 | 550 | 5 | 8 | 22.5 | 18.5 | 18 |
| FF 600 | 600 | 550 | 660 | 6 | 8 | 60 | 24 | 22 |
| FF 600 | 600 | 550 | 660 | 6 | 8 | 60 | 24 | 22 |
| FF 600 | 600 | 550 | 660 | 6 | 8 | 60 | 24 | 22 |

| Type | Main dimensions | | | | | | | | |
|---------------------|-----------------|------|-----|------|-----|-----|-----|-----|------|
| | AC* | LB | HJ | LJ | J | I | II | AD | AD1 |
| FLSD 80 L | 173 | 259 | 203 | 26 | 142 | 80 | 77 | - | - |
| FLSD 90 LU | 196 | 344 | 216 | 52 | 142 | 80 | 77 | 135 | 41 |
| FLSD 90 SL | 196 | 317 | 216 | 52 | 142 | 80 | 77 | 135 | 41 |
| FLSD 100 L | 209 | 345 | 216 | 32 | 142 | 80 | 77 | 135 | 41 |
| FLSD 100 LG | 231 | 347 | 225 | 33 | 142 | 80 | 77 | 148 | 34.5 |
| FLSD 112 MG | 231 | 346 | 225 | 33 | 142 | 80 | 77 | 148 | 34.5 |
| FLSD 112 MU | 231 | 387 | 225 | 33 | 142 | 80 | 77 | 148 | 34.5 |
| FLSD 132 M | 272 | 462 | 239 | 55.5 | 142 | 80 | 77 | 173 | 35 |
| FLSD 132 MU | 272 | 506 | 239 | 55.5 | 142 | 80 | 77 | 173 | 35 |
| FLSD 132 SM | 272 | 462 | 239 | 55.5 | 142 | 80 | 77 | 173 | 35 |
| FLSD 160 L | 309 | 596 | 358 | 30 | 242 | 134 | 145 | 214 | 52 |
| FLSD 160 LK | 347 | 657 | 380 | 51 | 242 | 134 | 145 | 214 | 52 |
| FLSD 160 M | 309 | 596 | 358 | 30 | 242 | 134 | 145 | 214 | 52 |
| FLSD 160 MA | 309 | 596 | 358 | 30 | 242 | 134 | 145 | 214 | 52 |
| FLSD 160 MB | 309 | 596 | 358 | 30 | 242 | 134 | 145 | 214 | 52 |
| FLSD 180 L | 347 | 653 | 380 | 51 | 242 | 134 | 145 | 230 | 52 |
| FLSD 180 M | 347 | 653 | 380 | 51 | 242 | 134 | 145 | 230 | 52 |
| FLSD 200 L/LA/LB | 384 | 776 | 400 | 54 | 242 | 134 | 145 | 265 | 48 |
| FLSD 225 MK 4 poles | 490 | 830 | 485 | 81 | 326 | 185 | 195 | 309 | 50 |
| FLSD 225 MK 6 poles | 490 | 830 | 453 | 123 | 242 | 134 | 145 | 309 | 50 |
| FLSD 225 MR | 384 | 776 | 400 | 54 | 242 | 134 | 145 | 265 | 48 |
| FLSD 225 SK | 490 | 830 | 453 | 123 | 242 | 134 | 145 | 309 | 50 |
| FLSD 250 M | 481 | 830 | 485 | 76 | 326 | 185 | 195 | 309 | 49 |
| FLSD 280 M | 481 | 980 | 485 | 45 | 326 | 185 | 195 | 322 | 49 |
| FLSD 280 S | 481 | 980 | 485 | 45 | 326 | 185 | 195 | 322 | 49 |
| FLSD 315 LA/LB | 624 | 1252 | 578 | 70 | 336 | 217 | 268 | - | - |
| FLSD 315 M | 624 | 1252 | 578 | 70 | 336 | 217 | 268 | - | - |
| FLSD 315 S | 624 | 1252 | 578 | 70 | 336 | 217 | 268 | - | - |

* AC: housing diameter without lifting rings

The shape of the FF flange-mounted motors in IM 3001 stops at frame size 250. Dimensions of shaft extensions identical to those for foot mounted motors.


IMfinity® ATEX 3-phase induction motors - IE3 efficiency class

ATEX GAS motors - Zone 1

FLSD series - Cast iron - Mechanical characteristics

Foot and face mounted IM 2101 (IM B34)

Dimensions in millimetres



Ex db IIB T4 - Ex db IIC T4 Gb

| Type | Main dimensions | | | | | | | | | | | | | | | | | | | |
|-------------|-----------------|-----|-----|-----|----|----|----|----|----|-----|-----|-----|-----|------|-----|----|----|-----|------|--------|
| | A | AB | B | BB | C | X | AA | K | HA | H | AC* | HD | LB | LJ | J | I | II | AD | AD1 | Symb. |
| FLSD 80 L | 125 | 157 | 100 | 133 | 50 | 10 | 34 | 10 | 10 | 80 | 173 | 283 | 259 | 26 | 142 | 80 | 77 | - | - | FT 100 |
| FLSD 90 LU | 140 | 170 | 125 | 155 | 56 | 10 | 33 | 12 | 10 | 90 | 196 | 306 | 324 | 32 | 142 | 80 | 77 | 135 | 41 | FT 115 |
| FLSD 90 SL | 140 | 170 | 100 | 155 | 56 | 10 | 33 | 12 | 10 | 90 | 196 | 306 | 297 | 32 | 142 | 80 | 77 | 135 | 41 | FT 115 |
| FLSD 100 L | 160 | 196 | 140 | 201 | 63 | 18 | 40 | 12 | 13 | 100 | 209 | 316 | 345 | 32 | 142 | 80 | 77 | 135 | 41 | FT 130 |
| FLSD 100 LG | 160 | 196 | 140 | 200 | 63 | 10 | 38 | 12 | 13 | 100 | 231 | 325 | 347 | 33 | 142 | 80 | 77 | 148 | 34.5 | FT 130 |
| FLSD 112 MG | 190 | 230 | 140 | 186 | 70 | 14 | 48 | 12 | 12 | 112 | 231 | 337 | 346 | 33 | 142 | 80 | 77 | 148 | 34.5 | FT 130 |
| FLSD 112 MU | 190 | 230 | 140 | 186 | 70 | 14 | 48 | 12 | 12 | 112 | 231 | 337 | 387 | 33 | 142 | 80 | 77 | 148 | 34.5 | FT 130 |
| FLSD 132 M | 216 | 255 | 178 | 243 | 89 | 15 | 63 | 12 | 16 | 132 | 272 | 371 | 462 | 55.5 | 142 | 80 | 77 | 173 | 35 | FT 215 |
| FLSD 132 MU | 216 | 255 | 178 | 243 | 89 | 15 | 63 | 12 | 16 | 132 | 272 | 371 | 506 | 55.5 | 142 | 80 | 77 | 173 | 35 | FT 215 |
| FLSD 132 SM | 216 | 255 | 140 | 243 | 89 | 15 | 63 | 12 | 16 | 132 | 272 | 371 | 462 | 55.5 | 142 | 80 | 77 | 173 | 35 | FT 215 |


*AC: housing diameter without lifting rings

Ex db eb IIB T4 Gb - Ex db eb IIC T4 Gb - Ex db eb IIC T4 Gb VIK

| Type | Main dimensions | | | | | | | | | | | | | | | | | | | |
|-------------|-----------------|-----|-----|-----|----|----|----|----|----|-----|-----|-------|-----|------|-----|----|----|-----|------|--------|
| | A | AB | B | BB | C | X | AA | K | HA | H | AC* | HD | LB | LJ | J | I | II | AD | AD1 | Symb. |
| FLSD 80 L | 125 | 157 | 100 | 133 | 50 | 10 | 34 | 10 | 10 | 80 | 173 | 269.5 | 259 | 29 | 136 | 68 | 68 | - | - | FT 100 |
| FLSD 90 LU | 140 | 170 | 125 | 155 | 56 | 10 | 33 | 12 | 10 | 90 | 196 | 292.5 | 324 | 35 | 136 | 68 | 68 | 135 | 41 | FT 115 |
| FLSD 90 SL | 140 | 170 | 100 | 155 | 56 | 10 | 33 | 12 | 10 | 90 | 196 | 292.5 | 297 | 35 | 136 | 68 | 68 | 135 | 41 | FT 115 |
| FLSD 100 L | 160 | 196 | 140 | 201 | 63 | 18 | 40 | 12 | 13 | 100 | 209 | 302.5 | 345 | 35 | 136 | 68 | 68 | 135 | 41 | FT 130 |
| FLSD 100 LG | 160 | 196 | 140 | 200 | 63 | 10 | 38 | 12 | 13 | 100 | 231 | 311.5 | 347 | 36 | 136 | 68 | 68 | 148 | 34.5 | FT 130 |
| FLSD 112 MG | 190 | 230 | 140 | 186 | 70 | 14 | 48 | 12 | 12 | 112 | 231 | 323.5 | 346 | 36 | 136 | 68 | 68 | 148 | 34.5 | FT 130 |
| FLSD 112 MU | 190 | 230 | 140 | 186 | 70 | 14 | 48 | 12 | 12 | 112 | 231 | 323.5 | 387 | 36 | 136 | 68 | 68 | 148 | 34.5 | FT 130 |
| FLSD 132 M | 216 | 255 | 178 | 243 | 89 | 15 | 63 | 12 | 16 | 132 | 272 | 357.5 | 462 | 58.5 | 136 | 68 | 68 | 173 | 35 | FT 215 |
| FLSD 132 MU | 216 | 255 | 178 | 243 | 89 | 15 | 63 | 12 | 16 | 132 | 272 | 357.5 | 506 | 58.5 | 136 | 68 | 68 | 173 | 35 | FT 215 |
| FLSD 132 SM | 216 | 255 | 140 | 243 | 89 | 15 | 63 | 12 | 16 | 132 | 272 | 357.5 | 462 | 58.5 | 136 | 68 | 68 | 173 | 35 | FT 215 |

*AC: housing diameter without lifting rings

Dimensions in millimetres




| Symbol IEC | Flange dimensions | | | | | | | | |
|---------------|-------------------|-----|-----|-----|---|----|-----|----|--|
| | M | N | D | T | n | α° | S | LA | |
| FT 100 | 100 | 80 | 120 | 3 | 4 | 45 | M6 | - | |
| FT 115 | 115 | 95 | 140 | 3 | 4 | 45 | M8 | - | |
| FT 115 | 115 | 95 | 140 | 3 | 4 | 45 | M8 | - | |
| FT 130 | 130 | 110 | 160 | 3.5 | 4 | 45 | M8 | - | |
| FT 130 | 130 | 110 | 160 | 3.5 | 4 | 45 | M8 | - | |
| FT 130 | 130 | 110 | 160 | 3.5 | 4 | 45 | M8 | - | |
| FT 130 | 130 | 110 | 160 | 3.5 | 4 | 45 | M8 | - | |
| FT 215 | 215 | 180 | 250 | 4 | 4 | 45 | M12 | - | |
| FT 215 | 215 | 180 | 250 | 4 | 4 | 45 | M12 | - | |
| FT 215 | 215 | 180 | 250 | 4 | 4 | 45 | M12 | - | |

| Type | Main dimensions | | | | | | | | | |
|-------------|-----------------|-----|-----|------|-----|----|----|-----|------|--|
| | AC* | LB | HJ | LJ | J | I | II | AD | AD1 | |
| FLSD 80 L | 173 | 259 | 203 | 26 | 142 | 80 | 77 | - | - | |
| FLSD 90 LU | 196 | 324 | 216 | 32 | 142 | 80 | 77 | 135 | 41 | |
| FLSD 90 SL | 196 | 297 | 216 | 32 | 142 | 80 | 77 | 135 | 41 | |
| FLSD 100 L | 209 | 345 | 216 | 32 | 142 | 80 | 77 | 135 | 41 | |
| FLSD 100 LG | 231 | 347 | 225 | 33 | 142 | 80 | 77 | 148 | 34.5 | |
| FLSD 112 MG | 231 | 346 | 225 | 33 | 142 | 80 | 77 | 148 | 34.5 | |
| FLSD 112 MU | 231 | 387 | 225 | 33 | 142 | 80 | 77 | 148 | 34.5 | |
| FLSD 132 M | 272 | 462 | 239 | 55.5 | 142 | 80 | 77 | 173 | 35 | |
| FLSD 132 MU | 272 | 506 | 239 | 55.5 | 142 | 80 | 77 | 173 | 35 | |
| FLSD 132 SM | 272 | 462 | 239 | 55.5 | 142 | 80 | 77 | 173 | 35 | |

*AC: housing diameter without lifting rings

Dimensions in millimetres

Increased safety "eb" terminal box



| Type | J | HJ | I | II |
|---------------------|-----|-----|-----|-----|
| FLSD 80 L | 142 | 203 | 80 | 77 |
| FLSD 90 LU | 142 | 216 | 80 | 77 |
| FLSD 90 SL | 142 | 216 | 80 | 77 |
| FLSD 100 L | 142 | 216 | 80 | 77 |
| FLSD 100 LG | 142 | 225 | 80 | 77 |
| FLSD 112 MG | 142 | 225 | 80 | 77 |
| FLSD 112 MU | 142 | 225 | 80 | 77 |
| FLSD 132 M | 142 | 239 | 80 | 77 |
| FLSD 132 MU | 142 | 239 | 80 | 77 |
| FLSD 132 SM | 142 | 239 | 80 | 77 |
| FLSD 160 L | 246 | 305 | 126 | 147 |
| FLSD 160 LK | 246 | 327 | 126 | 147 |
| FLSD 160 M | 246 | 305 | 126 | 147 |
| FLSD 160 MA | 246 | 305 | 126 | 147 |
| FLSD 160 MB | 246 | 305 | 126 | 147 |
| FLSD 180 L | 246 | 347 | 126 | 147 |
| FLSD 180 M | 246 | 347 | 126 | 147 |
| FLSD 200 L/LA/LB | 246 | 347 | 126 | 147 |
| FLSD 225 MK 4 poles | 246 | 400 | 126 | 147 |
| FLSD 225 MK 6 poles | 352 | 440 | 175 | 210 |
| FLSD 225 MR | 246 | 347 | 126 | 147 |
| FLSD 225 SK | 246 | 400 | 126 | 147 |
| FLSD 250 M | 352 | 440 | 175 | 210 |
| FLSD 280 M | 352 | 440 | 175 | 210 |
| FLSD 280 S | 352 | 440 | 175 | 210 |
| FLSD 315 LA/LB | 400 | 625 | 231 | 339 |
| FLSD 315 M | 400 | 625 | 231 | 339 |
| FLSD 315 S | 400 | 625 | 231 | 339 |

PERMANENTLY GREASED BEARINGS

Under normal operating conditions, the service life in hours (L_{10h}) of the lubricant is indicated in the table below for ambient temperatures less than 55°C.

| Type | Frame size | Polarity | Bearing type Permanently greased | |
|------|--------------------|----------|-------------------------------------|-----------------------|
| | | | Rear bearing N.D.E. | Front Bearing D.E. |
| FLSD | 80 | 2; 4; 6 | 6204 ZZ C3 | 6204 ZZ C3 |
| | 90 | 2; 4; 6 | 6205 ZZ C3 | 6205 ZZ C3 |
| | 100 L | 2; 4; 6 | 6205 ZZ C3 | 6206 ZZ C3 |
| | 100 LG - 112 MG/MU | 2; 4; 6 | 6206 ZZ C3 | 6206 ZZ C3 |
| | 132 M | 2; 4; 6 | 6308 ZZ C3 | 6308 ZZ C3 |

BEARINGS WITH GREASE NIPPLES

For open bearing assemblies of frame size ≥ 160 mm fitted with grease nipples, the table below indicates, depending on the type of motor, the lubrication intervals to be respected at 25°C, 40°C and 55°C for a machine installed with a horizontal shaft.

The table below is valid for FLSD motors lubricated with Polyrex EM103 grease used as standard.

| Series | Type | Polarity | Type of bearings for bearing housings with grease nipples | | 25°C | | | | 40°C | | | | 55°C | | | | |
|--------|------------------------|----------|---|---------|---------|-------|-----------------------------|-------------------------------|-----------------------------|-------------------------------|-----------------------------|-------------------------------|-----------------------------|-------------------------------|-----------------------------|-------------------------------|-------|
| | | | | | N.D.E. | | D.E. | | N.D.E. | | D.E. | | N.D.E. | | D.E. | | |
| | | | | | N.D.E. | D.E. | Quantity of grease in grams | Regreasing intervals in hours | Quantity of grease in grams | Regreasing intervals in hours | Quantity of grease in grams | Regreasing intervals in hours | Quantity of grease in grams | Regreasing intervals in hours | Quantity of grease in grams | Regreasing intervals in hours | |
| FLSD | 160 MA/MB/L | 2 | 6210 C3 | 6309 C3 | 8 | 19300 | 11 | 18500 | 8 | 19300 | 11 | 18500 | 8 | 19300 | 11 | 18500 | |
| | 180 M | | 6212 C3 | 6310 C3 | 11 | 14900 | 13 | 16200 | 11 | 14900 | 13 | 16200 | 11 | 14900 | 13 | 16200 | |
| | 200 LA/LB, 225 MR | | 6313 C3 | 6313 C3 | 20 | 11000 | 20 | 11000 | 20 | 11000 | 20 | 11000 | 20 | 11000 | 20 | 11000 | |
| | 250 M, 280 S/M | | 6314 C3 | 6316 C3 | 23 | 9700 | 29 | 7500 | 23 | 9700 | 29 | 7500 | 23 | 9700 | 29 | 7500 | |
| | 315 S/M (IIB/IIC) | | 6316 C3 | 6218 C3 | 29 | 7500 | 21 | 7500 | 29 | 7500 | 21 | 7500 | 29 | 7500 | 21 | 7500 | |
| | 315 LA/LB (IIB/IIC) | | 6316 C3 | 6218 C3 | 29 | 7500 | 21 | 7500 | 29 | 7500 | 21 | 7500 | 29 | 7500 | 21 | 4700 | |
| | 160 M/L | 4 | 6210 C3 | 6309 C3 | 8 | 25000 | 11 | 25000 | 8 | 25000 | 11 | 25000 | 8 | 25000 | 11 | 25000 | |
| | 180 M/L | | 6212 C3 | 6310 C3 | 11 | 25000 | 13 | 25000 | 11 | 25000 | 13 | 25000 | 11 | 25000 | 13 | 25000 | |
| | 200 L | | 6313 C3 | 6313 C3 | 20 | 25000 | 20 | 25000 | 20 | 25000 | 20 | 25000 | 20 | 25000 | 20 | 25000 | |
| | 225 SK/MK, 250 M | | 6314 C3 | 6316 C3 | 23 | 25000 | 29 | 21900 | 23 | 25000 | 29 | 21900 | 23 | 25000 | 29 | 21900 | |
| | 280 S/M | | 6314 C3 | 6316 C3 | 23 | 25000 | 29 | 21900 | 23 | 25000 | 29 | 21900 | 23 | 25000 | 29 | 13800 | |
| | 315 S (IIB/IIC) | | 6316 C3 | 6320 C3 | 29 | 21900 | 44 | 16600 | 29 | 21900 | 44 | 16600 | 29 | 21900 | 44 | 16600 | |
| | 315 M (IIB/IIC) | | 6316 C3 | 6320 C3 | 29 | 21900 | 44 | 16600 | 29 | 21900 | 44 | 16600 | 29 | 21900 | 44 | 13100 | |
| | 315 LA/LB (IIB/IIC) | | 6316 C3 | 6320 C3 | 29 | 21900 | 44 | 16600 | 29 | 21900 | 44 | 16600 | 29 | 21900 | 44 | 8200 | |
| | 160 M | | 6 | 6210 C3 | 6309 C3 | 8 | 25000 | 11 | 25000 | 8 | 25000 | 11 | 25000 | 8 | 25000 | 11 | 25000 |
| | 160 LK, 180 L | | | 6212 C3 | 6310 C3 | 11 | 25000 | 13 | 25000 | 11 | 25000 | 13 | 25000 | 11 | 25000 | 13 | 25000 |
| | 200 LA/LB | | | 6313 C3 | 6313 C3 | 20 | 25000 | 20 | 25000 | 20 | 25000 | 20 | 25000 | 20 | 25000 | 20 | 25000 |
| | 225 MK, 250 M, 280 S/M | | | 6314 C3 | 6316 C3 | 23 | 25000 | 29 | 25000 | 23 | 25000 | 29 | 25000 | 23 | 25000 | 29 | 25000 |
| | 315 S/M/LA/LB | | | 6316 C3 | 6320 C3 | 29 | 25000 | 44 | 25000 | 29 | 25000 | 44 | 25000 | 29 | 25000 | 44 | 25000 |

CONSTRUCTION AND SPECIAL ATMOSPHERES

For a machine installed with a vertical shaft, the lubrication intervals are approximately 80% of the values shown in the table above.
NB: The quality and quantity of grease along with the lubrication interval are indicated on the machine nameplate.

In the case of special fitting arrangements (motors with roller bearing at the front or other mountings), machines with frame size ≥ 160 mm are fitted with grease nipple bearings.


The instructions required for bearing housing maintenance are shown on the machine nameplate.

BEARING MOUNTING PRINCIPLE

| FLSD series | | Horizontal shaft | Vertical shaft | |
|---|-----------------------|--|--|---|
| | | | Shaft end down | Shaft end up |
| Foot mounted motors | Mounting arrangements | B3 / B6 / B7 / B8 | V5 | V6 |
| | standard fitting | The Front bearing is: - at Front stop for frame size ≤ 132 - locked for 160 ≤ frame size ≤ 315 S The Rear bearing is locked from 315 M to 315 LB. | The Front bearing is: - at Front stop for frame size ≤ 132 - locked for 160 ≤ frame size ≤ 315 S The Rear bearing is locked from 315 M to 315 LB. | The Front bearing is: - at Front stop for frame size ≤ 90 - locked for 100 ≤ frame size ≤ 315 S The Rear bearing is locked from 315 M to 315 LB. |
| | on request | Front bearing locked for frame size ≤ 132 | Front bearing locked for frame size ≤ 132 | Front bearing locked for frame size ≤ 90 |
| Flange mounted motors (or feet and flange) | Mounting arrangements | B5 / B35 / B14 / B34 | V1 / V15 / V18 / V58 | V3 / V36 / V19 / V69 |
| | standard fitting | The Front bearing is locked from 80 to 315 S. The Rear bearing is locked from 315 M to 315 LB. | The Front bearing is locked from 80 to 315 S. The Rear bearing is locked from 315 M to 315 LB. | The Front bearing is locked from 80 to 315 S. The Rear bearing is locked from 315 M to 315 LB. |

Horizontal motor

For a bearing service life L_{10h} of 25,000 hours and 40,000 hours



| Series | Type | Polarity | Permissible axial load (daN) on the main drive shaft for standard fitting of bearings IM B3 / B6 IM B7 / B8 IM B5 / B35 IM B14 / B34 | | | | | | | | | | | |
|--------|------|----------|--|--------------|--------------|--------------|--------------|--------------|--------------|--------------|--------------|--------------|--------------|--------------|
| | | | 3000 rpm | | | | 1500 rpm | | | | 1000 rpm | | | |
| | | | 25,000 hours | 40,000 hours | 25,000 hours | 40,000 hours | 25,000 hours | 40,000 hours | 25,000 hours | 40,000 hours | 25,000 hours | 40,000 hours | 25,000 hours | 40,000 hours |
| FLSD | 80 | 2; 4; 6 | 26.9 | 17.8 | 66.9 | 57.8 | 42.8 | 30.6 | 82.8 | 70.6 | 63.0 | 44.1 | 63.0 | 44.1 |
| | 90 | 2; 4; 6 | 24.7 | 14.9 | 74.7 | 64.9 | 40.2 | 27.0 | 90.2 | 77.0 | 82.0 | 57.4 | 110 | 77.0 |
| | 100 | 2; 4; 6 | 38.2 | 24.8 | 98.2 | 84.8 | 57.7 | 39.8 | 118 | 99.8 | 103 | 72.1 | 138 | 96.6 |
| | 112 | 2; 4; 6 | 36.9 | 23.5 | 96.9 | 83.5 | 58.0 | 40.0 | 118 | 100 | 101 | 70.7 | 140 | 98.0 |
| | 132 | 2; 4; 6 | 100 | 72.4 | 190 | 162 | 146 | 109 | 236 | 199 | 181 | 126.7 | 230 | 161 |
| | 160 | 2; 4; 6 | 201 | 161 | 201 | 161 | 262 | 209 | 262 | 209 | 296 | 235 | 296 | 235 |
| | 180 | 2; 4; 6 | 229 | 183 | 229 | 183 | 272 | 219 | 272 | 219 | 349 | 277 | 349 | 277 |
| | 200 | 2; 4; 6 | 348 | 280 | 348 | 280 | 466 | 372 | 466 | 372 | 530 | 423 | 530 | 423 |
| | 225 | 2; 4; 6 | 343 | 274 | 343 | 274 | 462 | 367 | 462 | 367 | 532 | 425 | 532 | 425 |
| | 250 | 2; 4; 6 | 425 | 332 | 425 | 332 | 531 | 412 | 531 | 412 | 657 | 513 | 657 | 513 |
| | 280 | 2; 4; 6 | 405 | 311 | 405 | 311 | 557 | 434 | 557 | 434 | 656 | 512 | 656 | 512 |
| | 315 | 2; 4; 6 | 486 | 411 | 326 | 276 | 728 | 546 | 528 | 396 | 847 | 635 | 647 | 485 |

IMfinity® ATEX 3-phase induction motors - IE3 efficiency class


ATEX GAS motors - Zone 1

FLSD series - Cast iron - Mechanical characteristics

Axial loads

Vertical motor
Shaft end downwards

For a bearing service life L_{10h}
of 25,000 hours
and 40,000 hours



| Series | Type | Polarity | Permissible axial load (daN) on the main drive shaft for standard fitting of bearings IM V5 IM V1 / V15 IM V18 / V58 | | | | | | | | | | | |
|--------|------|----------|--|--------------|--------------|--------------|--------------|--------------|--------------|--------------|--------------|--------------|--------------|--------------|
| | | | 3000 rpm | | | | 1500 rpm | | | | 1000 rpm | | | |
| | | | 25,000 hours | 40,000 hours | 25,000 hours | 40,000 hours | 25,000 hours | 40,000 hours | 25,000 hours | 40,000 hours | 25,000 hours | 40,000 hours | 25,000 hours | 40,000 hours |
| FLSD | 80 | 2; 4; 6 | 25.3 | 16 | 69.5 | 60.4 | 40.8 | 28.5 | 86.3 | 74.0 | 59.0 | 41.3 | 68.0 | 47.6 |
| | 90 | 2; 4; 6 | 21.9 | 12 | 79.4 | 69.5 | 36.7 | 23.5 | 95.7 | 82.5 | 76.0 | 53.2 | 117 | 81.9 |
| | 100 | 2; 4; 6 | 35.0 | 22 | 104 | 90.2 | 52.9 | 34.8 | 126 | 108 | 95.0 | 66.5 | 146 | 102 |
| | 112 | 2; 4; 6 | 31.0 | 18 | 107 | 93.0 | 50.6 | 32.5 | 130 | 112 | 89.0 | 62.3 | 152 | 106 |
| | 132 | 2; 4; 6 | 89.3 | 61 | 208 | 180 | 133 | 95.3 | 259 | 221 | 156 | 109 | 255 | 179 |
| | 160 | 2; 4; 6 | 176 | 136 | 239 | 199 | 182 | 235 | 309 | 256 | 267 | 205 | 354 | 292 |
| | 180 | 2; 4; 6 | 195 | 148 | 282 | 235 | 264 | 201 | 367 | 304 | 304 | 231 | 432 | 359 |
| | 200 | 2; 4; 6 | 299 | 230 | 422 | 353 | 409 | 314 | 558 | 464 | 471 | 364 | 640 | 533 |
| | 225 | 2; 4; 6 | 289 | 220 | 426 | 357 | 402 | 308 | 559 | 465 | 473 | 365 | 641 | 534 |
| | 250 | 2; 4; 6 | 349 | 257 | 538 | 446 | 525 | 399 | 715 | 589 | 649 | 508 | 837 | 697 |
| | 280 | 2; 4; 6 | 557 | 464 | 308 | 215 | 760 | 633 | 435 | 308 | 897 | 753 | 518 | 374 |
| | 315 | 2; 4; 6 | 306 | 259 | 545 | 461 | 514 | 386 | 861 | 646 | 644 | 483 | 976 | 732 |

Vertical motor
Shaft end upwards

For a bearing service life L_{10h}
of 25,000 hours
and 40,000 hours









| Series | Type | Polarity | Permissible axial load (daN) on the main drive shaft for standard fitting of bearings IM V6 IM V3 / V36 IM V19 / V69 | | | | | | | | | | | |
|--------|------|----------|--|--------------|--------------|--------------|--------------|--------------|--------------|--------------|--------------|--------------|--------------|--------------|
| | | | 3000 rpm | | | | 1500 rpm | | | | 1000 rpm | | | |
| | | | 25,000 hours | 40,000 hours | 25,000 hours | 40,000 hours | 25,000 hours | 40,000 hours | 25,000 hours | 40,000 hours | 25,000 hours | 40,000 hours | 25,000 hours | 40,000 hours |
| FLSD | 80 | 2; 4; 6 | 65.3 | 20.4 | 29.5 | 56.2 | 80.8 | 34.0 | 46.3 | 65.5 | 59.0 | 41.3 | 68.0 | 47.6 |
| | 90 | 2; 4; 6 | 71.9 | 19.5 | 29.4 | 62.0 | 86.7 | 73.5 | 45.7 | 32.5 | 105 | 73.5 | 87 | 60.9 |
| | 100 | 2; 4; 6 | 95.0 | 43.8 | 81.5 | 30.2 | 113 | 94.9 | 66.1 | 48.0 | 130 | 91.0 | 110 | 77.0 |
| | 112 | 2; 4; 6 | 91.0 | 77.5 | 46.5 | 33.0 | 111 | 92.5 | 70.2 | 52.1 | 128 | 89.6 | 112 | 78.4 |
| | 132 | 2; 4; 6 | 179 | 151 | 116 | 87.8 | 223 | 185 | 168 | 131 | 205 | 144 | 206 | 144 |
| | 160 | 2; 4; 6 | 176 | 136 | 238 | 198 | 235 | 182 | 309 | 256 | 267 | 205 | 354 | 292 |
| | 180 | 2; 4; 6 | 194 | 148 | 282 | 235 | 264 | 201 | 367 | 304 | 304 | 231 | 432 | 359 |
| | 200 | 2; 4; 6 | 305 | 236 | 421 | 351 | 409 | 314 | 558 | 464 | 471 | 364 | 640 | 533 |
| | 225 | 2; 4; 6 | 289 | 220 | 426 | 357 | 402 | 308 | 559 | 465 | 473 | 365 | 641 | 534 |
| | 250 | 2; 4; 6 | 349 | 257 | 538 | 446 | 525 | 399 | 715 | 589 | 649 | 508 | 839 | 697 |
| | 280 | 2; 4; 6 | 308 | 215 | 557 | 464 | 435 | 308 | 760 | 633 | 518 | 374 | 897 | 753 |
| | 315 | 2; 4; 6 | 306 | 259 | 545 | 461 | 514 | 386 | 861 | 646 | 644 | 483 | 976 | 732 |

STANDARD FITTING ARRANGEMENT

Permissible radial load on main shaft extension with a bearing life L10h of 25,000 hours.

FR: Radial Force

X: distance with respect to the shaft shoulder










STANDARD FITTING ARRANGEMENT

Permissible radial load on main shaft extension with a bearing life L10h of 25,000 hours.

FR: Radial Force

X: distance with respect to the shaft shoulder



SPECIAL FITTING ARRANGEMENT

Type of drive end roller bearings







| Series | Type | Polarity | Rear bearing (N.D.E.) | Front Bearing (D.E.) |
|--------|------------------------|----------|-----------------------|----------------------|
| FLSD | 160 M/L | 4 | 6210 C3 | NU 309 |
| | 180 M/L | | 6212 C3 | NU 310 |
| | 200 L | | 6313 C3 | NU 313 |
| | 225 SK/MK, 250 M | | 6314 C3 | NU 316 |
| | 280 S/M | | 6314 C3 | NU 316 |
| | 315 S (IIB/IIC) | | 6316 C3 | NU 320 |
| | 315 M (IIB/IIC) | | 6316 C3 | NU 320 |
| | 315 LA/LB (IIB/IIC) | | 6316 C3 | NU 320 |
| | 160 M | 6 | 6210 C3 | NU 309 |
| | 160 LK, 180 L | | 6212 C3 | NU 310 |
| | 200 LA/LB | | 6313 C3 | NU 313 |
| | 225 MK, 250 M, 280 S/M | | 6314 C3 | NU 316 |
| | 315 S/M/LA/LB | | 6316 C3 | NU 320 |

SPECIAL FITTING ARRANGEMENT

Permissible radial load on main shaft extension with a bearing life L10h of 25,000 hours.

FR: Radial Force

X: distance with respect to the shaft shoulder







SPECIAL FITTING ARRANGEMENT

Permissible radial load on main shaft extension with a bearing life L10h of 25,000 hours.

FR: Radial Force

X: distance with respect to the shaft shoulder



DESCRIPTIVE TABLE OF TERMINAL BOXES FOR RATED SUPPLY VOLTAGE 400 V (AS PER EN 50262)

| Series | Type | Number and type of standard drill holes | Max. size of power cable entry/entries | | |
|--------|------|---|--|---|---|
| | | | 1 main entry + 1 auxiliary drill hole ISO M20 x 1.5 | 1 main entry + 2 auxiliary drill holes ISO M20 x 1.5 | 2 main entries + 2 auxiliary drill holes ISO M20 x 1.5 |
| FLSD | 80 | 2 ISO M20 x 1.5 | 1 ISO M32 x 1.5 | 1 ISO M32* x 1.5 | NA |
| | 90 | | | | |
| | 100 | | | | |
| | 112 | 1 ISO M25 x 1.5 | 1 ISO M40 x 1.5 | 1 ISO M40 x 1.5 | 2 ISO M40 x 1.5 |
| | 132 | 1 ISO M20 x 1.5 | | | |
| | 160 | 1 ISO M40 x 1.5 | 1 ISO M63 x 1.5 | 1 ISO M63 x 1.5 | 2 ISO M63 x 1.5 |
| | 180 | 1 ISO M20 x 1.5 | | | |
| | 200 | 1 ISO M50 x 1.5 1 ISO M20 x 1.5 | | | |
| | 225 | 1 ISO M50 x 1.5 1 ISO M20 x 1.5 | 1 ISO M63 x 1.5 | 1 ISO M63 x 1.5 | 2 ISO M63 x 1.5 |
| | 250 | 1 ISO M63 x 1.5 1 ISO M20 x 1.5 | | | |
| | 280 | 1 ISO M63 x 1.5 1 ISO M20 x 1.5 | 1 ISO M80 x 1.5 | 1 ISO M80 x 1.5 | 2 ISO M80 x 1.5 |
| | 315 | 1 ISO M75 x 1.5 1 ISO M20 x 1.5 | | | |

* In "db" and "db eb" terminal boxes, the 2nd auxiliary entry must be installed in position 3.

SUPPLY CABLES

FLSD 80-112

The motors are supplied with cable entries with plugs.

On request, they can be fitted with:

- a larger cable gland,
- a second cable gland for power and/or an ISO M20 x 1.5 cable gland for accessories,
- cable glands for shielded cables.

FLSD 132-315

Motors of sizes greater than or equal to 132 are fitted as standard with a threaded cable entry with plug for power and an ISO M20 x 1.5 auxiliary entry with plug.

As an option, they can be fitted with:

- an oversized cable entry,
- a second cable entry for power and/or an additional entry for auxiliaries,
- cable glands for shielded or non-shielded cable(s).

Depending on the ambient temperature, especially above 40°C, the power cable must be suitable for 100°C.

TERMINAL BLOCKS

DIRECTION OF ROTATION

Standard motors are fitted with a 6-terminal safety block, with the terminal markings complying with or IEC 60034-8.

When the motor is running in U1, V1, W1 or 1U, 1V, 1W from a direct mains supply L1, L2, L3, it turns clockwise when seen from the drive shaft end.

If any two of the phases are changed over, the motor will run in the opposite direction (make sure that the motor has been designed to run in both directions).

If the motor is fitted with accessories (thermal protection or space heater), these must be connected on terminal blocks with labelled wires.

| Frame size | Terminals | Material | Torque tightening (Nm) |
|----------------|-----------|----------|------------------------|
| 80 L to 112 M | M5 | steel | 3.5 |
| 132 S & 132 M | M6 | steel | 5 |
| 160 M & 225 M | M8 | steel | 10 |
| 250 M & 280 M | M10 | steel | 20 |
| 315 S & 315 LB | M12 | steel | 35 |

CABLE GLAND TYPES FOR UNSHIELDED CABLES


(as option only)

Cable gland: Ex for unshielded cable(s)

Type: ADE 1F2

Anchoring: requires additional anchoring

Material: Nickel-plated brass as standard




Example of selection: ADE 1F2 M25 No. 5

| Selection table | | | Dimensions | | | | ADE size |
|-----------------|--------|-------------|-----------------------------------|-----|-----|----|----------|
| Series | Thread | Thread code | Tightening range | A | B | L | |
| | ISO | | External sheath Min - Max (mm) | | | | |
| ADE 1F2 | 12 | M12 | 4.5 - 8.0 | 17 | 17 | 25 | 4 |
| ADE 1F2 | 16 | M16 | 4.5 - 8.5 | 17 | 19 | 25 | 4 |
| ADE 1F2 | 16 | M16 | 7.0 - 12.0 | 19 | 19 | 28 | 5 |
| ADE 1F2 | 20 | M20 | 2.8 - 5.5 | 15 | 24 | 24 | 3 |
| ADE 1F2 | 20 | M20 | 4.5 - 8.5 | 17 | 24 | 25 | 4 |
| ADE 1F2 | 20 | M20 | 7.0 - 12.0 | 19 | 24 | 28 | 5 |
| ADE 1F2 | 20 | M20 | 10.0 - 16.0 | 24 | 24 | 32 | 6 |
| ADE 1F2 | 25 | M25 | 7.0 - 12.0 | 19 | 30 | 28 | 5 |
| ADE 1F2 | 25 | M25 | 10.0 - 16.0 | 24 | 30 | 32 | 6 |
| ADE 1F2 | 25 | M25 | 13.5 - 20.5 | 30 | 30 | 37 | 7 |
| ADE 1F2 | 32 | M32 | 18.0 - 27.5 | 41 | 41 | 46 | 8 |
| ADE 1F2 | 40 | M40 | 23.0 - 34.0 | 48 | 48 | 50 | 9 |
| ADE 1F2 | 50 | M50 | 29.0 - 41.0 | 55 | 55 | 52 | 10 |
| ADE 1F2 | 50 | M50 | 35.0 - 45.0 | 64 | 64 | 57 | 11 |
| ADE 1F2 | 63 | M63 | 42.0 - 56.0 | 72 | 72 | 60 | 12 |
| ADE 1F2 | 75 | M75 | 50.0 - 65.0 | 85 | 85 | 68 | 13 |
| ADE 1F2 | 90 | M90 | 58.0 - 74.0 | 95 | 95 | 69 | 14 |
| ADE 1F2 | 90 | M90 | 66.0 - 83.0 | 110 | 110 | 80 | 15 |
| ADE 1F2 | 110 | M110 | 75.0 - 93.0 | 120 | 120 | 80 | 16 |
| ADE 1F2 | 110 | M110 | 85.0 - 104.0 | 135 | 135 | 90 | 17 |

CABLE GLAND TYPES FOR SHIELDED CABLES

(as option only)

Cable gland: Ex for shielded cable(s)**Type:** ADE 4F**Anchoring:** 100%**Material:** Nickel-plated brass as standard*Example of selection: ADE 4F M25 No. 7*

| Selection table | | | Dimensions | | | | | | ADE size |
|-----------------|--------|-------------|-----------------------------------|-----------------------------------|-----------------------------|-----|-----|-----|----------|
| Series | Thread | Thread code | Tightening range | | Conductors | A | B | L | |
| | ISO | | Internal sheath Min - Max (mm) | External sheath Min - Max (mm) | Shielding thickness (mm) | | | | |
| ADE 4F | 12 | M12 | 4.5 - 8.0 | 7.0 - 12.0 | 0.2 - 0.9 | 19 | 19 | 46 | 5 |
| ADE 4F | 16 | M16 | 2.8 - 5.5 | 4.5 - 8.5 | 0.2 - 0.9 | 17 | 19 | 41 | 4 |
| ADE 4F | 16 | M16 | 4.5 - 8.5 | 7.0 - 12.0 | 0.2 - 0.9 | 19 | 19 | 46 | 5 |
| ADE 4F | 16 | M16 | 7.0 - 12.0 | 10.0 - 16.0 | 0.2 - 1.3 | 24 | 24 | 51 | 6 |
| ADE 4F | 20 | M20 | 2.8 - 5.5 | 4.5 - 8.5 | 0.2 - 0.9 | 17 | 24 | 41 | 4 |
| ADE 4F | 20 | M20 | 4.5 - 8.5 | 7.0 - 12.0 | 0.2 - 0.9 | 19 | 24 | 46 | 5 |
| ADE 4F | 20 | M20 | 7.0 - 12.0 | 10.0 - 16.0 | 0.2 - 1.25 | 24 | 24 | 51 | 6 |
| ADE 4F | 20 | M20 | 10.0 - 15.5 | 13.5 - 21.0 | 0.2 - 1.25 | 30 | 30 | 57 | 7 |
| ADE 4F | 25 | M25 | 7.0 - 12.0 | 10.0 - 16.0 | 0.2 - 1.25 | 24 | 30 | 51 | 6 |
| ADE 4F | 25 | M25 | 10.0 - 15.5 | 13.5 - 21.0 | 0.2 - 1.25 | 30 | 30 | 57 | 7 |
| ADE 4F | 25 | M25 | 13.5 - 20.5 | 18.0 - 27.5 | 0.2 - 1.6 | 41 | 41 | 68 | 8 |
| ADE 4F | 32 | M32 | 13.5 - 21.0 | 18.0 - 27.5 | 0.2 - 1.6 | 41 | 41 | 68 | 8 |
| ADE 4F | 32 | M32 | 18.0 - 26.0 | 23.0 - 34.0 | 0.2 - 1.6 | 48 | 48 | 76 | 9 |
| ADE 4F | 40 | M40 | 18.0 - 27.5 | 23.0 - 34.0 | 0.2 - 1.6 | 48 | 48 | 76 | 9 |
| ADE 4F | 40 | M40 | 23.0 - 34.0 | 29.0 - 41.0 | 0.2 - 2.0 | 55 | 55 | 88 | 10 |
| ADE 4F | 50 | M50 | 23.0 - 34.0 | 29.0 - 41.0 | 0.2 - 2.0 | 55 | 55 | 88 | 10 |
| ADE 4F | 50 | M50 | 29.0 - 41.0 | 35.0 - 48.0 | 0.2 - 2.5 | 64 | 64 | 97 | 11 |
| ADE 4F | 63 | M63 | 35.0 - 48.0 | 42.0 - 56.0 | 0.2 - 2.5 | 72 | 72 | 102 | 12 |
| ADE 4F | 63 | M63 | 42.0 - 53.0 | 50.0 - 65.0 | 0.2 - 2.5 | 85 | 85 | 117 | 13 |
| ADE 4F | 75 | M75 | 42.0 - 56.0 | 50.0 - 65.0 | 0.2 - 2.5 | 85 | 85 | 117 | 13 |
| ADE 4F | 75 | M75 | 52.0 - 62.5 | 58.0 - 74.0 | 0.2 - 2.5 | 95 | 95 | 124 | 14 |
| ADE 4F | 90 | M90 | 58.0 - 74.0 | 66.0 - 83.0 | 0.2 - 3.15 | 110 | 110 | 133 | 15 |
| ADE 4F | 90 | M90 | 66.0 - 78.0 | 75.0 - 93.0 | 0.2 - 3.15 | 120 | 120 | 140 | 16 |
| ADE 4F | 90 | M90 | 66.0 - 83.0 | 85.0 - 104.0 | 0.2 - 3.5 | 135 | 135 | 150 | 17 |
| ADE 4F | 110 | M110 | 75.0 - 93.0 | 85.0 - 104.0 | 0.2 - 3.5 | 135 | 135 | 150 | 17 |

| Mechanical adaptations | Frame size |
|--|----------------|
| DE and NDE bearings with 1 machining, for vibration sensor in position 12H, 12H-3H, or 12H-3H-9H | ≥ 160 |
| Different FF flanges from IEC | All |
| Different FT flanges from IEC | ≤ 132 |
| DE roller bearing | ≥ 160 - 4p & + |
| Insulated DE or NDE bearing | ≥ 280 |
| 2 nd standard catalogue NDE shaft end | All |
| 2 nd special NDE shaft end | All |
| Keyed cylindrical NDE shaft (secondary shaft end) as per IEC | All |
| Stainless-steel shaft | All |
| Class B balancing | All |
| Stainless steel fan cover | All |
| Steel fan cover + drip cover | All |
| Metal fan | All |
| Nameplate in stainless steel (as standard from HA 160 on) | All |
| Stainless-steel fastenings | ≥ 160 |
| Three-phase axial forced ventilation - IC 416 A | ≥ 160 |
| Incremental encoder / 1024 or 4096 pts / 5v or 11/30 V | All |
| Condensates evacuation holes | ≥ 160 |
| Positioning holes (jacking screws) | ≥ 250 |
| Radial seal for motor in vertical position with shaft end upwards | All |
| Electrical adaptations | Frame size |
| Terminal board with anti-rotation system as standard | All |
| Increased safety "eb" terminal box | All |
| Non-magnetic PE support plate for "db eb" version | ≥ 160 |
| Special voltages (excluding variable speed) | All |
| Definition for Id/In ≤ 7.5 | All |
| Insulation class H | ≥ 160 |
| Auxiliary boxes for "db eb" motors | ≥ 160 |
| ATEX brass PE for unshielded cable | All |
| ATEX brass PE for shielded cable | All |
| ATEX brass PE auxiliary for unshielded cable | All |
| ATEX brass PE auxiliary for shielded cable | All |
| Flying lead via 1 metre single-core cable 6 + 1 | ≥ 160 |
| Cable entry on the left as seen from the shaft end | All |
| Preparation for NPT cable glands | All |
| Protection | Frame size |
| Standard winding PTC thermistor probe (triple probe) | All |
| Winding PT 100 probe (1 per phase) | All |
| Endshield PTC thermistor probe (triple probe) | ≥ 160 |
| Endshield PT 100 probe (per probe) | ≥ 160 |
| Endshield thermocouple | ≥ 160 |
| Endshield PTO or PTF thermostatic probe | ≥ 160 |
| Space heaters when stopped (220-230 V) | All |
| Finish | Frame size |
| VIK version for "db eb IIC" motors (see page 20) | All |
| IP 65 | All |
| Definition for gas + dust motor, Ex t IIIB / IIIC T125°C Db | All |
| IP 56 stopped with fan (IC 411) | All |
| C3H, C4M, C4H, C5-IL or C5-IM paint | All |
| Other paint shades | All |
| Operating temperature: -55°C < T° < -20°C or -55°C < T° < +60°C | All |
| Version for temperature class T5 | All |
| Version for temperature class T6 | All |
| Complete tropicalization (stator + rotor) | All |

Dimensions in millimetres


MODIFIED FLANGES

| Motor type | Flange type | (FF) Flange mounted | | | | (FT) Face mounted | | | | |
|------------|-------------|---------------------|--------|--------|--------|-------------------|--------|--------|--------|--------|
| | | FF 130 | FF 165 | FF 215 | FF 265 | FT 100 | FT 115 | FT 130 | FT 165 | FT 215 |
| FLSD 80 | | ■ | ● | | | ● | | | | |
| FLSD 90 | | ◆ | ● | | | | ● | | | |
| FLSD 100 | | | ◆ | ● | | | | ● | | |
| FLSD 112 | | | ■ | ● | | | | ● | | |
| FLSD 132 | | | | | ● | | | | ■ | ● |

● Standard ■ Modified shaft ◆ Adaptable without shaft modifications

DRIP COVER FOR OPERATION IN VERTICAL POSITION, SHAFT END DOWNWARDS

| Motor type | LB' | Ø |
|--------------|----------|-----|
| FLSD 80 | LB + 22 | 145 |
| FLSD 90-100 | LB + 25 | 185 |
| FLSD 112 | LB + 25 | 208 |
| FLSD 132 | LB + 35 | 238 |
| FLSD 160 M/L | LB + 58 | 300 |
| FLSD 180 M/L | LB + 66 | 350 |
| FLSD 200 L | LB + 66 | 350 |
| FLSD 225 S/M | LB + 66 | 350 |
| FLSD 250 M | LB + 74 | 470 |
| FLSD 280 S/M | LB + 74 | 470 |
| FLSD 315 | LB + 125 | 420 |



SPACE HEATERS

| Type | Power (W) |
|-----------------|-----------|
| FLSD 80 | 16 |
| FLSD 90 to 132 | 25 |
| FLSD 160 to 200 | 50 |
| FLSD 225 to 250 | 100 |
| FLSD 280 to 315 | 100* |

The space heaters use 200/240 V single-phase, 50 or 60 Hz.

* Power increase possible subject to quote.

FORCED VENTILATION

The ATEX motors described in this catalogue are certified to be supplied with variable speed drives.

This type of application sometimes requires the installation of forced ventilation for use at low speed (heating) or high speed (noise), in addition to the thermal protections.

The installation of an axial forced ventilation is recommended for motors with frame size ≥ 160 .

Safety conditions: the forced ventilation is controlled by the power supply and must have the same degree of flameproof protection as the FLSD motor.

In order to adapt the motor to the application, it is necessary to inform the manufacturer of the operating characteristics (speed range, voltage, frequency, etc.).

LIFTING THE MOTOR ONLY
(not coupled to the machine)


The regulations stipulate that in excess of 25 kg suitable handling equipment must be used.

A diagram of the sling hoisting method appears below with the required dimensions.

To prevent any damage to the motor during handling (for example: switching


the motor from horizontal to vertical), it is essential to follow these instructions.

HORIZONTAL POSITION



| Type | Horizontal position | | | |
|----------------|---------------------|--------|--------|----|
| | A | min. e | min. h | Øt |
| FLSD 90 | 152 | 150 | 190 | 22 |
| FLSD 100 | 152 | 150 | 190 | 22 |
| FLSD 100 LG | 146 | 200 | 190 | 22 |
| FLSD 112 | 146 | 200 | 190 | 22 |
| FLSD 132 | 176 | 180 | 190 | 22 |
| FLSD 160 M/L | 292 | 250 | 300 | 30 |
| FLSD 160 LK | 324 | 250 | 300 | 30 |
| FLSD 180 M/L | 324 | 250 | 300 | 30 |
| FLSD 200 L | 350 | 300 | 300 | 35 |
| FLSD 225 MR | 350 | 300 | 300 | 35 |
| FLSD 225 SK/MK | 415 | 400 | 400 | 35 |
| FLSD 250 M | 415 | 400 | 400 | 35 |
| FLSD 280 S/M | 430 | 400 | 400 | 40 |
| FLSD 315 S/M/L | 445 | 400 | 500 | 35 |

VERTICAL POSITION



| Type | Vertical position | | | | | | |
|----------------|-------------------|-----|-----|-----|----|---------|--------|
| | C | E | D | n** | ØS | min. e* | min. h |
| FLSD 160 M/L | / | 292 | 270 | 3 | 30 | 360 | 400 |
| FLSD 160 LK | / | 324 | 300 | 3 | 30 | 410 | 450 |
| FLSD 180 M/L | / | 324 | 300 | 3 | 30 | 410 | 450 |
| FLSD 200 L | / | 350 | 360 | 3 | 35 | 445 | 500 |
| FLSD 225 MR | / | 350 | 360 | 3 | 35 | 445 | 500 |
| FLSD 225 SK/MK | / | 415 | 380 | 3 | 35 | 560 | 600 |
| FLSD 250 M | / | 415 | 380 | 3 | 35 | 560 | 600 |
| FLSD 280 S/M | / | 430 | 430 | 3 | 40 | 560 | 650 |
| FLSD 315 S/M/L | 630 | 445 | 817 | 2 | 35 | 650 | 550 |

* If the motor is fitted with a drip cover, allow an additional 50 to 100 mm to avoid damaging it when the load is swung.

** If n = 2, the lifting rings form an angle of 90° with respect to the terminal box axis.

If n = 4, this angle becomes 45°.

Separate ring ≤ 25 kg
Built-in ring > 25 kg


ATEX GAS motors - Zone 2

FLSN series




II 3 G Ex ec II C T3 Gc

Premium Efficiency
 IE3 cast iron on mains
 IE3 cast iron on drive



The complete motor **reference** described below will enable you to **order** the desired equipment.

The selection method consists of following the terms in the designation.



ATEX GAS - Zone 2 - Cast iron

NAMEPLATES

The nameplate identifies the motors, indicates the main performance and shows compatibility of the motor

concerned with the main standards and regulations concerning them.

All motors in this catalogue with power between 0.75 and 400 kW are fitted with two information plates: one indicating

the motor's performance when supplied from the mains, and the other the motor's performance when supplied from a drive.

DEFINITION OF SYMBOLS USED ON NAMEPLATES

 Legal mark of conformity of product to the requirements of European Directives

SPECIFIC MARKING: ATEX  **IECEX**

II 3G or II 3G and II 3D: ATEX/IECEX marking

Ex ec: "non-sparking enclosure" protection mode

IIC: "gas" equipment group

T3: "gas" temperature class

Gc: "gas" EPL level

Ex tc: "dust" protection mode (option)

IIIC: "dust" equipment group (if tc)

T125°C: max. surface temperature (if tc)

Dc: "dust" EPL level

INERIS ... X: ATEX attestation number

IECEX INE...: IECEX certificate No.

| Zone | ATEX/IECEX marking | Gas protection mode marking | Dust protection mode marking (if tc) | Protection rating min. |
|--------|--|-----------------------------|--------------------------------------|------------------------|
| 2 |  II 3 G | Ex ec IIC T3 Gc | / | IP 55 |
| 2 & 22 |  II 3 D | Ex ec IIC T3 Gc | Ex tc IIIC T125°C Dc | IP 65 |

MOTOR SYMBOLS

MOT 3 ~: three-phase AC motor

FLSN: motor type

280: frame size

M: housing symbol

4: 4 poles

B3: operating position

No.: Serial number

2017: year of construction

IM: operating position symbol

°C: maximum ambient temperature

Ins. cl.: winding insulation class

S: standard operating duty

%: operating duty

d/h: number of starts per hour

SF: duty factor

IE %: efficiency level and efficiency at rated load and voltage

2/4: efficiency at 2/4 load

3/4: efficiency at 3/4 load

kg: weight

DE: drive end bearing

NDE: non drive end bearing

g: quantity of grease to be added per bearing at each re-lubrication (in g)

h: interval in hours between re-lubrication

IP: protection rating

IK: shock resistance

m: maximum operating altitude

V: supply voltage

Hz: supply frequency

min⁻¹: speed of rotation (rpm)

kW: rated power

A: rated current

cos: power factor

%: efficiency at 4/4 load

Δ: delta coupling

∧: star coupling

POLYREX EM 103: bearing grease reference

Insulated bearing: NDE: isolated non drive end bearing

Manufactured by CEB: equipment manufacturer

EAC Ex: equipment for explosive atmospheres certified for Eurasia

cURus E68554: insulation system class F homologated for USA and Canada

 : vibration level code

 : balancing mode code

 : starting requirements code

279 E: plate reference

Inverter settings PWM: characteristics for setting the PWM drive enabling compliance with the motor temperature class

Motor performance valid for 400 V - 50 Hz at inverter input: motor performance valid for 400V - 50Hz at drive input

Duty S9: performances given for S9 duty

Min.Fsw: minimum switching frequency of the drive in kHz

Nmax: admissible maximum motor speed in min⁻¹ (rpm)

PTC 140°C: PTC sensor type - temperature limit = 140°C

IVIC: pulse voltage insulation class code

CAST IRON MOTOR NAMEPLATES - FLSN ZONE 2

Mains supply plate

MOT. 3 ~ FLSN 280 M4 B3
 N° E0776301EC01 2017 645 kg
 Nidec LEROY-SOMER DE 6316 C3 13 g 18500 h IP 55 1000 m
 NDE 6314 C3 10 g 18500 h IK 08 IM 1001 IE 3
 40°C Ins cl.F S1 % d/h SF 94,9 %

| V | Hz | min ⁻¹ | kW | A | cos φ | % |
|-------|----|-------------------|-----|-----|-------|------|
| Δ 400 | 50 | 1485 | 90 | 166 | 0,83 | 94,9 |
| Δ 690 | | | | 96 | | |
| Δ 415 | | 1485 | | 163 | 0,81 | 95,1 |
| Δ 460 | 60 | 1785 | 104 | 164 | 0,84 | 95 |

 POLYREX EM 103 PTC 140°C
 II 3 G - Ex ec IIC T3 Gc EAC : 2Ex e IIC T3 Gc X
 Manufactured by CEB - F 90500 BEAUCOURT
 INERIS 18ATEX3011 X IECEx INE 19.0015X
 IEC 60034-1 - MADE IN FRANCE

Drive supply plate

MOT. 3 ~ FLSN 280 M4 B3
 N° E0776301EC01
 Nidec LEROY-SOMER

| Inverter settings PWM | | | | | |
|-----------------------|----|-------------------|----|-----|-------|
| V | Hz | min ⁻¹ | kW | A | cos φ |
| Δ 400 | 50 | 1485 | 90 | 166 | 0,83 |

 Motor performance valid for : 400 V - 50 Hz at inverter input

| Hz | 10 | 17 | 25 | 50 | 60 | 87 |
|-------|----|----|----|-----|-----|----|
| T/Tn% | 87 | 92 | 98 | 100 | 100 | 57 |

 Duty S9 Min. Fsw : 3 kHz Nmax : 2610 min⁻¹
 PTC 140°C
 280 E IVIC C

3 ~ P FLSN132MR
 Nidec LEROY-SOMER IP65 IK08 T
 Ta40°C Ins Cl.F S1 1000m 89kg 90,4%
 IEC Ex IIC 04
 INERIS 01ATEX3004X IECEx INE10.0012X
 II 3 GD Exec IIC T3 Gc Ex tc IIC T125°C Dc
 DE 6308 ZZ C3 NDF 6308 ZZ C3

| V | Hz | min ⁻¹ | kW | cos φ | A |
|-------|----|-------------------|------|-------|------|
| Δ 230 | 50 | 1460 | 7.50 | 0.88 | 23.9 |
| Δ 400 | 50 | 1460 | 7.50 | 0.88 | 13.8 |
| Δ 415 | 50 | 1464 | 7.50 | 0.85 | 13.5 |
| Δ 460 | 60 | 1768 | 7.50 | 0.85 | 12.1 |

 PTC 130°C

3 ~ 4P FLSN132MR
 Nidec LEROY-SOMER IP65 IK08 T
 Ta40°C Ins Cl.F S9 1000m 89kg
 IEC Ex IIC 04
 INERIS 01ATEX3004X IECEx INE10.0012X
 II 3 GD Exec IIC T3 Gc Ex tc IIC T125°C Dc
 DE 6308 ZZ C3 NDF 6308 ZZ C3

| Inverter settings | | | | | |
|-------------------|----|-------------------|------|-------|------|
| V | Hz | min ⁻¹ | kW | cos φ | A |
| Δ 400 | 50 | 1456 | 7.50 | 0.88 | 14.9 |

| Motor performance | | | | | |
|-------------------|-----|-----|-----|-----|----|
| Hz | 10 | 17 | 25 | 50 | 87 |
| T/Tn% | 100 | 100 | 100 | 100 | 57 |

 min. Fsw (beta) 3
 Tn (beta) 49.1
 PTC 130°C

The motor enclosure is designed in such a way that no sparks can be produced under any motor operating conditions within the manufacturer's allowable limits, and no temperature rise can occur during normal operation.

The Ex ec motors in cast iron casings from Nidec Leroy-Somer are certified to

comply with Directive 2014/34/EU and the IECEx system regulations.

Nidec Leroy-Somer can also provide self-certification with a Declaration of Conformity.

Lastly, Ex ec motors can also be used for applications in Ex t zone 22 dusty atmospheres.

The following definitions are therefore possible:

- Ex tc IIIB T125°C Dc, IP 55 for zone 22 + Ex ec IIC T3
- Ex tc IIIC T125°C Dc, IP 65 for zone 22 + Ex ec IIC T3

| Designations | Materials | Comments |
|-----------------------------|---|--|
| Finned housing | Cast iron | - lifting rings for frame size ≥ 90 - ground terminal with an optional jumper screw - stainless steel nameplate with marking |
| Stator | Insulated low-carbon magnetic steel laminations Electroplated copper | - low carbon content guarantees long-term lamination pack stability - plate assemblies - semi-enclosed slots - class F insulation - 1 set of PTC sensors in the windings from FLSN 80 to FLSN 355 |
| Rotor | Insulated low-carbon magnetic steel laminations Aluminium | - inclined cage bars - rotor cage pressure die-cast in aluminum (or alloys for special applications) or copper-soldered - assembly by hot shrinking on the shaft or by keying for soldered rotor - class A rotor balanced dynamically, 1/2 key |
| Shaft | Steel | - for frame size ≤ 132: closed keyway - for frame size ≥ 160: open keyway |
| End shields | Cast iron | |
| Bearings and lubrication | | - protected ball bearings, permanently greased for frame size 80 to 225 - protected ball bearings, regreasable for frame size 250 to 355 - preloaded bearings at the rear up to 315 S, at the front from 315 M |
| Labyrinth seal Lip seals | Technopolymer or steel Synthetic rubber | - labyrinth seal at front for foot mounted motors with frame size ≤ 132 - front gasket for foot and face mounted motors or fastening flanges with frame size ≤ 132 - gasket at front and rear for frame sizes 160 to 250 included - decompression grooves for 280 M to 355 LD |
| Fan | Composite up to and including 280 Metallic from 315 S | - bi-directional: straight blades |
| Fan cover | Steel plate | - fitted, on request, with a drip cover for operation in vertical position, shaft end downwards |
| Terminal box | Body and cover in cast iron for all frame sizes | - IP 55 or IP 65 - fitted with a terminal block with 6 terminals up to 355 LD - terminal box fitted with plugs up to 132 - from 160 to 355, drilled cable gland support plate with plugs (optional flared feed and cable gland) - 1 ground terminal in each terminal box |

CORROBLOC FINISH

The Corrobloc finish is a top coat for the basic cast iron motor described above. In addition to the basic construction its special finishes resist corrosion in particularly harsh environments. and these qualities are enhanced with age.

| Designations | Materials | Comments |
|----------------|----------------------------------|--|
| Stator - Rotor | | - dielectric and anti-corrosion protection for frame sizes 80 to 132 |
| Nameplate | Stainless steel | - nameplate: indelible marking |
| Fastenings | Stainless steel | - captive terminal box cover screws frame size ≤ 132 |
| Terminal box | Body and cover made of cast-iron | |
| Cable gland | Brass | - optional |
| Paint finish | | - C4M system (see Paint section) |



ATEX GAS - Zone 2 - Cast iron

| Type | Rated power P _n kW | Rated torque M _n N.m | Starting torque/ Rated torque M _d /M _n | Maximum torque/ Rated torque M _m /M _n | Starting current/ Rated current I _d /I _n | Moment of inertia J kg.m ² | Weight IM B3 kg | Noise LP db(A) | 400V 50Hz | | | | | | | |
|----------------|-------------------------------------|---------------------------------------|--|---|--|---|-----------------------|----------------------|--|--------------------------------------|-------------------------------------|----------|--------------|------|--------------|------|
| | | | | | | | | | Rated speed N _n min ⁻¹ | Rated current I _n A | Efficiency IEC 60034-2-1 2007 | | Power factor | | | |
| | | | | | | | | | | | η 4/4 | η 3/4 | 2/4 | 4/4 | Cos φ 3/4 | 2/4 |
| 2 poles | | | | | | | | | | | | | | | | |
| FLSN 80 L | 0.75 | 2.5 | 2.8 | 3.6 | 7 | 0.00095 | 16.2 | 59 | 2885 | 1.6 | 82.6 | 82.7 | 80.5 | 0.82 | 0.75 | 0.62 |
| FLSN 80 LG | 1.1 | 3.65 | 2.4 | 3.1 | 6.8 | 0.00201 | 22.5 | 59 | 2885 | 2.2 | 85.6 | 86.6 | 85.9 | 0.85 | 0.79 | 0.68 |
| FLSN 90 SL | 1.5 | 4.95 | 2.9 | 3 | 7 | 0.00223 | 24 | 68 | 2890 | 3 | 85.1 | 86.1 | 85.4 | 0.85 | 0.79 | 0.68 |
| FLSN 90 LU | 2.2 | 7.25 | 3.4 | 3.2 | 8.1 | 0.00292 | 28.2 | 70 | 2895 | 4.25 | 87.0 | 88.2 | 88.1 | 0.86 | 0.80 | 0.70 |
| FLSN 100 LG | 3 | 9.8 | 3 | 3.6 | 8.3 | 0.00822 | 41.5 | 67 | 2935 | 5.6 | 88.5 | 88.8 | 87.6 | 0.88 | 0.83 | 0.73 |
| FLSN 112 MG | 4 | 13.1 | 2.1 | 3 | 7.3 | 0.00941 | 44.8 | 66 | 2920 | 7.3 | 88.5 | 89.5 | 89.4 | 0.89 | 0.85 | 0.77 |
| FLSN 132 SM | 5.5 | 17.9 | 2 | 2.8 | 6.4 | 0.00974 | 69.3 | 67 | 2935 | 10.3 | 90.0 | 90.8 | 90.4 | 0.86 | 0.82 | 0.73 |
| FLSN 132 SM | 7.5 | 24.4 | 2 | 2.9 | 6.9 | 0.01102 | 74.6 | 67 | 2940 | 13.8 | 91.2 | 92.0 | 91.8 | 0.86 | 0.82 | 0.75 |
| FLSN 160 M | 11 | 35.6 | 3.3 | 3 | 8.2 | 0.0712 | 120 | 68 | 2950 | 19.9 | 91.9 | 92.4 | 92.0 | 0.87 | 0.83 | 0.75 |
| FLSN 160 M | 15 | 48.6 | 2.9 | 2.9 | 7.2 | 0.0551 | 133 | 68 | 2950 | 26.7 | 92.4 | 93.1 | 93.1 | 0.88 | 0.85 | 0.79 |
| FLSN 160 LUR | 18.5 | 59.9 | 2.8 | 2.7 | 7.4 | 0.0626 | 135 | 69 | 2950 | 32.9 | 92.5 | 93.2 | 93.2 | 0.88 | 0.86 | 0.79 |
| FLSN 180 MUR | 22 | 71.2 | 3 | 3.4 | 8 | 0.1012 | 195 | 74 | 2952 | 38 | 93.6 | 94.1 | 93.8 | 0.89 | 0.87 | 0.81 |
| FLSN 200 LU | 30 | 97.1 | 2.1 | 3 | 7.2 | 0.1186 | 210 | 71 | 2950 | 53.1 | 93.9 | 94.3 | 94.0 | 0.87 | 0.84 | 0.77 |
| FLSN 200 LU | 37 | 120 | 2 | 3.3 | 6.9 | 0.1388 | 230 | 75 | 2945 | 64.5 | 94.0 | 94.6 | 94.5 | 0.88 | 0.86 | 0.80 |
| FLSN 225 MR | 45 | 145 | 2.3 | 3.1 | 7.1 | 0.1597 | 254 | 71 | 2956 | 81.8 | 94.4 | 94.7 | 94.4 | 0.84 | 0.80 | 0.70 |
| FLSN 250 M | 55 | 177 | 2.1 | 3.2 | 7.6 | 0.3356 | 378 | 78 | 2968 | 95.3 | 94.5 | 94.6 | 93.7 | 0.88 | 0.85 | 0.79 |
| FLSN 280 S | 75 | 241 | 2.1 | 2.7 | 7 | 0.48 | 565 | 79 | 2966 | 126 | 94.9 | 95.3 | 95.2 | 0.91 | 0.89 | 0.85 |
| FLSN 280 M | 90 | 290 | 2.2 | 2.8 | 7.4 | 0.57 | 615 | 80 | 2967 | 151 | 95.3 | 95.7 | 95.5 | 0.90 | 0.89 | 0.85 |
| FLSN 315 S | 110 | 353 | 2.1 | 2.6 | 6.7 | 1.17 | 940 | 82 | 2975 | 185 | 95.9 | 96.0 | 95.5 | 0.90 | 0.89 | 0.85 |
| FLSN 315 M | 132 | 424 | 2.1 | 2.5 | 6.7 | 1.25 | 1015 | 82 | 2975 | 221 | 96.0 | 96.1 | 95.6 | 0.90 | 0.89 | 0.84 |
| FLSN 315 LA | 160 | 514 | 2 | 2.9 | 6.6 | 1.34 | 1088 | 82 | 2975 | 268 | 96.0 | 96.1 | 95.6 | 0.90 | 0.89 | 0.84 |
| FLSN 315 LB | 200 | 643 | 2.1 | 2.9 | 6.9 | 1.45 | 1150 | 82 | 2973 | 334 | 96.3 | 96.5 | 96.0 | 0.90 | 0.88 | 0.84 |
| FLSN 355 LA | 250 | 802 | 2.2 | 2.9 | 6.8 | 3.02 | 1590 | 83 | 2978 | 428 | 96.0 | 96.0 | 95.3 | 0.88 | 0.86 | 0.80 |
| FLSN 355 LB | 315 | 1008 | 2.6 | 3 | 7.8 | 3.62 | 1740 | 84 | 2983 | 537 | 96.3 | 96.4 | 96.2 | 0.88 | 0.86 | 0.82 |
| FLSN 355 LC | 355 | 1137 | 2.8 | 2.7 | 7.1 | 3.64 | 1740 | 84 | 2981 | 610.2 | 96.3 | 96.4 | 96.2 | 0.87 | 0.86 | 0.82 |
| FLSN 355 LD | 400 | 1284 | 2.7 | 2.7 | 7 | 3.70 | 1770 | 84 | 2986 | 667.3 | 97.1 | 97.2 | 96.9 | 0.89 | 0.88 | 0.86 |

For power > 400 kW, please contact us.

| | | | | | | | | | | | | | | | | |
|----------------|------|------|-----|-----|-----|---------|------|----|------|-------|------|------|------|------|------|------|
| 4 poles | | | | | | | | | | | | | | | | |
| FLSN 80 LG | 0.75 | 4.95 | 2.2 | 3.1 | 6.6 | 0.00335 | 22 | 57 | 1452 | 1.6 | 83.8 | 84.4 | 83.1 | 0.79 | 0.71 | 0.58 |
| FLSN 90 SL | 1.1 | 7.25 | 2.4 | 3.2 | 7.5 | 0.00418 | 24.6 | 48 | 1450 | 2.3 | 84.9 | 85.8 | 85.0 | 0.81 | 0.74 | 0.61 |
| FLSN 90 LU | 1.5 | 9.85 | 2.8 | 3.5 | 7.3 | 0.00524 | 28.2 | 51 | 1454 | 3.2 | 85.4 | 85.8 | 84.1 | 0.78 | 0.70 | 0.56 |
| FLSN 100 LR | 2.2 | 14.5 | 3.4 | 3.8 | 8.2 | 0.00676 | 36.4 | 49 | 1452 | 4.6 | 86.9 | 87.4 | 86.2 | 0.78 | 0.70 | 0.57 |
| FLSN 100 LG | 3 | 19.6 | 2.4 | 3.2 | 7.3 | 0.01152 | 42.2 | 50 | 1462 | 6 | 88.7 | 89.3 | 88.7 | 0.82 | 0.76 | 0.64 |
| FLSN 112 MU | 4 | 26.2 | 2.7 | 3.1 | 7 | 0.01429 | 49 | 50 | 1458 | 8.1 | 88.8 | 89.5 | 88.9 | 0.80 | 0.75 | 0.64 |
| FLSN 132 SM | 5.5 | 35.9 | 2.8 | 3.6 | 8.3 | 0.02286 | 70.9 | 60 | 1462 | 10.5 | 90.1 | 90.7 | 90.2 | 0.84 | 0.78 | 0.67 |
| FLSN 132 MR | 7.5 | 49.1 | 2.8 | 3.4 | 8.4 | 0.03313 | 89.4 | 61 | 1460 | 13.8 | 90.6 | 91.5 | 91.3 | 0.86 | 0.81 | 0.71 |
| FLSN 160 M | 11 | 71.7 | 2.2 | 2.8 | 7.6 | 0.0712 | 115 | 59 | 1466 | 20.1 | 91.7 | 92.7 | 92.8 | 0.86 | 0.82 | 0.73 |
| FLSN 160 LUR | 15 | 97.4 | 2.3 | 3.2 | 8 | 0.0954 | 140 | 58 | 1470 | 27.2 | 92.3 | 93.0 | 92.9 | 0.86 | 0.82 | 0.72 |
| FLSN 180 M | 18.5 | 120 | 3 | 3.3 | 8 | 0.1333 | 165 | 67 | 1470 | 34.1 | 92.8 | 93.5 | 93.4 | 0.84 | 0.80 | 0.71 |
| FLSN 180 LUR | 22 | 143 | 3.3 | 3.3 | 7.9 | 0.1555 | 190 | 68 | 1470 | 41.3 | 93.0 | 93.6 | 93.4 | 0.83 | 0.79 | 0.69 |
| FLSN 200 LU | 30 | 194 | 3 | 2.9 | 7.2 | 0.2035 | 250 | 64 | 1474 | 54.9 | 93.9 | 94.4 | 94.2 | 0.84 | 0.80 | 0.70 |
| FLSN 225 S | 37 | 238 | 2 | 2.6 | 6.7 | 0.5753 | 355 | 65 | 1484 | 67.5 | 94.0 | 94.4 | 94.1 | 0.84 | 0.80 | 0.71 |
| FLSN 225 M | 45 | 289 | 2.1 | 2.7 | 6.7 | 0.6482 | 380 | 64 | 1486 | 84.4 | 94.9 | 95.2 | 94.9 | 0.81 | 0.76 | 0.66 |
| FLSN 250 MR | 55 | 354 | 2 | 2.4 | 6.9 | 0.7701 | 440 | 67 | 1482 | 101 | 94.8 | 95.2 | 95.1 | 0.83 | 0.79 | 0.70 |
| FLSN 280 S | 75 | 482 | 2.4 | 2.8 | 7.5 | 0.85 | 595 | 74 | 1484 | 137 | 95.0 | 95.2 | 94.9 | 0.83 | 0.79 | 0.69 |
| FLSN 280 M | 90 | 579 | 2.7 | 2.7 | 7.9 | 0.98 | 645 | 74 | 1483 | 165.2 | 95.3 | 95.7 | 95.3 | 0.83 | 0.78 | 0.68 |
| FLSN 315 S | 110 | 707 | 2.1 | 2.7 | 7.1 | 1.84 | 930 | 74 | 1486 | 196 | 95.6 | 95.7 | 95.2 | 0.85 | 0.81 | 0.73 |
| FLSN 315 M | 132 | 848 | 2.8 | 2.8 | 6.8 | 2.09 | 985 | 74 | 1487 | 234 | 95.9 | 95.9 | 95.6 | 0.85 | 0.82 | 0.76 |
| FLSN 315 LA | 160 | 1030 | 2.3 | 2.5 | 6.4 | 2.35 | 1045 | 74 | 1484 | 277 | 96.0 | 96.3 | 96.1 | 0.87 | 0.85 | 0.78 |
| FLSN 315 LB | 200 | 1287 | 2.7 | 3 | 7.2 | 2.86 | 1245 | 74 | 1486 | 354 | 96.2 | 96.4 | 96.0 | 0.85 | 0.81 | 0.72 |
| FLSN 355 LA | 250 | 1604 | 2.6 | 3.1 | 7.5 | 4.90 | 1445 | 80 | 1488 | 436 | 96.3 | 96.4 | 94.7 | 0.86 | 0.82 | 0.71 |
| FLSN 355 LAL | 280 | 1798 | 2.3 | 2.9 | 7.3 | 5.80 | 1560 | 80 | 1489 | 483 | 96.2 | 96.3 | 95.8 | 0.87 | 0.84 | 0.74 |
| FLSN 355 LB | 315 | 2028 | 2.4 | 2.9 | 7.5 | 6.56 | 1720 | 80 | 1488 | 549 | 96.3 | 96.4 | 96.2 | 0.86 | 0.83 | 0.76 |
| FLSN 355 LC | 355 | 2280 | 2.5 | 2.9 | 7.5 | 6.56 | 1720 | 80 | 1487 | 629 | 96.3 | 96.3 | 95.8 | 0.85 | 0.81 | 0.72 |
| FLSN 355 LD | 375 | 2402 | 1.7 | 3.2 | 8.3 | 6.60 | 1750 | 80 | 1491 | 651.7 | 96.6 | 96.4 | 95.7 | 0.86 | 0.82 | 0.74 |

For power > 375 kW, please contact us.

| | | | | | | | | | | | | | | | | |
|----------------|------|------|-----|-----|-----|---------|------|----|-----|------|------|------|------|------|------|------|
| 6 poles | | | | | | | | | | | | | | | | |
| FLSN 90 SL | 0.75 | 7.6 | 1.8 | 2.3 | 4.4 | 0.00378 | 24 | 40 | 950 | 1.9 | 79.1 | 80.1 | 78.3 | 0.72 | 0.63 | 0.49 |
| FLSN 90 LU | 1.1 | 11 | 2.2 | 2.5 | 4.8 | 0.00519 | 29 | 57 | 954 | 2.7 | 81.7 | 82.3 | 80.3 | 0.71 | 0.62 | 0.48 |
| FLSN 100 LG | 1.5 | 14.8 | 2.3 | 2.8 | 5.6 | 0.01523 | 41 | 47 | 966 | 3.6 | 83.8 | 84.4 | 82.9 | 0.72 | 0.63 | 0.50 |
| FLSN 112 MU | 2.2 | 21.7 | 2.2 | 2.7 | 5.6 | 0.01899 | 49 | 45 | 968 | 5.3 | 84.5 | 85.1 | 83.5 | 0.70 | 0.62 | 0.49 |
| FLSN 132 SM | 3 | 29.5 | 2.6 | 3 | 6.4 | 0.02528 | 65 | 50 | 972 | 6.8 | 87.3 | 87.7 | 86.3 | 0.73 | 0.66 | 0.53 |
| FLSN 132 M | 4 | 39.4 | 2.4 | 2.9 | 6.3 | 0.03027 | 73 | 54 | 970 | 9.2 | 86.9 | 87.0 | 85.8 | 0.72 | 0.65 | 0.53 |
| FLSN 132 MU | 5.5 | 54.4 | 2.6 | 2.8 | 6.3 | 0.03699 | 87 | 55 | 966 | 11.7 | 88.3 | 89.0 | 88.7 | 0.77 | 0.71 | 0.59 |
| FLSN 160 MU | 7.5 | 73.2 | 2 | 3 | 6.4 | 0.1295 | 117 | 57 | 978 | 17.4 | 89.5 | 88.7 | 88.3 | 0.77 | 0.67 | 0.57 |
| FLSN 180 L | 11 | 107 | 2.9 | 3.8 | 8.2 | 0.2048 | 170 | 61 | 982 | 22.6 | 91.0 | 91.3 | 90.3 | 0.77 | 0.70 | 0.58 |
| FLSN 180 LUR | 15 | 146 | 3.2 | 2.7 | 7.4 | 0.2530 | 202 | 60 | 978 | 31.9 | 91.3 | 91.6 | 90.9 | 0.74 | 0.68 | 0.56 |
| FLSN 200 LU | 18.5 | 181 | 2.4 | 3 | 7 | 0.2588 | 210 | 60 | 978 | 36.5 | 91.8 | 92.5 | 92.3 | 0.80 | 0.75 | 0.64 |
| FLSN 200 LU | 22 | 214 | 2.8 | 3.5 | 7.3 | 0.2588 | 245 | 62 | 980 | 44.6 | 92.5 | 92.9 | 92.5 | 0.77 | 0.72 | 0.61 |
| FLSN 225 M | 30 | 291 | 2.2 | 2.4 | 6.5 | 0.8802 | 342 | 65 | 986 | 55.3 | 93.2 | 93.7 | 93.4 | 0.84 | 0.80 | 0.71 |
| FLSN 250 M | 37 | 358 | 2.4 | 2.6 | 6.9 | 0.9142 | 397 | 64 | 986 | 68.1 | 93.5 | 94.0 | 93.7 | 0.84 | 0.80 | 0.71 |
| FLSN 280 S | 45 | 436 | 0.6 | 3.1 | 7.5 | 1.08 | 555 | 70 | 986 | 82 | 94.1 | 94.4 | 94.0 | 0.84 | 0.80 | 0.70 |
| FLSN 280 M | 55 | 533 | 2.9 | 3.1 | 7.3 | 1.28 | 605 | 70 | 986 | 100 | 94.4 | 94.6 | 94.2 | 0.84 | 0.79 | 0.69 |
| FLSN 315 S | 75 | 727 | 2 | 2.1 | 7 | 2.50 | 965 | 70 | 991 | 137 | 95.0 | 95.3 | 95.0 | 0.83 | 0.80 | 0.73 |
| FLSN 315 M | 90 | 867 | 3 | 2 | 7 | 2.96 | 1035 | 69 | 991 | 165 | 95.0 | 95.4 | 95.2 | 0.83 | 0.80 | 0.72 |
| FLSN 315 LA | 110 | 1066 | 3 | 2.2 | 6.6 | 3.44 | 1150 | 69 | 989 | 204 | 95.5 | 95.9 | 95.6 | 0.81 | 0.79 | 0.71 |
| FLSN 315 LB | 132 | 1276 | 3 | 2.3 | 6.9 | 3.77 | 1165 | 67 | 992 | 247 | 95.8 | 96.0 | 95.7 | | | |



| Type | Rated power P _n kW | 415V 50Hz | | | | 460V 60Hz | | | |
|----------------|-------------------------------------|-------------------------------------|---------------------|------------|--------------|-------------------------------------|---------------------|------------|--------------|
| | | Rated speed | Rated current | Efficiency | Power factor | Rated speed | Rated current | Efficiency | Power factor |
| | | N _n min ⁻¹ | I _n A | η 4/4 | Cos φ 4/4 | N _n min ⁻¹ | I _n A | η 4/4 | Cos φ 4/4 |
| 2 poles | | | | | | | | | |
| FLSN 80 L | 0.75 | 2895 | 1.6 | 83.0 | 0.79 | 3505 | 1.4 | 83.7 | 0.79 |
| FLSN 80 LG | 1.1 | 2895 | 2.15 | 85.9 | 0.83 | 3505 | 1.95 | 84.8 | 0.83 |
| FLSN 90 SL | 1.5 | 2900 | 2.95 | 85.3 | 0.83 | 3505 | 2.65 | 86.1 | 0.83 |
| FLSN 90 LU | 2.2 | 2905 | 4.1 | 87.5 | 0.85 | 3510 | 3.7 | 88.2 | 0.85 |
| FLSN 100 LG | 3 | 2940 | 5.5 | 88.7 | 0.86 | 3545 | 4.9 | 88.7 | 0.87 |
| FLSN 112 MG | 4 | 2930 | 7.15 | 88.9 | 0.88 | 3535 | 6.4 | 89.9 | 0.88 |
| FLSN 132 SM | 5.5 | 2940 | 9.9 | 90.5 | 0.85 | 3545 | 9 | 90.8 | 0.85 |
| FLSN 132 SM | 7.5 | 2945 | 13.5 | 91.5 | 0.85 | 3550 | 12 | 92.2 | 0.85 |
| FLSN 160 M | 11 | 2954 | 19.4 | 92.4 | 0.85 | 3554 | 17.3 | 92.4 | 0.86 |
| FLSN 160 M | 15 | 2956 | 25.7 | 92.7 | 0.87 | 3556 | 23 | 93.2 | 0.88 |
| FLSN 160 LUR | 18.5 | 2952 | 31.8 | 92.7 | 0.87 | 3558 | 28.4 | 93.2 | 0.87 |
| FLSN 180 MUR | 22 | 2958 | 37.1 | 93.8 | 0.88 | 3560 | 33.1 | 93.8 | 0.88 |
| FLSN 200 LU | 30 | 2954 | 51.7 | 94.0 | 0.86 | 3554 | 46.4 | 94.0 | 0.87 |
| FLSN 200 LU | 37 | 2950 | 62.8 | 94.3 | 0.87 | 3552 | 56.3 | 94.2 | 0.88 |
| FLSN 225 MR | 45 | 2960 | 80.7 | 94.4 | 0.82 | 3564 | 70.6 | 95.1 | 0.84 |
| FLSN 250 M | 55 | 2972 | 87.2 | 94.6 | 0.87 | 3574 | 83.3 | 94.3 | 0.88 |
| FLSN 280 S | 75 | 2968 | 122 | 95.2 | 0.90 | 3566 | 110 | 94.1 | 0.91 |
| FLSN 280 M | 90 | 2971 | 146 | 95.5 | 0.90 | 3567 | 132 | 95.0 | 0.90 |
| FLSN 315 S | 110 | 2977 | 177.3 | 95.9 | 0.90 | 3575 | 161 | 95.0 | 0.90 |
| FLSN 315 M | 132 | 2976 | 213 | 96.0 | 0.90 | 3575 | 193 | 95.4 | 0.90 |
| FLSN 315 LA | 160 | 2976 | 258.4 | 96.2 | 0.89 | 3575 | 233 | 95.8 | 0.90 |
| FLSN 315 LB | 200 | 2974 | 322.9 | 96.6 | 0.89 | 3575 | 291 | 95.8 | 0.90 |
| FLSN 355 LA | 250 | 2982 | 413 | 96.2 | 0.88 | 3578 | 372 | 95.8 | 0.88 |
| FLSN 355 LB | 315 | 2985 | 524 | 96.2 | 0.87 | 3583 | 469 | 95.8 | 0.88 |
| FLSN 355 LC | 355 | 2983 | 596 | 96.3 | 0.86 | 3581 | 535 | 95.8 | 0.87 |
| FLSN 355 LD | 400 | 2988 | 645.5 | 97.3 | 0.89 | 3589 | 585 | 96.5 | 0.89 |

For power > 400 kW, please contact us.

| 4 poles | | | | | | | | | |
|----------------|------|------|-------|------|------|------|-------|------|------|
| FLSN 80 LG | 0.75 | 1454 | 1.6 | 84.0 | 0.78 | 1762 | 1.4 | 85.7 | 0.76 |
| FLSN 90 SL | 1.1 | 1454 | 2.3 | 84.9 | 0.79 | 1758 | 2 | 86.5 | 0.78 |
| FLSN 90 LU | 1.5 | 1456 | 3.2 | 85.6 | 0.76 | 1762 | 2.9 | 86.9 | 0.75 |
| FLSN 100 LR | 2.2 | 1456 | 4.6 | 87.0 | 0.76 | 1762 | 4.1 | 88.3 | 0.76 |
| FLSN 100 LG | 3 | 1462 | 6 | 88.8 | 0.79 | 1768 | 5.2 | 89.9 | 0.80 |
| FLSN 112 MU | 4 | 1462 | 8 | 89.4 | 0.78 | 1764 | 7.6 | 85.5 | 0.77 |
| FLSN 132 SM | 5.5 | 1466 | 10.3 | 90.2 | 0.82 | 1768 | 9.2 | 91.7 | 0.82 |
| FLSN 132 MR | 7.5 | 1464 | 13.5 | 91.0 | 0.85 | 1768 | 12.1 | 92.0 | 0.85 |
| FLSN 160 M | 11 | 1468 | 19.5 | 92.2 | 0.85 | 1772 | 17.5 | 92.9 | 0.85 |
| FLSN 160 LUR | 15 | 1474 | 26.8 | 92.6 | 0.84 | 1774 | 23.8 | 93.4 | 0.85 |
| FLSN 180 M | 18.5 | 1472 | 33.5 | 93.0 | 0.83 | 1774 | 29.9 | 93.6 | 0.83 |
| FLSN 180 LUR | 22 | 1474 | 40.2 | 93.2 | 0.82 | 1776 | 35.9 | 93.7 | 0.82 |
| FLSN 200 LU | 30 | 1476 | 53.7 | 94.2 | 0.82 | 1780 | 48.3 | 94.5 | 0.83 |
| FLSN 225 S | 37 | 1486 | 65.7 | 94.5 | 0.83 | 1786 | 59.4 | 94.5 | 0.83 |
| FLSN 225 M | 45 | 1486 | 82.5 | 95.0 | 0.80 | 1788 | 74.1 | 95.3 | 0.80 |
| FLSN 250 MR | 55 | 1484 | 98.4 | 95.0 | 0.82 | 1784 | 88.2 | 95.4 | 0.82 |
| FLSN 280 S | 75 | 1486 | 132.6 | 94.8 | 0.83 | 1784 | 117 | 95.4 | 0.84 |
| FLSN 280 M | 90 | 1487 | 163 | 95.1 | 0.81 | 1785 | 141 | 95.4 | 0.84 |
| FLSN 315 S | 110 | 1487 | 193.3 | 95.4 | 0.83 | 1786 | 172 | 95.8 | 0.84 |
| FLSN 315 M | 132 | 1487 | 229 | 95.8 | 0.84 | 1787 | 203 | 96.0 | 0.85 |
| FLSN 315 LA | 160 | 1486 | 276 | 96.1 | 0.84 | 1784 | 245.6 | 96.2 | 0.85 |
| FLSN 315 LB | 200 | 1487 | 345 | 96.0 | 0.84 | 1786 | 307 | 96.2 | 0.85 |
| FLSN 355 LA | 250 | 1490 | 425 | 96.2 | 0.85 | 1788 | 379 | 96.2 | 0.86 |
| FLSN 355 LAL | 280 | 1488 | 471 | 96.1 | 0.86 | 1787 | 420 | 96.2 | 0.87 |
| FLSN 355 LB | 315 | 1489 | 530 | 96.3 | 0.86 | 1787 | 472 | 96.2 | 0.87 |
| FLSN 355 LC | 355 | 1488 | 623.7 | 96.0 | 0.83 | 1786 | 532 | 96.2 | 0.87 |
| FLSN 355 LD | 375 | 1492 | 644.5 | 96.4 | 0.84 | 1790 | 573.2 | 96.2 | 0.85 |

For power > 375 kW, please contact us.

| 6 poles | | | | | | | | | |
|----------------|------|-----|-------|------|------|------|------|------|------|
| FLSN 90 SL | 0.75 | 956 | 1.9 | 79.4 | 0.69 | - | - | - | - |
| FLSN 90 LU | 1.1 | 958 | 2.75 | 81.7 | 0.68 | - | - | - | - |
| FLSN 100 LG | 1.5 | 970 | 3.6 | 84.1 | 0.69 | - | - | - | - |
| FLSN 112 MU | 2.2 | 974 | 6.75 | 86.8 | 0.71 | - | - | - | - |
| FLSN 132 SM | 3 | 972 | 9.15 | 87.0 | 0.70 | - | - | - | - |
| FLSN 132 M | 4 | 970 | 11.5 | 88.5 | 0.75 | - | - | - | - |
| FLSN 132 MU | 5.5 | 970 | 11.7 | 88.5 | 0.74 | - | - | - | - |
| FLSN 160 MU | 7.5 | 980 | 17.1 | 89.6 | 0.74 | - | - | - | - |
| FLSN 180 L | 11 | 984 | 22.3 | 91.2 | 0.75 | - | - | - | - |
| FLSN 180 LUR | 15 | 982 | 31.7 | 91.4 | 0.72 | - | - | - | - |
| FLSN 200 LU | 18.5 | 980 | 36 | 92.1 | 0.78 | - | - | - | - |
| FLSN 200 LU | 22 | 984 | 42.2 | 92.7 | 0.74 | - | - | - | - |
| FLSN 225 M | 30 | 986 | 53.9 | 93.3 | 0.83 | - | - | - | - |
| FLSN 250 M | 37 | 986 | 66.5 | 93.7 | 0.83 | - | - | - | - |
| FLSN 280 S | 45 | 987 | 80 | 94.2 | 0.82 | 1186 | 70.3 | 94.5 | 0.85 |
| FLSN 280 M | 55 | 988 | 99 | 94.4 | 0.82 | 1186 | 87 | 94.5 | 0.84 |
| FLSN 315 S | 75 | 992 | 134 | 94.8 | 0.82 | 1190 | 122 | 95.0 | 0.81 |
| FLSN 315 M | 90 | 992 | 161 | 95.1 | 0.82 | 1191 | 145 | 95.0 | 0.82 |
| FLSN 315 LA | 110 | 992 | 198.7 | 95.5 | 0.81 | 1191 | 176 | 95.8 | 0.82 |
| FLSN 315 LB | 132 | 991 | 243 | 95.7 | 0.79 | 1190 | 217 | 95.8 | 0.80 |
| FLSN 355 LA | 160 | 994 | 276 | 96.0 | 0.84 | 1193 | 247 | 95.8 | 0.85 |
| FLSN 355 LB | 200 | 994 | 339 | 96.1 | 0.86 | 1193 | 312 | 95.8 | 0.84 |
| FLSN 355 LC | 250 | 994 | 454 | 95.9 | 0.80 | 1193 | 405 | 95.8 | 0.81 |

For power > 250 kW, please contact us.

* available March 2021

ATEX GAS - Zone 2 - Cast iron



ATEX GAS - Zone 2 - Cast iron

| Type | 400V 50Hz | | | | % Rated torque M_n at | | | | | 400V 87Hz Δ^1 | | | | Maximum mechanical speed ² |
|----------------|-------------|----------------------------|---------------|-------------------|-------------------------|--------|--------|--------|-------|----------------------|----------------------------|---------------|-------------------|---------------------------------------|
| | Rated power | Rated speed | Rated current | Power factor | 10Hz | 17Hz | 25Hz | 50Hz | 87Hz | Rated power | Rated speed | Rated current | Power factor | |
| | P_n kW | N_n min ⁻¹ | I_n A | Cos ϕ 4/4 | | | | | | P_n kW | N_n min ⁻¹ | I_n A | Cos ϕ 4/4 | |
| 2 poles | | | | | | | | | | | | | | |
| FLSN 80 L | 0.75 | 2885 | 1.6 | 0.83 | 2.3 | 2.5 | 2.5 | 2.5 | 1.4 | 1.31 | 4997 | 3 | 0.84 | 13500 |
| FLSN 80 LG | 1.1 | 2885 | 2.3 | 0.85 | 3.1 | 3.7 | 3.7 | 3.7 | 2.1 | 1.91 | 4997 | 4.3 | 0.86 | 13500 |
| FLSN 90 SL | 1.5 | 2890 | 3 | 0.85 | 4.2 | 5 | 5 | 5 | 2.8 | 2.61 | 5006 | 5.9 | 0.87 | 11700 |
| FLSN 90 LU | 2.2 | 2895 | 4.3 | 0.86 | 6.7 | 7.3 | 7.3 | 7.3 | 4.1 | 3.83 | 5014 | 8.2 | 0.89 | 11700 |
| FLSN 100 LG | 3 | 2875 | 6.2 | 0.88 | 9.2 | 9.9 | 9.9 | 9.9 | 5.6 | 5.22 | 5014 | 11.3 | 0.86 | 9900 |
| FLSN 112 MG | 4 | 2910 | 8 | 0.91 | 12.2 | 13.1 | 13.1 | 13.1 | 7.5 | 6.96 | 5058 | 14.7 | 0.87 | 9900 |
| FLSN 132 SM | 5.5 | 2925 | 11.1 | 0.88 | 16.7 | 17.9 | 17.9 | 17.9 | 10.2 | 9.57 | 5084 | 20.2 | 0.87 | 6700 |
| FLSN 132 SM | 7.5 | 2930 | 14.9 | 0.88 | 22.7 | 24.4 | 24.4 | 24.4 | 13.9 | 13.05 | 5092 | 27 | 0.86 | 6700 |
| FLSN 160 M | 11 | 2940 | 21.5 | 0.88 | 28.1 | 35.6 | 35.6 | 35.6 | 20.3 | 19.14 | 5120 | 38.2 | 0.89 | 6030 |
| FLSN 160 M | 15 | 2940 | 28.5 | 0.90 | 40.7 | 48.6 | 48.6 | 48.6 | 27.7 | 26.1 | 5110 | 52.4 | 0.88 | 6030 |
| FLSN 160 LUR | 18.5 | 2935 | 35.3 | 0.90 | 50.1 | 59.9 | 59.9 | 59.9 | 34.1 | 32.19 | 5110 | 65.1 | 0.88 | 4500 |
| FLSN 180 MUR | 22 | 2945 | 41.1 | 0.90 | 59.6 | 71.2 | 71.2 | 71.2 | 59.1 | 38.28 | 5113 | 75.8 | 0.89 | 4500 |
| FLSN 200 LU | 30 | 2945 | 56.9 | 0.88 | 72.2 | 87.4 | 97.1 | 97.1 | 80.6 | - | - | - | - | 4500 |
| FLSN 200 LU | 37 | 2935 | 69.4 | 0.89 | 89.3 | 108 | 120 | 120 | 99.6 | - | - | - | - | 4700 |
| FLSN 225 MR | 45 | 2940 | 84.7 | 0.89 | 108.6 | 131.4 | 146 | 146 | 121.2 | - | - | - | - | 4320 |
| FLSN 250 M | 55 | 2966 | 102 | 0.89 | 131.7 | 159.3 | 177 | 177 | 146.9 | - | - | - | - | 4050 |
| FLSN 280 S | 75 | 2950 | 142 | 0.91 | 200 | 212.1 | 224.1 | 224.1 | - | - | - | - | - | 3600 |
| FLSN 280 M | 90 | 2952 | 170 | 0.91 | 246.5 | 252.3 | 261 | 261 | - | - | - | - | - | 3600 |
| FLSN 315 S | 110 | 2966 | 207 | 0.90 | 353 | 353 | 353 | 353 | - | - | - | - | - | 3600 |
| FLSN 315 M | 132 | 2966 | 249.3 | 0.90 | 402.8 | 411.3 | 424 | 424 | - | - | - | - | - | 3600 |
| FLSN 315 LA | 160 | 2967 | 299.7 | 0.90 | 488.3 | 498.6 | 514 | 514 | - | - | - | - | - | 3600 |
| FLSN 315 LB | 200 | 2965 | 373.6 | 0.90 | 540.1 | 553 | 572.3 | 572.3 | - | - | - | - | - | 3600 |
| FLSN 355 LA | 250 | 2969 | 477 | 0.89 | 721.8 | 753.9 | 786 | 786 | - | - | - | - | - | 3600 |
| FLSN 355 LB | 315 | 2974 | 599.3 | 0.88 | 836.6 | 836.6 | 846.7 | 846.7 | - | - | - | - | - | 3600 |
| FLSN 355 LC | 355 | 2972 | 672.7 | 0.89 | 932.3 | 932.3 | 932.3 | 932.3 | - | - | - | - | - | 3600 |
| FLSN 355 LD | 400 | 2987 | 744.3 | 0.90 | 1065.7 | 1091.4 | 1129.9 | 1129.9 | - | - | - | - | - | 3600 |


For power > 400 kW, please contact us.

| | | | | | | | | | | | | | | |
|----------------|------|------|-------|------|--------|--------|--------|--------|--------|-------|------|-------|------|-------|
| 4 poles | | | | | | | | | | | | | | |
| FLSN 80 LG | 0.75 | 1450 | 1.7 | 0.80 | 4.5 | 5 | 5 | 5 | 2.8 | 1.31 | 2511 | 3.1 | 0.82 | 13500 |
| FLSN 90 SL | 1.1 | 1450 | 2.3 | 0.81 | 6.5 | 7.3 | 7.3 | 7.3 | 4.2 | 1.91 | 2511 | 4.5 | 0.83 | 11700 |
| FLSN 90 LU | 1.5 | 1454 | 3.2 | 0.79 | 8.9 | 9.9 | 9.9 | 9.9 | 5.7 | 2.61 | 2518 | 6.1 | 0.81 | 11700 |
| FLSN 100 LR | 2.2 | 1445 | 4.9 | 0.81 | 13.5 | 14.5 | 14.5 | 14.5 | 8.3 | 3.83 | 2515 | 8.8 | 0.79 | 9900 |
| FLSN 100 LG | 3 | 1456 | 6.4 | 0.84 | 16.4 | 19.6 | 19.6 | 19.6 | 11.2 | 5.22 | 2529 | 11.7 | 0.81 | 9900 |
| FLSN 112 MU | 4 | 1450 | 8.5 | 0.83 | 21.9 | 26.2 | 26.2 | 26.2 | 14.9 | 6.96 | 2525 | 15.4 | 0.80 | 9900 |
| FLSN 132 SM | 5.5 | 1456 | 11.2 | 0.86 | 33.4 | 35.9 | 35.9 | 35.9 | 20.5 | 9.57 | 2532 | 20.2 | 0.84 | 6700 |
| FLSN 132 MR | 7.5 | 1456 | 14.9 | 0.88 | 45.7 | 49.1 | 49.1 | 49.1 | 28 | 13.05 | 2529 | 27.3 | 0.86 | 6700 |
| FLSN 160 M | 11 | 1462 | 21.5 | 0.88 | 60 | 71.7 | 71.7 | 71.7 | 40.9 | 19.14 | 2539 | 39.5 | 0.86 | 6030 |
| FLSN 160 LUR | 15 | 1466 | 29.5 | 0.87 | 81.5 | 97.4 | 97.4 | 97.4 | 55.5 | 26.1 | 2546 | 53.4 | 0.85 | 5670 |
| FLSN 180 M | 18.5 | 1464 | 36.4 | 0.86 | 94.9 | 120 | 120 | 120 | 68.4 | 32.19 | 2546 | 66.7 | 0.84 | 5670 |
| FLSN 180 LUR | 22 | 1466 | 44.1 | 0.85 | 113 | 143 | 143 | 143 | 81.5 | 38.28 | 2546 | 80.1 | 0.83 | 4500 |
| FLSN 200 LU | 30 | 1472 | 58.9 | 0.85 | 144.3 | 194 | 194 | 194 | 110.6 | 52.2 | 2553 | 107.4 | 0.84 | 4500 |
| FLSN 225 S | 37 | 1482 | 72.8 | 0.85 | 188.1 | 238 | 238 | 238 | 135.7 | 64.38 | 2570 | 132.4 | 0.84 | 4320 |
| FLSN 225 M | 45 | 1484 | 89.1 | 0.83 | 228.5 | 289 | 289 | 289 | 164.7 | 78.3 | 2570 | 161.7 | 0.83 | 4320 |
| FLSN 250 MR | 55 | 1480 | 108 | 0.84 | 279.8 | 354 | 354 | 354 | 201.8 | 95.7 | 2567 | 198.4 | 0.83 | 4050 |
| FLSN 280 S | 75 | 1478 | 150.4 | 0.86 | 424.2 | 453.1 | 482 | 482 | 274.7 | - | - | - | - | 2610 |
| FLSN 280 M | 90 | 1479 | 181.4 | 0.85 | 503.7 | 532.7 | 567.4 | 573.2 | 326.7 | - | - | - | - | 2610 |
| FLSN 315 S | 110 | 1484 | 215.6 | 0.87 | 692.9 | 699.9 | 707 | 707 | 403 | - | - | - | - | 2610 |
| FLSN 315 M | 132 | 1482 | 256.2 | 0.88 | 814.1 | 831 | 848 | 848 | 483.4 | - | - | - | - | 2610 |
| FLSN 315 LA | 160 | 1479 | 309.6 | 0.88 | 896.1 | 947.6 | 1009.4 | 1009.4 | 575.4 | - | - | - | - | 2610 |
| FLSN 315 LB | 200 | 1480 | 386.8 | 0.87 | 1042.4 | 1081.1 | 1119.7 | 1119.7 | 638.2 | - | - | - | - | 2610 |
| FLSN 355 LA | 250 | 1482 | 479.2 | 0.88 | 1347.4 | 1443.6 | 1539.8 | 1539.8 | 877.7 | - | - | - | - | 2610 |
| FLSN 355 LAL | 315 | 1487 | 541.8 | 0.87 | 1510.3 | 1546.3 | 1600.2 | 1600.2 | 912.1 | - | - | - | - | 2610 |
| FLSN 355 LB | 355 | 1486 | 602.6 | 0.88 | 1622.4 | 1683.2 | 1764.4 | 1764.4 | 1005.7 | - | - | - | - | 2610 |
| FLSN 355 LC | 355 | 1483 | 681.9 | 0.88 | 1892.4 | 1915.2 | 1938 | 1938 | 1104.7 | - | - | - | - | 2610 |
| FLSN 355 LD | 375 | 1491 | 729.9 | 0.86 | 1993.7 | 2017.7 | 2065.7 | 2065.7 | 1177.4 | - | - | - | - | 2610 |

For power > 375 kW, please contact us.

| | | | | | | | | | | | | | | |
|----------------|------|-----|-------|------|--------|--------|--------|--------|--------|-------|------|-------|------|-------|
| 6 poles | | | | | | | | | | | | | | |
| FLSN 90 SL | 0.75 | 950 | 1.9 | 0.72 | 7.6 | 7.6 | 7.6 | 7.6 | 4.3 | 1.31 | 1645 | 3.6 | 0.75 | 11700 |
| FLSN 90 LU | 1.1 | 954 | 2.8 | 0.71 | 11 | 11 | 11 | 11 | 6.3 | 1.91 | 1652 | 5.1 | 0.74 | 11700 |
| FLSN 100 LG | 1.5 | 962 | 3.8 | 0.74 | 13.1 | 14.8 | 14.8 | 14.8 | 8.4 | 2.61 | 1667 | 6.8 | 0.72 | 9900 |
| FLSN 112 MU | 2.2 | 962 | 5.7 | 0.74 | 19.2 | 21.7 | 21.7 | 21.7 | 12.4 | 3.83 | 1677 | 10 | 0.70 | 9900 |
| FLSN 132 SM | 3 | 970 | 7.1 | 0.76 | 27.4 | 29.5 | 29.5 | 29.5 | 16.8 | 5.22 | 1684 | 12.7 | 0.73 | 6700 |
| FLSN 132 M | 4 | 966 | 9.7 | 0.75 | 36.6 | 39.4 | 39.4 | 39.4 | 22.5 | 6.96 | 1680 | 17.2 | 0.72 | 6700 |
| FLSN 132 MU | 5.5 | 962 | 12.5 | 0.79 | 50.6 | 54.4 | 54.4 | 54.4 | 31 | 9.57 | 1673 | 22.7 | 0.76 | 6700 |
| FLSN 160 MU | 7.5 | 974 | 18.7 | 0.79 | 68.1 | 73.2 | 73.2 | 73.2 | 41.7 | 13.05 | 1694 | 30.2 | 0.77 | 6030 |
| FLSN 180 L | 11 | 978 | 24 | 0.80 | 89.6 | 107 | 107 | 107 | 61 | 19.14 | 1701 | 42.9 | 0.77 | 5670 |
| FLSN 180 LUR | 15 | 976 | 34.1 | 0.76 | 122.2 | 146 | 146 | 146 | 83.2 | 26.1 | 1694 | 61.3 | 0.74 | 4500 |
| FLSN 200 LU | 18.5 | 974 | 38.9 | 0.81 | 151.5 | 181 | 181 | 181 | 103.2 | 32.19 | 1694 | 70.6 | 0.79 | 4500 |
| FLSN 200 LU | 22 | 978 | 45 | 0.79 | 179.1 | 214 | 214 | 214 | 122 | 38.28 | 1697 | 84.7 | 0.77 | 4500 |
| FLSN 225 M | 30 | 984 | 58.9 | 0.86 | 243.6 | 291 | 291 | 291 | 165.9 | 52.2 | 1708 | 107.4 | 0.84 | 4050 |
| FLSN 250 M | 37 | 984 | 72.2 | 0.86 | 299.7 | 358 | 358 | 358 | 204.1 | 64.38 | 1708 | 131.2 | 0.84 | 4050 |
| FLSN 280 S | 45 | 983 | 90.4 | 0.87 | 422.9 | 427.3 | 436 | 436 | 248.5 | - | - | - | - | 1740 |
| FLSN 280 M | 55 | 982 | 109.5 | 0.87 | 490.4 | 511.7 | 533 | 533 | 303.8 | - | - | - | - | 1740 |
| FLSN 315 S | 75 | 990 | 154.2 | 0.84 | 727 | 727 | 727 | 727 | 414.4 | - | - | - | - | 1740 |
| FLSN 315 M | 90 | 990 | 184 | 0.84 | 867 | 867 | 867 | 867 | 494.2 | - | - | - | - | 1740 |
| FLSN 315 LA | 110 | 987 | 228.7 | 0.83 | 1023.4 | 1044.7 | 1066 | 1066 | 607.6 | - | - | - | - | 1740 |
| FLSN 315 LB | 132 | 989 | 273.5 | 0.82 | 1033.6 | 1071.8 | 1110.1 | 1110.1 | 632.8 | - | - | - | - | 1740 |
| FLSN 355 LA | 160 | 990 | 311.6 | 0.87 | 1545 | 1545 | 1545 | 1545 | 880.7 | - | - | - | - | 1740 |
| FLSN 355 LB | 200 | 990 | 386.1 | 0.88 | 1910.7 | 1910.7 | 1930 | 1930 | 1100.1 | - | - | - | - | 1740 |
| FLSN 355 LC | 250 | 992 | 486.3 | 0.87 | | | | | | | | | | |

Dimensions in millimetres





| Type | Main shaft end | | | | | | | | | | | | | | | | | |
|--------------------------|----------------|----|-------|------|-----|-----|----|-----|----|---------|----|------|------|-----|-----|----|-----|----|
| | 4 and 6 poles | | | | | | | | | 2 poles | | | | | | | | |
| | F | GD | D | G | E | O | p | L | LO | F | GD | D | G | E | O | p | L | LO |
| FLSN 80 L/LG | 6 | 6 | 19j6 | 15.5 | 40 | M6 | 16 | 30 | 6 | 6 | 6 | 19j6 | 15.5 | 40 | M6 | 16 | 30 | 6 |
| FLSN 90 L/LU/SL | 8 | 7 | 24j6 | 20 | 50 | M8 | 19 | 40 | 6 | 8 | 7 | 24j6 | 20 | 50 | M8 | 19 | 40 | 6 |
| FLSN 100 L/LG/LR | 8 | 7 | 28j6 | 24 | 60 | M10 | 22 | 50 | 6 | 8 | 7 | 28j6 | 24 | 60 | M10 | 22 | 50 | 6 |
| FLSN 112 MG/MU | 8 | 7 | 28j6 | 24 | 60 | M10 | 22 | 50 | 6 | 8 | 7 | 28j6 | 24 | 60 | M10 | 22 | 50 | 6 |
| FLSN 132 M/MR/MU/SM | 10 | 8 | 38k6 | 33 | 80 | M12 | 28 | 63 | 10 | 10 | 8 | 38k6 | 33 | 80 | M12 | 28 | 63 | 10 |
| FLSN 160 L/LUR/M/MU | 12 | 8 | 42k6 | 37 | 110 | M16 | 36 | 90 | 20 | 12 | 8 | 42k6 | 37 | 110 | M16 | 36 | 90 | 20 |
| FLSN 180 L/LUR/M/MT/MUR | 14 | 9 | 48k6 | 42.5 | 110 | M16 | 36 | 90 | 20 | 14 | 9 | 48k6 | 42.5 | 110 | M16 | 36 | 90 | 20 |
| FLSN 200 LU | 16 | 10 | 55m6 | 49 | 110 | M20 | 42 | 90 | 20 | 16 | 10 | 55m6 | 49 | 110 | M20 | 42 | 90 | 20 |
| FLSN 225 M/S | 18 | 11 | 60m6 | 53 | 140 | M20 | 42 | 125 | 15 | - | - | - | - | - | - | - | - | - |
| FLSN 225 MR | - | - | - | - | - | - | - | - | - | 16 | 10 | 55m6 | 49 | 110 | M20 | 42 | 90 | 20 |
| FLSN 225 SR | 18 | 11 | 60m6 | 53 | 140 | M20 | 42 | 125 | 15 | - | - | - | - | - | - | - | - | - |
| FLSN 250 M/MR | 18 | 11 | 65m6 | 58 | 140 | M20 | 42 | 126 | 14 | 18 | 11 | 60m6 | 53 | 140 | M20 | 42 | 126 | 14 |
| FLSN 280 M/S | 20 | 12 | 75m6 | 67.5 | 140 | M20 | 42 | 125 | 15 | 18 | 11 | 65m6 | 58 | 140 | M20 | 42 | 125 | 15 |
| FLSN 315 LA/LB | 25 | 14 | 90m6 | 81 | 170 | M24 | 50 | 140 | 30 | 20 | 12 | 70m6 | 62.5 | 140 | M20 | 42 | 125 | 15 |
| FLSN 315 M/S | 22 | 14 | 80m6 | 71 | 170 | M20 | 42 | 140 | 30 | 18 | 11 | 65m6 | 58 | 140 | M20 | 42 | 125 | 15 |
| FLSN 355 LA/LAL/LB/LC/LD | 28 | 16 | 100m6 | 90 | 210 | M24 | 50 | 180 | 30 | 22 | 14 | 80m6 | 71 | 170 | M20 | 42 | 140 | 30 |

| Type | Secondary shaft ends | | | | | | | | | | | | | | | | | |
|--------------------------|----------------------|----|-------|------|-----|-----|----|-----|-----|---------|----|------|------|-----|-----|----|-----|-----|
| | 4 and 6 poles | | | | | | | | | 2 poles | | | | | | | | |
| | FA | GF | DA | GB | EA | OA | pA | L' | LO' | FA | GF | DA | GB | EA | OA | pA | L' | LO' |
| FLSN 80 L/LG | 5 | 5 | 14j6 | 11 | 30 | M5 | 15 | 25 | 3.5 | 5 | 5 | 14j6 | 11 | 30 | M5 | 15 | 25 | 3.5 |
| FLSN 90 L/LU/SL | 6 | 6 | 19j6 | 15.5 | 40 | M6 | 16 | 30 | 6 | 6 | 6 | 19j6 | 15.5 | 40 | M6 | 16 | 30 | 6 |
| FLSN 100 L/LG/LR | 8 | 7 | 24j6 | 20 | 50 | M8 | 19 | 40 | 6 | 8 | 7 | 24j6 | 20 | 50 | M8 | 19 | 40 | 6 |
| FLSN 112 MG/MU | 8 | 7 | 24j6 | 20 | 50 | M8 | 19 | 40 | 6 | 8 | 7 | 24j6 | 20 | 50 | M8 | 19 | 40 | 6 |
| FLSN 132 M/MR/MU/SM | 8 | 7 | 28k6 | 24 | 60 | M10 | 22 | 50 | 6 | 8 | 7 | 28k6 | 24 | 60 | M10 | 22 | 50 | 6 |
| FLSN 160 L/LUR/M/MU | 12 | 8 | 42k6 | 37 | 110 | M16 | 36 | 100 | 6 | 12 | 8 | 42k6 | 37 | 110 | M16 | 36 | 100 | 6 |
| FLSN 180 L/LUR/M/MT/MUR | 12 | 8 | 42k6 | 37 | 110 | M16 | 36 | 100 | 6 | 12 | 8 | 42k6 | 37 | 110 | M16 | 36 | 100 | 6 |
| FLSN 200 LU | 16 | 10 | 55m6 | 49 | 110 | M20 | 42 | 97 | 13 | 16 | 10 | 55m6 | 49 | 110 | M20 | 42 | 97 | 13 |
| FLSN 225 M/MR/S | 18 | 11 | 60m6 | 53 | 140 | M20 | 42 | 126 | 14 | 16 | 10 | 55m6 | 49 | 110 | M20 | 42 | 97 | 13 |
| FLSN 225 SR | 18 | 11 | 60m6 | 53 | 140 | M20 | 42 | 125 | 15 | - | - | - | - | - | - | - | - | - |
| FLSN 250 M/MR | 18 | 11 | 60m6 | 53 | 140 | M20 | 42 | 125 | 15 | 18 | 11 | 60m6 | 53 | 140 | M20 | 42 | 125 | 15 |
| FLSN 280 M/S | 18 | 11 | 60m6 | 53 | 140 | M20 | 42 | 125 | 15 | 18 | 11 | 60m6 | 53 | 140 | M20 | 42 | 125 | 15 |
| FLSN 315 LA/LB | 20 | 12 | 70m6 | 63.5 | 140 | M20 | 42 | 125 | 15 | 20 | 12 | 70m6 | 63.5 | 140 | M20 | 42 | 125 | 15 |
| FLSN 315 M/S | 20 | 12 | 70m6 | 63.5 | 140 | M20 | 42 | 125 | 15 | 18 | 11 | 65m6 | 58 | 140 | M20 | 42 | 125 | 15 |
| FLSN 355 LA/LAL/LB/LC/LD | 28 | 16 | 100m6 | 90 | 210 | M24 | 50 | 180 | 30 | 22 | 14 | 80m6 | 71 | 170 | M20 | 42 | 140 | 30 |

ATEX GAS - Zone 2 - Cast iron


Dimensions in millimetres



ATEX GAS - Zone 2 - Cast iron

| Type | Main dimensions | | | | | | | | | | | | | | | | | | |
|------------------|-----------------|-----|-----|-----|-------|----|-----|------|----|-----|-----|-----|------|------|-----|-----|-----|-----|------|
| | A | AB | B | BB | C | x | AA | K | HA | H | AC* | HD | LB | LJ | J | I | II | AD | AD1 |
| FLSN 80 L | 125 | 157 | 100 | 130 | 50 | 18 | 34 | 10 | 10 | 80 | 170 | 228 | 212 | 7 | 136 | 68 | 68 | - | - |
| FLSN 80 LG | 125 | 170 | 100 | 138 | 50 | 22 | 39 | 10 | 10 | 80 | 203 | 238 | 245 | 8 | 136 | 68 | 68 | 135 | 41 |
| FLSN 90 L | 140 | 170 | 125 | 162 | 56 | 28 | 33 | 10 | 10 | 90 | 203 | 248 | 239 | 8 | 136 | 68 | 68 | 135 | 41 |
| FLSN 90 LU | 140 | 170 | 125 | 162 | 56 | 28 | 33 | 10 | 10 | 90 | 203 | 248 | 266 | 8 | 136 | 68 | 68 | 135 | 41 |
| FLSN 90 SL | 140 | 170 | 125 | 162 | 56 | 28 | 33 | 10 | 10 | 90 | 203 | 248 | 239 | 8 | 136 | 68 | 68 | 135 | 41 |
| FLSN 100 L | 160 | 196 | 140 | 185 | 63 | 29 | 40 | 12 | 13 | 100 | 204 | 258 | 300 | 8 | 136 | 68 | 68 | 135 | 41 |
| FLSN 100 LG | 160 | 196 | 140 | 185 | 63 | 29 | 40 | 12 | 13 | 100 | 227 | 266 | 299 | 0.5 | 136 | 68 | 68 | 130 | 45 |
| FLSN 100 LR | 160 | 196 | 140 | 185 | 63 | 29 | 40 | 12 | 13 | 100 | 204 | 258 | 300 | 8 | 136 | 68 | 68 | 135 | 41 |
| FLSN 112 MG | 190 | 230 | 140 | 186 | 60 | 32 | 48 | 12 | 12 | 112 | 230 | 294 | 299 | 8 | 136 | 68 | 68 | 148 | 41 |
| FLSN 112 MU | 190 | 230 | 140 | 186 | 60 | 32 | 48 | 12 | 12 | 112 | 230 | 294 | 299 | 8 | 136 | 68 | 68 | 148 | 41 |
| FLSN 132 M | 216 | 255 | 178 | 240 | 89 | 50 | 63 | 12 | 16 | 132 | 270 | 335 | 385 | 22 | 136 | 68 | 68 | 165 | 37.5 |
| FLSN 132 MR | 216 | 255 | 178 | 240 | 89 | 50 | 63 | 12 | 16 | 132 | 270 | 335 | 447 | 22 | 136 | 68 | 68 | 165 | 37.5 |
| FLSN 132 MU | 216 | 255 | 178 | 240 | 89 | 50 | 63 | 12 | 16 | 132 | 270 | 335 | 447 | 22 | 136 | 68 | 68 | 165 | 37.5 |
| FLSN 132 SM | 216 | 255 | 140 | 240 | 89 | 50 | 63 | 12 | 16 | 132 | 270 | 335 | 385 | 22 | 136 | 68 | 68 | 165 | 37.5 |
| FLSN 160 L | 254 | 294 | 254 | 294 | 108 | 20 | 65 | 14.5 | 20 | 160 | 315 | 449 | 495 | 23 | 259 | 115 | 151 | 179 | 45 |
| FLSN 160 LR | 254 | 294 | 254 | 294 | 108 | 20 | 65 | 14.5 | 20 | 160 | 315 | 449 | 510 | 23 | 259 | 115 | 151 | 179 | 45 |
| FLSN 160 M | 254 | 294 | 210 | 294 | 108 | 20 | 65 | 14.5 | 20 | 160 | 315 | 449 | 495 | 23 | 259 | 115 | 151 | 179 | 45 |
| FLSN 160 MU | 254 | 294 | 210 | 294 | 108 | 20 | 65 | 14.5 | 20 | 160 | 315 | 449 | 510 | 23 | 259 | 115 | 151 | 179 | 45 |
| FLSN 180 L | 279 | 330 | 279 | 337 | 121 | 32 | 70 | 14.5 | 28 | 180 | 361 | 490 | 552 | 35.5 | 259 | 115 | 151 | 190 | 45 |
| FLSN 180 LR | 279 | 330 | 279 | 337 | 115 | 32 | 70 | 14.5 | 28 | 180 | 361 | 490 | 593 | 35.5 | 259 | 115 | 151 | 190 | 45 |
| FLSN 180 M | 279 | 330 | 241 | 337 | 121 | 32 | 70 | 14.5 | 28 | 180 | 361 | 490 | 552 | 35.5 | 259 | 115 | 151 | 190 | 45 |
| FLSN 180 MT | 279 | 330 | 241 | 337 | 121 | 32 | 70 | 14.5 | 28 | 180 | 361 | 490 | 537 | 29.5 | 259 | 115 | 151 | 190 | 45 |
| FLSN 180 MUR | 279 | 324 | 241 | 290 | 121 | 24 | 80 | 14.5 | 25 | 180 | 328 | 469 | 551 | 29.5 | 259 | 115 | 151 | 177 | 45 |
| FLSN 200 LU | 318 | 374 | 305 | 360 | 135 | 28 | 60 | 18.5 | 17 | 200 | 399 | 541 | 669 | 42.5 | 259 | 115 | 151 | 243 | 45 |
| FLSN 225 M (IE3) | 356 | 426 | 311 | 375 | 149 | 32 | 80 | 18.5 | 27 | 225 | 495 | 657 | 779 | 91.5 | 308 | 161 | 208 | 270 | 45 |
| FLSN 225 M (IE2) | 356 | 426 | 311 | 375 | 149 | 32 | 80 | 18.5 | 27 | 225 | 495 | 657 | 779 | 69.5 | 352 | 175 | 212 | 270 | 45 |
| FLSN 225 MR | 356 | 426 | 311 | 380 | 144.5 | 34 | 70 | 18.5 | 17 | 225 | 398 | 566 | 682 | 49 | 259 | 115 | 151 | 243 | 45 |
| FLSN 225 S | 356 | 426 | 286 | 375 | 149 | 32 | 80 | 18.5 | 27 | 225 | 487 | 661 | 779 | 91.5 | 308 | 161 | 208 | 276 | 45 |
| FLSN 225 SR | 356 | 426 | 286 | 380 | 144.5 | 34 | 70 | 18.5 | 17 | 225 | 398 | 566 | 674 | 44.5 | 259 | 115 | 151 | 243 | 45 |
| FLSN 250 M | 406 | 476 | 349 | 413 | 168 | 32 | 80 | 24 | 26 | 250 | 495 | 682 | 779 | 91.5 | 308 | 161 | 208 | 270 | 45 |
| FLSN 250 MR | 406 | 476 | 349 | 413 | 168 | 32 | 80 | 24 | 27 | 250 | 495 | 682 | 859 | 69.5 | 352 | 175 | 212 | 270 | 45 |
| FLSN 280 M | 457 | 527 | 419 | 486 | 92 | 33 | 80 | 24 | 30 | 280 | 481 | 717 | 959 | 69 | 352 | 175 | 212 | 303 | 45 |
| FLSN 280 S | 457 | 527 | 368 | 486 | 92 | 33 | 80 | 24 | 30 | 280 | 481 | 717 | 959 | 69 | 352 | 175 | 212 | 303 | 45 |
| FLSN 315 LA | 508 | 600 | 508 | 610 | 109 | 58 | 100 | 28 | 35 | 315 | 600 | 857 | 1177 | 119 | 416 | 217 | 264 | 343 | 45 |
| FLSN 315 LB | 508 | 600 | 508 | 610 | 109 | 58 | 100 | 28 | 35 | 315 | 600 | 847 | 1177 | 119 | 452 | 219 | 269 | 343 | 45 |
| FLSN 315 LB (6P) | 508 | 600 | 508 | 610 | 109 | 58 | 100 | 28 | 35 | 315 | 600 | 857 | 1177 | 101 | 416 | 217 | 264 | 343 | 45 |
| FLSN 315 M | 508 | 600 | 457 | 610 | 109 | 58 | 100 | 28 | 35 | 315 | 600 | 857 | 1177 | 119 | 416 | 217 | 264 | 343 | 45 |
| FLSN 315 S | 508 | 600 | 406 | 610 | 109 | 58 | 100 | 28 | 35 | 315 | 600 | 857 | 1177 | 119 | 416 | 217 | 264 | 343 | 45 |
| FLSN 355 LA | 610 | 710 | 630 | 756 | 127 | 76 | 100 | 28 | 35 | 355 | 688 | 925 | 1303 | 121 | 452 | 219 | 269 | - | - |
| FLSN 355 LA (6P) | 610 | 710 | 630 | 756 | 127 | 76 | 100 | 28 | 35 | 355 | 688 | 935 | 1303 | 139 | 416 | 217 | 264 | - | - |
| FLSN 355 LAL | 610 | 710 | 630 | 756 | 127 | 76 | 100 | 28 | 35 | 355 | 688 | 925 | 1303 | 121 | 452 | 219 | 269 | - | - |
| FLSN 355 LB | 610 | 710 | 630 | 756 | 127 | 76 | 100 | 28 | 35 | 355 | 688 | 925 | 1303 | 121 | 452 | 219 | 269 | - | - |
| FLSN 355 LC | 610 | 710 | 630 | 756 | 127 | 76 | 100 | 28 | 35 | 355 | 688 | 925 | 1303 | 121 | 452 | 219 | 269 | - | - |
| FLSN 355 LD | 610 | 710 | 630 | 756 | 127 | 76 | 100 | 28 | 35 | 355 | 688 | 925 | 1303 | 121 | 452 | 219 | 269 | - | - |


Dimensions in millimetres



| Type | Main dimensions | | | | | | | | | | | | | | | | | | | |
|------------------|-----------------|-----|-----|-----|-------|----|-----|------|----|-----|-----|-----|------|------|-----|-----|-----|-----|------|-------|
| | A | AB | B | BB | C | x | AA | K | HA | H | AC* | HD | LB | LJ | J | I | II | AD | AD1 | Symb |
| FLSN 80 L | 125 | 157 | 100 | 130 | 50 | 18 | 34 | 10 | 10 | 80 | 170 | 228 | 212 | 7 | 136 | 68 | 68 | - | - | FF165 |
| FLSN 80 LG | 125 | 170 | 100 | 138 | 50 | 22 | 39 | 10 | 10 | 80 | 203 | 238 | 245 | 8 | 136 | 68 | 68 | 135 | 41 | FF165 |
| FLSN 90 L | 140 | 170 | 125 | 162 | 56 | 28 | 33 | 10 | 10 | 90 | 203 | 248 | 239 | 8 | 136 | 68 | 68 | 135 | 41 | FF165 |
| FLSN 90 LU | 140 | 170 | 125 | 162 | 56 | 28 | 33 | 10 | 10 | 90 | 203 | 248 | 266 | 8 | 136 | 68 | 68 | 135 | 41 | FF165 |
| FLSN 90 SL | 140 | 170 | 125 | 162 | 56 | 28 | 33 | 10 | 10 | 90 | 203 | 248 | 239 | 8 | 136 | 68 | 68 | 135 | 41 | FF165 |
| FLSN 100 L | 160 | 196 | 140 | 185 | 63 | 29 | 40 | 12 | 13 | 100 | 204 | 258 | 300 | 8 | 136 | 68 | 68 | 135 | 41 | FF215 |
| FLSN 100 LG | 160 | 196 | 140 | 168 | 53 | 13 | 40 | 12 | 14 | 100 | 227 | 266 | 299 | 0.5 | 136 | 68 | 68 | 130 | 45 | FF215 |
| FLSN 100 LR | 160 | 196 | 140 | 185 | 63 | 29 | 40 | 12 | 13 | 100 | 204 | 258 | 300 | 8 | 136 | 68 | 68 | 135 | 41 | FF215 |
| FLSN 112 MG | 190 | 230 | 140 | 186 | 60 | 32 | 48 | 12 | 12 | 112 | 230 | 294 | 299 | 8 | 136 | 68 | 68 | 148 | 41 | FF215 |
| FLSN 112 MU | 190 | 230 | 140 | 186 | 60 | 32 | 48 | 12 | 12 | 112 | 230 | 294 | 299 | 8 | 136 | 68 | 68 | 148 | 41 | FF215 |
| FLSN 132 M | 216 | 255 | 178 | 240 | 89 | 50 | 63 | 12 | 16 | 132 | 270 | 335 | 385 | 22 | 136 | 68 | 68 | 165 | 37.5 | FF265 |
| FLSN 132 MR | 216 | 255 | 178 | 240 | 89 | 50 | 63 | 12 | 16 | 132 | 270 | 335 | 447 | 22 | 136 | 68 | 68 | 165 | 37.5 | FF265 |
| FLSN 132 MU | 216 | 255 | 178 | 240 | 89 | 50 | 63 | 12 | 16 | 132 | 270 | 335 | 447 | 22 | 136 | 68 | 68 | 165 | 37.5 | FF265 |
| FLSN 132 SM | 216 | 255 | 140 | 240 | 89 | 50 | 63 | 12 | 16 | 132 | 270 | 335 | 385 | 22 | 136 | 68 | 68 | 165 | 37.5 | FF265 |
| FLSN 160 L | 254 | 294 | 254 | 294 | 108 | 20 | 65 | 14.5 | 20 | 160 | 315 | 449 | 495 | 23 | 259 | 115 | 151 | 179 | 45 | FF265 |
| FLSN 160 LUR | 254 | 294 | 254 | 294 | 108 | 20 | 65 | 14.5 | 20 | 160 | 315 | 449 | 510 | 23 | 259 | 115 | 151 | 179 | 45 | FF300 |
| FLSN 160 M | 254 | 294 | 210 | 294 | 108 | 20 | 65 | 14.5 | 20 | 160 | 315 | 449 | 495 | 23 | 259 | 115 | 151 | 179 | 45 | FF300 |
| FLSN 160 MU | 254 | 294 | 210 | 294 | 108 | 20 | 65 | 14.5 | 20 | 160 | 315 | 449 | 510 | 23 | 259 | 115 | 151 | 179 | 45 | FF300 |
| FLSN 180 L | 279 | 330 | 279 | 337 | 121 | 32 | 70 | 14.5 | 28 | 180 | 361 | 490 | 552 | 35.5 | 259 | 115 | 151 | 190 | 45 | FF300 |
| FLSN 180 LUR | 279 | 330 | 279 | 337 | 115 | 32 | 70 | 14.5 | 28 | 180 | 361 | 490 | 593 | 35.5 | 259 | 115 | 151 | 190 | 45 | FF300 |
| FLSN 180 M | 279 | 330 | 241 | 337 | 121 | 32 | 70 | 14.5 | 28 | 180 | 361 | 490 | 552 | 35.5 | 259 | 115 | 151 | 190 | 45 | FF300 |
| FLSN 180 MT | 279 | 330 | 241 | 337 | 121 | 32 | 70 | 14.5 | 28 | 180 | 361 | 490 | 537 | 29.5 | 259 | 115 | 151 | 190 | 45 | FF300 |
| FLSN 180 MUR | 279 | 324 | 241 | 290 | 121 | 24 | 80 | 14.5 | 25 | 180 | 328 | 469 | 551 | 29.5 | 259 | 115 | 151 | 177 | 45 | FF300 |
| FLSN 200 LU | 318 | 374 | 305 | 360 | 135 | 28 | 60 | 18.5 | 17 | 200 | 399 | 541 | 669 | 42.5 | 259 | 115 | 151 | 243 | 45 | FF350 |
| FLSN 225 M (IE3) | 356 | 426 | 311 | 375 | 149 | 32 | 80 | 18.5 | 27 | 225 | 495 | 657 | 779 | 91.5 | 308 | 161 | 208 | 270 | 45 | FF400 |
| FLSN 225 M (IE2) | 356 | 426 | 311 | 375 | 149 | 32 | 80 | 18.5 | 27 | 225 | 495 | 657 | 779 | 69.5 | 352 | 175 | 212 | 270 | 45 | FF400 |
| FLSN 225 MR | 356 | 426 | 311 | 380 | 144.5 | 34 | 70 | 18.5 | 17 | 225 | 398 | 566 | 682 | 49 | 259 | 115 | 151 | 243 | 45 | FF400 |
| FLSN 225 S | 356 | 426 | 286 | 375 | 149 | 32 | 80 | 18.5 | 27 | 225 | 487 | 661 | 779 | 91.5 | 308 | 161 | 208 | 276 | 45 | FF400 |
| FLSN 225 SR | 356 | 426 | 286 | 380 | 144.5 | 34 | 70 | 18.5 | 17 | 225 | 398 | 566 | 674 | 44.5 | 259 | 115 | 151 | 243 | 45 | FF400 |
| FLSN 250 M | 406 | 476 | 349 | 413 | 168 | 32 | 80 | 24 | 26 | 250 | 495 | 682 | 779 | 91.5 | 308 | 161 | 208 | 270 | 45 | FF500 |
| FLSN 250 MR | 406 | 476 | 349 | 413 | 168 | 32 | 80 | 24 | 27 | 250 | 495 | 682 | 859 | 69.5 | 352 | 175 | 212 | 270 | 45 | FF500 |
| FLSN 280 M | 457 | 527 | 419 | 486 | 92 | 33 | 80 | 24 | 30 | 280 | 481 | 717 | 959 | 69 | 352 | 175 | 212 | 303 | 45 | FF500 |
| FLSN 280 S | 457 | 527 | 368 | 486 | 92 | 33 | 80 | 24 | 30 | 280 | 481 | 717 | 959 | 69 | 352 | 175 | 212 | 303 | 45 | FF500 |
| FLSN 315 LA | 508 | 600 | 508 | 610 | 109 | 58 | 100 | 28 | 35 | 315 | 600 | 857 | 1177 | 119 | 416 | 217 | 264 | 343 | 45 | FF600 |
| FLSN 315 LB | 508 | 600 | 508 | 610 | 109 | 58 | 100 | 28 | 35 | 315 | 600 | 847 | 1177 | 119 | 452 | 219 | 269 | 343 | 45 | FF600 |
| FLSN 315 LB (6P) | 508 | 600 | 508 | 610 | 109 | 58 | 100 | 28 | 35 | 315 | 600 | 857 | 1177 | 101 | 416 | 217 | 264 | 343 | 45 | FF600 |
| FLSN 315 M | 508 | 600 | 457 | 610 | 109 | 58 | 100 | 28 | 35 | 315 | 600 | 857 | 1177 | 119 | 416 | 217 | 264 | 343 | 45 | FF600 |
| FLSN 315 S | 508 | 600 | 406 | 610 | 109 | 58 | 100 | 28 | 35 | 315 | 600 | 857 | 1177 | 119 | 416 | 217 | 264 | 343 | 45 | FF600 |
| FLSN 355 LA | 610 | 710 | 630 | 756 | 127 | 76 | 100 | 28 | 35 | 355 | 688 | 925 | 1303 | 121 | 452 | 219 | 269 | - | - | FF740 |
| FLSN 355 LA (6P) | 610 | 710 | 630 | 756 | 127 | 76 | 100 | 28 | 35 | 355 | 688 | 935 | 1303 | 139 | 416 | 217 | 264 | - | - | FF740 |
| FLSN 355 LAL | 610 | 710 | 630 | 756 | 127 | 76 | 100 | 28 | 35 | 355 | 688 | 925 | 1303 | 121 | 452 | 219 | 269 | - | - | FF740 |
| FLSN 355 LB | 610 | 710 | 630 | 756 | 127 | 76 | 100 | 28 | 35 | 355 | 688 | 925 | 1303 | 121 | 452 | 219 | 269 | - | - | FF740 |
| FLSN 355 LC | 610 | 710 | 630 | 756 | 127 | 76 | 100 | 28 | 35 | 355 | 688 | 925 | 1303 | 121 | 452 | 219 | 269 | - | - | FF740 |
| FLSN 355 LD | 610 | 710 | 630 | 756 | 127 | 76 | 100 | 28 | 35 | 355 | 688 | 925 | 1303 | 121 | 452 | 219 | 269 | - | - | FF740 |

ATEX GAS - Zone 2 - Cast iron

Dimensions in millimetres




| Type | Main dimensions | | | | | | | | | | | | | | | | | | | |
|-------------|-----------------|-----|-----|-----|----|----|----|----|----|-----|-----|-----|-----|-----|-----|----|----|-----|------|-------|
| | A | AB | B | BB | C | x | AA | K | HA | H | AC* | HD | LB | LJ | J | I | II | AD | AD1 | Symb |
| FLSN 80 L | 125 | 157 | 100 | 130 | 50 | 18 | 34 | 10 | 10 | 80 | 170 | 228 | 212 | 7 | 136 | 68 | 68 | - | - | FT100 |
| FLSN 80 LG | 125 | 170 | 100 | 138 | 50 | 22 | 39 | 10 | 10 | 80 | 203 | 238 | 245 | 8 | 136 | 68 | 68 | 135 | 41 | FT100 |
| FLSN 90 L | 140 | 170 | 125 | 162 | 56 | 28 | 33 | 10 | 10 | 90 | 203 | 248 | 239 | 8 | 136 | 68 | 68 | 135 | 41 | FT115 |
| FLSN 90 LU | 140 | 170 | 125 | 162 | 56 | 28 | 33 | 10 | 10 | 90 | 203 | 248 | 266 | 8 | 136 | 68 | 68 | 135 | 41 | FT115 |
| FLSN 90 SL | 140 | 170 | 125 | 162 | 56 | 28 | 33 | 10 | 10 | 90 | 203 | 248 | 239 | 8 | 136 | 68 | 68 | 135 | 41 | FT115 |
| FLSN 100 L | 160 | 196 | 140 | 185 | 63 | 29 | 40 | 12 | 13 | 100 | 204 | 258 | 300 | 8 | 136 | 68 | 68 | 135 | 41 | FT130 |
| FLSN 100 LG | 160 | 196 | 140 | 168 | 53 | 13 | 40 | 12 | 14 | 100 | 227 | 266 | 299 | 0.5 | 136 | 68 | 68 | 130 | 45 | FT130 |
| FLSN 100 LR | 160 | 196 | 140 | 185 | 63 | 29 | 40 | 12 | 13 | 100 | 204 | 258 | 300 | 8 | 136 | 68 | 68 | 135 | 41 | FT130 |
| FLSN 112 MG | 190 | 230 | 140 | 186 | 60 | 32 | 48 | 12 | 12 | 112 | 230 | 294 | 299 | 8 | 136 | 68 | 68 | 148 | 41 | FT130 |
| FLSN 112 MU | 190 | 230 | 140 | 186 | 60 | 32 | 48 | 12 | 12 | 112 | 230 | 294 | 299 | 8 | 136 | 68 | 68 | 148 | 41 | FT130 |
| FLSN 132 M | 216 | 255 | 178 | 240 | 89 | 50 | 63 | 12 | 16 | 132 | 270 | 335 | 385 | 22 | 136 | 68 | 68 | 165 | 37.5 | FT165 |
| FLSN 132 MR | 216 | 255 | 178 | 240 | 89 | 50 | 63 | 12 | 16 | 132 | 270 | 335 | 447 | 22 | 136 | 68 | 68 | 165 | 37.5 | FT165 |
| FLSN 132 MU | 216 | 255 | 178 | 240 | 89 | 50 | 63 | 12 | 16 | 132 | 270 | 335 | 447 | 22 | 136 | 68 | 68 | 165 | 37.5 | FT165 |
| FLSN 132 SM | 216 | 255 | 140 | 240 | 89 | 50 | 63 | 12 | 16 | 132 | 270 | 335 | 385 | 22 | 136 | 68 | 68 | 165 | 37.5 | FT165 |

* AC: housing diameter without lifting rings

ATEX GAS - Zone 2 - Cast iron

Dimensions in millimetres



ATEX GAS - Zone 2 - Cast iron

| Type | Main dimensions | | | | | | | | |
|-------------|-----------------|-----|-----|-----|-----|----|----|-----|------|
| | AC* | LB | HJ | LJ | J | I | II | AD | AD1 |
| FLSN 80 L | 170 | 212 | 149 | 7 | 136 | 68 | 68 | - | - |
| FLSN 80 LG | 203 | 245 | 159 | 8 | 136 | 68 | 68 | 135 | 41 |
| FLSN 90 SL | 203 | 239 | 159 | 8 | 136 | 68 | 68 | 135 | 41 |
| FLSN 90 L | 203 | 266 | 159 | 8 | 136 | 68 | 68 | 135 | 41 |
| FLSN 90 LU | 203 | 239 | 159 | 8 | 136 | 68 | 68 | 135 | 41 |
| FLSN 100 L | 204 | 300 | 159 | 8 | 136 | 68 | 68 | 135 | 41 |
| FLSN 100 LR | 227 | 299 | 184 | 0.5 | 136 | 68 | 68 | 130 | 45 |
| FLSN 100 LG | 204 | 300 | 159 | 8 | 136 | 68 | 68 | 135 | 41 |
| FLSN 112 MG | 230 | 299 | 183 | 8 | 136 | 68 | 68 | 148 | 41 |
| FLSN 112 MU | 230 | 299 | 183 | 8 | 136 | 68 | 68 | 148 | 41 |
| FLSN 132 SM | 270 | 385 | 204 | 22 | 136 | 68 | 68 | 165 | 37.5 |
| FLSN 132 M | 270 | 447 | 204 | 22 | 136 | 68 | 68 | 165 | 37.5 |
| FLSN 132 MR | 270 | 447 | 204 | 22 | 136 | 68 | 68 | 165 | 37.5 |
| FLSN 132 MU | 270 | 385 | 204 | 22 | 136 | 68 | 68 | 165 | 37.5 |

| Type | Flange dimensions | | | | | | |
|-------|-------------------|-----|-----|-----|---|----|-----|
| | M | N | D | T | n | α° | S |
| FT100 | 100 | 80 | 120 | 3 | 4 | 45 | M6 |
| FT100 | 100 | 80 | 120 | 3 | 4 | 45 | M6 |
| FT115 | 115 | 95 | 140 | 3 | 4 | 45 | M8 |
| FT115 | 115 | 95 | 140 | 3 | 4 | 45 | M8 |
| FT115 | 115 | 95 | 140 | 3 | 4 | 45 | M8 |
| FT130 | 130 | 110 | 160 | 3.5 | 4 | 45 | M8 |
| FT130 | 130 | 110 | 160 | 3.5 | 4 | 45 | M8 |
| FT130 | 130 | 110 | 160 | 3.5 | 4 | 45 | M8 |
| FT130 | 130 | 110 | 160 | 3.5 | 4 | 45 | M8 |
| FT130 | 130 | 110 | 160 | 3.5 | 4 | 45 | M8 |
| FT165 | 165 | 130 | 200 | 3.5 | 4 | 45 | M10 |
| FT165 | 165 | 130 | 200 | 3.5 | 4 | 45 | M10 |
| FT165 | 165 | 130 | 200 | 3.5 | 4 | 45 | M10 |
| FT165 | 165 | 130 | 200 | 3.5 | 4 | 45 | M10 |

* AC: housing diameter without lifting rings

PERMANENTLY GREASED BEARINGS

Under normal operating conditions, the service life in hours (L_{10h}) of the lubricant is indicated in the table below for ambient temperatures less than 55°C.

| Series | Type | Polarity | Bearing types Permanently greased | | Bearing service life as a function of rotation speed | | | | | | | | |
|--------|----------|----------|--------------------------------------|---------|--|---------|-------|------------------------|---------|-------|------------------------|---------|---------|
| | | | N.D.E. | D.E. | 3000 min ⁻¹ | | | 1500 min ⁻¹ | | | 1000 min ⁻¹ | | |
| | | | | | 25°C | 40°C | 55°C | 25°C | 40°C | 55°C | 25°C | 40°C | 55°C |
| FLSN | 80 L | 2 | 6203 C3 | 6204 C3 | ≥ 40000 | ≥ 40000 | 25000 | - | - | - | - | - | - |
| | 80 LG | 4 | 6204 C3 | 6205 C3 | - | - | - | ≥ 40000 | ≥ 40000 | 31000 | - | - | - |
| | 90 SL/L | 2; 4; 6 | | | ≥ 40000 | ≥ 40000 | 24000 | ≥ 40000 | ≥ 40000 | 31000 | ≥ 40000 | ≥ 40000 | 34000 |
| | 90 LU | 2; 6 | 6205 C3 | 6205 C3 | ≥ 40000 | ≥ 40000 | 24000 | - | - | - | ≥ 40000 | ≥ 40000 | 34000 |
| | 100 L | 2; 4 | 6205 C3 | 6206 C3 | ≥ 40000 | ≥ 40000 | 22000 | ≥ 40000 | ≥ 40000 | 30000 | - | - | - |
| | 100 LG | 4; 6 | | | - | - | - | ≥ 40000 | ≥ 40000 | 30000 | - | - | - |
| | 112 MG | 2; 6 | | | ≥ 40000 | ≥ 40000 | 22000 | - | - | - | ≥ 40000 | ≥ 40000 | 33000 |
| | 112 MU | 4 | 6206 C3 | 6206 C3 | - | - | - | ≥ 40000 | ≥ 40000 | 30000 | - | - | - |
| | 132 SM/M | 2; 4; 6 | 6207 C3 | 6308 C3 | ≥ 40000 | ≥ 40000 | 19000 | ≥ 40000 | ≥ 40000 | 25000 | ≥ 40000 | ≥ 40000 | 30000 |
| | 132 MU | 2; 4 | 6307 C3 | 6308 C3 | ≥ 40000 | ≥ 40000 | 19000 | ≥ 40000 | ≥ 40000 | 25000 | - | - | - |
| | 132 MR | 4; 6 | 6308 C3 | 6308 C3 | - | - | - | ≥ 40000 | ≥ 40000 | 25000 | ≥ 40000 | ≥ 40000 | 30000 |
| | 160 M | 2; 4; 6 | 6210 C3 | 6309 C3 | ≥ 40000 | 37800 | 18900 | ≥ 40000 | ≥ 40000 | 36900 | ≥ 40000 | ≥ 40000 | 20050 |
| | 160 MU | 6 | | | - | - | - | - | - | - | - | ≥ 40000 | ≥ 40000 |
| | 160 LUR | 2; 4; 6 | 6210 C3 | 6310 C3 | ≥ 40000 | 24500 | 12250 | ≥ 40000 | 36400 | 18200 | ≥ 40000 | ≥ 40000 | 22450 |
| | 180 M | 2 | 6212 C3 | 6310 C3 | 34000 | 17000 | 8500 | - | - | - | - | - | - |
| | 180 MT | 4 | 6210 C3 | 6310 C3 | - | - | - | ≥ 40000 | 35500 | 17750 | - | - | - |
| | 180 MUR | 2 | 6312 C3 | 6310 C3 | ≥ 40000 | 22800 | 11400 | - | - | - | - | - | - |
| | 180 L | 4; 6 | 6212 C3 | 6310 C3 | - | - | - | ≥ 40000 | 39500 | 19750 | ≥ 40000 | ≥ 40000 | 29050 |
| | 180 LUR | 4; 6 | 6312 C3 | 6310 C3 | - | - | - | ≥ 40000 | ≥ 40000 | 22900 | ≥ 40000 | ≥ 40000 | 29900 |
| | 200 LU | 2; 4; 6 | 6312 C3 | 6312 C3 | 28600 | 14300 | 7150 | ≥ 40000 | 25400 | 12700 | ≥ 40000 | 33200 | 16600 |
| | 225 S | 4 | 6314 C3 | 6314 C3 | - | - | - | ≥ 40000 | 23700 | 11850 | - | - | - |
| | 225 SR | 4 | 6312 C3 | 6313 C3 | - | - | - | ≥ 40000 | ≥ 40000 | 21500 | - | - | - |
| | 225 M | 4; 6 | 6314 C3 | 6314 C3 | - | - | - | ≥ 40000 | 23700 | 11850 | ≥ 40000 | 25600 | 12800 |
| 225 MR | 2 | 6312 C3 | 6313 C3 | ≥ 40000 | 22800 | 11400 | - | - | - | - | - | - | |

ATEX GAS - Zone 2 - Cast iron

BEARINGS WITH GREASE NIPPLES

For open bearing assemblies of frame size ≥ 160 mm fitted with grease nipples, the table below indicates, depending on the type of motor, the lubrication intervals to be respected at 25°C, 40°C and 55°C for a machine installed with a horizontal shaft.

The table below is valid for FLSN motors lubricated with Polyrex EM103 grease used as standard.

| Series | Type | Polarity | Bearing type for bearing housings with grease nipples | | Quantity of grease g | Lubrication intervals in hours | | | | | | | | |
|-----------------|-----------|----------|---|---------|-------------------------|--------------------------------|-------|-------|------------------------|-------|-------|------------------------|-------|-------|
| | | | N.D.E. | D.E. | | 3000 min ⁻¹ | | | 1500 min ⁻¹ | | | 1000 min ⁻¹ | | |
| | | | | | | 25°C | 40°C | 55°C | 25°C | 40°C | 55°C | 25°C | 40°C | 55°C |
| FLSN | 160 M* | 2; 4; 6 | 6210 C3 | 6309 C3 | 13 | 22200 | 11100 | 5550 | 32400 | 16200 | 8100 | 39800 | 19900 | 9950 |
| | 160 MU | 6 | | | | - | - | - | - | - | - | 23400 | 11700 | 5850 |
| | 160 LUR* | 2; 4; 6 | 6210 C3 | 6310 C3 | 15 | 19600 | 9800 | 4900 | 30400 | 15200 | 7600 | 38200 | 19100 | 6600 |
| | 180 M* | 2 | 6212 C3 | 6310 C3 | 15 | 18000 | 9000 | 4500 | - | - | - | - | - | - |
| | 180 MT* | 4 | 6210 C3 | 6310 C3 | 15 | - | - | - | 30400 | 15200 | 7600 | - | - | - |
| | 180 MUR* | 2 | 6312 C3 | 6310 C3 | 15 | 10600 | 5300 | 2650 | - | - | - | - | - | - |
| | 180 L* | 4; 6 | 6212 C3 | 6310 C3 | 20 | - | - | - | 29200 | 14600 | 7300 | 37200 | 18600 | 9300 |
| | 180 LUR* | 4; 6 | 6312 C3 | 6310 C3 | 20 | - | - | - | 26800 | 13400 | 6700 | 35000 | 17500 | 8750 |
| | 200 LU* | 2; 4; 6 | 6312 C3 | 6312 C3 | 20 | 15200 | 7600 | 3800 | 26800 | 13400 | 6700 | 35000 | 17500 | 8750 |
| | 225 S* | 4 | 6314 C3 | 6314 C3 | 25 | - | - | - | 23600 | 11800 | 5900 | - | - | - |
| | 225 SR* | 4 | 6312 C3 | 6313 C3 | 25 | - | - | - | 25200 | 12600 | 6300 | - | - | - |
| | 225 M* | 4; 6 | 6314 C3 | 6314 C3 | 25 | - | - | - | 23600 | 11800 | 5900 | 32200 | 16100 | 8050 |
| | 225 MR* | 2 | 6312 C3 | 6313 C3 | 25 | 13400 | 6700 | 3350 | - | - | - | - | - | - |
| | 250 M | 2; 6 | 6314 C3 | 6314 C3 | 25 | 10400 | 5200 | 2600 | - | - | - | 32200 | 16100 | 8050 |
| | 250 MR | 4 | | | | - | - | - | 17800 | 8900 | 4450 | - | - | - |
| | 280 S/M | 2; 4; 6 | 6314 C3 | 6316 C3 | 35 | 7200 | 3600 | 1800 | 21000 | 13200 | 6615 | 29000 | 29000 | 18270 |
| | 315 S/M/L | 2 | 6316 C3 | 6218 C3 | 35 | 7400 | 5880 | 2920 | - | - | - | - | - | - |
| | 315 S/M/L | 4; 6 | 6316 C3 | 6320 C3 | 50 | - | - | - | 15600 | 12400 | 6160 | 25000 | 25000 | 12500 |
| 355 LA/LB/LC/LD | 2 | 6316 C3 | 6218 C3 | 35 | 7400 | 3700 | 1850 | - | - | - | - | - | - | |
| 355 LA/LB/LC/LD | 4; 6 | 6316 C3 | 6322 C3 | 60 | - | - | - | 13200 | 8316 | 4160 | 22000 | 13860 | 6930 | |

* bearing housings with grease nipples on request

CONSTRUCTION AND SPECIAL ATMOSPHERES

For a machine installed with a vertical shaft, the lubrication intervals are approximately 80% of the values shown in the tables above.

NB: The quality and quantity of grease along with the lubrication interval are indicated on the machine nameplate.

In the case of special fitting arrangements (motors with roller bearing at the front or other mountings), machines with frame size ≥ 160 mm are fitted with grease nipple bearings.


The instructions required for bearing housing maintenance are shown on the machine nameplate.

BEARING MOUNTING PRINCIPLE

| FLSN series | | Horizontal shaft | Vertical shaft | |
|---|-----------------------|--|--|--|
| | | | Shaft end down | Shaft end up |
| Foot mounted motors | Mounting arrangements | B3 | V5 | V6 |
| | standard fitting | Front bearing: - at Front stop for frame size ≤ 132 - locked for frame size ≥ 160 | Front bearing locked | Front bearing locked |
| Flange mounted motors (or feet and flange) | Mounting arrangements | B5 / B35 / B14 / B34 | V1 / V15 / V18 / V58 | V3 / V36 / V19 / V69 |
| | standard fitting | Front bearing locked for frame size from 80 to ≤ 355 LD Rear bearing locked from 355 LKA to 450 LD | Front bearing locked for frame size from 80 to ≤ 355 LD Rear bearing locked from 355 LKA to 450 LD | Front bearing locked for frame size from 80 to ≤ 355 LD Rear bearing locked from 355L KA to 450 LD |

HORIZONTAL MOTOR

For a bearing service life L_{10h} of 25,000 hours and 40,000 hours



| Series | Type | Polarity | Permissible axial load (daN) on the main drive shaft for standard fitting of bearings | | | | | | | | | | | | | |
|--------|-----------------|----------|---|--------------|--------------|--------------|--------------|--------------|------------------------|--------------|--------------|--------------|------------------------|--------------|--|--|
| | | | 3000 min ⁻¹ | | | | | | 1500 min ⁻¹ | | | | 1000 min ⁻¹ | | | |
| | | | → | | ← | | → | | ← | | → | | ← | | | |
| | | | 25,000 hours | 40,000 hours | 25,000 hours | 40,000 hours | 25,000 hours | 40,000 hours | 25,000 hours | 40,000 hours | 25,000 hours | 40,000 hours | 25,000 hours | 40,000 hours | | |
| | 80 L | 2 | 30 | 21 | (60) | (51) | - | - | - | - | - | - | - | - | | |
| | 80 LG | 2; 4 | 28 | 19 | (68) | (59) | 48 | 34 | (88) | (74) | - | - | - | - | | |
| | 90 SL/L | 2; 4; 6 | 29 | 23 | (69) | (56) | 45 | 32 | (85) | (72) | 56 | 40 | (96) | (80) | | |
| | 90 LU | 2; 4; 6 | 22 | 13 | (72) | (63) | 38 | 25 | (88) | (75) | 47 | 32 | (97) | (82) | | |
| | 100 L | 2; 4 | 40 | 26 | (90) | (76) | 61 | 43 | (111) | (93) | - | - | - | - | | |
| | 100 LR | 4 | - | - | - | - | 61 | 43 | (111) | (93) | - | - | - | - | | |
| | 100 LG | 4; 6 | - | - | - | - | 55 | 38 | (105) | (88) | 75 | 53 | (125) | (103) | | |
| | 112 MG | 2; 6 | 37 | 24 | (87) | (74) | - | - | - | - | 82 | 61 | (132) | (111) | | |
| | 112 MU | 4; 6 | - | - | - | - | 54 | 36 | (114) | (96) | 66 | 45 | (126) | (105) | | |
| | 132 SM/M | 2; 4; 6 | 101 | 74 | (171) | (144) | 146 | 109 | (216) | (179) | 182 | 138 | (252) | (208) | | |
| | 132 MU | 6 | - | - | - | - | - | - | - | - | 169 | 126 | (249) | (206) | | |
| | 132 MR | 4 | - | - | - | - | 129 | 93 | (219) | (183) | - | - | - | - | | |
| | 160 M | 2; 4 | 129 | 94 | 229 | 194 | 187 | 140 | 287 | 240 | 234 | 177 | 334 | 277 | | |
| | 160 MU | 6 | - | - | - | - | - | - | - | - | 219 | 164 | 319 | 264 | | |
| | 160 L | 2; 4 | 118 | 83 | 218 | 183 | 195 | 148 | 295 | 248 | - | - | - | - | | |
| | 160 LUR | 2; 4; 6 | 158 | 117 | 258 | 217 | 212 | 158 | 312 | 258 | 257 | 193 | 357 | 293 | | |
| | 180 M | 2; 4 | 189 | 148 | 237 | 196 | 228 | 174 | 291 | 237 | - | - | - | - | | |
| | 180 MT | 4 | - | - | - | - | 215 | 161 | 315 | 261 | - | - | - | - | | |
| | 180 MUR | 2 | 178 | 137 | 241 | 200 | - | - | - | - | - | - | - | - | | |
| | 180 L | 4; 6 | - | - | - | - | 240 | 186 | 288 | 234 | 272 | 208 | 320 | 256 | | |
| | 180 LUR | 4; 6 | - | - | - | - | 224 | 170 | 287 | 233 | 224 | 162 | 287 | 225 | | |
| | 200 LU | 2; 4; 6 | 249 | 196 | 312 | 259 | 316 | 245 | 379 | 308 | 327 | 245 | 390 | 308 | | |
| | 225 S | 4 | - | - | - | - | 427 | 336 | 490 | 399 | - | - | - | - | | |
| | 225 SR | 4 | - | - | - | - | 370 | 290 | 433 | 353 | - | - | - | - | | |
| | 225 M | 4; 6 | - | - | - | - | 416 | 325 | 496 | 405 | 511 | 402 | 591 | 482 | | |
| | 225 MR | 2 | 280 | 220 | 343 | 283 | - | - | - | - | - | - | - | - | | |
| | 250 M | 2; 6 | 308 | 240 | 388 | 320 | - | - | - | - | 506 | 400 | 506 | 400 | | |
| | 250 MR | 4 | - | - | - | - | 413 | 322 | 493 | 402 | - | - | - | - | | |
| | 280 S/M | 2; 4; 6 | 342 | 258 | 484 | 400 | 483 | 372 | 625 | 514 | 581 | 445 | 723 | 587 | | |
| | 315 S/M/LA/LB | 2; 6 | 411 | 348 | 165 | 102 | - | - | - | - | 933 | 761 | 687 | 515 | | |
| | 315 S/M/LA/LB | 4 | - | - | - | - | 814 | 670 | 568 | 424 | - | - | - | - | | |
| | 355 LA/LB/LC/LD | 2 | 393 | 333 | 147 | 87 | - | - | - | - | - | - | - | - | | |
| | 355 LAL | 4 | - | - | - | - | 876 | 724 | 630 | 478 | - | - | - | - | | |
| | 355 LA/LB/LC/LD | 4; 6 | - | - | - | - | 876 | 724 | 630 | 478 | 947 | 764 | 701 | 518 | | |

(): permissible axial loads with Front bearing locked

ATEX GAS - Zone 2 - Cast iron

**VERTICAL MOTOR
SHAFT END DOWNWARDS**

For a bearing service life L_{10h}
of 25,000 hours
and 40,000 hours



ATEX GAS - Zone 2 - Cast iron

| Series | Type | Polarity | Permissible axial load (daN) on the main drive shaft for standard fitting of bearings | | | | | | | | | | | |
|--------|-----------------|----------|---|--------------|--------------|--------------|------------------------|--------------|--------------|--------------|------------------------|--------------|--------------|--------------|
| | | | 3000 min ⁻¹ | | | | 1500 min ⁻¹ | | | | 1000 min ⁻¹ | | | |
| | | | 25,000 hours | 40,000 hours | 25,000 hours | 40,000 hours | 25,000 hours | 40,000 hours | 25,000 hours | 40,000 hours | 25,000 hours | 40,000 hours | 25,000 hours | 40,000 hours |
| | | | IM V5 IM V1 / V15 IM V18 / V58 | | | | | | | | | | | |
| | 80 L | 2 | 29 | 20 | (63) | (54) | - | - | - | - | - | - | - | - |
| | 80 LG | 2; 4 | 26 | 16 | (72) | (62) | 45 | 32 | (93) | (78) | - | - | - | - |
| | 90 SL/L | 2; 4; 6 | 26 | 16 | (73) | (63) | 42 | 28 | (91) | (78) | 53 | 37 | (101) | (86) |
| | 90 LU | 2; 4; 6 | 19 | 9 | (77) | (67) | 33 | 20 | (95) | (82) | 43 | 28 | (105) | (89) |
| | 100 L | 2; 4 | 36 | 23 | (96) | (83) | 56 | 38 | (119) | (101) | - | - | - | - |
| | 100 LR | 4 | - | - | - | 55 | 37 | (120) | (102) | - | - | - | - | |
| | 100 LG | 4; 6 | - | - | - | 48 | 31 | (116) | (99) | 68 | 46 | (137) | (115) | |
| | 112 MG | 2; 6 | 31 | 18 | (98) | (85) | - | - | - | - | 75 | 53 | (145) | (123) |
| | 112 MU | 4; 6 | - | - | - | 45 | 28 | (128) | (110) | 57 | 36 | (140) | (119) | |
| | 132 SM/M | 2; 4; 6 | 90 | 62 | (189) | (161) | 135 | 98 | (235) | (198) | 171 | 127 | (271) | (227) |
| | 132 MU | 6 | - | - | - | - | - | - | - | 154 | 110 | (275) | (231) | |
| | 132 MR | 4 | - | - | - | 113 | 77 | (245) | (208) | - | - | - | - | |
| | 160 M | 2; 4; 6 | 107 | 72 | 264 | 229 | 164 | 117 | 325 | 277 | 209 | 152 | 374 | 317 |
| | 160 MU | 6 | - | - | - | - | - | - | - | 189 | 133 | 375 | 319 | |
| | 160 L | 2; 4 | 94 | 59 | 256 | 221 | 174 | 126 | 331 | 284 | - | - | - | - |
| | 160 LUR | 2; 4; 6 | 133 | 92 | 297 | 256 | 185 | 130 | 362 | 308 | 227 | 162 | 417 | 352 |
| | 180 M | 2; 4 | 160 | 119 | 279 | 238 | 187 | 132 | 361 | 306 | - | - | - | - |
| | 180 MT | 4 | - | - | - | 190 | 135 | 361 | 306 | - | - | - | - | |
| | 180 MUR | 2 | 144 | 102 | 294 | 252 | - | - | - | - | - | - | - | - |
| | 180 L | 4; 6 | - | - | - | - | 206 | 151 | 346 | 291 | 233 | 169 | 391 | 326 |
| | 180 LUR | 4; 6 | - | - | - | - | 187 | 132 | 355 | 300 | 183 | 120 | 377 | 314 |
| | 200 LU | 2; 4; 6 | 207 | 153 | 375 | 320 | 262 | 190 | 471 | 398 | 269 | 186 | 505 | 422 |
| | 225 S | 4 | - | - | - | 351 | 260 | 611 | 520 | - | - | - | - | - |
| | 225 SR | 4 | - | - | - | 317 | 236 | 520 | 438 | - | - | - | - | - |
| | 225 M | 4; 6 | - | - | - | 333 | 241 | 627 | 535 | 428 | 319 | 723 | 613 | |
| | 225 MR | 2 | 234 | 174 | 413 | 352 | - | - | - | - | - | - | - | - |
| | 250 M | 2; 6 | 247 | 179 | 481 | 413 | - | - | - | - | 423 | 315 | 647 | 539 |
| | 250 MR | 4 | - | - | - | 315 | 223 | 639 | 547 | - | - | - | - | - |
| | 280 S/M | 2; 4; 6 | 396 | 307 | 484 | 395 | 507 | 394 | 670 | 557 | 602 | 461 | 793 | 651 |
| | 315 S/M/LA/LB | 2; 6 | 226 | 156 | 417 | 347 | - | - | - | - | - | - | - | - |
| | 315 S/M/LA/LB | 4 | - | - | - | 601 | 449 | 893 | 741 | 683 | 515 | 1042 | 873 | |
| | 355 LA/LB/LC/LD | 2 | 135 | 65 | 524 | 454 | - | - | - | - | - | - | - | - |
| | 355 LAL | 4 | - | - | - | 516 | 350 | 1123 | 957 | - | - | - | - | - |
| | 355 LA/LB/LC/LD | 4; 6 | - | - | - | 516 | 350 | 1123 | 957 | 566 | 364 | 1328 | 1126 | |

(): permissible axial loads with Front bearing locked

**VERTICAL MOTOR
SHAFT END UPWARDS**

For a bearing service life L_{10h}
of 25,000 hours
and 40,000 hours



| Series | Type | Polarity | Permissible axial load (daN) on the main drive shaft for standard fitting of bearings | | | | | | | | | | | | | | | |
|--------|------|----------|---|--------------|--------------|--------------|------------------------|--------------|--------------|--------------|------------------------|--------------|--------------|--------------|---|---|---|---|
| | | | 3000 min ⁻¹ | | | | 1500 min ⁻¹ | | | | 1000 min ⁻¹ | | | | | | | |
| | | | 25,000 hours | 40,000 hours | 25,000 hours | 40,000 hours | 25,000 hours | 40,000 hours | 25,000 hours | 40,000 hours | 25,000 hours | 40,000 hours | 25,000 hours | 40,000 hours | | | | |
| | | | IM V6 IM V3 / V36 IM V19 / V69 | | | | | | | | | | | | | | | |
| | | | (59) | (50) | 33 | 24 | - | - | - | - | - | - | - | - | - | - | - | - |
| | | | (66) | (56) | 32 | 22 | (85) | (71) | 53 | 39 | - | - | - | - | - | - | - | - |
| | | | (66) | (56) | 33 | 23 | (82) | (68) | 51 | 38 | (93) | (77) | 61 | 46 | | | | |
| | | | (69) | (59) | 27 | 18 | (81) | (76) | 43 | 38 | (93) | (82) | 55 | 32 | | | | |
| | | | (86) | (72) | 46 | 33 | (106) | (88) | 69 | 51 | - | - | - | - | | | | |
| | | | - | - | - | - | (105) | (87) | 70 | 52 | - | - | - | - | | | | |
| | | | - | - | - | - | (98) | (81) | 67 | 49 | (118) | (96) | 87 | 66 | | | | |
| | | | (81) | (68) | 48 | 35 | - | - | - | - | (125) | (103) | 95 | 73 | | | | |
| | | | - | - | - | - | (105) | (88) | 68 | 50 | (117) | (96) | 80 | 60 | | | | |
| | | | (159) | (132) | 120 | 91 | (205) | (168) | 165 | 128 | (249) | (205) | 179 | 135 | | | | |
| | | | - | - | - | - | - | - | - | - | (234) | (190) | 195 | 151 | | | | |
| | | | - | - | - | - | (203) | (167) | 155 | 118 | - | - | - | - | | | | |
| | | | 207 | 172 | 164 | 129 | 264 | 217 | 225 | 177 | 309 | 252 | 274 | 217 | | | | |
| | | | - | - | - | - | - | - | - | - | 289 | 233 | 275 | 219 | | | | |
| | | | 194 | 159 | 156 | 121 | 274 | 226 | 231 | 184 | - | - | - | - | | | | |
| | | | 233 | 192 | 197 | 156 | 285 | 230 | 262 | 208 | 327 | 262 | 317 | 252 | | | | |
| | | | 208 | 167 | 231 | 190 | 250 | 195 | 298 | 243 | - | - | - | - | | | | |
| | | | - | - | - | - | 290 | 235 | 261 | 206 | - | - | - | - | | | | |
| | | | 207 | 165 | 231 | 189 | - | - | - | - | - | - | - | - | | | | |
| | | | - | - | - | - | 254 | 199 | 298 | 243 | 281 | 217 | 343 | 278 | | | | |
| | | | - | - | - | - | 250 | 195 | 292 | 237 | 246 | 183 | 314 | 251 | | | | |
| | | | 270 | 216 | 312 | 257 | 325 | 253 | 408 | 335 | 332 | 249 | 442 | 359 | | | | |
| | | | - | - | - | - | 414 | 323 | 548 | 457 | - | - | - | - | | | | |
| | | | - | - | - | - | 380 | 299 | 457 | 375 | - | - | - | - | | | | |
| | | | - | - | - | - | 413 | 321 | 547 | 455 | 508 | 399 | 643 | 533 | | | | |
| | | | 297 | 237 | 350 | 289 | - | - | - | - | - | - | - | - | | | | |
| | | | 327 | 259 | 401 | 333 | - | - | - | - | 423 | 315 | 647 | 539 | | | | |
| | | | - | - | - | - | 395 | 303 | 559 | 467 | - | - | - | - | | | | |
| | | | 396 | 307 | 484 | 395 | 507 | 394 | 670 | 557 | 602 | 461 | 793 | 651 | | | | |
| | | | 226 | 156 | 417 | 347 | - | - | - | - | - | - | - | - | | | | |
| | | | - | - | - | - | 601 | 449 | 893 | 741 | 683 | 515 | 1042 | 873 | | | | |
| | | | 135 | 65 | 524 | 454 | - | - | - | - | - | - | - | - | | | | |
| | | | - | - | - | - | 516 | 350 | 1123 | 957 | 566 | 364 | 1328 | 1126 | | | | |

400 and 450: please contact us

(): permissible axial loads with Front bearing locked










STANDARD FITTING ARRANGEMENT

Permissible radial load on main shaft extension with a bearing life L_{10h} of 25,000 hours.

FR: Radial Force

X: distance with respect to the shaft shoulder

ATEX GAS - Zone 2 - Cast iron












STANDARD FITTING ARRANGEMENT

Permissible radial load on main shaft extension with a bearing life L10h of 25,000 hours.

FR: Radial Force

X: distance with respect to the shaft shoulder



ATEX GAS - Zone 2 - Cast iron







STANDARD FITTING ARRANGEMENT

Permissible radial load on main shaft extension with a bearing life L10h of 25,000 hours.

FR: Radial Force

X: distance with respect to the shaft shoulder

ATEX GAS - Zone 2 - Cast iron



SPECIAL FITTING ARRANGEMENT







Type of drive end roller bearings

| Series | Type | Polarity | Rear bearing (N.D.E.) | Front Bearing (D.E.) |
|--------|-----------|----------|-----------------------|----------------------|
| FLSN | 160 M/MU | 4; 6 | 6210 C3 | NU 309 |
| | 160 L | 4 | | |
| | 160 LUR | 6 | 6210 C3 | NU 310 |
| | 180 MT | 4 | | |
| | 180 M | 4 | 6212 C3 | NU 310 |
| | 180 L | 4; 6 | | |
| | 180 LUR | 4; 6 | 6312 C3 | NU 310 |
| | 200 LU | 4; 6 | | |
| | 225 S | 4 | 6314 C3 | NU 314 |
| | 225 SR | 4 | | |
| | 225 M | 4; 6 | 6314 C3 | NU 314 |
| | 225 MR | 2 | | |
| | 250 M | 6 | 6314 C3 | NU 314 |
| | 250 MR | 4 | | |
| | 280 S/M | 4; 6 | 6314 C3 | NU 316 |
| | 315 S/M/L | 4; 6 | | |
| 355 L | 4; 6 | 6316 C3 | NU 322 | |

Permissible radial load on main shaft extension with a bearing life L_{10h} of 25,000 hours.

FR: Radial Force

X: distance with respect to the shaft shoulder



ATEX GAS - Zone 2 - Cast iron










SPECIAL FITTING ARRANGEMENT

Permissible radial load on main shaft extension with a bearing life L_{10h} of 25,000 hours.

FR: Radial Force

X: distance with respect to the shaft shoulder

ATEX GAS - Zone 2 - Cast iron



INDICATION OF CABLE GLAND SIZE AND TYPE FOR 400V RATED SUPPLY VOLTAGE IF DRILLINGS REQUIRED WITHOUT DETAILS OF DIAMETERS

| Series | Type | Polarity | Power + auxiliaries | |
|--------|-------------|--------------------------------|-------------------------|--------------------------------|
| | | | Number of holes | Hole diameter |
| FLSN | 80 | 2; 4; 6 | 1 (2 if auxiliaries) | ISO M20 x 1.5 (1M20 + 1M16) |
| | 90 | 2; 4; 6 | | |
| | 100 | 2; 4; 6 | | |
| | 112 | 2; 4; 6 | | |
| | 132 | 2; 4; 6 | 2 (3 if auxiliaries) | ISO M25 x 1.5 (2M25 + 1M16) |
| | 160 | 2; 4; 6 | | |
| | 180 MR | 2; 4; 6 | 3 | 2M40 + 1M16 |
| | 180 M/L/LUR | 2; 4; 6 | | |
| | 200 | 2; 4; 6 | | |
| | 225 SR/MR | 2; 4; 6 | | |
| | 225 M | 2; 4; 6 | 1 (2 if auxiliaries) | 2M50 + 1M16 |
| | 250 | 2; 4; 6 | | |
| | 280 | 2; 4; 6 | | |
| | 315 | 2; 4; 6 | 1 (2 if auxiliaries) | ISO M63 x 1.5 (1M63 + 1M16) |
| 355 | 2; 4; 6 | ISO M75 x 1.5 (1M75 + 1M16) | | |

If the motor is supplied with a cable gland support plate or un-drilled conduits:

- The drilling diameter of the smooth holes for cable glands or conduits must not be greater than the diameter of the thread of the cable gland or conduit + 2 mm and must be de-burred (broken angles about 0.5 mm x 45°) on each side of the thin plate.
- The installation of cable glands or conduit entry glands by the installer must ensure that the degree of safety (preservation of the flameproof character and/or of the IP) required by the application (gas and/or dust) and the motor temperature class is preserved.

**TERMINAL BLOCKS
DIRECTION OF ROTATION**

Standard motors are fitted with a 6-terminal safety block, with the terminal markings complying with or IEC 60034-8.

When the motor is running in U1, V1, W1 or 1U, 1V, 1W from a direct mains supply L1, L2, L3, it turns clockwise when seen from the drive shaft end.

If any two of the phases are changed over, the motor will run in the opposite direction (make sure that the motor has been designed to run in both directions). If the motor is fitted with accessories (thermal protection or space heater), these must be connected on terminal blocks with labelled wires.

Tightening torque for the nuts on the terminal blocks.

| Terminal | M5 | M6 | M8 | M10 | M12 | M14 | M16 |
|------------|-----|----|----|-----|-----|-----|-----|
| Torque N.m | 3.2 | 5 | 10 | 20 | 35 | 50 | 65 |

| Series | Type | 230/400V connection | | 400/690V connection |
|--------|--------------|---------------------|-----------|---------------------|
| | | Polarity | Terminals | Terminals |
| FLSN | 80 to 112 | 2; 4; 6 | M5 | M5 |
| | 132 S to 160 | 2; 4; 6 | M6 | M6 |
| | 180 L | 6 | M6 | M6 |
| | 180 M | 4 | M8 | M6 |
| | 180 LUR | 6 | M6 | M6 |
| | 180 MUR | 2; 4 | M8 | M6 |
| | 200 LU | 2 (30 kW); 4; 6 | M8 | M8 |
| | | 2 (37 kW) | M10 | M8 |
| | 225 M | 4 | M10 | M8 |
| | | 6 | M8 | |
| | 225 to 250 | 2 | M10 | M8 |
| | | 4 | | M10 |
| | 250 M | 6 | M8 | M8 |
| | 280 to 315 | 2; 4; 6 | M12 | M12 |
| 355 L | 2; 4; 6 | M12 | M12 | |

| Mechanical adaptations | Frame size |
|--|---------------|
| DE and NDE bearings with 1 machining, for vibration sensor in position 12H, 12H-3H, or 12H-3H-9H | ≥ 132 |
| Different FF flanges from IEC | All |
| Different FT flanges from IEC | ≤ 132 |
| DE roller bearing | ≥ 160: 4p & + |
| Insulated DE or NDE bearing | ≥ 280 |
| 2 nd standard catalogue NDE shaft end | All |
| 2 nd special NDE shaft end | All |
| Conical shaft | All |
| Shaft with special keying | All |
| Keyed cylindrical NDE shaft (secondary shaft end) as per IEC | All |
| Stainless-steel shaft | All |
| Class B balancing | All |
| F type (full key) or N type (no key) balancing | All |
| Stainless steel fan cover | All |
| Steel fan cover + drip cover | All |
| Steel fan cover + anti-clogging | All |
| Metal fan | All |
| Stainless steel nameplate | All |
| Stainless-steel fastenings | All |
| Three-phase axial forced ventilation - IC 416 A | All |
| Incremental encoder / 1024 or 4096 pts / 5v or 11/30 V | All |
| Positioning holes (jacking screws) | ≥ 250 |
| Radial seal for motor in vertical position with shaft end upwards | All |
| Drain holes for operation in vertical position | All |
| Electrical adaptations | Frame size |
| Terminal board with anti-rotation system as standard | All |
| Special voltages (excluding variable speed) | All |
| Definition for Id/In ≤ 7.5 | All |
| Insulation class H | All |
| Main box in position B or D | All |
| Auxiliary boxes | ≥ 160 |
| Plastic PE | All |
| ATEX brass PE for unshielded cable | All |
| ATEX brass PE for shielded cable | All |
| ATEX brass PE auxiliary for unshielded cable | All |
| ATEX brass PE auxiliary for shielded cable | All |
| Flying lead via 1 metre single-core cable 6 + 1 | All |
| Cable entry on the left as seen from the shaft end | All |
| Preparation for NPT cable glands | All |
| Protection | Frame size |
| Winding PTC thermistor probe (triple probe) | All |
| Winding PT 100 probe (1 per phase) | All |
| Endshield PTC thermistor probe (triple probe) | ≥ 160 |
| Endshield PT 100 probe (per probe) | ≥ 160 |
| Endshield thermocouple | ≥ 160 |
| Space heaters when stopped (220-230 V) | All |
| Reinforced winding insulation system for variable speed drive power supply | All |
| Finish | Frame size |
| VIK version (see page 20) | All |
| IP 65 | All |
| Definition for gas + dust motor, Ex tc IIIB / IIIC T125°C Dc | All |
| IP 56 stopped with fan (IC 411) | All |
| C3H, C4M, C4H, C5-IL or C5-IM paint | All |
| Other paint shades | All |
| Operating temperature: -55°C < T° < -20°C | All |
| Complete tropicalization (stator + rotor) | All |

NON-STANDARD FLANGES

Optionally, Nidec Leroy-Somer motors can be fitted with flanges and faceplates that are larger or smaller than standard. This means that motors can be adapted to all types of situation without the need for costly and

time-consuming modifications.

The tables below give the flange and faceplate dimensions and also indicate flange/motor compatibility.

The bearing and shaft end for each frame size remain standard.


Dimensions in millimetres

(FF) Flange mounted

| Symbol IEC | Flange dimensions | | | | | | |
|------------|-------------------|------|------|-----|---|------|------|
| | M | N | D | T | n | S | LA |
| FF 115 | 115 | 95 | 140 | 3 | 4 | 10 | 10 |
| FF 130 | 130 | 110 | 160 | 3.5 | 4 | 10 | 10 |
| FF 165 | 165 | 130 | 200 | 3.5 | 4 | 12 | 10 |
| FF 215 | 215 | 180 | 250 | 4 | 4 | 15 | 12 |
| FF 265 | 265 | 230 | 300 | 4 | 4 | 15 | 14 |
| FF 300 | 300 | 250 | 350 | 5 | 4 | 18.5 | 14 |
| FF 350 | 350 | 300 | 400 | 5 | 4 | 18.5 | 15 |
| FF 400 | 400 | 350 | 450 | 5 | 8 | 18.5 | 16 |
| FF 500 | 500 | 450 | 550 | 5 | 8 | 18.5 | 18** |
| FF 600 | 600 | 550* | 660 | 6 | 8 | 24 | 22 |
| FF 740 | 740 | 680* | 800 | 6 | 8 | 24 | 25 |
| FF 940 | 940 | 880* | 1000 | 6 | 8 | 28 | 28 |


* Tolerance N js6

** shaft length = 22 for frame size ≥ 280



(FT) Face mounted

| Symbol IEC | Flange dimensions | | | | | | |
|------------|-------------------|-----|-----|-----|---|-----|--|
| | M | N | D | T | n | M.S | |
| FT 85 | 85 | 70 | 105 | 2.5 | 4 | M6 | |
| FT 100 | 100 | 80 | 120 | 3 | 4 | M6 | |
| FT 115 | 115 | 95 | 140 | 3 | 4 | M8 | |
| FT 130 | 130 | 110 | 160 | 3.5 | 4 | M8 | |
| FT 165 | 165 | 130 | 200 | 3.5 | 4 | M10 | |
| FT 215 | 215 | 180 | 250 | 4 | 4 | M12 | |
| FT 265 | 265 | 230 | 300 | 4 | 4 | M12 | |



MODIFIED FLANGES

| Motor type | Mountings | Flange type | (FF) Flange mounted | | | | | | | | | | | | | (FT) Face mounted | | | | | | | | | |
|------------|----------------|-----------------------|---------------------|--------|--------|--------|--------|--------|--------|--------|------------------|------------------|------------------|--------|--------|-------------------|-------|-------|-------|--------|--------|--------|--------|--------|--------|
| | | | FF 85 | FF 100 | FF 115 | FF 130 | FF 165 | FF 215 | FF 265 | FF 300 | FF 350 | FF 400 | FF 500 | FF 600 | FF 740 | FF 940 | FT 65 | FT 75 | FT 85 | FT 100 | FT 115 | FT 130 | FT 165 | FT 215 | FT 265 |
| FLSN | 80 L | all | ■ | ■ | ■ | ■ | ● | ◆ | | | | | | | | | ◆ | ◆ | ◆ | ● | ◆ | ◆ | ◆ | | |
| | 80 LG / 90 | B5/B35 ⁽¹⁾ | ◆ | ◆ | ◆ | ◆ | ● | ■ | ■ | | | | | | | | | | ◆ | ◆ | ■ | ■ | ◆ | | |
| | 80 LG / 90 | B3/B14/B34 | ■ | ■ | ■ | ■ | ■ | ■ | ■ | | | | | | | | | | ◆ | ◆ | ● | ◆ | ◆ | | |
| | 100 L/LR/LG | all | ■ | ■ | ■ | ■ | ■ | ● | ■ | | | | | | | | | | ◆ | ◆ | ◆ | ● | ◆ | | |
| | 112 MU/MG | all | | | | ■ | ■ | ● | ◆ | | | | | | | | | | | | ◆ | ● | ◆ | ◆ | |
| | 132 S/M/MR/MU | all | | | | | ■ | ■ | ● | ◆ | | | | | | | | | | | | ■ | ■ | ● | |
| | 160 M/L/LUR | all | | | | | | ◆ | ◆ | ● | ◆ | | | | | | | | | | | | | | |
| | 180 M/MT/L/LUR | all | | | | | | ● | ● | ◆ | ◆ ⁽¹⁾ | | | | | | | | | | | | | | |
| | 200 LU | all | | | | | | | | ● | ◆ | | | | | | | | | | | | | | |
| | 225 SR/M/MR | all | | | | | | | | | ● | ◆ | | | | | | | | | | | | | |
| | 250 M/MR | all | | | | | | | | | ◆ | ● | | | | | | | | | | | | | |
| | 280 S/M | all | | | | | | | | | ◆ ⁽¹⁾ | ● | | | | | | | | | | | | | |
| | 315 S | all | | | | | | | | | | ◆ ⁽¹⁾ | ● | | | | | | | | | | | | |
| | 315 M/ML | all | | | | | | | | | | | ● | | | | | | | | | | | | |
| | 355 L | all | | | | | | | | | | | ◆ ⁽¹⁾ | ● | | | | | | | | | | | |


● Standard ■ Modified shaft ◆ Adaptable without shaft modifications

(1) Dimension C need not comply with IEC 60072

ATEX GAS - Zone 2 - Cast iron

DRIP COVER FOR OPERATION IN VERTICAL POSITION, SHAFT END DOWNWARDS

| Series | Motor type | LB' | ∅ |
|-----------|-------------|----------|-----|
| FLSN | 80 L/LG | LB + 20 | 145 |
| | 90 S/L/LU | LB + 20 | 185 |
| | 100 L | LB + 20 | 185 |
| | 112 MG | LB + 20 | 185 |
| | 112 MU | LB + 25 | 210 |
| | 132 S | LB + 25 | 210 |
| | 132 MR/MU/M | LB + 30 | 240 |
| | 160 M/L/LU | LB + 60 | 320 |
| | 180 M/MR | LB + 60 | 320 |
| | 180 L/LUR | LB + 60 | 360 |
| | 200 LU | LB + 75 | 400 |
| | 225 SR | LB + 75 | 400 |
| | 225 M/MR | LB + 130 | 420 |
| | 250 M | LB + 130 | 420 |
| | 280 S/M | LB + 130 | 420 |
| 315 S/M/L | LB + 118 | 620 | |
| 355 L | LB + 112 | 710 | |



SPACE HEATERS

| Series | Type | Power (W) |
|--------|------------|-----------|
| FLSN | 80 L/LG | 10 |
| | 90 to 132 | 25 |
| | 160 to 200 | 52 |
| | 225 SR/MR | 52 |
| | 225 M | 100 |
| | 250 M | 100 |
| | 280 to 315 | 100* |
| | 355 | 150* |

The space heaters use 200/240 V single-phase, 50 or 60 Hz.


* Power increase possible subject to quote.

FORCED VENTILATION

The integration of high-efficiency motors within a process often requires accessories to make operation easier: forced ventilation for motors used at high or low speeds.

Notes:

- Without forced ventilation, there is a possibility of overspeed with optional class B balancing.
- The motor temperature is monitored by sensors built into the winding.



| Series | Type | LB dimensions with forced ventilation | |
|--------------|-----------|---------------------------------------|----------------------|
| | | Foot or face mounted motor | Flange mounted motor |
| FLSN | 160 M | 641 | |
| | 160 L | | |
| | 160 LU | | |
| | 180 MR | 641 | |
| | 180 M | | |
| | 180 L | 689 | |
| | 180 LUR | | |
| | 200 LU | | |
| | 225 SR | 825.5 | |
| | 225 MR | | |
| | 225 M | 917 | |
| | 250 M | | |
| | 280 S | 1167 | |
| | 280 M | | |
| | 315 S | 1477 | |
| | 315 M | | |
| | 315 LA/LB | | |
| 355 LA/LB/LC | 1668 | | |

* Forced ventilation only available for types 280, 315 and 355.


LIFTING THE MOTOR ONLY
(not coupled to the machine)

The regulations stipulate that in excess of 25 kg suitable handling equipment must be used.

All our motors are fitted with grab handles, making them easier to handle without risk. A diagram of the sling hoisting method appears below with the required dimensions.


To prevent any damage to the motor during handling (for example: switching the motor from horizontal to vertical), it is essential to follow these instructions.

HORIZONTAL POSITION



| Series | Type | Horizontal position | | | |
|--------|---------------|---------------------|--------|--------|----|
| | | A | min. e | min. h | Øt |
| FLSN | 100 | 152 | 200 | 150 | 22 |
| | 112 | 145 | 200 | 150 | 22 |
| | 132 | 180 | 200 | 150 | 25 |
| | 160 | 200 | 260 | 150 | 14 |
| | 180 M/MR | 200 | 260 | 150 | 14 |
| | 180 L/LUR | 200 | 260 | 150 | 14 |
| | 225 SR/MR | 270 | 260 | 150 | 14 |
| | 225 M | 360 | 265 | 200 | 30 |
| | 250 | 360 | 380 | 200 | 30 |
| | 280 | 360 | 380 | 500 | 30 |
| | 315 S/M/LA/LB | 440 | 400 | 500 | 60 |
| | 355 | 545 | 500 | 500 | 60 |

VERTICAL POSITION



| Series | Type | Vertical position | | | | | | |
|--------|--------------|-------------------|-----|-----|-----|----|---------|--------|
| | | C | E | D | n** | ØS | min. e* | min. h |
| FLSN | 160 | 320 | 200 | 230 | 2 | 14 | 320 | 350 |
| | 180 M/MR | 320 | 200 | 230 | 2 | 14 | 320 | 270 |
| | 180 L/LUR | 390 | 265 | 290 | 2 | 14 | 390 | 320 |
| | 225 SR/MR | 410 | 300 | 295 | 2 | 14 | 410 | 450 |
| | 225 M | 480 | 360 | 405 | 4 | 30 | 540 | 350 |
| | 250 | 480 | 360 | 405 | 4 | 30 | 590 | 550 |
| | 280 S | 480 | 360 | 585 | 4 | 30 | 590 | 550 |
| | 280 M | 480 | 360 | 585 | 4 | 30 | 590 | 550 |
| | 315S/M/LA/LB | 620 | - | 715 | 2 | 35 | 650 | 550 |
| | 355 | 760 | - | 750 | 2 | 35 | 800 | 550 |

* If the motor is fitted with a drip cover, allow an additional 50 to 100 mm to avoid damaging it when the load is swung.

** If n = 2, the lifting rings form an angle of 90° with respect to the terminal box axis.

If n = 4, this angle becomes 45°.


Separate ring ≤ 25 kg
Built-in ring > 25 kg

| | | | | | | | | | | |
|---|---|----|---|---|----|----|----|---|----|----|
| ATEX GAS motors - Zone 2 | LSN series | | | | | | | | | |
|  |  | II | 3 | G | Ex | ec | II | C | T3 | Gc |
| | Premium Efficiency | | | | | | | | | |
| | IE3 aluminium on mains IE3 aluminium on drive | | | | | | | | | |



The complete motor **reference** described below will enable you to **order** the desired equipment.

The selection method consists of following the terms in the designation.



ATEX GAS - Zone 2 - Aluminium

ATEX GAS motors - Zone 2

LSN series - Aluminium

General information - Identification and marking

NAMEPLATES

The nameplate identifies the motors, indicates the main performance and shows compatibility of the motor

concerned with the main standards and regulations concerning them.

All motors in this catalogue with power between 0.75 and 90 kW are fitted with

two information plates: one indicating the motor's performance when supplied from the mains, and the other the motor's performance when supplied from a drive.

DEFINITION OF SYMBOLS USED ON NAMEPLATES

 Legal mark indicating the conformity of equipment with the requirements of European Directives

SPECIAL MARKING (ATEX)



: protection marking against explosive risks

II 3G or II 3GD : ATEX marking

Ex ec : "gas" protection mode

IIC : "gas" equipment group

T3 : "gas" temperature class

Gc : "gas" EPL level

Ex tc : "dust" protection mode (option)

IIIC : "dust" equipment group (option)

T125°C : max. surface temperature (option)

Dc : "dust" EPL level

0080 : INERIS Notified Body

INERIS 01ATEX3004X* : CE type examination certificate No.:

* IECExINE10.0012X: IECEx certificate No.

| Zone | ATEX marking | Marking of type of gas protection | Marking of type of dust protection (option) | Index of protection |
|--------|--|-----------------------------------|---|---------------------|
| 2 |  II 3 G | Ex ec IIC T3 Gc | - | IP55 |
| 2 & 22 |  II 3 G | Ex ec IIC T3 Gc | Ex tc IIIC T125°C Dc | IP65 |

MAINS SUPPLY PLATE

MOT 3 ~ : three-phase AC motor

LSN : series

132 : frame size

MU : housing symbol

T : impregnation index

Motor no.

0123456 : motor serial number

J : month of production

11 : year of production

001 : batch number

IE3 : efficiency class

90.4% : efficiency at 4/4 load

kg : weight

IP55 : protection rating

IK08 : shock resistance

I cl.F : insulation class F

40°C : max. ambient operating temperature

S1 : duty

V : supply voltage

Hz : supply frequency

min⁻¹ : speed of rotation

kW : rated power

cos φ : power factor

A : rated current

Δ : delta connection

Y : star connection

Bearings

DE : drive end
Drive end bearing

NDE : non drive end
Bearing side opposite the drive

g : amount of grease at each regreasing (in g)

h : regreasing interval (hours)

 : vibration level

 : balancing mode

DRIVE SUPPLY PLATE

Inverter settings : required values for setting the frequency inverter

Motor performance : torque available on the motor shaft in % rated torque at the plate frequencies

Min. Fsw (kHz) : minimum switching frequency acceptable for the motor

Nmax (min⁻¹) : maximum mechanical speed acceptable for the motor

ALUMINIUM MOTOR NAMEPLATES - LSN ZONE 2

Mains supply plate

Nidec 3~4P LSN132MU 0080
LEROY-SOMER IP65 IK08 T **IE3**
 Motors Leroy-Somer C150015 14112 Aluminium Zone 2 - France
 Ta40°C Ins. Cl.F S1 1000m 63kg 90.4%

INERIS 01ATED3004X IECEINE10.0012X
 II 3 GD Excc IIC T3 Gc Ex tc IIIC T125°C Dc

DE: 6308 ZZ C3
 NDE: 6307 ZZ C3

| V | Hz | min-1 | kW | cosφ | A |
|-------|----|-------|------|------|------|
| Δ 230 | 50 | 1458 | 7.50 | 0.87 | 23.9 |
| Δ 400 | 50 | 1458 | 7.50 | 0.87 | 13.8 |
| Δ 415 | 50 | 1462 | 7.50 | 0.85 | 13.5 |
| Δ 400 | 60 | 1766 | 7.50 | 0.85 | 12.0 |

IEC80034-1
 PTC 130°C

Drive supply plate

Nidec 3~4P LSN132MU 0080
LEROY-SOMER IP65 IK08 T **IE3**
 Motors Leroy-Somer C150015 14112 Aluminium Zone 2 - France
 Ta40°C Ins. Cl.F S9 1000m 63kg

INERIS 01ATED3004X IECEINE10.0012X
 II 3 GD Excc IIC T3 Gc Ex tc IIIC T125°C Dc

DE: 6308 ZZ C3
 NDE: 6307 ZZ C3

| Inverter settings | | | | | |
|-------------------|----|-------|------|------|------|
| V | Hz | min-1 | kW | cosφ | A |
| Δ 400 | 50 | 1450 | 7.50 | 0.88 | 15.0 |

| Motor performance | | | | | min. F _{ew} (Hz) |
|-------------------|------|-----|-----|-----|---------------------------|
| Hz | 10 | 17 | 25 | 50 | 87 |
| T/Tn% | 100 | 100 | 100 | 100 | 57 |
| Tn (min) | 49.1 | | | | |

IEC80034-1
 PTC 130°C

ATEX GAS - Zone 2 - Aluminium

The motor enclosure is designed in such a way that no sparks can be produced under any motor operating conditions within the manufacturer's allowable limits, and no temperature rise can occur during normal operation.

The Ex ec motors in aluminium casings from Nidec Leroy-Somer are certified to comply with Directive 2014/34/EU.

Nidec Leroy-Somer can also provide self-certification with a Declaration of Conformity.

Lastly, Ex ec motors can also be used for applications in Ex t zone 22 dusty atmospheres.

The following definitions are therefore possible:

- Ex tc IIIB T125°C Dc, IP 55 for zone 22 + Ex ec IIC T3
- Ex tc IIIC T125°C Dc, IP 65 for zone 22 + Ex ec IIC T3

| Designations | Materials | Comments |
|-------------------------------------|---|--|
| Finned housing | Aluminium alloy | <ul style="list-style-type: none"> - with integral or screwed feet, or without feet - 4 or 6 securing holes for housings with feet - lifting rings for frame size \geq 100 - ground terminal with an optional jumper screw |
| Stator | Insulated low-carbon magnetic steel laminations Electroplated copper | <ul style="list-style-type: none"> - low carbon content guarantees long-term lamination pack stability - semi-enclosed slots - class F insulation |
| Rotor | Insulated low-carbon magnetic steel laminations Aluminium | <ul style="list-style-type: none"> - inclined cage bars - rotor cage pressure die-cast in aluminum (or alloys for special applications) - assembly by hot shrinking on the shaft - rotor balanced dynamically, 1/2 key |
| Shaft | Steel | <ul style="list-style-type: none"> - for frame size \leq 160 MP - LR: <ul style="list-style-type: none"> • tapped centre hole • closed keyway - for frame size \geq 160 M - L: <ul style="list-style-type: none"> • tapped centre hole • open keyway |
| End shields | Aluminium alloy | - 80 - 90 rear bearing |
| | Cast iron | - 80 - 90 front bearing (except 6-pole and optional for 80 and 90 rear bearings) - 100 to 280 front and rear bearings |
| Bearings and lubrication | | <ul style="list-style-type: none"> - protected ball bearings, permanently greased for frame size 56 to 225 - protected ball bearings, regreasable for frame size 250 to 280 - bearings preloaded at rear |
| Labyrinth seal Lip seals | Technopolymer or steel Synthetic rubber | <ul style="list-style-type: none"> - gasket or deflector at the front for all face mounted motors - gasket, deflector or labyrinth seal for foot mounted motor |
| Fan | Composite material or aluminium alloy | - bi-directional: straight blades |
| Fan cover | Composite material or steel plate | - fitted, on request, with a drip cover for operation in vertical position, shaft end downwards (steel plate fan cover) |
| Terminal box | Composite material or aluminium alloy | <ul style="list-style-type: none"> - IP 55 - can be rotated 90° - fitted with a terminal block with 6 steel terminals as standard (brass as an option) - terminal box fitted with threaded plugs (supplied without cable glands) (cable glands as an option) - 1 ground terminal in each terminal box - fastening system consisting of a cover with captive screws |



| Type | Rated power P _n kW | Rated torque M _n N.m | Starting torque/ Rated torque M _d /M _n | Maximum torque/ Rated torque M _m /M _n | Starting current/ Rated current I _d /I _n | Moment of inertia J kg.m ² | Weight IM B3 kg | Noise LP db(A) | 400V 50Hz | | | | | | | |
|----------------|-------------------------------------|---------------------------------------|--|---|--|---|-----------------------|----------------------|--|--------------------------------------|-------------------------------------|------|------|--------------|--------------|------|
| | | | | | | | | | Rated speed N _n min ⁻¹ | Rated current I _n A | Efficiency IEC 60034-2-1 2007 | | | Power factor | | |
| | | | | | | | | | | | 4/4 | 3/4 | 2/4 | 4/4 | Cos φ 3/4 | 2/4 |
| 2 poles | | | | | | | | | | | | | | | | |
| LSN 80 L | 0.75 | 2.5 | 3.4 | 3.4 | 7.7 | 0.00095 | 9.9 | 58 | 2890 | 1.6 | 82.4 | 82.4 | 80.2 | 0.83 | 0.76 | 0.64 |
| LSN 80 LG | 1.1 | 3.65 | 2.6 | 2.6 | 7 | 0.00223 | 14.1 | 64 | 2885 | 2.2 | 85.6 | 86.9 | 86.7 | 0.85 | 0.80 | 0.69 |
| LSN 90 SL | 1.5 | 4.95 | 2.9 | 2.9 | 7.4 | 0.00223 | 15.6 | 64 | 2890 | 3 | 85.3 | 86.3 | 85.5 | 0.84 | 0.78 | 0.67 |
| LSN 90 LU | 2.2 | 7.25 | 3.1 | 3.1 | 8 | 0.00292 | 20.4 | 67 | 2895 | 4.25 | 86.9 | 88.1 | 87.8 | 0.86 | 0.80 | 0.69 |
| LSN 100 LG | 3 | 9.8 | 3 | 3 | 8.4 | 0.00941 | 32.4 | 67 | 2935 | 5.6 | 88.5 | 88.8 | 87.6 | 0.88 | 0.83 | 0.73 |
| LSN 112 MG | 4 | 13.1 | 2 | 2 | 7.1 | 0.00941 | 32.7 | 71 | 2920 | 7.2 | 89.0 | 90.1 | 90.1 | 0.90 | 0.86 | 0.78 |
| LSN 132 S | 5.5 | 18 | 2.3 | 2.3 | 7.5 | 0.01116 | 39.2 | 63 | 2925 | 10.1 | 89.4 | 90.5 | 90.5 | 0.88 | 0.84 | 0.75 |
| LSN 132 SM | 7.5 | 24.4 | 2.1 | 2.1 | 6.8 | 0.01102 | 55.7 | 67 | 2935 | 13.8 | 91.2 | 92.1 | 92.1 | 0.86 | 0.83 | 0.74 |
| LSN 132 M | 9 | 29.2 | 2.1 | 2.1 | 7.6 | 0.01203 | 59.3 | 67 | 2945 | 16.7 | 91.7 | 92.4 | 92.2 | 0.85 | 0.81 | 0.72 |
| LSN 160 MP | 11 | 35.7 | 1.9 | 1.9 | 6.9 | 0.01390 | 62.6 | 72 | 2940 | 19.9 | 91.5 | 92.3 | 92.1 | 0.87 | 0.83 | 0.74 |
| LSN 160 M | 15 | 48.6 | 2.3 | 2.3 | 7.9 | 0.0490 | 95 | 69 | 2945 | 26.5 | 91.9 | 92.6 | 92.6 | 0.89 | 0.87 | 0.81 |
| LSN 160 L | 18.5 | 59.9 | 2.8 | 2.8 | 7.6 | 0.0551 | 100 | 68 | 2950 | 32.8 | 92.6 | 93.3 | 93.2 | 0.88 | 0.84 | 0.76 |
| LSN 180 MR | 22 | 71.1 | 3.1 | 3.1 | 8.7 | 0.0628 | 105 | 69 | 2954 | 38.7 | 93.2 | 93.9 | 94.0 | 0.88 | 0.85 | 0.77 |
| LSN 200 LR | 30 | 97.3 | 2.6 | 2.6 | 7.6 | 0.1106 | 170 | 73 | 2945 | 51.5 | 93.5 | 94.2 | 94.4 | 0.90 | 0.88 | 0.83 |
| LSN 200 L | 37 | 120 | 2 | 2 | 7.1 | 0.2492 | 201 | 73 | 2945 | 63.9 | 93.9 | 94.5 | 94.4 | 0.89 | 0.87 | 0.81 |
| LSN 225 MR | 45 | 145 | 3.7 | 2.7 | 7.9 | 0.1597 | 227 | 76 | 2962 | 79.7 | 94.8 | 95.1 | 94.7 | 0.86 | 0.82 | 0.73 |
| LSN 250 ME | 55 | 176 | 2.3 | 2.4 | 8.3 | 0.3340 | 320 | 78 | 2974 | 95 | 94.5 | 94.6 | 90.3 | 0.88 | 0.86 | 0.79 |
| LSN 280 SC** | 75 | 241 | 2.3 | 2.3 | 8 | 0.4092 | 350 | 79 | 2970 | 126 | 95.2 | 95.5 | 95.1 | 0.90 | 0.88 | 0.82 |
| LSN 280 MC** | 90 | 289 | 2.5 | 2.5 | 8.5 | 0.4760 | 382 | 80 | 2972 | 151 | 95.5 | 95.8 | 95.5 | 0.90 | 0.87 | 0.82 |

** motors proposed in self-certification only

| | | | | | | | | | | | | | | | | |
|----------------|------|------|-----|-----|-----|---------|------|----|------|------|------|------|------|------|------|------|
| 4 poles | | | | | | | | | | | | | | | | |
| LSN 80 LG | 0.75 | 4.95 | 2.2 | 2.9 | 6.4 | 0.00335 | 13.6 | 48 | 1450 | 1.6 | 83.6 | 84.3 | 83.0 | 0.81 | 0.73 | 0.59 |
| LSN 90 SL | 1.1 | 7.25 | 2.4 | 3.2 | 6.9 | 0.00418 | 16.2 | 45 | 1450 | 2.3 | 84.8 | 85.7 | 85.0 | 0.81 | 0.74 | 0.61 |
| LSN 90 LU | 1.5 | 9.85 | 2.9 | 3.7 | 7.6 | 0.00524 | 20.4 | 51 | 1452 | 3.2 | 85.6 | 86.2 | 85.1 | 0.79 | 0.70 | 0.57 |
| LSN 100 L | 1.8 | 11.8 | 2.4 | 2.8 | 6.4 | 0.00561 | 23 | 48 | 1456 | 3.8 | 86.6 | 87.3 | 86.1 | 0.79 | 0.71 | 0.57 |
| LSN 100 LR | 2.2 | 14.4 | 3.2 | 3.7 | 8 | 0.00676 | 25.8 | 47 | 1454 | 4.65 | 87.1 | 87.7 | 86.7 | 0.78 | 0.70 | 0.57 |
| LSN 100 LG | 3 | 19.6 | 2.4 | 3.2 | 7.2 | 0.01152 | 31 | 55 | 1464 | 6 | 89.2 | 89.9 | 89.9 | 0.81 | 0.74 | 0.61 |
| LSN 112 MU | 4 | 26.2 | 2.7 | 3.1 | 7.2 | 0.01312 | 34.4 | 54 | 1456 | 7.9 | 88.9 | 89.8 | 89.6 | 0.82 | 0.77 | 0.65 |
| LSN 132 SM | 5.5 | 35.9 | 2.8 | 3.6 | 8.4 | 0.02286 | 52 | 59 | 1462 | 10.5 | 90.3 | 91.0 | 90.6 | 0.84 | 0.77 | 0.65 |
| LSN 132 MU | 7.5 | 49.1 | 2.9 | 3.3 | 8.1 | 0.02965 | 62.6 | 61 | 1458 | 13.8 | 90.4 | 91.5 | 91.9 | 0.87 | 0.82 | 0.73 |
| LSN 160 MR | 9 | 58.7 | 3.1 | 3.6 | 8.7 | 0.03574 | 77.8 | 62 | 1464 | 17 | 91.0 | 91.8 | 91.7 | 0.84 | 0.78 | 0.67 |
| LSN 160 M | 11 | 71.7 | 2.2 | 3.1 | 7.3 | 0.0712 | 93 | 59 | 1466 | 20.2 | 91.4 | 92.4 | 92.6 | 0.86 | 0.82 | 0.73 |
| LSN 160 LUR | 15 | 97.6 | 2.5 | 3.4 | 8.5 | 0.0954 | 100 | 58 | 1468 | 27.3 | 92.1 | 92.9 | 93.0 | 0.86 | 0.82 | 0.72 |
| LSN 180 M | 18.5 | 120 | 2.9 | 2.8 | 7.7 | 0.1333 | 130 | 68 | 1468 | 33.9 | 92.8 | 93.6 | 93.5 | 0.85 | 0.81 | 0.72 |
| LSN 180 LUR | 22 | 143 | 3.2 | 3.1 | 8.2 | 0.1555 | 155 | 68 | 1470 | 41.1 | 93.0 | 93.4 | 93.3 | 0.83 | 0.79 | 0.69 |
| LSN 200 LU | 30 | 194 | 3 | 2.8 | 7.3 | 0.2704 | 225 | 63 | 1476 | 55 | 93.7 | 94.3 | 94.1 | 0.84 | 0.79 | 0.70 |
| LSN 225 SR | 37 | 239 | 3.2 | 3.1 | 7.9 | 0.2897 | 236 | 63 | 1480 | 70.2 | 93.9 | 94.2 | 93.8 | 0.81 | 0.76 | 0.65 |
| LSN 225 MG | 45 | 289 | 2.3 | 2.9 | 7.2 | 0.6573 | 318 | 70 | 1486 | 83.6 | 94.8 | 95.0 | 94.5 | 0.82 | 0.77 | 0.66 |
| LSN 250 ME | 55 | 354 | 2.3 | 2.7 | 7.3 | 0.7793 | 350 | 69 | 1484 | 101 | 94.7 | 95.1 | 95.0 | 0.83 | 0.79 | 0.70 |
| LSN 280 SD** | 75 | 482 | 2.4 | 3.2 | 8.1 | 0.9595 | 428 | 69 | 1486 | 139 | 95.0 | 95.2 | 94.9 | 0.82 | 0.78 | 0.69 |
| LSN 280 MD** | 90 | 579 | 2.6 | 3.4 | 8.3 | 1.0799 | 470 | 68 | 1484 | 168 | 95.5 | 95.7 | 95.4 | 0.81 | 0.76 | 0.65 |

** motors proposed in self-certification only

| | | | | | | | | | | | | | | | | |
|----------------|------|------|-----|-----|-----|---------|------|----|-----|------|------|------|------|------|------|------|
| 6 poles | | | | | | | | | | | | | | | | |
| LSN 90 SL | 0.75 | 7.5 | 1.9 | 2.3 | 4.3 | 0.00378 | 16 | 56 | 952 | 1.95 | 79.2 | 80.0 | 79.1 | 0.71 | 0.62 | 0.48 |
| LSN 90 LU | 1.1 | 11 | 2.3 | 2.7 | 4.8 | 0.00519 | 21.5 | 56 | 956 | 2.75 | 81.9 | 82.3 | 80.3 | 0.70 | 0.61 | 0.47 |
| LSN 100 LG | 1.5 | 14.8 | 2.3 | 2.8 | 5.6 | 0.01523 | 30 | 43 | 966 | 3.6 | 83.8 | 84.4 | 82.9 | 0.72 | 0.63 | 0.50 |
| LSN 112 MU | 2.2 | 21.7 | 2.3 | 2.7 | 5.4 | 0.01899 | 37 | 46 | 966 | 5.4 | 84.3 | 84.8 | 83.5 | 0.70 | 0.61 | 0.49 |
| LSN 132 SM | 3 | 29.5 | 2.7 | 3.1 | 6.6 | 0.02528 | 48 | 50 | 972 | 6.8 | 87.5 | 88.0 | 86.9 | 0.73 | 0.65 | 0.53 |
| LSN 132 M | 4 | 39.3 | 2.6 | 2.9 | 6.4 | 0.03027 | 54 | 56 | 972 | 9.05 | 87.4 | 88.1 | 87.1 | 0.73 | 0.65 | 0.53 |
| LSN 132 MU | 5.5 | 54.4 | 2.6 | 2.8 | 6.4 | 0.03699 | 63.1 | 57 | 966 | 11.7 | 88.1 | 89.2 | 89.1 | 0.77 | 0.70 | 0.58 |
| LSN 160 MU | 7.5 | 73.2 | 2 | 3 | 6.9 | 0.1295 | 82 | 58 | 978 | 16.1 | 89.6 | 89.7 | 88.4 | 0.75 | 0.67 | 0.54 |
| LSN 180 L | 11 | 107 | 3 | 3.4 | 8.6 | 0.2048 | 130 | 62 | 982 | 22.6 | 91.1 | 91.3 | 90.3 | 0.77 | 0.70 | 0.57 |
| LSN 180 LUR | 15 | 146 | 3 | 3.1 | 8.4 | 0.2530 | 150 | 63 | 980 | 30.7 | 91.5 | 91.9 | 91.3 | 0.77 | 0.70 | 0.58 |
| LSN 200 L | 18.5 | 180 | 2.2 | 2.8 | 7.1 | 0.3300 | 200 | 61 | 980 | 36.2 | 92.1 | 92.8 | 92.6 | 0.80 | 0.75 | 0.66 |
| LSN 200 LU | 22 | 214 | 2.8 | 3.5 | 7.3 | 0.3901 | 236 | 62 | 980 | 44.6 | 92.5 | 93.0 | 92.5 | 0.77 | 0.71 | 0.61 |
| LSN 225 MG | 30 | 291 | 2.2 | 2.4 | 6.6 | 0.7222 | 284 | 64 | 986 | 55.3 | 93.3 | 93.7 | 93.3 | 0.84 | 0.80 | 0.70 |
| LSN 250 ME | 37 | 358 | 2.3 | 2.8 | 7.1 | 0.9234 | 310 | 64 | 986 | 66.9 | 93.9 | 94.4 | 94.3 | 0.85 | 0.81 | 0.72 |
| LSN 280 SC** | 45 | 437 | 2.2 | 2.4 | 6.6 | 1.1279 | 377 | 64 | 984 | 80.4 | 93.9 | 94.5 | 94.5 | 0.86 | 0.83 | 0.74 |
| LSN 280 MD** | 55 | 533 | 2.8 | 3 | 7.7 | 1.3995 | 444 | 59 | 986 | 98.6 | 94.7 | 95.2 | 95.0 | 0.85 | 0.81 | 0.72 |

** motors proposed in self-certification only

* available March 2021

ATEX GAS - Zone 2 - Aluminium



| Type | Rated power | 415V 50Hz | | | | 460V 60Hz | | | |
|----------------|----------------------|-------------------------------------|---------------------|------------|--------------|-------------------------------------|---------------------|------------|--------------|
| | | Rated speed | Rated current | Efficiency | Power factor | Rated speed | Rated current | Efficiency | Power factor |
| | P _n kW | N _n min ⁻¹ | I _n A | η 4/4 | Cos φ 4/4 | N _n min ⁻¹ | I _n A | η 4/4 | Cos φ 4/4 |
| 2 poles | | | | | | | | | |
| LSN 80 L | 0.75 | 2900 | 1.55 | 82.3 | 0.81 | 3505 | 1.4 | 83.3 | 0.80 |
| LSN 80 LG | 1.1 | 2895 | 2.1 | 86.2 | 0.84 | 3505 | 1.9 | 87.0 | 0.83 |
| LSN 90 SL | 1.5 | 2900 | 2.9 | 86.1 | 0.83 | 3510 | 2.65 | 86.9 | 0.82 |
| LSN 90 LU | 2.2 | 2905 | 4.1 | 87.3 | 0.85 | 3505 | 3.7 | 88.2 | 0.85 |
| LSN 100 L | 3 | 2940 | 5.5 | 88.7 | 0.86 | 3545 | 4.9 | 88.7 | 0.87 |
| LSN 112 MG | 4 | 2930 | 6.95 | 89.7 | 0.89 | 3535 | 6.25 | 90.0 | 0.89 |
| LSN 132 S | 5.5 | 2930 | 9.8 | 89.8 | 0.87 | 3540 | 8.75 | 90.7 | 0.87 |
| LSN 132 SM | 7.5 | 2945 | 13.4 | 91.5 | 0.85 | 3550 | 12 | 92.1 | 0.85 |
| LSN 132 M | 9 | 2950 | 16.4 | 91.9 | 0.83 | 3558 | 14.4 | 92.4 | 0.85 |
| LSN 160 MP | 11 | 2945 | 19.6 | 91.8 | 0.85 | 3550 | 17.4 | 92.2 | 0.86 |
| LSN 160 M | 15 | 2950 | 25.4 | 92.2 | 0.89 | 3550 | 22.9 | 92.4 | 0.89 |
| LSN 160 L | 18.5 | 2954 | 32.2 | 92.9 | 0.86 | 3558 | 28.6 | 93.4 | 0.87 |
| LSN 180 MR | 22 | 2958 | 38.1 | 93.5 | 0.86 | 3564 | 33.8 | 94.0 | 0.87 |
| LSN 200 LR | 30 | 2954 | 50 | 93.8 | 0.89 | 3556 | 44.5 | 94.0 | 0.90 |
| LSN 200 L | 37 | 2950 | 62 | 94.2 | 0.88 | 3552 | 56.2 | 93.9 | 0.88 |
| LSN 225 MR | 45 | 2962 | 79.5 | 94.9 | 0.83 | 3566 | 69.8 | 95.2 | 0.85 |
| LSN 250 ME | 55 | 2978 | 92.2 | 94.7 | 0.87 | 3575 | 83 | 94.3 | 0.88 |
| LSN 280 SC** | 75 | 2974 | 123 | 95.5 | 0.89 | 3574 | 110 | 95.3 | 0.90 |
| LSN 280 MC** | 90 | 2972 | 147 | 95.5 | 0.89 | 3574 | 133 | 95.5 | 0.89 |

** motors proposed in self-certification only

| 4 poles | | | | | | | | | |
|----------------|------|------|------|------|------|------|------|------|------|
| LSN 80 LG | 0.75 | 1452 | 1.6 | 83.7 | 0.78 | 1758 | 1.45 | 85.1 | 0.77 |
| LSN 90 SL | 1.1 | 1454 | 2.25 | 85.4 | 0.79 | 1760 | 2.05 | 86.6 | 0.78 |
| LSN 90 LU | 1.5 | 1456 | 3.2 | 85.7 | 0.76 | 1760 | 2.85 | 87.2 | 0.76 |
| LSN 100 L | 1.8 | 1458 | 3.75 | 86.8 | 0.79 | 1762 | 3.35 | 88.2 | 0.76 |
| LSN 100 LR | 2.2 | 1456 | 4.6 | 87.3 | 0.76 | 1760 | 4.15 | 88.4 | 0.76 |
| LSN 100 LG | 3 | 1466 | 6 | 89.2 | 0.78 | 1770 | 5.25 | 90.5 | 0.79 |
| LSN 112 MU | 4 | 1460 | 7.8 | 89.0 | 0.80 | 1764 | 7.05 | 90.3 | 0.79 |
| LSN 132 SM | 5.5 | 1466 | 10.3 | 90.6 | 0.82 | 1770 | 9.2 | 91.7 | 0.82 |
| LSN 132 MU | 7.5 | 1462 | 13.5 | 90.9 | 0.85 | 1766 | 12.1 | 91.8 | 0.85 |
| LSN 160 MR | 9 | 1466 | 16.7 | 91.3 | 0.84 | 1768 | 14.9 | 92.2 | 0.82 |
| LSN 160 M | 11 | 1470 | 19.6 | 91.7 | 0.85 | 1774 | 17.6 | 92.5 | 0.85 |
| LSN 160 LUR | 15 | 1472 | 26.6 | 92.4 | 0.85 | 1774 | 24 | 93.2 | 0.84 |
| LSN 180 M | 18.5 | 1474 | 32.9 | 93.0 | 0.84 | 1774 | 29.5 | 93.6 | 0.84 |
| LSN 180 LUR | 22 | 1474 | 40.5 | 93.2 | 0.81 | 1770 | 36.3 | 93.8 | 0.81 |
| LSN 200 LU | 30 | 1478 | 54.1 | 94.1 | 0.82 | 1778 | 48 | 94.5 | 0.83 |
| LSN 225 SR | 37 | 1482 | 69.4 | 93.9 | 0.79 | 1782 | 61.4 | 94.5 | 0.80 |
| LSN 225 MG | 45 | 1488 | 82.5 | 94.9 | 0.80 | 1788 | 73.4 | 95.0 | 0.81 |
| LSN 250 ME | 55 | 1486 | 98.4 | 94.9 | 0.82 | 1786 | 88.1 | 95.4 | 0.82 |
| LSN 280 SD** | 75 | 1486 | 135 | 95.1 | 0.81 | 1788 | 120 | 95.5 | 0.82 |
| LSN 280 MD** | 90 | 1488 | 165 | 95.5 | 0.79 | 1788 | 147 | 95.8 | 0.80 |

** motors proposed in self-certification only

| 6 poles | | | | | | | | | |
|----------------|------|-----|------|------|------|---|---|---|---|
| LSN 90 SL | 0.75 | 956 | 1.95 | 79.7 | 0.68 | - | - | - | - |
| LSN 90 LU | 1.1 | 960 | 2.8 | 81.9 | 0.67 | - | - | - | - |
| LSN 100 LG | 1.5 | 970 | 3.65 | 83.7 | 0.68 | - | - | - | - |
| LSN 112 MU | 2.2 | 970 | 5.4 | 84.3 | 0.67 | - | - | - | - |
| LSN 132 SM | 3 | 974 | 6.75 | 87.7 | 0.71 | - | - | - | - |
| LSN 132 M | 4 | 974 | 9.05 | 87.7 | 0.70 | - | - | - | - |
| LSN 132 MU | 5.5 | 968 | 11.5 | 88.6 | 0.75 | - | - | - | - |
| LSN 160 MU | 7.5 | 980 | 15.9 | 97.7 | 0.73 | - | - | - | - |
| LSN 180 L | 11 | 984 | 22.4 | 91.4 | 0.75 | - | - | - | - |
| LSN 180 LUR | 15 | 982 | 30.8 | 91.6 | 0.74 | - | - | - | - |
| LSN 200 L | 18.5 | 982 | 35.3 | 92.3 | 0.79 | - | - | - | - |
| LSN 200 LU | 22 | 984 | 42.2 | 92.7 | 0.74 | - | - | - | - |
| LSN 225 MG | 30 | 986 | 53.9 | 93.3 | 0.83 | - | - | - | - |
| LSN 250 ME | 37 | 988 | 65.9 | 94.1 | 0.83 | - | - | - | - |
| LSN 280 SC** | 45 | 986 | 78.4 | 94.0 | 0.85 | - | - | - | - |
| LSN 280 MD** | 55 | 988 | 96.1 | 94.8 | 0.84 | - | - | - | - |

** motors proposed in self-certification only



| Type | 400V 50Hz | | | | % Rated torque M_n at | | | | | 400V 87Hz Δ^1 | | | | Maximum mechanical speed ² |
|----------------|-------------|----------------------------|---------------|-------------------|-------------------------|-------|------|------|-------|----------------------|----------------------------|---------------|-------------------|---------------------------------------|
| | Rated power | Rated speed | Rated current | Power factor | 10Hz | 17Hz | 25Hz | 50Hz | 87Hz | Rated power | Rated speed | Rated current | Power factor | |
| | P_n kW | N_n min ⁻¹ | I_n A | Cos ϕ 4/4 | | | | | | P_n kW | N_n min ⁻¹ | I_n A | Cos ϕ 4/4 | |
| 2 poles | | | | | | | | | | | | | | |
| LSN 80 L | 0.75 | 2875 | 1.7 | 0.85 | 2.3 | 2.5 | 2.5 | 2.5 | 1.4 | 1.31 | 5006 | 2.9 | 0.85 | 13500 |
| LSN 80 LG | 1.1 | 2865 | 2.4 | 0.87 | 3.4 | 3.7 | 3.7 | 3.7 | 2.1 | 1.91 | 4997 | 4.1 | 0.87 | 11700 |
| LSN 90 SL | 1.5 | 2880 | 3.3 | 0.86 | 4.6 | 5 | 5 | 5 | 2.8 | 2.61 | 5006 | 5.5 | 0.86 | 11700 |
| LSN 90 LU | 2.2 | 2875 | 4.6 | 0.88 | 6.7 | 7.3 | 7.3 | 7.3 | 4.1 | 3.83 | 5014 | 7.9 | 0.88 | 11700 |
| LSN 100 LG | 3 | 2870 | 6.2 | 0.88 | 9.3 | 10 | 10 | 10 | 5.7 | 5.22 | 4997 | 10.7 | 0.86 | 9900 |
| LSN 112 MG | 4 | 2905 | 7.9 | 0.91 | 12.2 | 13.1 | 13.1 | 13.1 | 7.5 | 6.96 | 5058 | 13.8 | 0.89 | 9900 |
| LSN 132 S | 5.5 | 2910 | 11 | 0.90 | 16.7 | 18 | 18 | 18 | 10.3 | 9.57 | 5066 | 19 | 0.87 | 6700 |
| LSN 132 SM | 7.5 | 2925 | 15 | 0.88 | 22.7 | 24.4 | 24.4 | 24.4 | 13.9 | 13.05 | 5084 | 25.6 | 0.86 | 6700 |
| LSN 132 M | 9 | 2935 | 17.8 | 0.87 | 27.2 | 29.2 | 29.2 | 29.2 | 16.6 | 15.66 | 5101 | 30.5 | 0.86 | 6700 |
| LSN 160 MP | 11 | 2930 | 21.8 | 0.88 | 33.2 | 35.7 | 35.7 | 35.7 | 20.4 | 19.14 | 5092 | 37.1 | 0.86 | 6700 |
| LSN 160 M | 15 | 2935 | 28.8 | 0.90 | 40.7 | 48.6 | 48.6 | 48.6 | 27.7 | 26.1 | 5101 | 49.9 | 0.88 | 6000 |
| LSN 160 L | 18.5 | 2945 | 35 | 0.89 | 53 | 60 | 60 | 60 | 34.2 | 62.19 | 5110 | 61 | 0.88 | 6000 |
| LSN 180 MR | 22 | 2940 | 41.5 | 0.90 | 56.3 | 67.6 | 71.2 | 71.2 | 40.6 | 38.28 | 5110 | 72.5 | 0.88 | 5670 |
| LSN 200 LR | 30 | 2935 | 56.2 | 0.90 | 76.9 | 92.4 | 97.3 | 97.3 | 80.8 | - | - | - | - | 4500 |
| LSN 200 L | 37 | 2930 | 69.9 | 0.89 | 89.3 | 108 | 120 | 120 | 99.6 | - | - | - | - | 4500 |
| LSN 225 MR | 45 | 2952 | 86 | 0.87 | 107.9 | 130.5 | 145 | 145 | 120.4 | - | - | - | - | 4320 |
| LSN 250 ME | 55 | 2940 | 103 | 0.89 | 132.4 | 160.2 | 178 | 178 | 147.7 | - | - | - | - | 4320 |
| LSN 280 SC** | 75 | 2964 | 136 | 0.90 | 179.3 | 216.9 | 241 | 241 | 200 | - | - | - | - | 4050 |
| LSN 280 MC** | 90 | 2968 | 163 | 0.9 | 241.9 | 289 | 289 | 289 | 239.9 | - | - | - | - | 4050 |

** motors proposed in self-certification only

| 4 poles | | | | | | | | | | | | | | |
|----------------|------|------|------|------|-------|------|------|------|-------|-------|------|-------|------|-------|
| LSN 80 LG | 0.75 | 1440 | 1.7 | 0.83 | 4.6 | 5 | 5 | 5 | 2.8 | 1.31 | 2511 | 3 | 0.83 | 11700 |
| LSN 90 SL | 1.1 | 1445 | 2.5 | 0.84 | 6.7 | 7.3 | 7.3 | 7.3 | 4.1 | 1.91 | 2511 | 4.2 | 0.84 | 11700 |
| LSN 90 LU | 1.5 | 1445 | 3.5 | 0.82 | 9.2 | 9.9 | 9.9 | 9.9 | 5.6 | 2.61 | 2515 | 5.8 | 0.79 | 11700 |
| LSN 100 LR | 2.2 | 1445 | 4.9 | 0.81 | 13.4 | 14.4 | 14.4 | 14.4 | 8.2 | 3.83 | 2518 | 8.3 | 0.79 | 9900 |
| LSN 100 LG | 3 | 1456 | 6.4 | 0.83 | 16.4 | 19.6 | 19.6 | 19.6 | 11.2 | 5.22 | 2529 | 11.1 | 0.81 | 9900 |
| LSN 112 MU | 4 | 1452 | 8.5 | 0.85 | 21.9 | 26.2 | 26.2 | 26.2 | 14.9 | 6.96 | 2525 | 14.6 | 0.80 | 9900 |
| LSN 132 SM | 5.5 | 1456 | 11.3 | 0.86 | 33.4 | 35.9 | 35.9 | 35.9 | 20.5 | 9.57 | 2532 | 19.1 | 0.85 | 6700 |
| LSN 132 MU | 7.5 | 1450 | 15 | 0.88 | 45.7 | 49.1 | 49.1 | 49.1 | 28.0 | 13.05 | 2525 | 25.9 | 0.86 | 6700 |
| LSN 160 MR | 9 | 1458 | 18.2 | 0.86 | 54.6 | 58.7 | 58.7 | 58.7 | 33.5 | 15.66 | 2536 | 31 | 0.85 | 6000 |
| LSN 160 M | 11 | 1462 | 21.7 | 0.88 | 60.0 | 71.7 | 71.7 | 71.7 | 40.9 | 19.14 | 2539 | 37.6 | 0.85 | 6000 |
| LSN 160 LUR | 15 | 1464 | 29.6 | 0.87 | 81.7 | 97.6 | 97.6 | 97.6 | 55.6 | 26.1 | 2543 | 50.8 | 0.85 | 5670 |
| LSN 180 M | 18.5 | 1466 | 36.4 | 0.87 | 94.9 | 120 | 120 | 120 | 68.4 | 32.19 | 2543 | 63.2 | 0.85 | 5670 |
| LSN 180 LUR | 22 | 1466 | 44.1 | 0.85 | 113.0 | 143 | 143 | 143 | 81.5 | 38.28 | 2546 | 75.9 | 0.83 | 4500 |
| LSN 200 LU | 30 | 1472 | 59.1 | 0.85 | 144.3 | 194 | 194 | 194 | 110.6 | 52.2 | 2557 | 102.9 | 0.84 | 4500 |
| LSN 225 SR | 37 | 1476 | 74.5 | 0.83 | 177.8 | 239 | 239 | 239 | 136.2 | 64.38 | 2584 | 127 | 0.81 | 4320 |
| LSN 225 MG | 45 | 1480 | 89 | 0.84 | 229.3 | 290 | 290 | 290 | 165.3 | 78.3 | 2570 | 152.9 | 0.83 | 4050 |
| LSN 250 ME | 55 | 1482 | 107 | 0.85 | 279.8 | 354 | 354 | 354 | 201.8 | 95.7 | 2570 | 187.9 | 0.83 | 4050 |
| LSN 280 SD** | 75 | 1484 | 147 | 0.84 | 381.0 | 482 | 482 | 482 | 274.7 | - | - | - | - | 3420 |
| LSN 280 MD** | 90 | 1482 | 177 | 0.83 | 457.7 | 579 | 579 | 579 | 330 | - | - | - | - | 3420 |

** motors proposed in self-certification only


| 6 poles | | | | | | | | | | | | | | |
|----------------|------|-----|------|------|-------|------|------|------|-------|-------|------|-------|------|-------|
| LSN 90 SL | 0.75 | 945 | 2.1 | 0.75 | 7 | 7.6 | 7.6 | 7.6 | 4.3 | 1.31 | 1645 | 3.4 | 0.75 | 11700 |
| LSN 90 LU | 1.1 | 950 | 2.9 | 0.74 | 10.2 | 11 | 11 | 11 | 6.3 | 1.91 | 1656 | 4.7 | 0.71 | 11700 |
| LSN 100 LG | 1.5 | 962 | 3.9 | 0.73 | 13.1 | 14.8 | 14.8 | 14.8 | 8.4 | 2.61 | 1673 | 6.6 | 0.72 | 9900 |
| LSN 112 MU | 2.2 | 960 | 5.7 | 0.73 | 19.2 | 21.7 | 21.7 | 21.7 | 12.4 | 3.83 | 1673 | 9.6 | 0.70 | 9900 |
| LSN 132 SM | 3 | 968 | 7.2 | 0.77 | 27.4 | 29.5 | 29.5 | 29.5 | 16.8 | 5.22 | 1684 | 12 | 0.73 | 6700 |
| LSN 132 M | 4 | 968 | 9.6 | 0.76 | 36.6 | 39.3 | 39.3 | 39.3 | 22.4 | 6.96 | 1684 | 16.2 | 0.73 | 6700 |
| LSN 132 MU | 5.5 | 960 | 12.6 | 0.79 | 50.6 | 54.4 | 54.4 | 54.4 | 31 | 9.57 | 1673 | 21.3 | 0.76 | 6700 |
| LSN 160 MU | 7.5 | 974 | 18.7 | 0.79 | 68.1 | 73.2 | 73.2 | 73.2 | 41.7 | 13.05 | 1694 | 28.4 | 0.76 | 6700 |
| LSN 180 L | 11 | 980 | 23.9 | 0.79 | 89.6 | 107 | 107 | 107 | 61 | 19.14 | 1701 | 40.8 | 0.77 | 5670 |
| LSN 180 LUR | 15 | 976 | 32.4 | 0.79 | 122.2 | 146 | 146 | 146 | 83.2 | 26.1 | 1697 | 55.7 | 0.77 | 4500 |
| LSN 200 L | 18.5 | 976 | 38.9 | 0.82 | 150.7 | 180 | 180 | 180 | 102.6 | 32.19 | 1697 | 66.5 | 0.80 | 4500 |
| LSN 200 LU | 22 | 978 | 45 | 0.79 | 179.1 | 214 | 214 | 214 | 186.2 | 38.28 | 1697 | 80.6 | 0.77 | 4500 |
| LSN 225 MG | 30 | 984 | 58.9 | 0.86 | 243.6 | 291 | 291 | 291 | 165.9 | 52.2 | 1708 | 101.9 | 0.84 | 4050 |
| LSN 250 ME | 37 | 984 | 71.1 | 0.87 | 299.7 | 358 | 358 | 358 | 204.1 | 64.38 | 1708 | 124.4 | 0.85 | 4050 |
| LSN 280 SC** | 45 | 982 | 86.9 | 0.87 | 365.8 | 437 | 437 | 437 | 249.1 | - | - | - | - | 3420 |
| LSN 280 MD** | 55 | 984 | 105 | 0.87 | 446.1 | 533 | 533 | 533 | 303.8 | - | - | - | - | 3420 |

** motors proposed in self-certification only

* available March 2021

ATEX GAS - Zone 2 - Aluminium



Dimensions in millimetres



| Type | Main shaft end | | | | | | | | | | | | | | | | | |
|----------------------------|----------------|----|------|------|-----|-----|----|-----|----|---------|----|------|------|-----|-----|----|-----|----|
| | 4 and 6 poles | | | | | | | | | 2 poles | | | | | | | | |
| | F | GD | D | G | E | O | p | L | LO | F | GD | D | G | E | O | p | L | LO |
| LSN 80 L/LG | 6 | 6 | 19j6 | 15.5 | 40 | M6 | 16 | 30 | 6 | 6 | 6 | 19j6 | 15.5 | 40 | M6 | 16 | 30 | 6 |
| LSN 90 L/LU/SL | 8 | 7 | 24j6 | 20 | 50 | M8 | 19 | 40 | 6 | 8 | 7 | 24j6 | 20 | 50 | M8 | 19 | 40 | 6 |
| LSN 100 L/LG/LR | 8 | 7 | 28j6 | 24 | 60 | M10 | 22 | 50 | 6 | 8 | 7 | 28j6 | 24 | 60 | M10 | 22 | 50 | 6 |
| LSN 112 MG/MU | 8 | 7 | 28j6 | 24 | 60 | M10 | 22 | 50 | 6 | - | - | - | - | - | - | - | - | - |
| LSN 132 M/MU/S/SM/SU | 10 | 8 | 38k6 | 33 | 80 | M12 | 28 | 63 | 10 | 10 | 8 | 38k6 | 33 | 80 | M12 | 28 | 63 | 10 |
| LSN 160 L/LUR/M/MP/MR/MU | 12 | 8 | 42k6 | 37 | 110 | M16 | 36 | 100 | 6 | 12 | 8 | 42k6 | 37 | 110 | M16 | 36 | 100 | 6 |
| LSN 180 L/LR/LUR/M/ MR /MT | 14 | 9 | 48k6 | 42.5 | 110 | M16 | 36 | 98 | 12 | 14 | 9 | 48k6 | 42.5 | 110 | M16 | 36 | 98 | 12 |
| LSN 200 L/LR/LU | 16 | 10 | 55m6 | 49 | 110 | M20 | 42 | 97 | 13 | 16 | 10 | 55m6 | 49 | 110 | M20 | 42 | 97 | 13 |
| LSN 225 MG/MR | 18 | 11 | 60m6 | 53 | 140 | M20 | 42 | 126 | 14 | 18 | 11 | 60m6 | 49 | 110 | M20 | 42 | 97 | 13 |
| LSN 225 SR/ST | 18 | 11 | 60m6 | 53 | 140 | M20 | 42 | 126 | 14 | - | - | - | - | - | - | - | - | - |
| LSN 250 ME | 18 | 11 | 65m6 | 58 | 140 | M20 | 42 | 126 | 14 | 18 | 11 | 60m6 | 53 | 140 | M20 | 42 | 126 | 14 |
| LSN 280 MC/MD/SC | 20 | 12 | 75m6 | 67.5 | 140 | M20 | 42 | 125 | 15 | 18 | 11 | 65m6 | 58 | 140 | M20 | 42 | 126 | 14 |
| LSN 280 SD | 20 | 12 | 75m6 | 67.5 | 140 | M20 | 42 | 125 | 15 | - | - | - | - | - | - | - | - | - |

| Type | Secondary shaft ends | | | | | | | | | | | | | | | | | |
|-----------------------|----------------------|----|------|------|-----|-----|----|-----|-----|---------|----|------|------|-----|-----|----|-----|-----|
| | 4 and 6 poles | | | | | | | | | 2 poles | | | | | | | | |
| | FA | GF | DA | GB | EA | OA | pA | L' | LO' | FA | GF | DA | GB | EA | OA | pA | L' | LO' |
| LSN 80 L/LG | 5 | 5 | 14j6 | 11 | 30 | M5 | 15 | 25 | 3.5 | 5 | 5 | 14j6 | 11 | 30 | M5 | 15 | 25 | 3.5 |
| LSN 90 L/LU/SL | 6 | 6 | 19j6 | 15.5 | 40 | M6 | 16 | 30 | 6 | 6 | 6 | 19j6 | 15.5 | 40 | M6 | 16 | 30 | 6 |
| LSN 100 L/LG/LR | 8 | 7 | 24j6 | 20 | 50 | M8 | 19 | 40 | 6 | 8 | 7 | 24j6 | 20 | 50 | M8 | 19 | 40 | 6 |
| LSN 112 MG/MU | 8 | 7 | 24j6 | 20 | 50 | M8 | 19 | 40 | 6 | 8 | 7 | 24j6 | 20 | 50 | M8 | 19 | 40 | 6 |
| LSN 132 M/MU/S/SM/SU | 8 | 7 | 28k6 | 24 | 60 | M10 | 22 | 50 | 6 | 8 | 7 | 28k6 | 24 | 60 | M10 | 22 | 50 | 6 |
| LSN 160 MP/MR | 10 | 8 | 38k6 | 33 | 80 | M12 | 28 | 63 | 10 | 10 | 8 | 38k6 | 33 | 80 | M12 | 28 | 63 | 10 |
| LSN 160 L/LUR/M/MU | 12 | 8 | 42k6 | 37 | 110 | M16 | 36 | 100 | 6 | 12 | 8 | 42k6 | 37 | 110 | M16 | 36 | 100 | 6 |
| LSN 180 L/LR/LUR/M/MT | 14 | 9 | 48k6 | 42.5 | 110 | M16 | 36 | 97 | 13 | 14 | 9 | 48k6 | 42.5 | 110 | M16 | 36 | 97 | 13 |
| LSN 180 MR | - | - | - | - | - | - | - | - | - | 14 | 9 | 48k6 | 42.5 | 110 | M16 | 36 | 97 | 13 |
| LSN 200 L/LR/LU | 16 | 10 | 55m6 | 49 | 110 | M20 | 42 | 97 | 13 | 16 | 10 | 55m6 | 49 | 110 | M20 | 42 | 97 | 13 |
| LSN 225 MG/MR | 18 | 11 | 60m6 | 53 | 140 | M20 | 42 | 126 | 14 | 18 | 11 | 60m6 | 49 | 110 | M20 | 42 | 97 | 13 |
| LSN 225 SR/ST | 18 | 11 | 60m6 | 53 | 140 | M20 | 42 | 126 | 14 | - | - | - | - | - | - | - | - | - |
| LSN 250 ME | 18 | 11 | 60m6 | 53 | 140 | M20 | 42 | 126 | 14 | 18 | 11 | 60m6 | 53 | 140 | M20 | 42 | 126 | 14 |
| LSN 280 MC/MD/SC | 18 | 11 | 65m6 | 58 | 140 | M20 | 42 | 126 | 14 | 18 | 11 | 65m6 | 58 | 140 | M20 | 42 | 126 | 14 |
| LSN 280 SD | 18 | 11 | 65m6 | 58 | 140 | M20 | 42 | 126 | 14 | - | - | - | - | - | - | - | - | - |


Dimensions in millimetres



| Type | Main dimensions | | | | | | | | | | | | | | | | | | |
|-------------|-----------------|-----|-----|-----|-----|----|-----|------|------|-----|-----|-----|-------|------|-----|-----|-----|-----|-----|
| | A | AB | B | BB | C | x | AA | K | HA | H | AC* | HD | LB | LJ | J | I | II | AD | AD1 |
| LSN 80 L | 125 | 157 | 100 | 120 | 50 | 10 | 29 | 9 | 10 | 80 | 170 | 159 | 212 | 5.5 | 126 | 63 | 63 | - | - |
| LSN 80 LG | 125 | 157 | 100 | 125 | 50 | 14 | 31 | 9 | 10 | 80 | 189 | 169 | 242 | 5.5 | 126 | 63 | 63 | - | - |
| LSN 90 L | 140 | 172 | 125 | 164 | 56 | 28 | 39 | 10 | 11 | 90 | 189 | 179 | 246 | 5.5 | 126 | 63 | 63 | - | - |
| LSN 90 LU | 140 | 172 | 125 | 164 | 56 | 28 | 39 | 10 | 11 | 90 | 189 | 179 | 266 | 5.5 | 126 | 63 | 63 | - | - |
| LSN 90 SL | 140 | 172 | 100 | 164 | 56 | 28 | 39 | 10 | 11 | 90 | 189 | 179 | 246 | 5.5 | 126 | 63 | 63 | - | - |
| LSN 100 L | 160 | 196 | 140 | 165 | 53 | 12 | 40 | 12 | 13 | 100 | 200 | 194 | 290 | 6.5 | 126 | 63 | 63 | 118 | 45 |
| LSN 100 LG | 160 | 196 | 140 | 168 | 53 | 13 | 40 | 12 | 14 | 100 | 227 | 203 | 299 | 5.5 | 126 | 63 | 63 | 130 | 45 |
| LSN 100 LR | 160 | 196 | 140 | 165 | 63 | 12 | 40 | 12 | 13 | 100 | 200 | 194 | 318 | 6.5 | 126 | 63 | 63 | 118 | 45 |
| LSN 112 MG | 190 | 219 | 140 | 168 | 60 | 14 | 52 | 12 | 13.5 | 112 | 231 | 215 | 300 | 5.5 | 126 | 63 | 63 | 130 | 45 |
| LSN 112 MU | 190 | 219 | 140 | 168 | 60 | 14 | 52 | 12 | 13.5 | 112 | 231 | 215 | 322 | 5.5 | 126 | 63 | 63 | 130 | 45 |
| LSN 132 M | 216 | 250 | 178 | 208 | 89 | 15 | 50 | 12 | 15 | 132 | 272 | 253 | 385 | 17 | 126 | 63 | 63 | 140 | 45 |
| LSN 132 MU | 216 | 250 | 178 | 208 | 89 | 15 | 50 | 12 | 15 | 132 | 272 | 253 | 412 | 17 | 126 | 63 | 63 | 140 | 45 |
| LSN 132 S | 216 | 250 | 140 | 170 | 89 | 15 | 42 | 12 | 16 | 132 | 227 | 235 | 351 | 32.5 | 126 | 63 | 63 | 130 | 45 |
| LSN 132 SM | 216 | 250 | 140 | 208 | 89 | 15 | 50 | 12 | 15 | 132 | 272 | 254 | 385 | 17 | 126 | 63 | 63 | 140 | 45 |
| LSN 132 SU | 216 | 250 | 140 | 170 | 89 | 15 | 42 | 12 | 16 | 132 | 227 | 235 | 383 | 32.5 | 126 | 63 | 63 | 130 | 45 |
| LSN 160 L | 254 | 294 | 254 | 294 | 108 | 20 | 60 | 14.5 | 25 | 160 | 324 | 297 | 495 | 47 | 126 | 63 | 63 | 186 | 45 |
| LSN 160 LUR | 254 | 294 | 254 | 294 | 108 | 20 | 60 | 14.5 | 25 | 160 | 324 | 297 | 510 | 47 | 126 | 63 | 63 | 186 | 45 |
| LSN 160 M | 254 | 294 | 210 | 294 | 108 | 20 | 60 | 14.5 | 25 | 160 | 324 | 297 | 495 | 47 | 126 | 63 | 63 | 186 | 45 |
| LSN 160 MP | 254 | 294 | 210 | 294 | 108 | 20 | 64 | 14 | 25 | 160 | 272 | 281 | 468 | 58.5 | 126 | 63 | 63 | 156 | 45 |
| LSN 160 MR | 254 | 294 | 210 | 294 | 108 | 20 | 64 | 14 | 25 | 160 | 272 | 281 | 495 | 58.5 | 126 | 63 | 63 | 156 | 45 |
| LSN 160 MU | 254 | 294 | 210 | 294 | 108 | 20 | 60 | 14.5 | 25 | 160 | 324 | 297 | 510 | 47 | 126 | 63 | 63 | 186 | 45 |
| LSN 180 L | 279 | 339 | 279 | 329 | 121 | 25 | 86 | 14.5 | 25 | 180 | 350 | 345 | 552 | 27 | 259 | 115 | 151 | 225 | 45 |
| LSN 180 LR | 279 | 324 | 279 | 321 | 121 | 20 | 79 | 14.5 | 29 | 180 | 317 | 317 | 520 | 54 | 186 | 112 | 98 | 177 | 45 |
| LSN 180 LUR | 279 | 339 | 279 | 329 | 121 | 25 | 86 | 14.5 | 25 | 180 | 350 | 345 | 614 | 27 | 259 | 115 | 151 | 225 | 45 |
| LSN 180 M | 279 | 339 | 241 | 291 | 121 | 25 | 86 | 14.5 | 25 | 180 | 350 | 345 | 552 | 27 | 259 | 115 | 151 | 225 | 45 |
| LSN 180 MR | 279 | 324 | 279 | 321 | 121 | 20 | 79 | 14.5 | 29 | 180 | 317 | 317 | 520 | 54 | 186 | 112 | 98 | 177 | 45 |
| LSN 180 MT | 279 | 324 | 241 | 321 | 121 | 20 | 79 | 14.5 | 29 | 180 | 317 | 317 | 495 | 54 | 186 | 112 | 98 | 177 | 45 |
| LSN 200 L | 318 | 391 | 305 | 375 | 133 | 35 | 103 | 18.5 | 33 | 200 | 390 | 385 | 620.5 | 77.5 | 186 | 112 | 98 | - | - |
| LSN 200 LR | 318 | 378 | 305 | 365 | 133 | 30 | 108 | 18.5 | 30 | 200 | 350 | 365 | 620 | 70 | 186 | 112 | 98 | 225 | 45 |
| LSN 200 LU | 318 | 391 | 305 | 375 | 133 | 35 | 103 | 18.5 | 33 | 200 | 390 | 385 | 669.5 | 77.5 | 186 | 112 | 98 | - | - |
| LSN 225 MG | 356 | 420 | 311 | 375 | 149 | 30 | 65 | 18.5 | 33 | 225 | 479 | 451 | 810 | 68 | 292 | 151 | 181 | 283 | 45 |
| LSN 225 MR | 356 | 434 | 311 | 385 | 149 | 50 | 126 | 18.5 | 32 | 225 | 390 | 410 | 676 | 61 | 231 | 119 | 141 | - | - |
| LSN 225 SR | 356 | 434 | 286 | 385 | 149 | 50 | 126 | 18.5 | 32 | 225 | 390 | 410 | 676 | 61 | 231 | 119 | 141 | - | - |
| LSN 225 ST | 356 | 434 | 286 | 385 | 149 | 50 | 126 | 18.5 | 32 | 225 | 390 | 410 | 627 | 61 | 231 | 119 | 141 | - | - |
| LSN 250 ME | 406 | 470 | 349 | 420 | 168 | 35 | 90 | 24 | 35 | 250 | 479 | 476 | 810 | 68 | 292 | 151 | 181 | 283 | 45 |
| LSN 280 MC | 457 | 520 | 419 | 478 | 190 | 35 | 90 | 24 | 35 | 280 | 479 | 506 | 810 | 68 | 292 | 151 | 181 | 283 | 45 |
| LSN 280 MD | 457 | 520 | 419 | 478 | 190 | 35 | 90 | 24 | 35 | 280 | 479 | 506 | 870 | 68 | 292 | 151 | 181 | 283 | 45 |
| LSN 280 SC | 457 | 520 | 368 | 478 | 190 | 35 | 90 | 24 | 35 | 280 | 479 | 506 | 810 | 68 | 292 | 151 | 181 | 283 | 45 |
| LSN 280 SD | 457 | 520 | 368 | 478 | 190 | 35 | 90 | 24 | 35 | 280 | 479 | 506 | 870 | 68 | 292 | 151 | 181 | 283 | 45 |

* AC: housing diameter without lifting rings

Dimensions in millimetres



| Type | Main dimensions | | | | | | | | | | | | | | | | | | | Symb |
|-------------|-----------------|-----|-----|-----|-----|----|-----|------|------|-----|-----|-----|-------|------|-----|-----|-----|-----|-----|-------|
| | A | AB | B | BB | C | x | AA | K | HA | H | AC* | HD | LB | LJ | J | I | II | AD | AD1 | |
| LSN 80 LG | 125 | 157 | 100 | 125 | 50 | 14 | 31 | 9 | 10 | 80 | 189 | 169 | 242 | 5.5 | 126 | 63 | 63 | - | - | FF165 |
| LSN 90 L | 140 | 172 | 125 | 164 | 56 | 28 | 39 | 10 | 11 | 90 | 189 | 179 | 246 | 5.5 | 126 | 63 | 63 | - | - | FF165 |
| LSN 90 LU | 140 | 172 | 125 | 164 | 56 | 28 | 39 | 10 | 11 | 90 | 189 | 179 | 266 | 5.5 | 126 | 63 | 63 | - | - | FF165 |
| LSN 90 SL | 140 | 172 | 100 | 164 | 56 | 28 | 39 | 10 | 11 | 90 | 189 | 179 | 246 | 5.5 | 126 | 63 | 63 | - | - | FF165 |
| LSN 100 L | 160 | 196 | 140 | 165 | 53 | 12 | 40 | 12 | 13 | 100 | 200 | 194 | 290 | 6.5 | 126 | 63 | 63 | 118 | 45 | FF215 |
| LSN 100 LG | 160 | 196 | 140 | 168 | 53 | 13 | 40 | 12 | 14 | 100 | 227 | 203 | 299 | 5.5 | 126 | 63 | 63 | 130 | 45 | FF215 |
| LSN 100 LR | 160 | 196 | 140 | 165 | 63 | 12 | 40 | 12 | 13 | 100 | 200 | 194 | 318 | 6.5 | 126 | 63 | 63 | 118 | 45 | FF215 |
| LSN 112 MG | 190 | 219 | 140 | 168 | 60 | 14 | 52 | 12 | 13.5 | 112 | 231 | 215 | 300 | 5.5 | 126 | 63 | 63 | 130 | 45 | FF215 |
| LSN 112 MU | 190 | 219 | 140 | 168 | 60 | 14 | 52 | 12 | 13.5 | 112 | 231 | 215 | 322 | 5.5 | 126 | 63 | 63 | 130 | 45 | FF215 |
| LSN 132 M | 216 | 250 | 178 | 208 | 89 | 15 | 50 | 12 | 15 | 132 | 272 | 253 | 385 | 17 | 126 | 63 | 63 | 140 | 45 | FF265 |
| LSN 132 MU | 216 | 250 | 178 | 208 | 89 | 15 | 50 | 12 | 15 | 132 | 272 | 253 | 412 | 17 | 126 | 63 | 63 | 140 | 45 | FF265 |
| LSN 132 S | 216 | 250 | 140 | 170 | 89 | 15 | 42 | 12 | 16 | 132 | 227 | 235 | 351 | 32.5 | 126 | 63 | 63 | 130 | 45 | FF265 |
| LSN 132 SM | 216 | 250 | 140 | 208 | 89 | 15 | 50 | 12 | 15 | 132 | 272 | 254 | 385 | 17 | 126 | 63 | 63 | 140 | 45 | FF265 |
| LSN 132 SU | 216 | 250 | 140 | 170 | 89 | 15 | 42 | 12 | 16 | 132 | 227 | 235 | 383 | 32.5 | 126 | 63 | 63 | 130 | 45 | FF265 |
| LSN 160 L | 254 | 294 | 254 | 294 | 108 | 20 | 60 | 14.5 | 25 | 160 | 324 | 297 | 495 | 47 | 126 | 63 | 63 | 186 | 45 | FF300 |
| LSN 160 LUR | 254 | 294 | 254 | 294 | 108 | 20 | 60 | 14.5 | 25 | 160 | 324 | 297 | 510 | 47 | 126 | 63 | 63 | 186 | 45 | FF300 |
| LSN 160 M | 254 | 294 | 210 | 294 | 108 | 20 | 60 | 14.5 | 25 | 160 | 324 | 297 | 495 | 47 | 126 | 63 | 63 | 186 | 45 | FF300 |
| LSN 160 MP | 254 | 294 | 210 | 294 | 108 | 20 | 64 | 14 | 25 | 160 | 272 | 281 | 468 | 58.5 | 126 | 63 | 63 | 156 | 45 | FF300 |
| LSN 160 MR | 254 | 294 | 210 | 294 | 108 | 20 | 64 | 14 | 25 | 160 | 272 | 281 | 495 | 58.5 | 126 | 63 | 63 | 156 | 45 | FF300 |
| LSN 160 MU | 254 | 294 | 210 | 294 | 108 | 20 | 60 | 14.5 | 25 | 160 | 324 | 297 | 510 | 47 | 126 | 63 | 63 | 186 | 45 | FF300 |
| LSN 180 L | 279 | 339 | 279 | 329 | 121 | 25 | 86 | 14.5 | 25 | 180 | 350 | 345 | 552 | 27 | 259 | 115 | 151 | 225 | 45 | FF300 |
| LSN 180 LR | 279 | 324 | 279 | 321 | 121 | 20 | 79 | 14.5 | 29 | 180 | 317 | 317 | 520 | 54 | 186 | 112 | 98 | 177 | 45 | FF300 |
| LSN 180 LUR | 279 | 339 | 279 | 329 | 121 | 25 | 86 | 14.5 | 25 | 180 | 350 | 345 | 614 | 27 | 259 | 115 | 151 | 225 | 45 | FF300 |
| LSN 180 M | 279 | 339 | 241 | 291 | 121 | 25 | 86 | 14.5 | 25 | 180 | 350 | 345 | 552 | 27 | 259 | 115 | 151 | 225 | 45 | FF300 |
| LSN 180 MR | 279 | 324 | 279 | 321 | 121 | 20 | 79 | 14.5 | 29 | 180 | 317 | 317 | 520 | 54 | 186 | 112 | 98 | 177 | 45 | FF300 |
| LSN 180 MT | 279 | 324 | 241 | 321 | 121 | 20 | 79 | 14.5 | 29 | 180 | 317 | 317 | 495 | 54 | 186 | 112 | 98 | 177 | 45 | FF300 |
| LSN 200 L | 318 | 391 | 305 | 375 | 133 | 35 | 103 | 18.5 | 33 | 200 | 390 | 385 | 620.5 | 77.5 | 186 | 112 | 98 | - | - | FF350 |
| LSN 200 LR | 318 | 378 | 305 | 365 | 133 | 30 | 108 | 18.5 | 30 | 200 | 350 | 365 | 620 | 70 | 186 | 112 | 98 | 225 | 45 | FF350 |
| LSN 200 LU | 318 | 391 | 305 | 375 | 133 | 35 | 103 | 18.5 | 33 | 200 | 390 | 385 | 669.5 | 77.5 | 186 | 112 | 98 | - | - | FF350 |
| LSN 225 MG | 356 | 420 | 311 | 375 | 149 | 30 | 65 | 18.5 | 33 | 225 | 479 | 451 | 810 | 68 | 292 | 151 | 181 | 283 | 45 | FF400 |
| LSN 225 MR | 356 | 434 | 311 | 385 | 149 | 50 | 126 | 18.5 | 32 | 225 | 390 | 410 | 676 | 61 | 231 | 119 | 141 | - | - | FF400 |
| LSN 225 SR | 356 | 434 | 286 | 385 | 149 | 50 | 126 | 18.5 | 32 | 225 | 390 | 410 | 676 | 61 | 231 | 119 | 141 | - | - | FF400 |
| LSN 225 ST | 356 | 434 | 286 | 385 | 149 | 50 | 126 | 18.5 | 32 | 225 | 390 | 410 | 627 | 61 | 231 | 119 | 141 | - | - | FF400 |
| LSN 250 ME | 406 | 470 | 349 | 420 | 168 | 35 | 90 | 24 | 35 | 250 | 479 | 476 | 810 | 68 | 292 | 151 | 181 | 283 | 45 | FF500 |
| LSN 280 MC | 457 | 520 | 419 | 478 | 190 | 35 | 90 | 24 | 35 | 280 | 479 | 506 | 810 | 68 | 292 | 151 | 181 | 283 | 45 | FF500 |
| LSN 280 MD | 457 | 520 | 419 | 478 | 190 | 35 | 90 | 24 | 35 | 280 | 479 | 506 | 870 | 68 | 292 | 151 | 181 | 283 | 45 | FF500 |
| LSN 280 SC | 457 | 520 | 368 | 478 | 190 | 35 | 90 | 24 | 35 | 280 | 479 | 506 | 810 | 68 | 292 | 151 | 181 | 283 | 45 | FF500 |
| LSN 280 SD | 457 | 520 | 368 | 478 | 190 | 35 | 90 | 24 | 35 | 280 | 479 | 506 | 870 | 68 | 292 | 151 | 181 | 283 | 45 | FF500 |

* AC: housing diameter without lifting rings


IMfinity® ATEX 3-phase induction motors - IE3 efficiency class

ATEX GAS motors - Zone 2

LSN series - Aluminium - Mechanical characteristics

Flange mounted IM 3001 (IM B5) - IM 3011 (IM V1)

Dimensions in millimetres



| Type | Main dimensions | | | | | | |
|-------------|-----------------|-----|------|-----|-----|-----|-----|
| | AC* | HJ | LJ | I | II | AD | AD1 |
| LSN 80 L | 170 | 148 | 5.5 | 63 | 63 | - | - |
| LSN 80 LG | 189 | 158 | 5.5 | 63 | 63 | - | - |
| LSN 90 L | 189 | 158 | 5.5 | 63 | 63 | - | - |
| LSN 90 LU | 189 | 158 | 5.5 | 63 | 63 | - | - |
| LSN 90 SL | 189 | 158 | 5.5 | 63 | 63 | - | - |
| LSN 100 L | 200 | 163 | 6.5 | 63 | 63 | 118 | 45 |
| LSN 100 LG | 227 | 172 | 5.5 | 63 | 63 | 130 | 45 |
| LSN 100 LR | 200 | 163 | 6.5 | 63 | 63 | 118 | 45 |
| LSN 112 MG | 231 | 172 | 5.5 | 63 | 63 | 130 | 45 |
| LSN 112 MU | 231 | 172 | 5.5 | 63 | 63 | 130 | 45 |
| LSN 132 M | 272 | 190 | 17 | 63 | 63 | 140 | 45 |
| LSN 132 MU | 272 | 190 | 17 | 63 | 63 | 140 | 45 |
| LSN 132 S | 227 | 172 | 32.5 | 63 | 63 | 130 | 45 |
| LSN 132 SM | 272 | 191 | 17 | 63 | 63 | 140 | 45 |
| LSN 132 SU | 227 | 172 | 32.5 | 63 | 63 | 130 | 45 |
| LSN 160 L | 324 | 221 | 47 | 63 | 63 | 186 | 45 |
| LSN 160 LUR | 324 | 221 | 47 | 63 | 63 | 186 | 45 |
| LSN 160 M | 324 | 221 | 47 | 63 | 63 | 186 | 45 |
| LSN 160 MP | 272 | 190 | 58.5 | 63 | 63 | 156 | 45 |
| LSN 160 MR | 272 | 190 | 58.5 | 63 | 63 | 156 | 45 |
| LSN 160 MU | 324 | 221 | 47 | 63 | 63 | 186 | 45 |
| LSN 180 L | 350 | 296 | 27 | 115 | 151 | 225 | 45 |
| LSN 180 LR | 317 | 248 | 54 | 112 | 98 | 177 | 45 |
| LSN 180 LUR | 350 | 296 | 27 | 115 | 151 | 225 | 45 |
| LSN 180 M | 350 | 296 | 27 | 115 | 151 | 225 | 45 |
| LSN 180 MR | 317 | 248 | 54 | 112 | 98 | 177 | 45 |
| LSN 180 MT | 317 | 248 | 54 | 112 | 98 | 177 | 45 |
| LSN 200 L | 390 | 276 | 77.5 | 112 | 98 | - | - |
| LSN 200 LR | 350 | 256 | 70 | 112 | 98 | 225 | 45 |
| LSN 200 LU | 390 | 276 | 77.5 | 112 | 98 | - | - |
| LSN 225 MG | 479 | 405 | 68 | 151 | 181 | 283 | 45 |
| LSN 225 MR | 390 | 310 | 61 | 119 | 141 | - | - |
| LSN 225 SR | 390 | 310 | 61 | 119 | 141 | - | - |
| LSN 225 ST | 390 | 310 | 61 | 119 | 141 | - | - |
| LSN 250 ME | 479 | 405 | 68 | 151 | 181 | 283 | 45 |
| LSN 280 MC | 479 | 405 | 68 | 151 | 181 | 283 | 45 |
| LSN 280 MD | 479 | 405 | 68 | 151 | 181 | 283 | 45 |
| LSN 280 SC | 479 | 405 | 68 | 151 | 181 | 283 | 45 |
| LSN 280 SD | 479 | 405 | 68 | 151 | 181 | 283 | 45 |

* AC: housing diameter without lifting rings


For frame sizes ≥ 250 mm for IM 3001 use, please contact us.

Dimensions of shaft extensions identical to those for foot mounted motors.

| IEC symbol | Flange dimensions | | | | | | | |
|------------|-------------------|-----|-----|-----|---|----------------|------|----|
| | M | N | D | T | n | α° | S | LA |
| FF165 | 165 | 130 | 200 | 3.5 | 4 | 45 | 12 | 10 |
| FF165 | 165 | 130 | 200 | 3.5 | 4 | 45 | 12 | 10 |
| FF165 | 165 | 130 | 200 | 3.5 | 4 | 45 | 12 | 10 |
| FF165 | 165 | 130 | 200 | 3.5 | 4 | 45 | 12 | 10 |
| FF215 | 215 | 180 | 250 | 4 | 4 | 45 | 14.5 | 12 |
| FF215 | 215 | 180 | 250 | 4 | 4 | 45 | 14.5 | 13 |
| FF215 | 215 | 180 | 250 | 4 | 4 | 45 | 14.5 | 12 |
| FF215 | 215 | 180 | 250 | 4 | 4 | 45 | 14.5 | 13 |
| FF215 | 215 | 180 | 250 | 4 | 4 | 45 | 14.5 | 13 |
| FF265 | 265 | 230 | 300 | 4 | 4 | 45 | 14.5 | 14 |
| FF265 | 265 | 230 | 300 | 4 | 4 | 45 | 14.5 | 14 |
| FF265 | 265 | 230 | 300 | 4 | 4 | 45 | 14.5 | 14 |
| FF265 | 265 | 230 | 300 | 4 | 4 | 45 | 14.5 | 14 |
| FF300 | 300 | 250 | 350 | 5 | 4 | 45 | 18.5 | 15 |
| FF300 | 300 | 250 | 350 | 5 | 4 | 45 | 18.5 | 15 |
| FF300 | 300 | 250 | 350 | 5 | 4 | 45 | 18.5 | 15 |
| FF300 | 300 | 250 | 350 | 5 | 4 | 45 | 18.5 | 15 |
| FF300 | 300 | 250 | 350 | 5 | 4 | 45 | 18.5 | 15 |
| FF300 | 300 | 250 | 350 | 5 | 4 | 45 | 18.5 | 15 |
| FF300 | 300 | 250 | 350 | 5 | 4 | 45 | 18.5 | 15 |
| FF300 | 300 | 250 | 350 | 5 | 4 | 45 | 18.5 | 15 |
| FF300 | 300 | 250 | 350 | 5 | 4 | 45 | 18.5 | 15 |
| FF300 | 300 | 250 | 350 | 5 | 4 | 45 | 18.5 | 15 |
| FF350 | 350 | 300 | 400 | 5 | 4 | 45 | 18.5 | 15 |
| FF350 | 350 | 300 | 400 | 5 | 4 | 45 | 18.5 | 15 |
| FF350 | 350 | 300 | 400 | 5 | 4 | 45 | 18.5 | 15 |
| FF400 | 400 | 350 | 450 | 5 | 8 | 22.5 | 18.5 | 16 |
| FF400 | 400 | 350 | 450 | 5 | 8 | 22.5 | 18.5 | 16 |
| FF400 | 400 | 350 | 450 | 5 | 8 | 22.5 | 18.5 | 16 |
| FF400 | 400 | 350 | 450 | 5 | 8 | 22.5 | 18.5 | 16 |
| FF500 | 500 | 450 | 550 | 5 | 8 | 22.5 | 18.5 | 22 |
| FF500 | 500 | 450 | 550 | 5 | 8 | 22.5 | 18.5 | 22 |
| FF500 | 500 | 450 | 550 | 5 | 8 | 22.5 | 18.5 | 22 |
| FF500 | 500 | 450 | 550 | 5 | 8 | 22.5 | 18.5 | 22 |

ATEX GAS - Zone 2 - Aluminium

Dimensions in millimetres




| Type | Main dimensions | | | | | | | | | | | | | | | | | | | |
|------------|-----------------|-----|-----|-----|-----|----|----|----|------|-----|-----|-----|-----|------|-----|----|----|-----|-----|-------|
| | A | AB | B | BB | C | x | AA | K | HA | H | AC* | HD | LB | LJ | J | I | II | AD | AD1 | Symb |
| LSN 80 L | 125 | 157 | 100 | 120 | 50 | 10 | 29 | 9 | 10 | 80 | 170 | 159 | 212 | 5.5 | 126 | 63 | 63 | - | - | FT100 |
| LSN 80 LG | 125 | 157 | 100 | 125 | 50 | 14 | 31 | 9 | 10 | 80 | 189 | 169 | 242 | 5.5 | 126 | 63 | 63 | - | - | FT100 |
| LSN 90 L | 140 | 172 | 125 | 164 | 56 | 28 | 39 | 10 | 11 | 90 | 189 | 179 | 246 | 5.5 | 126 | 63 | 63 | - | - | FT115 |
| LSN 90 LU | 140 | 172 | 125 | 164 | 56 | 28 | 39 | 10 | 11 | 90 | 189 | 179 | 266 | 5.5 | 126 | 63 | 63 | - | - | FT115 |
| LSN 90 SL | 140 | 172 | 100 | 164 | 56 | 28 | 39 | 10 | 11 | 90 | 189 | 179 | 246 | 5.5 | 126 | 63 | 63 | - | - | FT115 |
| LSN 100 L | 160 | 196 | 140 | 165 | 53 | 12 | 40 | 12 | 13 | 100 | 200 | 194 | 290 | 6.5 | 126 | 63 | 63 | 118 | 45 | FT130 |
| LSN 100 LG | 160 | 196 | 140 | 168 | 53 | 13 | 40 | 12 | 14 | 100 | 227 | 203 | 299 | 5.5 | 126 | 63 | 63 | 130 | 45 | FT130 |
| LSN 100 LR | 160 | 196 | 140 | 165 | 63 | 12 | 40 | 12 | 13 | 100 | 200 | 194 | 318 | 6.5 | 126 | 63 | 63 | 118 | 45 | FT130 |
| LSN 112 MG | 190 | 219 | 140 | 168 | 60 | 14 | 52 | 12 | 13.5 | 112 | 231 | 215 | 300 | 5.5 | 126 | 63 | 63 | 130 | 45 | FT130 |
| LSN 112 MU | 190 | 219 | 140 | 168 | 60 | 14 | 52 | 12 | 13.5 | 112 | 231 | 215 | 322 | 5.5 | 126 | 63 | 63 | 130 | 45 | FT130 |
| LSN 132 M | 216 | 250 | 178 | 208 | 89 | 15 | 50 | 12 | 15 | 132 | 272 | 253 | 385 | 17 | 126 | 63 | 63 | 140 | 45 | FT165 |
| LSN 132 MU | 216 | 250 | 178 | 208 | 89 | 15 | 50 | 12 | 15 | 132 | 272 | 253 | 412 | 17 | 126 | 63 | 63 | 140 | 45 | FT165 |
| LSN 132 S | 216 | 250 | 140 | 170 | 89 | 15 | 42 | 12 | 16 | 132 | 227 | 235 | 351 | 32.5 | 126 | 63 | 63 | 130 | 45 | FT165 |
| LSN 132 SM | 216 | 250 | 140 | 208 | 89 | 15 | 50 | 12 | 15 | 132 | 272 | 254 | 385 | 17 | 126 | 63 | 63 | 140 | 45 | FT165 |
| LSN 132 SU | 216 | 250 | 140 | 170 | 89 | 15 | 42 | 12 | 16 | 132 | 227 | 235 | 383 | 32.5 | 126 | 63 | 63 | 130 | 45 | FT165 |
| LSN 160 MP | 254 | 294 | 210 | 294 | 108 | 20 | 64 | 14 | 25 | 160 | 272 | 281 | 468 | 58.5 | 126 | 63 | 63 | 156 | 45 | FT215 |
| LSN 160 MR | 254 | 294 | 210 | 294 | 108 | 20 | 64 | 14 | 25 | 160 | 272 | 281 | 495 | 58.5 | 126 | 63 | 63 | 156 | 45 | FT215 |

*AC: housing diameter without lifting rings

ATEX GAS - Zone 2 - Aluminium

IMfinity® ATEX 3-phase induction motors - IE3 efficiency class
ATEX GAS motors - Zone 2
LSN series - Aluminium - Mechanical characteristics
Face mounted IM 3601 (IM B14)

Dimensions in millimetres



| Type | Main dimensions | | | | | | | | |
|------------|-----------------|-----|-----|------|-----|----|----|-----|-----|
| | AC* | LB | HJ | LJ | J | I | II | AD | AD1 |
| LSN 80 L | 170 | 212 | 148 | 5.5 | 126 | 63 | 63 | - | - |
| LSN 80 LG | 189 | 242 | 158 | 5.5 | 126 | 63 | 63 | - | - |
| LSN 90 L | 189 | 246 | 158 | 5.5 | 126 | 63 | 63 | - | - |
| LSN 90 LU | 189 | 266 | 158 | 5.5 | 126 | 63 | 63 | - | - |
| LSN 90 SL | 189 | 246 | 158 | 5.5 | 126 | 63 | 63 | - | - |
| LSN 100 L | 200 | 290 | 163 | 6.5 | 126 | 63 | 63 | 118 | 45 |
| LSN 100 LG | 227 | 299 | 172 | 5.5 | 126 | 63 | 63 | 130 | 45 |
| LSN 100 LR | 200 | 318 | 163 | 6.5 | 126 | 63 | 63 | 118 | 45 |
| LSN 112 MG | 231 | 300 | 172 | 5.5 | 126 | 63 | 63 | 130 | 45 |
| LSN 112 MU | 231 | 322 | 172 | 5.5 | 126 | 63 | 63 | 130 | 45 |
| LSN 132 M | 272 | 385 | 190 | 17 | 126 | 63 | 63 | 140 | 45 |
| LSN 132 MU | 272 | 412 | 190 | 17 | 126 | 63 | 63 | 140 | 45 |
| LSN 132 S | 227 | 351 | 172 | 32.5 | 126 | 63 | 63 | 130 | 45 |
| LSN 132 SM | 272 | 385 | 191 | 17 | 126 | 63 | 63 | 140 | 45 |
| LSN 132 SU | 227 | 383 | 172 | 32.5 | 126 | 63 | 63 | 130 | 45 |
| LSN 160 MP | 272 | 468 | 190 | 58.5 | 126 | 63 | 63 | 156 | 45 |
| LSN 160 MR | 272 | 495 | 190 | 58.5 | 126 | 63 | 63 | 156 | 45 |

* AC: housing diameter without lifting rings

| Type | Flange dimensions | | | | | | |
|-------|-------------------|-----|-----|-----|---|----------------|-----|
| | M | N | D | T | n | α° | S |
| FT100 | 100 | 80 | 120 | 3 | 4 | 45 | M6 |
| FT100 | 100 | 80 | 120 | 3 | 4 | 45 | M6 |
| FT115 | 115 | 95 | 140 | 3 | 4 | 45 | M8 |
| FT115 | 115 | 95 | 140 | 3 | 4 | 45 | M8 |
| FT115 | 115 | 95 | 140 | 3 | 4 | 45 | M8 |
| FT130 | 130 | 110 | 160 | 3.5 | 4 | 45 | M8 |
| FT130 | 130 | 110 | 160 | 3.5 | 4 | 45 | M8 |
| FT130 | 130 | 110 | 160 | 3.5 | 4 | 45 | M8 |
| FT130 | 130 | 110 | 160 | 3.5 | 4 | 45 | M8 |
| FT130 | 130 | 110 | 160 | 3.5 | 4 | 45 | M8 |
| FT165 | 165 | 130 | 200 | 3.5 | 4 | 45 | M10 |
| FT165 | 165 | 130 | 200 | 3.5 | 4 | 45 | M10 |
| FT165 | 165 | 130 | 200 | 3.5 | 4 | 45 | M10 |
| FT165 | 165 | 130 | 200 | 3.5 | 4 | 45 | M10 |
| FT165 | 165 | 130 | 200 | 3.5 | 4 | 45 | M10 |
| FT215 | 215 | 180 | 250 | 4 | 4 | 45 | M12 |
| FT215 | 215 | 180 | 250 | 4 | 4 | 45 | M12 |

ATEX GAS - Zone 2 - Aluminium

PERMANENTLY GREASED BEARINGS

Under normal operating conditions, the service life in hours (L_{10h}) of the lubricant is indicated in the table below for ambient temperatures less than 55°C.

| Series | Type | Polarity | Permanently greased bearing types | | Bearing service life as a function of rotation speed | | | | | | | | |
|--------|----------|----------|-----------------------------------|---------|--|---------|---------|------------------------|---------|---------|------------------------|---------|-------|
| | | | N.D.E. | D.E. | 3000 min ⁻¹ | | | 1500 min ⁻¹ | | | 1000 min ⁻¹ | | |
| | | | | | 25°C | 40°C | 55°C | 25°C | 40°C | 55°C | 25°C | 40°C | 55°C |
| LSN | 80 L | 2 | 6203 CN | 6204 C3 | ≥ 40000 | ≥ 40000 | 25000 | - | - | - | - | - | - |
| | 80 LG | 2; 4 | 6204 C3 | 6205 C3 | ≥ 40000 | ≥ 40000 | 24000 | ≥ 40000 | ≥ 40000 | 31000 | - | - | - |
| | 90 SL/L | 2; 4; 6 | | | | | | | | | ≥ 40000 | ≥ 40000 | 34000 |
| | 90 LU | 4 | 6205 C3 | 6205 C3 | - | - | - | ≥ 40000 | ≥ 40000 | 30000 | - | - | - |
| | 100 L | 2; 4; 6 | 6205 C3 | 6206 C3 | ≥ 40000 | ≥ 40000 | 22000 | ≥ 40000 | ≥ 40000 | 30000 | ≥ 40000 | ≥ 40000 | 33000 |
| | 100 LR | 4 | | | | | | | | | - | - | - |
| | 112 M | 2 | 6205 C3 | 6206 C3 | ≥ 40000 | ≥ 40000 | 22000 | - | - | - | - | - | - |
| | 112 MG | 2; 6 | | | | | | | | | ≥ 40000 | ≥ 40000 | 33000 |
| | 112 MU | 4 | 6206 C3 | 6206 C3 | - | - | - | ≥ 40000 | ≥ 40000 | 30000 | - | - | - |
| | 132 S | 2; 6 | 6206 C3 | 6208 C3 | ≥ 40000 | ≥ 40000 | 19000 | - | - | - | ≥ 40000 | ≥ 40000 | 30000 |
| | 132 SU | 2; 4 | | | | | | ≥ 40000 | ≥ 40000 | 25000 | - | - | - |
| | 132 SM/M | 2; 4; 6 | 6207 C3 | 6308 C3 | ≥ 40000 | ≥ 40000 | 19000 | ≥ 40000 | ≥ 40000 | 25000 | ≥ 40000 | ≥ 40000 | 30000 |
| | 132 MU | 4; 6 | 6307 C3 | 6308 C3 | - | - | - | ≥ 40000 | ≥ 40000 | 25000 | ≥ 40000 | ≥ 40000 | 30000 |
| | 160 MR | 2; 4 | 6308 C3 | 6309 C3 | ≥ 40000 | 35000 | 15000 | ≥ 40000 | ≥ 40000 | 24000 | - | - | - |
| | 160 MP | 2; 4 | 6208 C3 | 6309 C3 | ≥ 40000 | 35000 | 18000 | ≥ 40000 | ≥ 40000 | 24000 | - | - | - |
| | 160 M/MU | 6 | 6210 C3 | 6309 C3 | - | - | - | - | - | - | - | - | - |
| | 160 L | 2; 4; 6 | | | ≥ 40000 | 30000 | 15000 | ≥ 40000 | ≥ 40000 | 23000 | ≥ 40000 | ≥ 40000 | 27000 |
| | 160 LUR | 4; 6 | 6210 C3 | 6310 C3 | - | - | - | ≥ 40000 | ≥ 40000 | 23000 | ≥ 40000 | ≥ 40000 | 27000 |
| | 180 MT | 2; 4 | | | ≥ 40000 | 30000 | 15000 | ≥ 40000 | ≥ 40000 | 23000 | - | - | - |
| | 180 M | 4 | 6212 C3 | 6310 C3 | - | - | - | ≥ 40000 | ≥ 40000 | 24900 | - | - | - |
| | 180 L | 6 | | | - | - | - | - | - | - | ≥ 40000 | ≥ 40000 | 28000 |
| | 180 LR | 4 | 6210 C3 | 6310 C3 | - | - | - | ≥ 40000 | ≥ 40000 | 23000 | - | - | - |
| | 180 LUR | 4; 6 | 6312 C3 | 6310 C3 | - | - | - | ≥ 40000 | ≥ 40000 | 22000 | ≥ 40000 | ≥ 40000 | 27000 |
| | 200 L | 2; 6 | 6214 C3 | 6312 C3 | ≥ 40000 | 25000 | 12500 | - | - | - | ≥ 40000 | ≥ 40000 | 27000 |
| | 200 LR | 2; 4; 6 | 6312 C3 | 6312 C3 | ≥ 40000 | 25000 | 12500 | ≥ 40000 | ≥ 40000 | 22000 | ≥ 40000 | ≥ 40000 | 27000 |
| | 200 LU | 4; 6 | | | - | - | - | - | - | - | - | - | - |
| 225 ST | 4 | 6214 C3 | 6313 C3 | - | - | - | ≥ 40000 | ≥ 40000 | 21000 | - | - | - | |
| 225 MT | 2 | | | ≥ 40000 | 22000 | 11000 | - | - | - | - | - | - | - |
| 225 SR | 4 | 6312 C3 | 6313 C3 | - | - | - | ≥ 40000 | ≥ 40000 | 21000 | - | - | - | |
| 225 MR | 2; 4; 6 | | | ≥ 40000 | 22000 | 11000 | ≥ 40000 | ≥ 40000 | 21000 | ≥ 40000 | ≥ 40000 | 26000 | |
| 225 MG | 4; 6 | 6216 C3 | 6314 C3 | - | - | - | ≥ 40000 | ≥ 40000 | 20000 | ≥ 40000 | ≥ 40000 | 25000 | |

ATEX GAS - Zone 2 - Aluminium

BEARINGS WITH GREASE NIPPLES

For open bearing assemblies of frame size ≥ 160 mm fitted with grease nipples, the table below indicates, depending on the type of motor, the lubrication intervals to be respected at 25°C, 40°C and 55°C for a machine installed with a horizontal shaft.

The table below is valid for motors lubricated with Polyrex EM103 grease used as standard.

CONSTRUCTION AND SPECIAL ATMOSPHERES

For a machine installed with a vertical shaft, the lubrication intervals are approximately 80% of the values shown in the table below.

NB: The quality and quantity of grease along with the lubrication interval are indicated on the machine nameplate.

In the case of special fitting arrangements (motors with roller bearing at the front or other mountings), machines with frame size ≥ 160 mm are fitted with grease nipple bearings.

The instructions required for bearing housing maintenance are shown on the machine nameplate.

| Series | Type | Polarity | Bearing type for bearing housings with grease nipples | | Quantity of grease g | Lubrication intervals in hours | | | | | | | | |
|-----------|------------|----------|---|---------|-------------------------|--------------------------------|-------|-------|------------------------|-------|-------|------------------------|-------|------|
| | | | N.D.E. | D.E. | | 3000 min ⁻¹ | | | 1500 min ⁻¹ | | | 1000 min ⁻¹ | | |
| | | | | | | 25°C | 40°C | 55°C | 25°C | 40°C | 55°C | 25°C | 40°C | 55°C |
| LSN | 160 M/MU* | 2; 4; 6 | 6210 C3 | 6309 C3 | 13 | 22200 | 11100 | 5550 | 32400 | 16200 | 8100 | 39800 | 19900 | 9950 |
| | 160 L* | | | | | - | - | - | - | - | - | | | |
| | 180 MR* | 2 | 6210 C3 | 6310 C3 | 15 | 19600 | 9800 | 4900 | - | - | - | - | - | - |
| | 180 MT* | 2; 4 | | | | - | - | - | 30400 | 15200 | 7600 | - | - | - |
| | 180 LR* | 4 | | | | - | - | - | - | - | - | - | - | - |
| | 180 LUR* | 4; 6 | 6312 C3 | 6310 C3 | 20 | - | - | - | 26800 | 13400 | 6700 | 35000 | 17500 | 8750 |
| | 180 M* | 4 | 6212 C3 | 6310 C3 | 15 | - | - | - | 29200 | 14600 | 7300 | - | - | - |
| | 180 L* | 6 | | | | - | - | - | - | - | - | 37200 | 18600 | 9300 |
| | 200 LR* | 2; 4; 6 | 6312 C3 | 6312 C3 | 20 | 15200 | 7600 | 3800 | 26800 | 13400 | 6700 | 35000 | 17500 | 8750 |
| | 200 LU* | 4; 6 | | | | - | - | - | - | - | - | - | - | - |
| | 200 L* | 2; 6 | 6214 C3 | 6312 C3 | 20 | 14600 | 7300 | 3650 | - | - | - | 34600 | 17300 | 8650 |
| | 225 ST* | 4 | 6214 C3 | 6313 C3 | 25 | - | - | - | 25200 | 12600 | 6300 | - | - | - |
| | 225 MT* | 2 | | | | 10600 | 5300 | 2650 | - | - | - | - | - | - |
| | 225 SR/MR* | 2; 4; 6 | 6312 C3 | 6313 C3 | 25 | 13400 | 6700 | 3350 | 25200 | 12600 | 6300 | 33600 | 16800 | 8400 |
| | 225 MG* | 4; 6 | 6216 C3 | 6314 C3 | 25 | - | - | - | 23600 | 11800 | 5900 | 32200 | 16100 | 8050 |
| | 250 ME | 4; 6 | 6216 C3 | 6314 C3 | 25 | - | - | - | 23600 | 11800 | 5900 | 32200 | 16100 | 8050 |
| | 280 SC/MC | 2 | | | | 11800 | 5900 | 2950 | - | - | - | - | - | - |
| 280 SC | 6 | 6216 C3 | 6316 C3 | 35 | - | - | - | - | - | - | 32200 | 16100 | 8050 | |
| 280 SD/MD | 4; 6 | 6218 C3 | 6316 C3 | 35 | - | - | - | 20800 | 10400 | 5200 | 29600 | 14800 | 7400 | |

* bearing housings with grease nipples on request

CONSTRUCTION AND SPECIAL ATMOSPHERES

For a machine installed with a vertical shaft, the lubrication intervals are approximately 80% of the values shown in the tables above.

NB: The quality and quantity of grease along with the lubrication interval are indicated on the machine nameplate.

In the case of special fitting arrangements (motors with roller bearing at the front or other mountings), machines with frame size ≥ 160 mm are fitted with grease nipple bearings.


The instructions required for bearing housing maintenance are shown on the machine nameplate.

STANDARD BEARING MOUNTING PRINCIPLE

| LSN series | | Horizontal shaft | Vertical shaft | |
|---|-----------------------|--|----------------------|----------------------|
| | | | Shaft end down | Shaft end up |
| Foot mounted motors | Mounting arrangements | B3 | V5 | V6 |
| | standard fitting | Front bearing: - Front stop for types ≤ 160 MP/MR/LR - locked for types ≥ 160 M/MU/L/LUR | Front bearing locked | Front bearing locked |
| Flange mounted motors (or feet and flange) | Mounting arrangements | B5 / B35 / B14 / B34 | V1 / V15 / V18 / V58 | V3 / V36 / V19 / V69 |
| | standard fitting | Front bearing locked | Front bearing locked | Front bearing locked |

Horizontal motor

For a bearing service life L_{10h} of 25,000 hours and 40,000 hours




| Series | Type | Polarity | Permissible axial load (daN) on the main drive shaft for standard fitting of bearings | | | | | | | | | | | | | |
|--------|----------|----------|---|--------------|--------------|--------------|--------------|--------------|------------------------|--------------|--------------|--------------|------------------------|--------------|--|--|
| | | | 3000 min ⁻¹ | | | | | | 1500 min ⁻¹ | | | | 1000 min ⁻¹ | | | |
| | | | → | | ← | | → | | ← | | → | | ← | | | |
| | | | 25,000 hours | 40,000 hours | 25,000 hours | 40,000 hours | 25,000 hours | 40,000 hours | 25,000 hours | 40,000 hours | 25,000 hours | 40,000 hours | 25,000 hours | 40,000 hours | | |
| LSN | 80 L | 2 | 30 | 21 | (60) | (51) | - | - | - | - | - | - | - | - | | |
| | 80 LG | 2; 4 | 28 | 19 | (68) | (59) | 48 | 34 | (88) | (74) | - | - | - | - | | |
| | 90 SL/L | 2; 4; 6 | 29 | 23 | (69) | (56) | 45 | 32 | (85) | (72) | 56 | 40 | (96) | (80) | | |
| | 90 LU | 2; 4; 6 | 22 | 13 | (72) | (63) | 38 | 25 | (88) | (75) | 47 | 32 | (97) | (82) | | |
| | 100 L | 2; 6 | 42 | 28 | (92) | (78) | - | - | - | - | 78 | 57 | (128) | (107) | | |
| | 100 LR | 4 | - | - | - | - | 58 | 39 | (108) | (90) | - | - | - | - | | |
| | 100 LG | 4; 6 | - | - | - | - | 55 | 38 | (105) | (88) | 75 | 53 | (125) | (103) | | |
| | 112 M | 2 | 38 | 25 | (88) | (75) | - | - | - | - | - | - | - | - | | |
| | 112 MG | 2; 6 | 37 | 24 | (87) | (74) | - | - | - | - | 126 | 104 | (76) | (54) | | |
| | 112 MU | 4; 6 | - | - | - | - | 54 | 36 | (114) | (96) | 66 | 45 | (126) | (105) | | |
| | 132 S | 2; 6 | 69 | 49 | (129) | (109) | - | - | - | - | 124 | 93 | (184) | (153) | | |
| | 132 SU | 2; 4 | 65 | 46 | (125) | (106) | 99 | 73 | (159) | (133) | - | - | - | - | | |
| | 132 SM/M | 2; 4; 6 | 101 | 74 | (171) | (144) | 148 | 111 | (218) | (181) | 178 | 134 | (248) | (204) | | |
| | 132 MU | 4; 6 | - | - | - | - | 139 | 103 | (219) | (183) | 168 | 124 | (248) | (204) | | |
| | 160 MP | 2 | 140 | 104 | (220) | (184) | - | - | - | - | - | - | - | - | | |
| | 160 MR | 2; 4 | 131 | 95 | (221) | (185) | 193 | 145 | (283) | (235) | - | - | - | - | | |
| | 160 M | 2; 4; 6 | 132 | 96 | 232 | 196 | 187 | 140 | 287 | 240 | 235 | 179 | 335 | 279 | | |
| | 160 MU | 6 | - | - | - | - | - | - | - | - | 219 | 164 | 319 | 264 | | |
| | 160 L | 2; 4; 6 | 128 | 96 | 228 | 196 | 183 | 136 | 283 | 236 | 231 | 175 | 331 | 275 | | |
| | 160 LUR | 4; 6 | - | - | - | - | 213 | 159 | 313 | 259 | 257 | 193 | 357 | 293 | | |
| | 180 M | 4 | - | - | - | - | 228 | 174 | 291 | 237 | - | - | - | - | | |
| | 180 MR | 2 | 156 | 115 | 256 | 215 | - | - | - | - | - | - | - | - | | |
| | 180 MT | 2; 4 | 159 | 118 | 259 | 218 | 214 | 160 | 314 | 260 | - | - | - | - | | |
| | 180 L | 6 | - | - | - | - | - | - | - | - | 265 | 201 | 328 | 264 | | |
| | 180 LR | 4 | - | - | - | - | 203 | 150 | 303 | 250 | - | - | - | - | | |
| | 180 LUR | 4; 6 | - | - | - | - | 224 | 170 | 287 | 233 | 224 | 162 | 287 | 225 | | |
| | 200 L | 2; 6 | 244 | 190 | 310 | 256 | - | - | - | - | 362 | 278 | 428 | 344 | | |
| | 200 LR | 2; 4; 6 | 244 | 191 | 307 | 254 | 312 | 241 | 375 | 304 | 341 | 258 | 404 | 321 | | |
| | 200 LU | 4; 6 | - | - | - | - | 316 | 245 | 379 | 308 | 327 | 245 | 390 | 308 | | |
| | 225 SG | 4 | - | - | - | - | 411 | 321 | 481 | 391 | - | - | - | - | | |
| | 225 SR | 4 | - | - | - | - | 350 | 271 | 420 | 341 | - | - | - | - | | |
| | 225 ST | 4 | - | - | - | - | 372 | 292 | 438 | 358 | - | - | - | - | | |
| 225 MG | 4; 6 | - | - | - | - | 407 | 317 | 477 | 387 | 535 | 426 | 605 | 496 | | | |
| 225 MR | 2; 4; 6 | 280 | 220 | 343 | 283 | 358 | 278 | 421 | 341 | 409 | 315 | 472 | 378 | | | |
| 225 MT | 2 | 281 | 221 | 347 | 287 | - | - | - | - | - | - | - | - | | | |
| 250 ME | 4; 6 | - | - | - | - | 400 | 311 | 470 | 381 | 471 | 365 | 541 | 435 | | | |
| 280 SC | 2; 6 | 303 | 236 | 373 | 306 | - | - | - | - | 461 | 355 | 531 | 425 | | | |
| 280 SD | 4 | - | - | - | - | 454 | 349 | 542 | 437 | - | - | - | - | | | |
| 280 MC | 2 | 300 | 233 | 370 | 303 | - | - | - | - | - | - | - | - | | | |
| 280 MD | 4; 6 | - | - | - | - | 446 | 342 | 534 | 430 | 524 | 401 | 612 | 489 | | | |

(): permissible axial loads with Front bearing locked

Vertical motor
Shaft end downwards

For a bearing service life L_{10h}
of 25,000 hours
and 40,000 hours



| Series | Type | Polarity | Permissible axial load (daN) on the main drive shaft for standard fitting of bearings | | | | | | | | | | | |
|--------|----------|----------|---|--------------|--------------|--------------|------------------------|--------------|--------------|--------------|------------------------|--------------|--------------|--------------|
| | | | 3000 min ⁻¹ | | | | 1500 min ⁻¹ | | | | 1000 min ⁻¹ | | | |
| | | | 25,000 hours | 40,000 hours | 25,000 hours | 40,000 hours | 25,000 hours | 40,000 hours | 25,000 hours | 40,000 hours | 25,000 hours | 40,000 hours | 25,000 hours | 40,000 hours |
| | | | IM V5 IM V1 / V15 IM V18 / V58 | | | | | | | | | | | |
| | 80 L | 2 | 29 | 20 | (63) | (54) | - | - | (93) | (78) | - | - | - | - |
| | 80 LG | 2; 4 | 26 | 16 | (72) | (62) | 45 | 32 | (93) | (78) | - | - | - | - |
| | 90 SL/L | 2; 4; 6 | 26 | 16 | (73) | (63) | 42 | 28 | (91) | (78) | 53 | 37 | (101) | (86) |
| | 90 LU | 2; 4; 6 | 19 | 9 | (77) | (67) | 33 | 20 | (95) | (82) | 43 | 28 | (105) | (89) |
| | 100 L | 2; 6 | 38 | 24 | (98) | (85) | - | - | - | - | 73 | 52 | (137) | (115) |
| | 100 LR | 4 | - | - | - | - | 52 | 34 | (117) | (99) | - | - | - | - |
| | 100 LG | 4; 6 | - | - | - | - | 48 | 31 | (116) | (99) | 68 | 46 | (137) | (115) |
| | 112 M | 2 | 35 | 21 | (95) | (81) | - | - | - | - | - | - | - | - |
| | 112 MG | 2; 6 | 31 | 18 | (98) | (85) | - | - | - | - | 68 | 47 | (138) | (116) |
| | 112 MU | 4; 6 | - | - | - | - | 45 | 28 | (128) | (110) | 57 | 36 | (140) | (119) |
| | 132 S | 2; 6 | 61 | 41 | (142) | (122) | - | - | - | - | 115 | 84 | (200) | (169) |
| | 132 SU | 2; 4 | 57 | 37 | (139) | (120) | 90 | 63 | (176) | (149) | - | - | - | - |
| | 132 SM/M | 2; 4; 6 | 90 | 62 | (189) | (161) | 137 | 100 | (237) | (200) | 165 | 121 | (270) | (226) |
| | 132 MU | 4; 6 | - | - | - | - | 125 | 89 | (242) | (206) | 152 | 108 | (273) | (230) |
| | 160 MP | 2 | 126 | 90 | (243) | (207) | - | - | - | - | - | - | - | - |
| | 160 MR | 2; 4 | 115 | 80 | (246) | (210) | 175 | 127 | (311) | (264) | - | - | - | - |
| | 160 M | 2; 4; 6 | 111 | 75 | 264 | 229 | 164 | 117 | 326 | 278 | 210 | 154 | 375 | 319 |
| | 160 MU | 6 | - | - | - | - | - | - | - | - | 189 | 133 | 375 | 319 |
| | 160 L | 2; 4; 6 | 106 | 70 | 263 | 228 | 160 | 113 | 322 | 274 | 208 | 151 | 371 | 314 |
| | 160 LUR | 4; 6 | - | - | - | - | 186 | 131 | 363 | 309 | 227 | 162 | 417 | 352 |
| LSN | 180 M | 4 | - | - | - | - | 187 | 132 | 361 | 306 | - | - | - | - |
| | 180 MR | 2 | 131 | 90 | 296 | 255 | - | - | - | - | - | - | - | - |
| | 180 MT | 2; 4 | 136 | 95 | 295 | 254 | 189 | 134 | 360 | 305 | - | - | - | - |
| | 180 L | 6 | - | - | - | - | - | - | - | - | 226 | 161 | 398 | 334 |
| | 180 LR | 4 | - | - | - | - | 177 | 122 | 355 | 300 | - | - | - | - |
| | 180 LUR | 4; 6 | - | - | - | - | 187 | 132 | 355 | 300 | 183 | 120 | 377 | 314 |
| | 200 L | 2; 6 | 194 | 139 | 384 | 330 | - | - | - | - | 308 | 223 | 524 | 439 |
| | 200 LR | 2; 4; 6 | 209 | 154 | 360 | 306 | 275 | 203 | 445 | 373 | 299 | 215 | 496 | 412 |
| | 200 LU | 4; 6 | - | - | - | - | 262 | 190 | 471 | 398 | 269 | 186 | 505 | 422 |
| | 225 SG | 4 | - | - | - | - | 335 | 244 | 616 | 524 | - | - | - | - |
| | 225 SR | 4 | - | - | - | - | 294 | 213 | 520 | 439 | - | - | - | - |
| | 225 ST | 4 | - | - | - | - | 322 | 241 | 519 | 438 | - | - | - | - |
| | 225 MG | 4; 6 | - | - | - | - | 324 | 232 | 621 | 530 | 456 | 345 | 749 | 638 |
| | 225 MR | 2; 4; 6 | 234 | 173 | 413 | 352 | 302 | 221 | 520 | 439 | 348 | 253 | 587 | 492 |
| | 225 MT | 2 | 240 | 179 | 410 | 349 | - | - | - | - | - | - | - | - |
| | 250 ME | 4; 6 | - | - | - | - | 305 | 214 | 632 | 541 | 378 | 270 | 712 | 604 |
| 280 SC | 2; 6 | 233 | 165 | 488 | 420 | - | - | - | - | 348 | 240 | 728 | 621 | |
| 280 SD | 4 | - | - | - | - | 340 | 233 | 738 | 632 | - | - | - | - | |
| 280 MC | 2 | 221 | 153 | 496 | 428 | - | - | - | - | - | - | - | - | |
| 280 MD | 4; 6 | - | - | - | - | 319 | 213 | 745 | 639 | 391 | 265 | 853 | 728 | |

(): permissible axial loads with Front bearing locked

Vertical motor
Shaft end upwards

For a bearing service life L_{10h}
of 25,000 hours
and 40,000 hours



| Series | Type | Polarity | Permissible axial load (daN) on the main drive shaft for standard fitting of bearings | | | | | | | | | | | | |
|--------|----------|----------|---|--------------|--------------|--------------|------------------------|--------------|--------------|--------------|------------------------|--------------|--------------|--------------|---|
| | | | 3000 min ⁻¹ | | | | 1500 min ⁻¹ | | | | 1000 min ⁻¹ | | | | |
| | | | ↓ | | ↑ | | ↓ | | ↑ | | ↓ | | ↑ | | |
| | | | 25,000 hours | 40,000 hours | 25,000 hours | 40,000 hours | 25,000 hours | 40,000 hours | 25,000 hours | 40,000 hours | 25,000 hours | 40,000 hours | 25,000 hours | 40,000 hours | |
| LSN | 80 L | 2 | (59) | (50) | 33 | 24 | - | - | - | - | - | - | - | - | - |
| | 80 LG | 2; 4 | (66) | (56) | 32 | 22 | (85) | (71) | 53 | 39 | - | - | - | - | - |
| | 90 SL/L | 2; 4; 6 | (66) | (56) | 33 | 23 | (82) | (68) | 51 | 38 | (93) | (77) | 61 | 46 | - |
| | 90 LU | 2; 4; 6 | (69) | (59) | 27 | 18 | (83) | (70) | 45 | 32 | (93) | (77) | 54 | 39 | - |
| | 100 L | 2; 6 | (88) | (74) | 48 | 35 | - | - | - | - | (123) | (102) | 87 | 65 | - |
| | 100 LR | 4 | - | - | - | - | (102) | (84) | 67 | 49 | - | - | - | - | - |
| | 100 LG | 4; 6 | - | - | - | - | (98) | (81) | 67 | - | (118) | (96) | 87 | 66 | - |
| | 112 M | 2 | (84) | (71) | 45 | 31 | - | - | - | - | - | - | - | - | - |
| | 112 MG | 2; 6 | (81) | (68) | 48 | 35 | - | - | - | - | (118) | (97) | 88 | 66 | - |
| | 112 MU | 4; 6 | - | - | - | - | (105) | (88) | 68 | 50 | (117) | (96) | 80 | 60 | - |
| | 132 S | 2; 6 | (121) | (101) | 82 | 62 | - | - | - | - | (175) | (143) | 140 | 109 | - |
| | 132 SU | 2; 4 | (117) | (97) | 79 | 60 | (150) | (123) | 116 | 89 | - | - | - | - | - |
| | 132 SM/M | 2; 4; 6 | (160) | (132) | 119 | 91 | (207) | (170) | 167 | 130 | (235) | (191) | 200 | 156 | - |
| | 132 MU | 4; 6 | - | - | - | - | (206) | (169) | 163 | 126 | (232) | (188) | 193 | 150 | - |
| | 160 MP | 2 | (206) | (170) | 163 | 127 | - | - | - | - | - | - | - | - | - |
| | 160 MR | 2; 4 | (205) | (170) | 156 | 120 | (265) | (217) | 222 | 174 | - | - | - | - | - |
| | 160 M | 2; 4; 6 | 211 | 175 | 164 | 129 | 264 | 217 | 226 | 178 | 310 | 254 | 275 | 219 | - |
| | 160 MU | 6 | - | - | - | - | - | - | - | - | 289 | 233 | 275 | 219 | - |
| | 160 L | 2; 4; 6 | 206 | 170 | 163 | 128 | 260 | 213 | 222 | 174 | 308 | 251 | 271 | 214 | - |
| | 160 LUR | 4; 6 | - | - | - | - | 286 | 231 | 263 | 209 | 327 | 262 | 317 | 252 | - |
| | 180 M | 4 | - | - | - | - | 250 | 195 | 298 | 243 | - | - | - | - | - |
| | 180 MR | 2 | 231 | 190 | 196 | 155 | - | - | - | - | - | - | - | - | - |
| | 180 MT | 2; 4 | 236 | 195 | 195 | 154 | 289 | 234 | 260 | 205 | - | - | - | - | - |
| | 180 L | 6 | - | - | - | - | - | - | - | - | 289 | 224 | 335 | 271 | - |
| | 180 LR | 4 | - | - | - | - | 277 | 222 | 255 | 200 | - | - | - | - | - |
| | 180 LUR | 4; 6 | - | - | - | - | 250 | 195 | 292 | 237 | 246 | 183 | 314 | 251 | - |
| | 200 L | 2; 6 | 260 | 205 | 318 | 264 | - | - | - | - | 374 | 289 | 458 | 373 | - |
| | 200 LR | 2; 4; 6 | 272 | 217 | 297 | 243 | 338 | 266 | 382 | 310 | 362 | 278 | 433 | 349 | - |
| | 200 LU | 4; 6 | - | - | - | - | 325 | 253 | 408 | 335 | 332 | 249 | 442 | 359 | - |
| | 225 SG | 4 | - | - | - | - | 405 | 314 | 546 | 454 | - | - | - | - | - |
| | 225 SR | 4 | - | - | - | - | 364 | 283 | 450 | 369 | - | - | - | - | - |
| | 225 ST | 4 | - | - | - | - | 388 | 307 | 453 | 372 | - | - | - | - | - |
| 225 MG | 4; 6 | - | - | - | - | 394 | 302 | 551 | 460 | 526 | 415 | 679 | 568 | - | |
| 225 MR | 2; 4; 6 | 297 | 236 | 350 | 289 | 365 | 284 | 457 | 376 | 411 | 316 | 524 | 429 | - | |
| 225 MT | 2 | 306 | 245 | 344 | 283 | - | - | - | - | - | - | - | - | - | |
| 250 ME | 4; 6 | - | - | - | - | 375 | 284 | 562 | 471 | 448 | 340 | 642 | 534 | - | |
| 280 SC | 2; 6 | 303 | 235 | 418 | 350 | - | - | - | - | 418 | 310 | 658 | 551 | - | |
| 280 SD | 4 | - | - | - | - | 428 | 321 | 650 | 544 | - | - | - | - | - | |
| 280 MC | 2 | 291 | 223 | 426 | 358 | - | - | - | - | - | - | - | - | - | |
| 280 MD | 4; 6 | - | - | - | - | 407 | 301 | 657 | 551 | 479 | 353 | 765 | 640 | - | |

(): permissible axial loads with Front bearing locked










STANDARD FITTING ARRANGEMENT

Permissible radial load on main shaft extension with a bearing life L10h of 25,000 hours.

FR: Radial Force

X: distance with respect to the shaft shoulder

ATEX GAS - Zone 2 - Aluminium












STANDARD FITTING ARRANGEMENT

Permissible radial load on main shaft extension with a bearing life L10h of 25,000 hours.

FR: Radial Force

X: distance with respect to the shaft shoulder



ATEX GAS - Zone 2 - Aluminium







STANDARD FITTING ARRANGEMENT

Permissible radial load on main shaft extension with a bearing life L10h of 25,000 hours.

FR: Radial Force

X: distance with respect to the shaft shoulder

ATEX GAS - Zone 2 - Aluminium






STANDARD FITTING ARRANGEMENT

Permissible radial load on main shaft extension with a bearing life L10h of 25,000 hours.

FR: Radial Force

X: distance with respect to the shaft shoulder



SPECIAL FITTING ARRANGEMENT

Type of drive end roller bearings




| Series | Type | Polarity | Rear bearing (N.D.E.) | Front Bearing (D.E.) |
|--------|-----------|----------|-----------------------|----------------------|
| LSN | 160 M/MU | 4; 6 | 6210 C3 | NU 309 |
| | 160 L | | | |
| | 180 MT | 4 | 6210 C3 | NU 310 |
| | 180 LR | | | |
| | 180 LUR | 4; 6 | 6312 C3 | NU 310 |
| | 180 M | 4 | 6212 C3 | NU 310 |
| | 180 L | 6 | | |
| | 200 L | 6 | 6214 C3 | NU 312 |
| | 200 LR | 4; 6 | 6312 C3 | NU 312 |
| | 200 LU | | | |
| | 225 ST | 4 | 6214 C3 | NU 313 |
| | 225 SR/MR | 4; 6 | 6312 C3 | NU 313 |
| | 225 SG | 4 | 6216 C3 | NU 314 |
| | 225 MG | 4; 6 | | |
| | 250 ME | 4; 6 | 6216 C3 | NU 314 |
| | 280 SC | 6 | 6216 C3 | NU 316 |
| | 280 SD/MD | 4; 6 | 6218 C3 | NU 316 |

SPECIAL FITTING ARRANGEMENT

Permissible radial load on main shaft extension with a bearing life L_{10h} of 25,000 hours.

FR: Radial Force

X: distance with respect to the shaft shoulder












SPECIAL FITTING ARRANGEMENT

Permissible radial load on main shaft extension with a bearing life L_{10h} of 25,000 hours.

FR: Radial Force

X: distance with respect to the shaft shoulder



ATEX GAS - Zone 2 - Aluminium





SPECIAL FITTING ARRANGEMENT

Permissible radial load on main shaft extension with a bearing life L_{10h} of 25,000 hours.

FR: Radial Force

X: distance with respect to the shaft shoulder

ATEX GAS - Zone 2 - Aluminium



INDICATION OF CABLE GLAND SIZE AND TYPE FOR 400 V RATED SUPPLY VOLTAGE IF DRILLINGS REQUIRED WITHOUT DETAILS OF DIAMETERS

| Series | Type | Polarity | Terminal box material | Power + auxiliaries | |
|--------|---------|-------------------|-----------------------|-------------------------|--------------------------------|
| | | | | Number of holes | Hole diameter* |
| LSN | 80 | 2; 4; 6 | Aluminium alloy | 1 (2 if auxiliaries) | ISO M20 x 1.5 (1M20 + 1M16) |
| | 90 | 2; 4; 6 | | | |
| | 100 | 2; 4; 6 | | 2 (3 if auxiliaries) | ISO M25 x 1.5 (2M25 + 1M16) |
| | 112 | 2; 4; 6 | | | |
| | 132 | 2; 4; 6 | | 3 | 2 x M40 + 1 x M16 |
| | 160 | 2; 4; 6 | | | |
| | 180 | 2; 4; 6 | | | |
| | 200 | 2; 4; 6 | | 2 x M50 + 1 x M16 | |
| | 225 | 2; 4; 6 | | | |
| | 250 ME | 4; 6 | | | |
| 280 | 2; 4; 6 | 2 x M63 + 1 x M16 | | | |

*As an option, both ISO M25 holes may be replaced by 1 ISO x M25 and 1 ISO x M32 (to comply with standard DIN 42925).

**TERMINAL BLOCKS
DIRECTION OF ROTATION**

Standard motors are fitted with a block of 6 terminals complying with standard NFC 51 120, with the terminal markings complying with IEC 60034-8 (or NF EN 60034-8).

When the motor is running in U1, V1, W1 or 1U, 1V, 1W from a direct mains supply L1, L2, L3, it turns clockwise when seen from the drive shaft end.

If any two of the phases are changed over, the motor will run in the opposite direction (make sure that the motor has been designed to run in both directions). If the motor is fitted with accessories (thermal protection or space heater), these must be connected on terminal blocks with labelled wires.

Tightening torque for the nuts on the terminal blocks.

| Terminal | M4 | M5 | M6 | M8 | M10 | M12 | M16 |
|------------|----|-----|----|----|-----|-----|-----|
| Torque N.m | 2 | 3.2 | 5 | 10 | 20 | 35 | 65 |

| Series | Type | 400 V mains supply | | |
|--------|-------------|----------------------|-----------|------------------------|
| | | 230/400 V connection | | 400 V drive connection |
| | | Polarity | Terminals | Terminals |
| LSN | 80 to 112 | 2; 4; 6 | M5 | M5 |
| | 132 S/SU | 2; 4; 6 | M5 | M5 |
| | 132 M/MP/MU | 2; 4; 6 | M6 | M6 |
| | 160 | 2; 4; 6 | M6 | M6 |
| | 180 MT/L | 2; 4; 6 | M6 | M6 |
| | 180 LR | 4 | M8 | M6 |
| | 200 LR | 2; 4; 6 | M8 | M6 |
| | 200 L | 2; 6 | M8 | M8 |
| | 225 ST | 4 | M10 | M8 |
| | 225 MR | 4 | M10 | M8 |
| | | 6 | M8 | M8 |
| | 250 ME | 4; 6 | M10 | M8 |
| | | 2 | M12 | M10 |
| | 280 SC | 4 | M12 | M8 |
| | | 6 | M10 | M8 |
| | 280 MC | 2 | M12 | M10 |
| 6 | | M10 | M8 | |
| 280 MD | 4 | M12 | M10 | |

| Mechanical adaptations | Frame size |
|--|---------------|
| DE and NDE bearings with 1 machining, for vibration sensor in position 12H, 12H-3H, or 12H-3H-9H | ≥ 132 |
| Different FF flanges from IEC | All |
| Different FT flanges from IEC | ≤ 132 |
| DE roller bearing | ≥ 160: 4p & + |
| Insulated DE or NDE bearing | ≥ 280 |
| 2 nd standard catalogue NDE shaft end | All |
| 2 nd special NDE shaft end | All |
| Conical shaft | All |
| Shaft with special keying | All |
| Keyed cylindrical NDE shaft (secondary shaft end) as per IEC | All |
| Stainless-steel shaft | All |
| Class B balancing | All |
| F type (full key) or N type (no key) balancing | All |
| Stainless steel fan cover | All |
| Steel fan cover + drip cover | All |
| Steel fan cover + anti-clogging | All |
| Metal fan | All |
| Stainless steel nameplate | All |
| Stainless-steel fastenings | All |
| Three-phase axial forced ventilation - IC 416 A | All |
| Incremental encoder / 1024 or 4096 pts / 5v or 11/30 V | All |
| Positioning holes (jacking screws) | ≥ 250 |
| Radial seal for motor in vertical position with shaft end upwards | All |
| Drain holes for operation in vertical position | All |
| Electrical adaptations | Frame size |
| Terminal board with anti-rotation system as standard | All |
| Special voltages (excluding variable speed) | All |
| Definition for Id/In ≤ 7.5 | All |
| Insulation class H | All |
| Main box in position B or D | All |
| Auxiliary boxes | ≥ 160 |
| Plastic PE | All |
| ATEX brass PE for unshielded cable | All |
| ATEX brass PE for shielded cable | All |
| ATEX brass PE auxiliary for unshielded cable | All |
| ATEX brass PE auxiliary for shielded cable | All |
| Flying lead via 1 metre single-core cable 6 + 1 | All |
| Cable entry on the left as seen from the shaft end | All |
| Preparation for NPT cable glands | All |
| Protections | Frame size |
| Winding PTC thermistor probe (triple probe) | All |
| Winding PT 100 probe (1 per phase) | All |
| Endshield PTC thermistor probe (triple probe) | ≥ 160 |
| Endshield PT 100 probe (per probe) | ≥ 160 |
| Endshield thermocouple | ≥ 160 |
| Space heaters when stopped (220-230 V) | All |
| Reinforced winding insulation system for variable speed drive power supply | All |
| Finish | Frame size |
| VIK version (see page 23) | All |
| IP 65 | All |
| Definition for gas + dust motor, Ex tc IIIB / IIIC T125°C Dc | All |
| IP 56 stopped with fan (IC 411) | All |
| C3H, C4M, C4H, C5-IL or C5-IM paint | All |
| Other paint shades | All |
| Operating temperature: -55°C < T° < -20°C | All |
| Complete tropicalization (stator + rotor) | All |

Optionally, Nidec Leroy-Somer motors can be fitted with flanges and faceplates that are larger or smaller than standard. This means that motors can be adapted to all types of situation without the need for costly and time-consuming modifications.

The tables below give the flange and faceplate dimensions and also indicate flange/motor compatibility. The bearing and shaft end for each frame size remain standard.


Dimensions in millimetres

(FF) FLANGE MOUNTED

| Symbol IEC | Flange dimensions | | | | | | |
|------------|-------------------|-----|-----|-----|---|------|------|
| | M | N | D | T | n | S | LA |
| FF 115 | 115 | 95 | 140 | 3 | 4 | 10 | 10 |
| FF 130 | 130 | 110 | 160 | 3.5 | 4 | 10 | 10 |
| FF 165 | 165 | 130 | 200 | 3.5 | 4 | 12 | 10 |
| FF 215 | 215 | 180 | 250 | 4 | 4 | 15 | 12 |
| FF 265 | 265 | 230 | 300 | 4 | 4 | 15 | 14 |
| FF 300 | 300 | 250 | 350 | 5 | 4 | 18.5 | 14 |
| FF 350 | 350 | 300 | 400 | 5 | 4 | 18.5 | 15 |
| FF 400 | 400 | 350 | 450 | 5 | 8 | 18.5 | 16 |
| FF 500 | 500 | 450 | 550 | 5 | 8 | 18.5 | 18** |


* Tolerance N js6

** shaft length = 22 for frame size ≥ 280



(FT) FACE MOUNTED

| Symbol IEC | Flange dimensions | | | | | | |
|------------|-------------------|-----|-----|-----|---|-----|--|
| | M | N | D | T | n | M.S | |
| FT 85 | 85 | 70 | 105 | 2.5 | 4 | M6 | |
| FT 100 | 100 | 80 | 120 | 3 | 4 | M6 | |
| FT 115 | 115 | 95 | 140 | 3 | 4 | M8 | |
| FT 130 | 130 | 110 | 160 | 3.5 | 4 | M8 | |
| FT 165 | 165 | 130 | 200 | 3.5 | 4 | M10 | |
| FT 215 | 215 | 180 | 250 | 4 | 4 | M12 | |
| FT 265 | 265 | 230 | 300 | 4 | 4 | M12 | |



MODIFIED FLANGES

| Motor type | Flange type Fastening forms | (FF) Flange mounted | | | | | | | | | | | | | | (FT) Face mounted | | | | | | | | | |
|------------|--------------------------------|-----------------------|--------|--------|--------|--------|--------|--------|--------|--------|--------|------------------|--------|--------|--------|-------------------|-------|-------|--------|--------|--------|--------|--------|--------|--|
| | | FF 85 | FF 100 | FF 115 | FF 130 | FF 165 | FF 215 | FF 265 | FF 300 | FF 350 | FF 400 | FF 500 | FF 600 | FF 740 | FF 940 | FT 65 | FT 75 | FT 85 | FT 100 | FT 115 | FT 130 | FT 165 | FT 215 | FT 265 | |
| LSN | 80 L | all | ■ | ■ | ■ | ■ | ● | ◆ | | | | | | | | ◆ | ◆ | ◆ | ● | ◆ | ◆ | | | | |
| | 80 LG / 90 | B5/B35 ⁽¹⁾ | ◆ | ◆ | ◆ | ◆ | ● | ■ | ■ | | | | | | | | | | | | | | | | |
| | 80 LG / 90 | B3/B14/B34 | | | | | | | | | | | | | | | | ◆ | ◆ | ● | ◆ | ◆ | | | |
| | 100 L/LR | all | ■ | ■ | ■ | ■ | ■ | ● | ■ | | | | | | | | | ◆ | ◆ | ◆ | ● | ◆ | | | |
| | 100 LG | all | | | | ■ | ■ | ● | ◆ | | | | | | | | | | | | ◆ | ● | ◆ | ◆ | |
| | 112 MU/MG | all | | | | ■ | ■ | ● | ◆ | | | | | | | | | | | | ◆ | ● | ◆ | ◆ | |
| | 132 S/SU | all | | | | | ■ | ◆ | ● | | | | | | | | | | | | | ◆ | ◆ | ● | |
| | 132 SM/M/MU | all | | | | | ■ | ■ | ● | ◆ | | | | | | | | | | | | ■ | ■ | ● | |
| | 160 MR/LR/MP | all | | | | | | | ■ | ● | ■ | | | | | | | | | | | | | ● | |
| | 160 M/L/LU/LUR | all | | | | | | ◆ | ◆ | ● | ◆ | | | | | | | | | | | | | | |
| | 180 | all | | | | | | | ● | ● | ◆ | ◆ ⁽¹⁾ | | | | | | | | | | | | | |
| | 200 | all | | | | | | | | ● | ◆ | | | | | | | | | | | | | | |
| | 225 | all | | | | | | | | | ● | ◆ | | | | | | | | | | | | | |
| | 250 | all | | | | | | | | | ◆ | ● | | | | | | | | | | | | | |
| | 280 | all | | | | | | | | | ◆ | ● | ◆ | | | | | | | | | | | | |

● Standard ■ Modified shaft ◆ Adaptable without shaft modifications


(1) Dimension C need not comply with IEC 60072

ATEX GAS - Zone 2 - Aluminium

DRIP COVER FOR OPERATION IN VERTICAL POSITION SHAFT END DOWNWARDS

Dimensions in millimetres

| Series | Motor type | LB' | Ø |
|--------|-------------|-----------|-----|
| LSN | 80 | LB + 20 | 145 |
| | 90 | LB + 20 | 185 |
| | 100 | LB + 20 | 185 |
| | 112 MR | LB + 20 | 185 |
| | 112 MG/MU | LB + 25 | 210 |
| | 132 S/SU | LB + 25 | 210 |
| | 132 M/MU/SM | LB + 30 | 240 |
| | 160 MP/LR | LB + 30 | 240 |
| | 160 M/L/LU | LB + 36.5 | 265 |
| | 180 MT/LR | LB + 36.5 | 265 |
| | 180 L | LB + 36.5 | 305 |
| | 200 LR | LB + 36.5 | 305 |
| | 200 L/LU | LB + 36.5 | 350 |
| | 225 | LB + 36.5 | 350 |
| | 250 ME | LB + 55 | 420 |
| | 280 | LB + 55 | 420 |



SPACE HEATERS

| Series | Type | Power (W) |
|--------|------------------------|-----------|
| LSN | 80 L/LG | 10 |
| | 90 to 160 MP/LR | 25 |
| | 160 M/L à 225 ST/MT/MR | 52 |
| | 250 ME/MF | 84 |
| | 280 SC/SU/MC/MD | 84 |

The space heaters use 200/240 V single-phase, 50 or 60 Hz.


LIFTING THE MOTOR ONLY
(not coupled to the machine)

The regulations stipulate that in excess of 25 kg suitable handling equipment must be used.

All our motors are fitted with grab handles, making them easier to handle without risk. A diagram of the sling hoisting method appears below with the required dimensions.


To prevent any damage to the motor during handling (for example: switching the motor from horizontal to vertical), it is essential to follow these instructions.

HORIZONTAL POSITION



| Series | Type | Horizontal position | | | |
|--------------|--------------|---------------------|--------|--------|----|
| | | A | min. e | min. h | Øt |
| LSN | 100 L/LR | 165 | 165 | 150 | 9 |
| | 112 M/MR | 165 | 165 | 150 | 9 |
| | 112 MG/MU | - | - | - | 9 |
| | 132 S/SU | 180 | 180 | 150 | 9 |
| | 132 M/MU/SM | 200 | 180 | 150 | 14 |
| | 160 MP/MR/LR | 200 | 180 | 110 | 14 |
| | 160 L/LU | 200 | 180 | 110 | 14 |
| | 180 L | 200 | 260 | 150 | 14 |
| | 200 L/LR | 270 | 260 | 165 | 14 |
| | 225 ST/MT | 270 | 260 | 150 | 14 |
| | 250 ME | 400 | 400 | 500 | 30 |
| 280 SC/MC/MD | 400 | 400 | 500 | 30 | |

VERTICAL POSITION



| Series | Type | Vertical position | | | | | | |
|--------|-----------------|-------------------|-----|-----|-----|----|---------|--------|
| | | C | E | D | n** | ØS | min. e* | min. h |
| LSN | 160 M/L/LU | 320 | 200 | 230 | 2 | 14 | 320 | 350 |
| | 180 MR | 320 | 200 | 230 | 2 | 14 | 320 | 270 |
| | 180 L | 390 | 265 | 290 | 2 | 14 | 390 | 320 |
| | 200 L/LR | 410 | 300 | 295 | 2 | 14 | 410 | 450 |
| | 225 ST/MT/MR | 410 | 300 | 295 | 2 | 14 | 410 | 450 |
| | 250 ME | 500 | 400 | 502 | 4 | 30 | 500 | 500 |
| | 280 SC/SD/MC/MD | 500 | 400 | 502 | 4 | 30 | 500 | 500 |

* If the motor is fitted with a drip cover, allow an additional 50 to 100 mm to avoid damaging it when the load is swung.

** If n = 2, the lifting rings form an angle of 90° with respect to the terminal box axis.

If n = 4, this angle becomes 45°.


Separate ring ≤ 25 kg
Built-in ring > 25 kg

| | |
|---|---|
| ATEX DUST motors - Zone 21 | FLSPX series |
|  |  II 2 D Ex tb III C T125°C Db |
| | Premium Efficiency IE3 cast iron on mains IE3 cast iron on drive |
| | |



The complete motor **reference** described below will enable you to **order** the desired equipment.

The selection method consists of following the terms in the designation.




| | |
|---|---|
| ATEX DUST motors - Zone 22 | FLSES series |
|  |  II 3 D Ex tc III B T125°C Dc |
| | Premium Efficiency IE3 cast iron on mains IE3 cast iron on drive |
| | |



The complete motor **reference** described below will enable you to **order** the desired equipment.

The selection method consists of following the terms in the designation.



NAMEPLATES

The nameplate identifies the motors, indicates the main performance and shows compatibility of the motor

concerned with the main standards and regulations concerning them.

All motors in this catalogue with power between 0.75 and 400 kW are fitted with

two information plates: one indicating the motor's performance when supplied from the mains, and the other the motor's performance when supplied from a drive.

DEFINITION OF SYMBOLS USED ON NAMEPLATES



Legal mark indicating the conformity of equipment with the requirements of European Directives

SPECIAL MARKING (ATEX)



: protection marking against explosive risks

II 2D or II 3D : ATEX marking

Ex tb or tc : "dust" protection mode

IIIB or IIIC : "dust" equipment group

T125°C : max. surface temperature

Db or Dc : "dust" EPL level

0080 : INERIS Notified Body

INERIS 00ATEX0004X* : CE type examination certificate No.

* IECExINE10.0012X: IECEx certificate No.

| Zone | Type | ATEX marking | Marking of type of dust protection | Protection rating |
|------|----------------------------------|--|------------------------------------|-------------------|
| 21 | FLSPX |  II 2 D | Ex tb IIIC T125°C Db | IP65 |
| 22 | FLSES Non-conductive dusts |  II 3 D | Ex tc IIIB T125°C Dc | IP55 |

MAINS SUPPLY PLATE

MOT 3 ~ : three-phase AC motor

FLSPX : series

112 : frame size

MU : housing symbol

T : impregnation index

Motor no.

456789 : motor serial number

G : month of production

12 : year of production

001 : batch number

IE3 : efficiency class

88.6% : efficiency at 4/4 load

kg : weight

IP65 : protection rating

IK08 : shock resistance

I cl.F : insulation class F

40°C : max. ambient operating temperature

S1 : duty

V : supply voltage

Hz : supply frequency

min⁻¹ : speed of rotation

kW : rated power

cos φ : power factor

A : rated current

Δ : delta connection

Y : star connection

Bearings

DE : drive end.
Drive end bearing

NDE : non drive end.
Bearing side opposite the drive

g : amount of grease at each regreasing (in g)

h : regreasing interval (hours)

 : vibration level

 : balancing mode

DRIVE SUPPLY PLATE

Inverter settings : required values for setting the frequency inverter

Motor performance : torque available on the motor shaft in % rated torque at the plate frequencies

Min. Fsw (kHz) : minimum switching frequency acceptable for the motor

Nmax (min⁻¹) : maximum mechanical speed acceptable for the motor

INFORMATION PLATES CAST IRON MOTORS

FLSPX Zone 21 and FLSES Zone 22

Mains supply plate

MOT. 3~ FLSES 280 M4 B3  

N° E0776301EC01 2017 645 kg 0080

LEROIY-SOMER DE 6316 C3 13 g 18500 h IP 55 1000 m

NDE 6314 C3 10 g 18500 h IK 08 IM 1001

40 °C Ins. Cl. F S 1 % d/h SF 94,9 %

| V | Hz | min ⁻¹ | kW | A | cos φ | % |
|-------|----|-------------------|-----|-----|-------|------|
| Δ 400 | 50 | 1485 | 90 | 166 | 0,83 | 94,9 |
| Δ 415 | | 1485 | | 96 | | 96 |
| Δ 460 | 60 | 1785 | 104 | 164 | 0,84 | 95 |

POLYREX EM 103 PTC 140°C

II 3 D - Ex tc IIIB T125°C Dc EAC : Ex tc IIIB T125°C Dc X

Manufactured by CEB - F 90500 BEAUCOURT

INERIS 18ATEX3011X IECEX INE 19.0015X

279 E

Drive supply plate

MOT. 3~ FLSES 280 M4 B3  

N° E0776301EC01

Inverter settings PWM

| V | Hz | min ⁻¹ | kW | A | cos φ |
|-------|----|-------------------|----|-----|-------|
| Δ 400 | 50 | 1485 | 90 | 166 | 0,83 |

Motor performance valid for : 400 V - 50 Hz at inverter input

| Hz | 10 | 17 | 25 | 50 | 60 | 87 |
|-------|----|----|----|-----|-----|----|
| T/Tn% | 87 | 92 | 98 | 100 | 100 | 57 |

Duty S9 Min. Fsw : 3 kHz Nmax : 2610 min⁻¹

PTC 140°C

280 E

Nidec 3~2P FLSES100L  

LEROIY-SOMER IP55 IK08 T

Ta40°C Ins. Cl. F S1 1000m 35kg 87.1%

IECEX INE 10.0012X

II 3 D Ex tc IIIB T125°C Dc

DE 6206 ZZ C3 NDE 6205 ZZ C3

| V | Hz | min ⁻¹ | kW | cos φ | A |
|-------|----|-------------------|------|-------|------|
| Δ 380 | 50 | 2875 | 3.00 | 0.88 | 5.95 |
| Δ 230 | 50 | 2895 | 3.00 | 0.86 | 9.95 |
| Δ 400 | 50 | 2895 | 3.00 | 0.86 | 5.75 |
| Δ 415 | 50 | 2910 | 3.00 | 0.85 | 5.60 |
| Δ 480 | 60 | 3515 | 3.00 | 0.85 | 5.05 |

PTC 140°C

Nidec 3~2P FLSES100L  

LEROIY-SOMER IP55 IK08 T

Ta40°C Ins. Cl. F S9 1000m 35kg

IECEX INE 10.0012X

II 3 D Ex tc IIIB T125°C Dc

DE 6206 ZZ C3 NDE 6205 ZZ C3

Inverter settings

| V | Hz | min ⁻¹ | kW | cos φ | A |
|-------|----|-------------------|------|-------|------|
| Δ 400 | 50 | 2875 | 3.00 | 0.88 | 6.15 |

Motor performance

| Hz | 10 | 17 | 25 | 50 | 87 | min. Fsw (kHz) |
|-------|-----|-----|-----|-----|----|----------------|
| T/Tn% | 100 | 100 | 100 | 100 | 57 | 9.90 |

PTC 140°C

Nidec 3~4P FLSPX112MU  

LEROIY-SOMER IP65 IK08 T

Ta40°C Ins. Cl. F S1 1000m 88.6%

IECEX INE 10.0012X

II 2 D Ex tc IIIC T125°C Dc

DE 6206 ZZ C3 NDE 6205 ZZ C3

| V | Hz | min ⁻¹ | kW | cos φ | A |
|-------|----|-------------------|------|-------|------|
| Δ 230 | 50 | 1456 | 4.00 | 0.83 | 13.6 |
| Δ 400 | 50 | 1456 | 4.00 | 0.83 | 7.85 |
| Δ 415 | 50 | 1460 | 4.00 | 0.81 | 7.75 |
| Δ 480 | 60 | 1764 | 4.00 | 0.81 | 6.90 |

PTC 130°C

Nidec 3~4P FLSPX112MU  

LEROIY-SOMER IP65 IK08 T

Ta40°C Ins. Cl. F S9 1000m 49kg

IECEX INE 10.0012X

II 2 D Ex tc IIIC T125°C Dc

DE 6206 ZZ C3 NDE 6205 ZZ C3

Inverter settings

| V | Hz | min ⁻¹ | kW | cos φ | A |
|-------|----|-------------------|------|-------|------|
| Δ 400 | 50 | 1450 | 4.00 | 0.83 | 8.50 |

Motor performance

| Hz | 10 | 17 | 25 | 50 | 87 | min. Fsw (kHz) |
|-------|----|-----|-----|-----|----|----------------|
| T/Tn% | 90 | 100 | 100 | 100 | 57 | 26.2 |

PTC 130°C

Combustible dust is dangerous because it can form potentially explosive atmospheres when dispersed in the air.

Furthermore, a layer of combustible dust can ignite and act as a source of ignition in an explosive atmosphere.

Explosive dust atmospheres can be found in many industries, such as agriculture, chemicals, plastics and food and drink related industries.

FLSPX and FLSES cast iron motors are designed to prevent any explosion due to dust:

- The ingress of dust into the motor is prevented by the IP protection, either IP55 (dustproof for FLSES motors) or IP65 (dustproof for FLSPX).
- The maximum surface temperature outside the engine must not exceed the temperature class for which the motor is certified.
- No sparks must reach the outside of the motor enclosure.

These motors are certified to comply with Directive 2014/34/EU and the IECEx system regulations.

For zone 22 FLSES motors, Nidec Leroy-Somer also provides self-certification with a Declaration of Conformity.

| Designations | Materials | Comments |
|-------------------------------------|--|--|
| Finned housing | Cast iron | - lifting rings for frame size \geq 90 - ground terminal with an optional jumper screw - stainless steel nameplate with marking |
| Stator | Insulated low-carbon magnetic steel laminations Electroplated copper | - low carbon content guarantees long-term lamination pack stability - plate assemblies - semi-enclosed slots - class F insulation - 1 set of PTC sensors in the windings from FLSPX 80 to FLSPX 355 and from FLSES 80 zone 22 to FLSES 355 zone 22 |
| Rotor | Insulated low-carbon magnetic steel laminations Aluminium | - inclined cage bars - rotor cage pressure die-cast in aluminum (or alloys for special applications) or copper-soldered - assembly by hot shrinking on the shaft or by keying for soldered rotor - class A rotor balanced dynamically, 1/2 key |
| Shaft | Steel | - for frame size \leq 132: closed keyway - for frame size \geq 160: open keyway |
| End shields | Cast iron | |
| Bearings and lubrication | | - protected ball bearings, permanently greased for frame size 80 to 225 - protected ball bearings, regreasable for frame size 250 to 450 - preloaded bearings at the rear up to 315 S, at the front from 315 M |
| Labyrinth seal Lip seals | Technopolymer or steel Synthetic rubber | - labyrinth seal at front for foot mounted motors with frame size \leq 132 - front gasket for foot and face mounted motors or fastening flanges with frame size \leq 132 - gasket at front and rear for frame sizes 160 to 250 included - decompression grooves for 280 M to 355 LD - labyrinth seal at front and rear for frame sizes \geq 355 LK |
| Fan | antistatic thermoplastic or aluminium up to and including 280 Metallic from 315 S | - bi-directional: straight blades |
| Fan cover | Steel plate | - fitted, on request, with a drip cover for operation in vertical position, shaft end downwards |
| Terminal box | Body and cover in cast iron for all frame sizes | - IP 55 or IP 65 - fitted with a terminal block with 6 terminals up to 355 LD, 6 or 12 terminals for frame sizes 355LK/400/450 - terminal box fitted with plugs up to 132 - from 160 to 355, drilled cable gland support plate with plugs (FLSPX) or undrilled (FLSES) (optional flared feed and cable gland) - 1 ground terminal in each terminal box |



| Type | Rated power P _n kW | Rated torque M _n N.m | Starting torque/ Rated torque M _d /M _n | Maximum torque/ Rated torque M _m /M _n | Starting current/ Rated current I _d /I _n | Moment of inertia J kg.m ² | Weight IM B3 kg | Noise LP db(A) | 400V 50Hz | | | | | | | | |
|----------------|-------------------------------------|---------------------------------------|--|---|--|---|-----------------------|----------------------|--|--------------------------------------|-------------------------------------|------|------|--------------|--------------|------|------|
| | | | | | | | | | Rated speed N _n min ⁻¹ | Rated current I _n A | Efficiency IEC 60034-2-1 2007 | | | Power factor | | | |
| | | | | | | | | | | | 4/4 | 3/4 | 2/4 | 4/4 | Cos φ 3/4 | 2/4 | |
| 2 poles | | | | | | | | | | | | | | | | | |
| FLSPX FLSES | 80 L | 0.75 | 2.5 | 2.8 | 3.6 | 7 | 0.00095 | 16.2 | 59 | 2885 | 1.6 | 82.6 | 82.7 | 80.5 | 0.82 | 0.75 | 0.62 |
| | 80 LG | 1.1 | 3.7 | 2.41 | 3.11 | 6.82 | 0.00201 | 22.5 | 59 | 2885 | 2.2 | 85.6 | 86.6 | 85.9 | 0.85 | 0.79 | 0.68 |
| | 90 SL | 1.5 | 5 | 2.88 | 2.98 | 7 | 0.00223 | 24 | 68 | 2890 | 3 | 85.1 | 86.1 | 85.4 | 0.85 | 0.79 | 0.68 |
| | 90 LU | 2.2 | 7.3 | 3.38 | 3.23 | 8.05 | 0.00292 | 28.2 | 70 | 2895 | 4.3 | 87.0 | 88.2 | 88.1 | 0.86 | 0.80 | 0.70 |
| | 100 L | 3 | 9.9 | 3.2 | 3.6 | 8.03 | 0.00364 | 35.2 | 66 | 2895 | 5.8 | 87.1 | 88.1 | 87.8 | 0.86 | 0.81 | 0.70 |
| | 112 MG | 4 | 13.1 | 2.1 | 2.95 | 7.34 | 0.00941 | 44.8 | 66 | 2920 | 7.3 | 88.5 | 89.5 | 89.4 | 0.89 | 0.85 | 0.77 |
| | 132 SM | 5.5 | 17.9 | 2 | 2.8 | 6.39 | 0.00974 | 69.3 | 67 | 2935 | 10.3 | 90.0 | 90.8 | 90.4 | 0.86 | 0.82 | 0.73 |
| | 132 SM | 7.5 | 24.4 | 2.05 | 2.9 | 6.95 | 0.01102 | 74.6 | 67 | 2940 | 13.8 | 91.2 | 92.0 | 91.8 | 0.86 | 0.82 | 0.75 |
| | 160 M | 11 | 35.6 | 3.34 | 3.04 | 8.25 | 0.0712 | 120 | 68 | 2950 | 19.9 | 91.9 | 92.4 | 92.0 | 0.87 | 0.83 | 0.75 |
| | 160 M | 15 | 48.6 | 2.9 | 2.9 | 7.25 | 0.0551 | 133 | 68 | 2950 | 26.7 | 92.4 | 93.1 | 93.1 | 0.88 | 0.85 | 0.79 |
| | 160 LUR | 18.5 | 59.9 | 2.85 | 2.75 | 7.4 | 0.0626 | 135 | 69 | 2950 | 32.9 | 92.5 | 93.2 | 93.2 | 0.88 | 0.86 | 0.79 |
| | 180 MUR | 22 | 71.2 | 3 | 3.4 | 8.05 | 0.1012 | 195 | 74 | 2952 | 38 | 93.6 | 94.1 | 93.8 | 0.89 | 0.87 | 0.81 |
| | 200 LU | 30 | 97.1 | 2.1 | 3.05 | 7.25 | 0.1186 | 210 | 71 | 2950 | 53.1 | 93.9 | 94.3 | 94.0 | 0.87 | 0.84 | 0.77 |
| | 200 LU | 37 | 120 | 2.05 | 3.35 | 6.95 | 0.1388 | 230 | 75 | 2945 | 64.5 | 94.0 | 94.6 | 94.5 | 0.88 | 0.86 | 0.80 |
| | 225 MR | 45 | 145 | 2.27 | 3.07 | 7.17 | 0.1597 | 254 | 71 | 2956 | 81.8 | 94.4 | 94.7 | 94.4 | 0.84 | 0.80 | 0.70 |
| | 250 M | 55 | 177 | 2.1 | 3.2 | 7.65 | 0.3356 | 378 | 78 | 2968 | 95.3 | 94.5 | 94.6 | 93.7 | 0.88 | 0.85 | 0.79 |
| | 280 S | 75 | 241 | 2.1 | 2.7 | 7 | 0.48 | 565 | 79 | 2966 | 126 | 94.7 | 95.0 | 94.7 | 0.91 | 0.89 | 0.85 |
| | 280 M | 90 | 290 | 2.2 | 2.8 | 7.4 | 0.57 | 615 | 80 | 2967 | 151.1 | 95.1 | 95.4 | 95.1 | 0.90 | 0.89 | 0.85 |
| | 315 S | 110 | 353 | 2.1 | 2.6 | 6.7 | 1.17 | 940 | 82 | 2975 | 185 | 95.7 | 95.7 | 95.1 | 0.90 | 0.89 | 0.85 |
| | 315 M | 132 | 424 | 2.1 | 2.5 | 6.7 | 1.25 | 1015 | 82 | 2975 | 221 | 95.8 | 95.9 | 95.3 | 0.90 | 0.89 | 0.84 |
| | 315 LA | 160 | 514 | 2 | 2.9 | 6.59 | 1.34 | 1088 | 82 | 2975 | 268.6 | 95.9 | 95.9 | 95.3 | 0.90 | 0.89 | 0.84 |
| | 315 LB | 200 | 643 | 2.1 | 2.9 | 6.88 | 1.45 | 1150 | 82 | 2973 | 334.8 | 96.2 | 96.4 | 95.8 | 0.90 | 0.88 | 0.84 |
| | 355 LA | 250 | 802 | 2.2 | 2.9 | 6.8 | 3.02 | 1590 | 83 | 2978 | 428.2 | 95.9 | 95.9 | 95.1 | 0.88 | 0.86 | 0.80 |
| | 355 LB | 315 | 1008 | 2.6 | 3 | 7.76 | 3.62 | 1740 | 84 | 2983 | 539.5 | 96.2 | 96.2 | 96.0 | 0.88 | 0.86 | 0.82 |
| 355 LC | 355 | 1137 | 2.8 | 2.7 | 7.09 | 3.64 | 1740 | 84 | 2981 | 610.8 | 96.2 | 96.3 | 96.0 | 0.87 | 0.86 | 0.82 | |
| 355 LD | 400 | 1284 | 1.9 | 2.75 | 6.99 | 3.70 | 1770 | 84 | 2986 | 667.9 | 97.0 | 97.0 | 96.8 | 0.89 | 0.88 | 0.86 | |

For power > 400 kW, please contact us.

| 4 poles | | | | | | | | | | | | | | | | | |
|----------------|---------|------|------|------|------|------|---------|------|------|-------|-------|------|------|------|------|------|------|
| FLSPX FLSES | 80 LG | 0.75 | 5 | 2.18 | 3.12 | 6.41 | 0.00335 | 22 | 57 | 1452 | 1.7 | 83.8 | 84.4 | 83.1 | 0.79 | 0.71 | 0.58 |
| | 90 SL | 1.1 | 7.3 | 2.38 | 3.18 | 7.52 | 0.00418 | 24.6 | 48 | 1450 | 2.3 | 84.9 | 85.8 | 85.0 | 0.81 | 0.74 | 0.61 |
| | 90 LU | 1.5 | 9.9 | 2.84 | 3.54 | 7.21 | 0.00524 | 28.2 | 51 | 1454 | 3.3 | 85.4 | 85.8 | 84.1 | 0.78 | 0.70 | 0.56 |
| | 100 LR | 2.2 | 14.5 | 3.45 | 3.85 | 8.09 | 0.00676 | 36.4 | 49 | 1452 | 4.7 | 86.9 | 87.4 | 86.2 | 0.78 | 0.70 | 0.57 |
| | 100 LG | 3 | 19.6 | 2.45 | 3.25 | 7.22 | 0.01152 | 42.2 | 50 | 1462 | 6 | 88.7 | 89.3 | 88.7 | 0.82 | 0.76 | 0.64 |
| | 112 MU | 4 | 26.2 | 2.7 | 3.1 | 7.05 | 0.01429 | 49 | 50 | 1458 | 8.1 | 88.8 | 89.5 | 88.9 | 0.80 | 0.75 | 0.64 |
| | 132 SM | 5.5 | 35.9 | 2.85 | 3.65 | 8.35 | 0.02286 | 70.9 | 60 | 1462 | 10.5 | 90.1 | 90.7 | 90.2 | 0.84 | 0.78 | 0.67 |
| | 132 MR | 7.5 | 49.1 | 2.8 | 3.4 | 8.45 | 0.03313 | 89.4 | 61 | 1460 | 13.8 | 90.6 | 91.5 | 91.3 | 0.86 | 0.81 | 0.71 |
| | 160 M | 11 | 71.7 | 2.25 | 2.85 | 7.6 | 0.0712 | 115 | 59 | 1466 | 20.1 | 91.7 | 92.7 | 92.8 | 0.86 | 0.82 | 0.73 |
| | 160 LUR | 15 | 97.4 | 2.3 | 3.2 | 8.04 | 0.0954 | 140 | 58 | 1470 | 27.2 | 92.3 | 93.0 | 92.9 | 0.86 | 0.82 | 0.72 |
| | 180 M | 18.5 | 120 | 3.05 | 3.35 | 8.05 | 0.1333 | 165 | 67 | 1470 | 34.1 | 92.8 | 93.5 | 93.4 | 0.84 | 0.80 | 0.71 |
| | 180 LUR | 22 | 143 | 3.3 | 3.3 | 7.88 | 0.1555 | 190 | 68 | 1470 | 41.3 | 93.0 | 93.6 | 93.4 | 0.83 | 0.79 | 0.69 |
| | 200 LU | 30 | 194 | 3.05 | 2.9 | 7.25 | 0.2035 | 250 | 64 | 1474 | 54.9 | 93.9 | 94.4 | 94.2 | 0.84 | 0.80 | 0.70 |
| | 225 S | 37 | 238 | 2 | 2.65 | 6.75 | 0.5753 | 355 | 65 | 1484 | 67.5 | 94.0 | 94.4 | 94.1 | 0.84 | 0.80 | 0.71 |
| | 225 M | 45 | 289 | 2.11 | 2.71 | 6.68 | 0.6482 | 380 | 64 | 1486 | 84.4 | 94.9 | 95.2 | 94.9 | 0.81 | 0.76 | 0.66 |
| | 250 MR | 55 | 354 | 2.05 | 2.45 | 6.9 | 0.7701 | 440 | 67 | 1482 | 101 | 94.8 | 95.2 | 95.1 | 0.83 | 0.79 | 0.70 |
| | 280 S | 75 | 482 | 2.4 | 2.8 | 7.5 | 0.85 | 595 | 74 | 1484 | 137 | 95.0 | 95.2 | 94.9 | 0.83 | 0.79 | 0.69 |
| | 280 M | 90 | 579 | 2.7 | 2.7 | 7.89 | 0.98 | 645 | 74 | 1483 | 165.5 | 95.2 | 95.6 | 95.0 | 0.83 | 0.78 | 0.68 |
| | 315 S | 110 | 707 | 2.1 | 2.7 | 7.1 | 1.84 | 930 | 74 | 1486 | 196 | 95.5 | 95.6 | 95.0 | 0.85 | 0.81 | 0.73 |
| | 315 M | 132 | 848 | 2.8 | 2.8 | 6.8 | 2.09 | 985 | 74 | 1487 | 234 | 95.8 | 95.8 | 95.4 | 0.85 | 0.82 | 0.76 |
| | 315 LA | 160 | 1030 | 2.3 | 2.5 | 6.44 | 2.35 | 1045 | 74 | 1484 | 277 | 95.9 | 96.1 | 95.9 | 0.87 | 0.85 | 0.78 |
| | 315 LB | 200 | 1287 | 2.7 | 3 | 7.19 | 2.86 | 1245 | 75 | 1486 | 354.6 | 96.1 | 96.3 | 95.8 | 0.85 | 0.81 | 0.72 |
| | 355 LA | 250 | 1604 | 2.6 | 3.1 | 7.46 | 4.90 | 1445 | 80 | 1488 | 438.1 | 96.2 | 96.2 | 94.6 | 0.86 | 0.82 | 0.71 |
| | 355 LAL | 280 | 1798 | 2.3 | 2.9 | 7.3 | 5.80 | 1560 | 80 | 1489 | 483.3 | 96.1 | 96.2 | 95.7 | 0.87 | 0.84 | 0.74 |
| 355 LB | 315 | 2028 | 2.4 | 2.9 | 7.5 | 6.56 | 1720 | 80 | 1488 | 549 | 96.2 | 96.5 | 96.1 | 0.86 | 0.83 | 0.76 | |
| 355 LC | 355 | 2280 | 2.5 | 2.9 | 7.5 | 6.56 | 1720 | 80 | 1487 | 629 | 96.2 | 96.2 | 95.7 | 0.85 | 0.81 | 0.72 | |
| 355 LD | 400 | 2402 | 1.69 | 3.21 | 8.3 | 6.60 | 1750 | 80 | 1491 | 652.1 | 96.5 | 96.3 | 95.6 | 0.86 | 0.82 | 0.74 | |

For power > 400 kW, please contact us.

ATEX DUST - Zones 21 & 22 - Cast iron



| Type | Rated power P_n kW | Rated torque M_n N.m | Starting torque/ Rated torque M_d/M_n | Maximum torque/ Rated torque M_m/M_n | Starting current/ Rated current I_d/I_n | Moment of inertia J kg.m ² | Weight IM B3 kg | Noise LP db(A) | 400V 50Hz | | | | | | | | |
|----------------|----------------------------|------------------------------|---|--|---|---|-----------------------|----------------------|---|-----------------------------|-------------------------------------|------|------|--------------|-------------------|------|------|
| | | | | | | | | | Rated speed N_n min ⁻¹ | Rated current I_n A | Efficiency IEC 60034-2-1 2007 | | | Power factor | | | |
| | | | | | | | | | | | 4/4 | 3/4 | 2/4 | 4/4 | Cos ϕ 3/4 | 2/4 | |
| 6 poles | | | | | | | | | | | | | | | | | |
| FLSPX FLSES | 90 SL | 0.75 | 7.6 | 1.84 | 2.29 | 4.47 | 0.00378 | 24.2 | 40 | 950 | 1.9 | 79.1 | 80.1 | 78.3 | 0.72 | 0.63 | 0.49 |
| | 90 LU | 1.1 | 11 | 2.25 | 2.55 | 4.71 | 0.00519 | 29.3 | 57 | 954 | 2.8 | 81.7 | 82.3 | 80.3 | 0.71 | 0.62 | 0.48 |
| | 100 LG | 1.5 | 14.8 | 2.35 | 2.8 | 5.64 | 0.01523 | 41.3 | 47 | 966 | 3.6 | 83.8 | 84.4 | 82.9 | 0.72 | 0.63 | 0.50 |
| | 112 MU | 2.2 | 21.7 | 2.25 | 2.75 | 5.56 | 0.01899 | 49 | 45 | 968 | 5.4 | 84.5 | 85.1 | 83.5 | 0.70 | 0.62 | 0.49 |
| | 132 SM | 3 | 29.5 | 2.65 | 3.05 | 6.4 | 0.02528 | 65 | 50 | 972 | 6.8 | 87.3 | 87.7 | 86.3 | 0.73 | 0.66 | 0.53 |
| | 132 M | 4 | 39.4 | 2.4 | 2.9 | 6.27 | 0.03027 | 72.7 | 54 | 970 | 9.2 | 87.3 | 87.7 | 86.3 | 0.72 | 0.65 | 0.53 |
| | 132 MU | 5.5 | 54.4 | 2.65 | 2.8 | 6.36 | 0.03699 | 87 | 55 | 966 | 11.7 | 88.3 | 89.0 | 88.7 | 0.77 | 0.71 | 0.59 |
| | 160 MU | 7.5 | 73.2 | 2 | 3.05 | 6.45 | 0.1295 | 117 | 57 | 978 | 17.4 | 89.5 | 88.7 | 88.3 | 0.77 | 0.67 | 0.57 |
| | 180 L | 11 | 107 | 2.95 | 3.8 | 8.2 | 0.2048 | 170 | 61 | 982 | 22.6 | 91.0 | 91.3 | 90.3 | 0.77 | 0.70 | 0.58 |
| | 180 LUR | 15 | 146 | 3.25 | 2.75 | 7.45 | 0.2530 | 202 | 60 | 978 | 31.9 | 91.3 | 91.6 | 90.9 | 0.74 | 0.68 | 0.56 |
| | 200 LU | 18.5 | 181 | 2.45 | 3 | 7.02 | 0.2588 | 210 | 60 | 978 | 36.5 | 91.8 | 92.5 | 92.3 | 0.80 | 0.75 | 0.64 |
| | 200 LU | 22 | 214 | 2.8 | 3.55 | 7.35 | 0.2588 | 245 | 62 | 980 | 44.6 | 92.5 | 92.9 | 92.5 | 0.77 | 0.72 | 0.61 |
| | 225 M | 30 | 291 | 2.2 | 2.45 | 6.55 | 0.8802 | 342 | 65 | 986 | 55.3 | 93.2 | 93.7 | 93.4 | 0.84 | 0.80 | 0.71 |
| | 250 M | 37 | 358 | 2.45 | 2.65 | 6.95 | 0.9142 | 397 | 64 | 986 | 68.1 | 93.5 | 94.0 | 93.7 | 0.84 | 0.80 | 0.71 |
| | 280 S | 45 | 436 | 2.9 | 3.1 | 7.5 | 1.08 | 555 | 70 | 986 | 82 | 94.0 | 94.3 | 93.9 | 0.84 | 0.80 | 0.70 |
| | 280 M | 55 | 533 | 2.9 | 3.1 | 7.3 | 1.28 | 605 | 70 | 986 | 100 | 94.3 | 94.5 | 94.1 | 0.84 | 0.79 | 0.69 |
| | 315 S | 75 | 727 | 2 | 2.09 | 6.98 | 2.50 | 965 | 70 | 991 | 137.3 | 94.9 | 95.2 | 94.8 | 0.83 | 0.80 | 0.73 |
| | 315 M | 90 | 867 | 2.7 | 2 | 7 | 2.96 | 1035 | 69 | 991 | 165 | 95.0 | 95.3 | 95.0 | 0.83 | 0.80 | 0.72 |
| | 315 LA | 110 | 1066 | 2.8 | 2.2 | 6.6 | 3.44 | 1150 | 69 | 989 | 204.1 | 95.4 | 95.8 | 95.5 | 0.81 | 0.79 | 0.71 |
| | 315 LB | 132 | 1276 | 3.1 | 2.3 | 6.88 | 3.77 | 1165 | 67 | 992 | 247.6 | 95.7 | 95.9 | 95.5 | 0.80 | 0.76 | 0.67 |
| 355 LA | 160 | 1545 | 2 | 2.9 | 7.28 | 8.02 | 1520 | 76 | 993 | 283.8 | 96.0 | 96.0 | 95.3 | 0.85 | 0.81 | 0.73 | |
| 355 LB | 200 | 1930 | 1.9 | 2.7 | 7.06 | 9.84 | 1750 | 76 | 993 | 347.1 | 96.0 | 96.2 | 95.8 | 0.87 | 0.84 | 0.77 | |
| 355 LC | 250 | 2404 | 2.2 | 1.95 | 7.6 | 10.44 | 1800 | 76 | 993 | 455.4 | 96.2 | 96.1 | 95.4 | 0.82 | 0.78 | 0.67 | |

* For power > 250 kW, please contact us.



| Type | Rated power | 415V 50Hz | | | | 460V 60Hz | | | | |
|----------------|----------------------|-------------------------------------|---------------------|------------|--------------|-------------------------------------|---------------------|------------|--------------|------|
| | | Rated speed | Rated current | Efficiency | Power factor | Rated speed | Rated current | Efficiency | Power factor | |
| | P _n kW | N _n min ⁻¹ | I _n A | η 4/4 | Cos φ 4/4 | N _n min ⁻¹ | I _n A | η 4/4 | Cos φ 4/4 | |
| 2 poles | | | | | | | | | | |
| FLSPX FLSES | 80 L | 0.75 | 2895 | 1.6 | 83.0 | 0.79 | 3505 | 1.4 | 83.7 | 0.79 |
| | 80 LG | 1.1 | 2895 | 2.2 | 85.9 | 0.83 | 3505 | 2 | 84.8 | 0.83 |
| | 90 SL | 1.5 | 2900 | 3 | 85.3 | 0.83 | 3505 | 2.7 | 86.1 | 0.83 |
| | 90 LU | 2.2 | 2905 | 4.1 | 87.5 | 0.85 | 3510 | 3.7 | 88.2 | 0.85 |
| | 100 L | 3 | 2910 | 5.6 | 87.5 | 0.85 | 3515 | 5.1 | 88.3 | 0.85 |
| | 112 MG | 4 | 2930 | 7.2 | 88.9 | 0.88 | 3535 | 6.4 | 89.9 | 0.88 |
| | 132 SM | 5.5 | 2940 | 9.9 | 90.5 | 0.85 | 3545 | 9 | 90.8 | 0.85 |
| | 132 SM | 7.5 | 2945 | 13.5 | 91.5 | 0.85 | 3550 | 12 | 92.2 | 0.85 |
| | 160 M | 11 | 2954 | 19.4 | 92.4 | 0.85 | 3554 | 17.3 | 92.4 | 0.86 |
| | 160 M | 15 | 2956 | 25.7 | 92.7 | 0.87 | 3556 | 23 | 93.2 | 0.88 |
| | 160 LUR | 18.5 | 2952 | 31.8 | 92.7 | 0.87 | 3558 | 28.4 | 93.2 | 0.87 |
| | 180 MUR | 22 | 2958 | 37.1 | 93.8 | 0.88 | 3560 | 33.1 | 93.8 | 0.88 |
| | 200 LU | 30 | 2954 | 51.7 | 94.0 | 0.86 | 3554 | 46.4 | 94.0 | 0.87 |
| | 200 LU | 37 | 2950 | 62.8 | 94.3 | 0.87 | 3552 | 56.3 | 94.2 | 0.88 |
| | 225 MR | 45 | 2960 | 80.7 | 94.4 | 0.82 | 3564 | 70.6 | 95.1 | 0.84 |
| | 250 M | 55 | 2972 | 87.2 | 94.6 | 0.87 | 3574 | 83.3 | 94.3 | 0.88 |
| | 280 S | 75 | 2968 | 122 | 95.2 | 0.90 | 3566 | 110 | 94.1 | 0.91 |
| | 280 M | 90 | 2971 | 146 | 95.3 | 0.90 | 3567 | 132 | 95.0 | 0.90 |
| | 315 S | 110 | 2977 | 177.6 | 95.7 | 0.90 | 3575 | 161 | 95.0 | 0.90 |
| | 315 M | 132 | 2976 | 213.8 | 96.0 | 0.90 | 3575 | 193 | 95.4 | 0.90 |
| 315 LA | 160 | 2976 | 259.4 | 96.1 | 0.89 | 3575 | 233 | 95.8 | 0.90 | |
| 315 LB | 200 | 2974 | 323.3 | 96.5 | 0.89 | 3575 | 291 | 95.8 | 0.90 | |
| 355 LA | 250 | 2982 | 413.7 | 96.1 | 0.88 | 3578 | 372 | 95.8 | 0.88 | |
| 355 LB | 315 | 2985 | 524.2 | 96.1 | 0.87 | 3583 | 469 | 95.8 | 0.88 | |
| 355 LC | 355 | 2983 | 596.9 | 96.2 | 0.86 | 3581 | 535 | 95.8 | 0.87 | |
| 355 LD | 400 | 2988 | 646.1 | 97.2 | 0.89 | 3589 | 585 | 96.5 | 0.89 | |

For power > 400 kW, please contact us.

| 4 poles | | | | | | | | | | |
|----------------|---------|------|------|-------|------|------|------|-------|------|------|
| FLSPX FLSES | 80 LG | 0.75 | 1454 | 1.6 | 84.0 | 0.78 | 1762 | 1.5 | 85.7 | 0.76 |
| | 90 SL | 1.1 | 1454 | 2.3 | 84.9 | 0.79 | 1758 | 2.1 | 86.5 | 0.78 |
| | 90 LU | 1.5 | 1456 | 3.2 | 85.6 | 0.76 | 1762 | 2.9 | 86.9 | 0.75 |
| | 100 LR | 2.2 | 1456 | 4.7 | 87.0 | 0.76 | 1762 | 4.1 | 88.3 | 0.76 |
| | 100 LG | 3 | 1462 | 6 | 88.8 | 0.79 | 1768 | 5.2 | 89.9 | 0.80 |
| | 112 MU | 4 | 1462 | 8.1 | 89.4 | 0.78 | 1764 | 7.7 | 85.5 | 0.77 |
| | 132 SM | 5.5 | 1466 | 10.3 | 90.2 | 0.82 | 1768 | 9.2 | 91.7 | 0.82 |
| | 132 MR | 7.5 | 1464 | 13.5 | 91.0 | 0.85 | 1768 | 12.1 | 92.0 | 0.85 |
| | 160 M | 11 | 1468 | 19.5 | 92.2 | 0.85 | 1772 | 17.5 | 92.9 | 0.85 |
| | 160 LUR | 15 | 1474 | 26.8 | 92.6 | 0.84 | 1774 | 23.8 | 93.4 | 0.85 |
| | 180 M | 18.5 | 1472 | 33.5 | 93.0 | 0.83 | 1774 | 29.9 | 93.6 | 0.83 |
| | 180 LUR | 22 | 1474 | 40.2 | 93.2 | 0.82 | 1776 | 35.9 | 93.7 | 0.82 |
| | 200 LU | 30 | 1476 | 53.7 | 94.2 | 0.82 | 1780 | 48.3 | 94.5 | 0.83 |
| | 225 S | 37 | 1486 | 65.7 | 94.5 | 0.83 | 1786 | 59.4 | 94.5 | 0.83 |
| | 225 M | 45 | 1486 | 82.5 | 95.0 | 0.80 | 1788 | 74.1 | 95.3 | 0.80 |
| | 250 MR | 55 | 1484 | 98.4 | 95.0 | 0.82 | 1784 | 88.2 | 95.4 | 0.82 |
| | 280 S | 75 | 1486 | 132.6 | 94.8 | 0.83 | 1784 | 117 | 95.4 | 0.84 |
| | 280 M | 90 | 1487 | 163.1 | 94.9 | 0.81 | 1785 | 141 | 95.4 | 0.84 |
| | 315 S | 110 | 1487 | 193.5 | 95.3 | 0.83 | 1786 | 172 | 95.8 | 0.84 |
| | 315 M | 132 | 1487 | 229 | 95.7 | 0.84 | 1787 | 203 | 96.0 | 0.85 |
| | 315 LA | 160 | 1486 | 276.1 | 96.0 | 0.84 | 1784 | 245.6 | 96.2 | 0.85 |
| | 315 LB | 200 | 1487 | 345.4 | 95.9 | 0.84 | 1786 | 307 | 96.2 | 0.85 |
| | 355 LA | 250 | 1490 | 425.8 | 96.1 | 0.85 | 1788 | 379 | 96.2 | 0.86 |
| | 355 LAL | 280 | 1488 | 471.7 | 96.0 | 0.86 | 1787 | 420 | 96.2 | 0.87 |
| | 355 LB | 315 | 1488 | 530 | 96.2 | 0.86 | 1787 | 472 | 96.2 | 0.87 |
| | 355 LC | 355 | 1488 | 624.1 | 95.9 | 0.83 | 1786 | 532 | 96.2 | 0.87 |
| | 355 LD | 400 | 1492 | 645 | 96.3 | 0.84 | 1792 | 573.2 | 96.2 | 0.85 |

For power > 400 kW, please contact us.



| Type | Rated power | 415V 50Hz | | | | 460V 60Hz | | | | |
|----------------|-------------|----------------------------|---------------|---------------|-------------------|----------------------------|---------------|---------------|-------------------|------|
| | | Rated speed | Rated current | Efficiency | Power power | Rated speed | Rated current | Efficiency | Power factor | |
| | P_n kW | N_n min ⁻¹ | I_n A | η 4/4 | Cos ϕ 4/4 | N_n min ⁻¹ | I_n A | η 4/4 | Cos ϕ 4/4 | |
| 6 poles | | | | | | | | | | |
| FLSPX FLSES | 90 SL | 0.75 | 956 | 1.9 | 79.4 | 0.69 | 1160 | 1.7 | 82.5 | 0.67 |
| | 90 LU | 1.1 | 958 | 2.8 | 81.7 | 0.68 | - | - | - | - |
| | 100 LG | 1.5 | 970 | 3.6 | 84.1 | 0.69 | - | - | - | - |
| | 112 MU | 2.2 | 972 | 6.75 | 86.8 | 0.71 | - | - | - | - |
| | 132 SM | 3 | 974 | 9.15 | 87.0 | 0.70 | - | - | - | - |
| | 132 M | 4 | 972 | 11.5 | 88.5 | 0.75 | - | - | - | - |
| | 132 MU | 5.5 | 970 | 11.7 | 88.5 | 0.74 | - | - | - | - |
| | 160 MU | 7.5 | 980 | 17.1 | 89.6 | 0.74 | - | - | - | - |
| | 180 L | 11 | 984 | 22.3 | 91.2 | 0.75 | - | - | - | - |
| | 180 LUR | 15 | 982 | 31.7 | 91.4 | 0.72 | - | - | - | - |
| | 200 LU | 18.5 | 980 | 36 | 92.1 | 0.78 | - | - | - | - |
| | 200 LU | 22 | 984 | 42.2 | 92.7 | 0.74 | - | - | - | - |
| | 225 M | 30 | 986 | 53.9 | 93.3 | 0.83 | - | - | - | - |
| | 250 M | 37 | 986 | 66.5 | 93.7 | 0.83 | - | - | - | - |
| | 280 S | 45 | 987 | 80.9 | 94.1 | 0.82 | 1186 | 70.3 | 94.5 | 0.85 |
| | 280 M | 55 | 988 | 99 | 94.3 | 0.82 | 1186 | 87 | 94.5 | 0.84 |
| | 315 S | 75 | 992 | 134.4 | 94.7 | 0.82 | 1190 | 122 | 95.0 | 0.81 |
| | 315 M | 90 | 992 | 161 | 95.0 | 0.82 | 1191 | 145 | 95.0 | 0.82 |
| | 315 LA | 110 | 992 | 198.9 | 95.5 | 0.81 | 1191 | 176 | 95.8 | 0.82 |
| | 315 LB | 132 | 991 | 243.1 | 95.7 | 0.79 | 1190 | 217 | 95.8 | 0.80 |
| 355 LA | 160 | 994 | 276.2 | 96.0 | 0.84 | 1193 | 247 | 95.8 | 0.85 | |
| 355 LB | 200 | 994 | 338.6 | 96.0 | 0.86 | 1193 | 312 | 95.8 | 0.84 | |
| 355 LC | 250 | 994 | 454 | 95.9 | 0.80 | 1193 | 405 | 95.8 | 0.81 | |

For power > 250 kW, please contact us.



| Type | 400V 50Hz | | | | % Rated torque M_n at | | | | | 400V 87Hz Δ^1 | | | | Maximum mechanical speed ² | |
|----------------|-------------|----------------------------|---------------|-------------------|-------------------------|--------|--------|--------|--------|----------------------|----------------------------|---------------|-------------------|---------------------------------------|-------|
| | Rated power | Rated speed | Rated current | Power factor | 10Hz | 17Hz | 25Hz | 50Hz | 87Hz | Rated power | Rated speed | Rated current | Power factor | | |
| | P_n kW | N_n min ⁻¹ | I_n A | Cos ϕ 4/4 | | | | | | P_n kW | N_n min ⁻¹ | I_n A | Cos ϕ 4/4 | | |
| 2 poles | | | | | | | | | | | | | | | |
| FLSPX FLSES | 80 L | 0.75 | 2815 | 1.75 | 0.88 | 2.33 | 2.5 | 2.5 | 2.5 | 1.43 | 1.31 | 4928 | 3.13 | 0.88 | 13500 |
| | 80 L | 1.1 | 2825 | 2.5 | 0.87 | 3.27 | 3.7 | 3.7 | 3.7 | 2.11 | 1.91 | 4936 | 4.56 | 0.87 | 13500 |
| | 90 SL | 1.5 | 2830 | 3.3 | 0.89 | 4.19 | 5 | 5 | 5 | 2.85 | 2.61 | 4945 | 5.99 | 0.89 | 11700 |
| | 90 L | 2.2 | 2855 | 4.8 | 0.85 | 5.81 | 7.35 | 7.35 | 7.35 | 4.19 | 3.83 | 4945 | 8.85 | 0.85 | 11700 |
| | 100 L | 3 | 2830 | 6.35 | 0.89 | 8.45 | 10.1 | 10.1 | 10.1 | 5.76 | 5.22 | 4945 | 11.44 | 0.87 | 9900 |
| | 112 MG | 4 | 2910 | 8.15 | 0.88 | 12.18 | 13.1 | 13.1 | 13.1 | 7.47 | 6.96 | 5066 | 14.65 | 0.86 | 9900 |
| | 132 SM | 5.5 | 2910 | 11.1 | 0.87 | 15.07 | 18 | 18 | 18 | 10.26 | 9.57 | 5066 | 20.55 | 0.86 | 6700 |
| | 132 SM | 7.5 | 2920 | 15.1 | 0.86 | 20.42 | 24.4 | 24.4 | 24.4 | 13.91 | 13.05 | 5058 | 28.24 | 0.87 | 6700 |
| | 132 M | 9 | 2925 | 18.2 | 0.87 | 24.52 | 29.3 | 29.3 | 29.3 | 16.7 | 15.66 | 5066 | 33.06 | 0.86 | 6700 |
| | 160 M | 11 | 2940 | 21.5 | 0.88 | 28.14 | 35.6 | 35.6 | 35.6 | 20.29 | 19.14 | 5110 | 39.14 | 0.86 | 6030 |
| | 160 M | 15 | 2930 | 29 | 0.90 | 38.42 | 48.6 | 48.6 | 48.6 | 27.7 | 26.1 | 5101 | 52.36 | 0.89 | 6030 |
| | 160 L | 18.5 | 2935 | 35.6 | 0.90 | 47.59 | 57.19 | 60.2 | 60.2 | 34.31 | 32.19 | 5084 | 65.05 | 0.89 | 5670 |
| | 180 M | 22 | 2925 | 73.6 | 0.90 | 53.20 | 67.93 | 71.5 | 71.5 | 59.35 | 36.27 | 5092 | 74.34 | 0.88 | 5670 |
| | 200 LU | 30 | 2945 | 56.9 | 0.88 | 72.24 | 87.39 | 97.1 | 97.1 | 80.59 | - | - | - | - | 4500 |
| | 200 LU | 37 | 2935 | 69.4 | 0.89 | 89.28 | 108 | 120 | 120 | 99.6 | - | - | - | - | 4500 |
| | 225 MR | 45 | 2940 | 84.7 | 0.89 | 108.62 | 131.4 | 146 | 146 | 121.18 | - | - | - | - | 4320 |
| | 250 M | 55 | 2966 | 102 | 0.89 | 131.69 | 159.3 | 177 | 177 | 146.91 | - | - | - | - | 4050 |
| | 280 S | 75 | 2950 | 142 | 0.91 | 200 | 212.1 | 224.1 | 224.1 | - | - | - | - | - | 3600 |
| | 280 M | 90 | 2952 | 170 | 0.91 | 246.5 | 252.3 | 261 | 261 | - | - | - | - | - | 3600 |
| | 315S | 110 | 2966 | 207 | 0.90 | 353 | 353 | 353 | 353 | - | - | - | - | - | 3600 |
| | 315 M | 132 | 2966 | 249.3 | 0.90 | 402.8 | 411.3 | 424 | 424 | - | - | - | - | - | 3600 |
| | 315 LA | 160 | 2967 | 299.7 | 0.90 | 488.3 | 498.6 | 514 | 514 | - | - | - | - | - | 3600 |
| | 315 LB | 200 | 2965 | 373.6 | 0.90 | 540.1 | 553 | 572.3 | 572.3 | - | - | - | - | - | 3600 |
| | 355 LA | 250 | 2969 | 477 | 0.89 | 721.8 | 753.9 | 786 | 786 | - | - | - | - | - | 3600 |
| | 355 LB | 315 | 2974 | 599.3 | 0.88 | 836.6 | 836.6 | 846.7 | 846.7 | - | - | - | - | - | 3600 |
| | 355 LC | 355 | 2972 | 672.7 | 0.89 | 932.3 | 932.3 | 932.3 | 932.3 | - | - | - | - | - | 3600 |
| | 355 LD | 400 | 2987 | 744.3 | 0.90 | 1065.7 | 1091.4 | 1129.9 | 1129.9 | - | - | - | - | - | 3600 |

For power > 400 kW, please contact us.

| 4 poles | | | | | | | | | | | | | | | |
|----------------|---------|------|------|-------|------|--------|--------|--------|--------|--------|-------|------|--------|------|-------|
| FLSPX FLSES | 80 LG | 0.75 | 1435 | 1.8 | 0.82 | 4.14 | 4.95 | 4.95 | 4.95 | 2.82 | 1.31 | 2503 | 3.31 | 0.82 | 11700 |
| | 90 SL | 1.1 | 1430 | 2.5 | 0.84 | 6.11 | 7.3 | 7.3 | 7.3 | 4.16 | 1.91 | 2494 | 4.56 | 0.84 | 11700 |
| | 90 L | 1.5 | 1430 | 3.45 | 0.84 | 8.33 | 9.95 | 9.95 | 9.95 | 5.67 | 2.61 | 2494 | 6.17 | 0.84 | 9900 |
| | 100 L | 2.2 | 1435 | 4.8 | 0.85 | 12.14 | 14.5 | 14.5 | 14.5 | 8.27 | 3.83 | 2503 | 8.85 | 0.82 | 9900 |
| | 100 LG | 3 | 1445 | 6.4 | 0.86 | 16.49 | 19.7 | 19.7 | 19.7 | 11.23 | 5.22 | 2511 | 11.53 | 0.83 | 9900 |
| | 112 MU | 4 | 1440 | 8.5 | 0.86 | 22.01 | 26.3 | 26.3 | 26.3 | 14.99 | 6.96 | 2511 | 15.64 | 0.84 | 9900 |
| | 132 SM | 5.5 | 1450 | 11.5 | 0.86 | 30.13 | 36 | 36 | 36 | 20.52 | 9.57 | 2525 | 20.91 | 0.83 | 6700 |
| | 132 M | 7.5 | 1445 | 15.6 | 0.87 | 41.26 | 49.3 | 49.3 | 49.3 | 28.1 | 13.05 | 2518 | 27.88 | 0.85 | 6700 |
| | 132 M | 9 | 1450 | 18.5 | 0.86 | 49.47 | 59.1 | 59.1 | 59.1 | 33.69 | 15.66 | 2518 | 33.6 | 0.83 | 6700 |
| | 160 M | 11 | 1464 | 22.3 | 0.86 | 49.94 | 71.6 | 71.6 | 71.6 | 40.81 | 19.14 | 2543 | 40.21 | 0.84 | 6030 |
| | 160 L | 15 | 1458 | 30 | 0.87 | 68.36 | 98 | 98 | 98 | 55.86 | 26.1 | 2532 | 54.5 | 0.85 | 6030 |
| | 180 MT | 18.5 | 1460 | 37.2 | 0.86 | 84.4 | 121 | 121 | 121 | 68.97 | 31.73 | 2536 | 66.23 | 0.84 | 6030 |
| | 180 L | 22 | 1462 | 44.2 | 0.86 | 106.39 | 143 | 143 | 143 | 81.51 | 38.28 | 2539 | 80.42 | 0.84 | 6030 |
| | 200 LU | 30 | 1466 | 59.8 | 0.85 | 136.01 | 185.25 | 195 | 195 | 111.15 | 52.2 | 2546 | 109.54 | 0.83 | 4500 |
| | 225 SR | 37 | 1466 | 73.5 | 0.85 | 167.4 | 228 | 240 | 240 | 136.8 | 64.38 | 2546 | 134.92 | 0.83 | 4320 |
| | 225 M | 45 | 1484 | 89.1 | 0.83 | 228.45 | 289 | 289 | 289 | 164.73 | 78.3 | 2570 | 161.73 | 0.84 | 4050 |
| | 250 MR | 55 | 1480 | 108 | 0.84 | 279.84 | 354 | 354 | 354 | 201.78 | 95.7 | 2567 | 198.36 | 0.83 | 4050 |
| | 280 S | 75 | 1478 | 150.4 | 0.86 | 424.2 | 453.1 | 482 | 482 | 274.7 | - | - | - | - | 2160 |
| | 280 M | 90 | 1479 | 181.4 | 0.85 | 503.7 | 532.7 | 567.4 | 573.2 | 326.7 | - | - | - | - | 2160 |
| | 315 S | 110 | 1484 | 215.6 | 0.87 | 692.9 | 699.9 | 707 | 707 | 403 | - | - | - | - | 2160 |
| | 315 M | 132 | 1482 | 256.2 | 0.88 | 814.1 | 831 | 848 | 848 | 483.4 | - | - | - | - | 2160 |
| | 315 LA | 160 | 1479 | 309.6 | 0.88 | 896.1 | 947.6 | 1009.4 | 1009.4 | 575.4 | - | - | - | - | 2160 |
| | 315 LB | 200 | 1480 | 386.8 | 0.87 | 1042.4 | 1081.1 | 1119.7 | 1119.7 | 638.2 | - | - | - | - | 2160 |
| | 355 LA | 250 | 1482 | 479.2 | 0.88 | 1347.4 | 1443.6 | 1539.8 | 1539.8 | 877.7 | - | - | - | - | 2160 |
| | 355 LAL | 280 | 1487 | 541.8 | 0.87 | 1510.3 | 1546.3 | 1546.3 | 1600.2 | 912.1 | - | - | - | - | 2160 |
| | 355 LB | 315 | 1486 | 602.6 | 0.88 | 1622.4 | 1683.2 | 1764.4 | 1764.4 | 1005.7 | - | - | - | - | 2160 |
| | 355 LC | 355 | 1483 | 681.9 | 0.88 | 1892.4 | 1915.2 | 1938.0 | 1938.0 | 1104.7 | - | - | - | - | 2160 |
| | 355 LD | 400 | 2562 | 729.9 | 0.86 | 2138 | 2229 | 2306 | 2562 | 1510 | - | - | - | - | 2160 |


For power > 400 kW, please contact us.



| Type | 400V 50Hz | | | | % Rated torque M_n at | | | | | 400V 87Hz Δ^1 | | | | Maximum mechanical speed ² | |
|----------------|-------------|----------------------------|---------------|----------------------|-------------------------|--------|--------|--------|--------|----------------------|----------------------------|---------------|----------------------|---------------------------------------|-------|
| | Rated power | Rated speed | Rated current | Power factor | 10Hz | 17Hz | 25Hz | 50Hz | 87Hz | Rated power | Rated speed | Rated current | Power factor | | |
| | P_n kW | N_n min ⁻¹ | I_n A | Cos φ 4/4 | | | | | | P_n kW | N_n min ⁻¹ | I_n A | Cos φ 4/4 | | |
| 6 poles | | | | | | | | | | | | | | | |
| FLSPX FLSES | 90 SL | 0.75 | 940 | 2.1 | 0.74 | 5.65 | 7.6 | 7.6 | 7.6 | 4.33 | 1.31 | 1637 | 3.66 | 0.70 | 11700 |
| | 90 L | 1.1 | 930 | 3 | 0.74 | 8.33 | 11.2 | 11.2 | 11.2 | 6.38 | 1.91 | 1628 | 5.36 | 0.71 | 11700 |
| | 100 LG | 1.5 | 930 | 3.75 | 0.71 | 14.9 | 14.9 | 14.9 | 14.9 | 8.56 | 1.5 | 930 | 3.75 | 0.71 | 9900 |
| | 112 MG | 2.2 | 954 | 5.7 | 0.75 | 15.28 | 20.81 | 21.9 | 21.9 | 12.48 | 2.2 | 954 | 5.70 | 0.75 | 9900 |
| | 132 SM | 3 | 960 | 7.25 | 0.77 | 24.86 | 29.7 | 29.7 | 29.7 | 16.93 | 5.22 | 1673 | 13.13 | 0.74 | 6700 |
| | 132 M | 4 | 954 | 9.45 | 0.79 | 31.38 | 37.72 | 39.7 | 39.7 | 22.63 | 6.96 | 1666 | 17.07 | 0.77 | 6700 |
| | 132 M | 5.5 | 960 | 12.9 | 0.75 | 43 | 51.68 | 54.4 | 54.4 | 31.01 | 9.57 | 1673 | 23.95 | 0.73 | 6700 |
| | 160 M | 7.5 | 970 | 17.4 | 0.77 | 61.44 | 73.4 | 73.4 | 73.4 | 41.84 | 13.05 | 1690 | 30.92 | 0.84 | 6030 |
| | 160 LUR | 11 | 972 | 24.7 | 0.79 | 90.4 | 108 | 108 | 108 | 61.56 | 19.14 | 1687 | 44.32 | 0.84 | 6030 |
| | 180 L | 15 | 964 | 32 | 0.84 | 124.71 | 149 | 149 | 149 | 84.93 | 26.1 | 1684 | 58.26 | 0.84 | 6030 |
| | 200 LU | 18.5 | 974 | 39.6 | 0.81 | 134.66 | 181 | 181 | 181 | 103.17 | 32.19 | 1694 | 71.12 | 0.84 | 4500 |
| | 200 LU | 22 | 968 | 45.8 | 0.83 | 160.7 | 216 | 216 | 216 | 123.12 | 38.28 | 1684 | 85.42 | 0.84 | 4500 |
| | 225 M | 30 | 984 | 58.9 | 0.86 | 243.57 | 291 | 291 | 291 | 165.87 | 30 | 984 | 58.90 | 0.86 | 4050 |
| | 250 M | 37 | 984 | 72.2 | 0.86 | 299.65 | 358 | 358 | 358 | 204.06 | 64.38 | 1708 | 131.17 | 0.85 | 4050 |
| | 280 S | 45 | 983 | 90.4 | 0.87 | 422.9 | 427.3 | 436 | 436 | 248.5 | - | - | - | - | 1740 |
| | 280 M | 55 | 982 | 109.5 | 0.87 | 490.4 | 511.7 | 533 | 533 | 303.8 | - | - | - | - | 1740 |
| | 315 S | 75 | 990 | 154.2 | 0.84 | 727 | 727 | 727 | 727 | 414.4 | - | - | - | - | 1740 |
| | 315 M | 90 | 990 | 184 | 0.84 | 868 | 867 | 867 | 867 | 494.2 | - | - | - | - | 1740 |
| | 315 LA | 110 | 987 | 228.7 | 0.83 | 1023.4 | 1044.7 | 1066 | 1066 | 607.6 | - | - | - | - | 1740 |
| | 315 LB | 132 | 989 | 273.5 | 0.82 | 1033.6 | 1071.8 | 1110.1 | 1110.1 | 632.8 | - | - | - | - | 1740 |
| | 355 LA | 160 | 990 | 311.6 | 0.87 | 1545 | 1545 | 1545 | 1545 | 880.7 | - | - | - | - | 1740 |
| | 355 LB | 200 | 990 | 386.1 | 0.88 | 1910.7 | 1910.7 | 1930 | 1930 | 1100.1 | - | - | - | - | 1740 |
| | 355 LC | 250 | 992 | 486.3 | 0.87 | 2283.8 | 2331.9 | 2380 | 2380 | 1356.6 | - | - | - | - | 1740 |

For power > 250 kW, please contact us.

Dimensions in millimetres



| Type | Main shaft end | | | | | | | | | | | | | | | | | |
|---------------------|----------------|----|-------|------|-----|-----|----|-----|----|---------|----|------|------|-----|-----|----|-----|----|
| | 4 and 6 poles | | | | | | | | | 2 poles | | | | | | | | |
| | F | GD | D | G | E | O | p | L | LO | F | GD | D | G | E | O | p | L | LO |
| 80 L/LG | 6 | 6 | 19j6 | 15.5 | 40 | M6 | 16 | 30 | 6 | 6 | 6 | 19j6 | 15.5 | 40 | M6 | 16 | 30 | 6 |
| 90 L/LU/SL | 8 | 7 | 24j6 | 20 | 50 | M8 | 19 | 40 | 6 | 8 | 7 | 24j6 | 20 | 50 | M8 | 19 | 40 | 6 |
| 100 L/LG/LR | 8 | 7 | 28j6 | 24 | 60 | M10 | 22 | 50 | 6 | 8 | 7 | 28j6 | 24 | 60 | M10 | 22 | 50 | 6 |
| 112 MG/MU | 8 | 7 | 28j6 | 24 | 60 | M10 | 22 | 50 | 6 | 8 | 7 | 28j6 | 24 | 60 | M10 | 22 | 50 | 6 |
| 132 M/MR/MU/SM | 10 | 8 | 38k6 | 33 | 80 | M12 | 28 | 63 | 10 | 10 | 8 | 38k6 | 33 | 80 | M12 | 28 | 63 | 10 |
| 160 L/LUR/M/MU | 12 | 8 | 42k6 | 37 | 110 | M16 | 36 | 90 | 20 | 12 | 8 | 42k6 | 37 | 110 | M16 | 36 | 90 | 20 |
| 180 L/LUR/M/MT/MUR | 14 | 9 | 48k6 | 42.5 | 110 | M16 | 36 | 90 | 20 | 14 | 9 | 48k6 | 42.5 | 110 | M16 | 36 | 90 | 20 |
| 200 LU | 16 | 10 | 55m6 | 49 | 110 | M20 | 42 | 90 | 20 | 16 | 10 | 55m6 | 49 | 110 | M20 | 42 | 90 | 20 |
| 225 M/S/SR | 18 | 11 | 60m6 | 53 | 140 | M20 | 42 | 125 | 15 | - | - | - | - | - | - | - | - | - |
| 225 MR | - | - | - | - | - | - | - | - | - | 16 | 10 | 55m6 | 49 | 110 | M20 | 42 | 90 | 20 |
| 250 M | 18 | 11 | 65m6 | 58 | 140 | M20 | 42 | 125 | 15 | 18 | 11 | 60m6 | 53 | 140 | M20 | 42 | 125 | 15 |
| 250 MR | 18 | 11 | 65m6 | 58 | 140 | M20 | 42 | 125 | 15 | - | - | - | - | - | - | - | - | - |
| 280 M/S | 20 | 12 | 75m6 | 67.5 | 140 | M20 | 42 | 125 | 15 | 18 | 11 | 65m6 | 58 | 140 | M20 | 42 | 125 | 15 |
| 315 LA/LB | 25 | 14 | 90m6 | 81 | 170 | M24 | 50 | 140 | 30 | 20 | 12 | 70m6 | 62.5 | 140 | M20 | 42 | 125 | 15 |
| 315 M/S | 22 | 14 | 80m6 | 71 | 170 | M20 | 42 | 140 | 30 | 18 | 11 | 65m6 | 58 | 140 | M20 | 42 | 125 | 15 |
| 355 LA/LAL/LB/LC/LD | 28 | 16 | 100m6 | 90 | 210 | M24 | 50 | 180 | 30 | 22 | 14 | 80m6 | 71 | 170 | M20 | 42 | 140 | 30 |

| Type | Secondary shaft ends | | | | | | | | | | | | | | | | | |
|---------------------|----------------------|----|-------|------|-----|-----|----|-----|-----|---------|----|------|------|-----|-----|----|-----|-----|
| | 4 and 6 poles | | | | | | | | | 2 poles | | | | | | | | |
| | F | GD | D | G | E | O | p | L' | LO' | F | GD | D | G | E | O | p | L' | LO' |
| 80 L | 5 | 5 | 14j6 | 11 | 30 | M5 | 15 | 25 | 3.5 | 5 | 5 | 14j6 | 11 | 30 | M5 | 15 | 25 | 3.5 |
| 80 LG | 6 | 6 | 19j6 | 15.5 | 40 | M6 | 16 | 30 | 6 | 6 | 6 | 19j6 | 15.5 | 40 | M6 | 16 | 30 | 6 |
| 90 L/LU/SL | 6 | 6 | 19j6 | 15.5 | 40 | M6 | 16 | 30 | 6 | 6 | 6 | 19j6 | 15.5 | 40 | M6 | 16 | 30 | 6 |
| 100 L/LG/LR | 8 | 7 | 24j6 | 20 | 50 | M8 | 19 | 40 | 6 | 8 | 7 | 24j6 | 20 | 50 | M8 | 19 | 40 | 6 |
| 112 MG/MU | 8 | 7 | 24j6 | 20 | 50 | M8 | 19 | 40 | 6 | 8 | 7 | 24j6 | 20 | 50 | M8 | 19 | 40 | 6 |
| 132 M/MR/MU/SM | 8 | 7 | 28k6 | 24 | 60 | M10 | 22 | 50 | 6 | 8 | 7 | 28k6 | 24 | 60 | M10 | 22 | 50 | 6 |
| 160 L/LUR/M/MU | 12 | 8 | 42k6 | 37 | 110 | M16 | 36 | 90 | 20 | 12 | 8 | 42k6 | 37 | 110 | M16 | 36 | 90 | 20 |
| 180 L/LUR/M/MT/MUR | 14 | 9 | 48k6 | 42.5 | 110 | M16 | 36 | 90 | 20 | 14 | 9 | 48k6 | 42.5 | 110 | M16 | 36 | 90 | 20 |
| 200 LU | 16 | 10 | 55m6 | 49 | 110 | M20 | 42 | 90 | 20 | 16 | 10 | 55m6 | 49 | 110 | M20 | 42 | 90 | 20 |
| 225 M/S/SR | 18 | 11 | 60m6 | 53 | 140 | M20 | 42 | 125 | 15 | - | - | - | - | - | - | - | - | - |
| 225 MR | - | - | - | - | - | - | - | - | - | 16 | 10 | 55m6 | 49 | 110 | M20 | 42 | 90 | 20 |
| 250 M | 18 | 11 | 60m6 | 53 | 140 | M20 | 42 | 125 | 15 | 18 | 11 | 60m6 | 53 | 140 | M20 | 42 | 125 | 15 |
| 250 MR | 18 | 11 | 60m6 | 53 | 140 | M20 | 42 | 125 | 15 | - | - | - | - | - | - | - | - | - |
| 280 M/S | 18 | 11 | 60m6 | 53 | 140 | M20 | 42 | 125 | 15 | 18 | 11 | 60m6 | 53 | 140 | M20 | 42 | 125 | 15 |
| 315 LA/LB | 20 | 12 | 70m6 | 63.5 | 140 | M20 | 42 | 125 | 15 | 20 | 12 | 70m6 | 63.5 | 140 | M20 | 42 | 125 | 15 |
| 315 M/S | 20 | 12 | 70m6 | 63.5 | 140 | M20 | 42 | 125 | 15 | 18 | 11 | 65m6 | 58 | 140 | M20 | 42 | 125 | 15 |
| 355 LA/LAL/LB/LC/LD | 28 | 16 | 100m6 | 90 | 210 | M24 | 50 | 180 | 30 | 22 | 14 | 80m6 | 71 | 170 | M20 | 42 | 140 | 30 |

ATEX DUST - Zones 21 & 22 - Cast iron


IMfinity® ATEX 3-phase induction motors - IE3 efficiency class

ATEX DUST motors - Zones 21 & 22

FLSPX & FLSES series - Cast iron

Mechanical characteristics - Foot mounted IM 1001 (IMB3)

Dimensions in millimetres




| Type | Main dimensions | | | | | | | | | | | | | | | | | | |
|---------|-----------------|-----|-----|-----|-------|----|-----|------|----|-----|-----|-----|------|------|-----|-----|-----|-----|------|
| | A | AB | B | BB | C | x | AA | K | HA | H | AC* | HD | LB | LJ | J | I | II | AD | AD1 |
| 80 L | 125 | 157 | 100 | 130 | 50 | 18 | 34 | 10 | 10 | 80 | 170 | 228 | 212 | 7 | 136 | 68 | 68 | - | - |
| 80 LG | 125 | 170 | 100 | 138 | 50 | 22 | 39 | 10 | 10 | 80 | 203 | 238 | 245 | 8 | 136 | 68 | 68 | 135 | 41 |
| 90 L | 140 | 170 | 125 | 162 | 56 | 28 | 33 | 10 | 10 | 90 | 203 | 248 | 239 | 8 | 136 | 68 | 68 | 135 | 41 |
| 90 LU | 140 | 170 | 125 | 162 | 56 | 28 | 33 | 10 | 10 | 90 | 203 | 248 | 266 | 8 | 136 | 68 | 68 | 135 | 41 |
| 90 SL | 140 | 170 | 125 | 162 | 56 | 28 | 33 | 10 | 10 | 90 | 203 | 248 | 239 | 8 | 136 | 68 | 68 | 135 | 41 |
| 100 L | 160 | 196 | 140 | 185 | 63 | 29 | 40 | 12 | 13 | 100 | 204 | 258 | 300 | 8 | 136 | 68 | 68 | 135 | 41 |
| 100 LG | 160 | 196 | 140 | 168 | 53 | 13 | 40 | 12 | 14 | 100 | 227 | 266 | 299 | 0.5 | 136 | 68 | 68 | 130 | 45 |
| 100 LR | 160 | 196 | 140 | 185 | 63 | 29 | 40 | 12 | 13 | 100 | 204 | 258 | 300 | 8 | 136 | 68 | 68 | 135 | 41 |
| 112 MG | 190 | 230 | 140 | 186 | 60 | 32 | 48 | 12 | 12 | 112 | 230 | 294 | 299 | 8 | 136 | 68 | 68 | 148 | 41 |
| 112 MU | 190 | 230 | 140 | 186 | 60 | 32 | 48 | 12 | 12 | 112 | 230 | 294 | 299 | 8 | 136 | 68 | 68 | 148 | 41 |
| 132 M | 216 | 255 | 178 | 240 | 89 | 50 | 63 | 12 | 16 | 132 | 270 | 335 | 385 | 22 | 136 | 68 | 68 | 165 | 37.5 |
| 132 MR | 216 | 255 | 178 | 240 | 89 | 50 | 63 | 12 | 16 | 132 | 270 | 335 | 447 | 22 | 136 | 68 | 68 | 165 | 37.5 |
| 132 MU | 216 | 255 | 178 | 240 | 89 | 50 | 63 | 12 | 16 | 132 | 270 | 335 | 447 | 22 | 136 | 68 | 68 | 165 | 37.5 |
| 132 SM | 216 | 255 | 140 | 240 | 89 | 50 | 63 | 12 | 16 | 132 | 270 | 335 | 385 | 22 | 136 | 68 | 68 | 165 | 37.5 |
| 160 L | 254 | 294 | 254 | 294 | 108 | 20 | 65 | 14.5 | 20 | 160 | 315 | 449 | 495 | 23 | 259 | 115 | 151 | 179 | 45 |
| 160 LUR | 254 | 294 | 254 | 294 | 108 | 20 | 65 | 14.5 | 20 | 160 | 315 | 449 | 510 | 23 | 259 | 115 | 151 | 179 | 45 |
| 160 M | 254 | 294 | 210 | 294 | 108 | 20 | 65 | 14.5 | 20 | 160 | 315 | 449 | 495 | 23 | 259 | 115 | 151 | 179 | 45 |
| 160 MU | 254 | 294 | 210 | 294 | 108 | 20 | 65 | 14.5 | 20 | 160 | 315 | 449 | 510 | 23 | 259 | 115 | 151 | 179 | 45 |
| 180 L | 279 | 330 | 279 | 337 | 121 | 32 | 70 | 14.5 | 28 | 180 | 361 | 490 | 552 | 35.5 | 259 | 115 | 151 | 190 | 45 |
| 180 LUR | 279 | 330 | 279 | 337 | 115 | 32 | 70 | 14.5 | 28 | 180 | 361 | 490 | 593 | 35.5 | 259 | 115 | 151 | 190 | 45 |
| 180 M | 279 | 330 | 241 | 337 | 121 | 32 | 70 | 14.5 | 28 | 180 | 361 | 490 | 552 | 35.5 | 259 | 115 | 151 | 190 | 45 |
| 180 MT | 279 | 330 | 241 | 337 | 121 | 32 | 70 | 14.5 | 28 | 180 | 361 | 490 | 537 | 29.5 | 259 | 115 | 151 | 190 | 45 |
| 180 MUR | 279 | 324 | 241 | 290 | 121 | 24 | 80 | 14.5 | 25 | 180 | 328 | 469 | 551 | 29.5 | 259 | 115 | 151 | 177 | 45 |
| 200 LU | 318 | 374 | 305 | 360 | 135 | 28 | 60 | 18.5 | 17 | 200 | 399 | 541 | 669 | 42.5 | 259 | 115 | 151 | 243 | 45 |
| 225 M | 356 | 426 | 311 | 375 | 149 | 32 | 80 | 18.5 | 27 | 225 | 495 | 648 | 779 | 69.5 | 352 | 175 | 212 | 270 | 45 |
| 225 MR | 356 | 426 | 311 | 380 | 144.5 | 34 | 70 | 18.5 | 17 | 225 | 398 | 566 | 682 | 49 | 259 | 115 | 151 | 243 | 45 |
| 225 S | 356 | 426 | 286 | 375 | 149 | 32 | 80 | 18.5 | 27 | 225 | 487 | 661 | 779 | 91.5 | 308 | 161 | 208 | 276 | 45 |
| 225 SR | 356 | 426 | 286 | 380 | 144.5 | 34 | 70 | 18.5 | 17 | 225 | 398 | 566 | 674 | 44.5 | 259 | 115 | 151 | 243 | 45 |
| 250 M | 406 | 476 | 349 | 413 | 168 | 32 | 80 | 24 | 26 | 250 | 495 | 682 | 779 | 91.5 | 308 | 161 | 208 | 270 | 45 |
| 250 MR | 406 | 476 | 349 | 413 | 168 | 32 | 80 | 24 | 27 | 250 | 495 | 673 | 859 | 69.5 | 352 | 175 | 212 | 270 | 45 |
| 280 M | 457 | 527 | 419 | 486 | 92 | 33 | 80 | 24 | 30 | 280 | 481 | 717 | 959 | 69 | 352 | 175 | 212 | 303 | 45 |
| 280 S | 457 | 527 | 368 | 486 | 92 | 33 | 80 | 24 | 30 | 280 | 481 | 717 | 959 | 69 | 352 | 175 | 212 | 303 | 45 |
| 315 LA | 508 | 600 | 508 | 610 | 109 | 58 | 100 | 28 | 35 | 315 | 600 | 857 | 1177 | 119 | 416 | 217 | 264 | 343 | 45 |
| 315 LB | 508 | 600 | 508 | 610 | 109 | 58 | 100 | 28 | 35 | 315 | 600 | 847 | 1177 | 101 | 452 | 219 | 269 | 343 | 45 |
| 315 M | 508 | 600 | 457 | 610 | 109 | 58 | 100 | 28 | 35 | 315 | 600 | 857 | 1177 | 119 | 416 | 217 | 264 | 343 | 45 |
| 315 S | 508 | 600 | 406 | 610 | 109 | 58 | 100 | 28 | 35 | 315 | 600 | 857 | 1177 | 119 | 416 | 217 | 264 | 343 | 45 |
| 355 LA | 610 | 710 | 630 | 756 | 127 | 76 | 100 | 28 | 35 | 355 | 688 | 925 | 1303 | 121 | 452 | 219 | 269 | - | - |
| 355 LAL | 610 | 710 | 630 | 756 | 127 | 76 | 100 | 28 | 35 | 355 | 688 | 925 | 1303 | 121 | 452 | 219 | 269 | - | - |
| 355 LB | 610 | 710 | 630 | 756 | 127 | 76 | 100 | 28 | 35 | 355 | 688 | 925 | 1303 | 121 | 452 | 219 | 269 | - | - |
| 355 LC | 610 | 710 | 630 | 756 | 127 | 76 | 100 | 28 | 35 | 355 | 688 | 925 | 1303 | 121 | 452 | 219 | 269 | - | - |
| 355 LD | 610 | 710 | 630 | 756 | 127 | 76 | 100 | 28 | 35 | 355 | 688 | 925 | 1303 | 121 | 452 | 219 | 269 | - | - |

* AC: housing diameter without lifting rings

ATEX DUST - Zones 21 & 22 - Cast iron

Dimensions in millimetres



| Type | Main dimensions | | | | | | | | | | | | | | | | | | | |
|---------|-----------------|-----|-----|-----|-------|----|-----|------|----|-----|-----|-----|------|------|-----|-----|-----|-----|------|-------|
| | A | AB | B | BB | C | x | AA | K | HA | H | AC* | HD | LB | LJ | J | I | II | AD | AD1 | Symb |
| 80 L | 125 | 157 | 100 | 130 | 50 | 18 | 34 | 10 | 10 | 80 | 170 | 228 | 212 | 7 | 136 | 68 | 68 | - | - | FF165 |
| 80 LG | 125 | 170 | 100 | 138 | 50 | 22 | 39 | 10 | 10 | 80 | 203 | 238 | 245 | 8 | 136 | 68 | 68 | 135 | 41 | FF165 |
| 90 L | 140 | 170 | 125 | 162 | 56 | 28 | 33 | 10 | 10 | 90 | 203 | 248 | 239 | 8 | 136 | 68 | 68 | 135 | 41 | FF165 |
| 90 LU | 140 | 170 | 125 | 162 | 56 | 28 | 33 | 10 | 10 | 90 | 203 | 248 | 266 | 8 | 136 | 68 | 68 | 135 | 41 | FF165 |
| 90 SL | 140 | 170 | 125 | 162 | 56 | 28 | 33 | 10 | 10 | 90 | 203 | 248 | 239 | 8 | 136 | 68 | 68 | 135 | 41 | FF165 |
| 100 L | 160 | 196 | 140 | 185 | 63 | 29 | 40 | 12 | 13 | 100 | 204 | 258 | 300 | 8 | 136 | 68 | 68 | 135 | 41 | FF215 |
| 100 LG | 160 | 196 | 140 | 168 | 53 | 13 | 40 | 12 | 14 | 100 | 227 | 266 | 299 | 0.5 | 136 | 68 | 68 | 130 | 45 | FF215 |
| 100 LR | 160 | 196 | 140 | 185 | 63 | 29 | 40 | 12 | 13 | 100 | 204 | 258 | 300 | 8 | 136 | 68 | 68 | 135 | 41 | FF215 |
| 112 MG | 190 | 230 | 140 | 186 | 60 | 32 | 48 | 12 | 12 | 112 | 230 | 294 | 299 | 8 | 136 | 68 | 68 | 148 | 41 | FF215 |
| 112 MU | 190 | 230 | 140 | 186 | 60 | 32 | 48 | 12 | 12 | 112 | 230 | 294 | 299 | 8 | 136 | 68 | 68 | 148 | 41 | FF215 |
| 132 M | 216 | 255 | 178 | 240 | 89 | 50 | 63 | 12 | 16 | 132 | 270 | 335 | 385 | 22 | 136 | 68 | 68 | 165 | 37.5 | FF265 |
| 132 MR | 216 | 255 | 178 | 240 | 89 | 50 | 63 | 12 | 16 | 132 | 270 | 335 | 447 | 22 | 136 | 68 | 68 | 165 | 37.5 | FF265 |
| 132 MU | 216 | 255 | 178 | 240 | 89 | 50 | 63 | 12 | 16 | 132 | 270 | 335 | 447 | 22 | 136 | 68 | 68 | 165 | 37.5 | FF265 |
| 132 SM | 216 | 255 | 140 | 240 | 89 | 50 | 63 | 12 | 16 | 132 | 270 | 335 | 385 | 22 | 136 | 68 | 68 | 165 | 37.5 | FF265 |
| 160 L | 254 | 294 | 254 | 294 | 108 | 20 | 65 | 14.5 | 20 | 160 | 315 | 449 | 495 | 23 | 259 | 115 | 151 | 179 | 45 | FF265 |
| 160 LUR | 254 | 294 | 254 | 294 | 108 | 20 | 65 | 14.5 | 20 | 160 | 315 | 449 | 510 | 23 | 259 | 115 | 151 | 179 | 45 | FF300 |
| 160 M | 254 | 294 | 210 | 294 | 108 | 20 | 65 | 14.5 | 20 | 160 | 315 | 449 | 495 | 23 | 259 | 115 | 151 | 179 | 45 | FF300 |
| 160 MU | 254 | 294 | 210 | 294 | 108 | 20 | 65 | 14.5 | 20 | 160 | 315 | 449 | 510 | 23 | 259 | 115 | 151 | 179 | 45 | FF300 |
| 180 L | 279 | 330 | 279 | 337 | 121 | 32 | 70 | 14.5 | 28 | 180 | 361 | 490 | 552 | 35.5 | 259 | 115 | 151 | 190 | 45 | FF300 |
| 180 LUR | 279 | 330 | 279 | 337 | 115 | 32 | 70 | 14.5 | 28 | 180 | 361 | 490 | 593 | 35.5 | 259 | 115 | 151 | 190 | 45 | FF300 |
| 180 M | 279 | 330 | 241 | 337 | 121 | 32 | 70 | 14.5 | 28 | 180 | 361 | 490 | 552 | 35.5 | 259 | 115 | 151 | 190 | 45 | FF300 |
| 180 MT | 279 | 330 | 241 | 337 | 121 | 32 | 70 | 14.5 | 28 | 180 | 361 | 490 | 537 | 29.5 | 259 | 115 | 151 | 190 | 45 | FF300 |
| 180 MUR | 279 | 324 | 241 | 290 | 121 | 24 | 80 | 14.5 | 25 | 180 | 328 | 469 | 551 | 29.5 | 259 | 115 | 151 | 177 | 45 | FF300 |
| 200 LU | 318 | 374 | 305 | 360 | 135 | 28 | 60 | 18.5 | 17 | 200 | 399 | 541 | 669 | 42.5 | 259 | 115 | 151 | 243 | 45 | FF350 |
| 225 M | 356 | 426 | 311 | 375 | 149 | 32 | 80 | 18.5 | 27 | 225 | 495 | 648 | 779 | 69.5 | 352 | 175 | 212 | 270 | 45 | FF400 |
| 225 MR | 356 | 426 | 311 | 380 | 144.5 | 34 | 70 | 18.5 | 17 | 225 | 398 | 566 | 682 | 49 | 259 | 115 | 151 | 243 | 45 | FF400 |
| 225 S | 356 | 426 | 286 | 375 | 149 | 32 | 80 | 18.5 | 27 | 225 | 487 | 661 | 779 | 91.5 | 308 | 161 | 208 | 276 | 45 | FF400 |
| 225 SR | 356 | 426 | 286 | 380 | 144.5 | 34 | 70 | 18.5 | 17 | 225 | 398 | 566 | 674 | 44.5 | 259 | 115 | 151 | 243 | 45 | FF400 |
| 250 M | 406 | 476 | 349 | 413 | 168 | 32 | 80 | 24 | 26 | 250 | 495 | 682 | 779 | 91.5 | 308 | 161 | 208 | 270 | 45 | FF500 |
| 250 MR | 406 | 476 | 349 | 413 | 168 | 32 | 80 | 24 | 27 | 250 | 495 | 673 | 859 | 69.5 | 352 | 175 | 212 | 270 | 45 | FF500 |
| 280 M | 457 | 527 | 419 | 486 | 92 | 33 | 80 | 24 | 30 | 280 | 481 | 717 | 959 | 69 | 352 | 175 | 212 | 303 | 45 | FF500 |
| 280 S | 457 | 527 | 368 | 486 | 92 | 33 | 80 | 24 | 30 | 280 | 481 | 717 | 959 | 69 | 352 | 175 | 212 | 303 | 45 | FF500 |
| 315 LA | 508 | 600 | 508 | 610 | 109 | 58 | 100 | 28 | 35 | 315 | 600 | 857 | 1177 | 119 | 416 | 217 | 264 | 343 | 45 | FF600 |
| 315 LB | 508 | 600 | 508 | 610 | 109 | 58 | 100 | 28 | 35 | 315 | 600 | 847 | 1177 | 101 | 452 | 219 | 269 | 343 | 45 | FF600 |
| 315 M | 508 | 600 | 457 | 610 | 109 | 58 | 100 | 28 | 35 | 315 | 600 | 857 | 1177 | 119 | 416 | 217 | 264 | 343 | 45 | FF600 |
| 315 S | 508 | 600 | 406 | 610 | 109 | 58 | 100 | 28 | 35 | 315 | 600 | 857 | 1177 | 119 | 416 | 217 | 264 | 343 | 45 | FF600 |
| 355 LA | 610 | 710 | 630 | 756 | 127 | 76 | 100 | 28 | 35 | 355 | 688 | 925 | 1303 | 121 | 452 | 219 | 269 | - | - | FF740 |
| 355 LAL | 610 | 710 | 630 | 756 | 127 | 76 | 100 | 28 | 35 | 355 | 688 | 925 | 1303 | 121 | 452 | 219 | 269 | - | - | FF740 |
| 355 LB | 610 | 710 | 630 | 756 | 127 | 76 | 100 | 28 | 35 | 355 | 688 | 925 | 1303 | 121 | 452 | 219 | 269 | - | - | FF740 |
| 355 LC | 610 | 710 | 630 | 756 | 127 | 76 | 100 | 28 | 35 | 355 | 688 | 925 | 1303 | 121 | 452 | 219 | 269 | - | - | FF740 |
| 355 LD | 610 | 710 | 630 | 756 | 127 | 76 | 100 | 28 | 35 | 355 | 688 | 925 | 1303 | 121 | 452 | 219 | 269 | - | - | FF740 |

* AC: housing diameter without lifting rings

ATEX DUST - Zones 21 & 22 - Cast iron


IMfinity® ATEX 3-phase induction motors - IE3 efficiency class

ATEX DUST motors - Zones 21 & 22

FLSPX & FLSES series - Cast iron - Mechanical characteristics

Flange mounted IM 3001 (IM B5) - IM 3011 (IM V1)

Dimensions in millimetres




| Type | Main dimensions | | | | | | | | |
|---------|-----------------|-------|-----|------|-----|-----|-----|-----|------|
| | AC* | LB | HJ | LJ | J | I | II | AD | AD1 |
| 80 L | 170 | 212 | 148 | 7 | 136 | 68 | 68 | - | - |
| 80 LG | 203 | 265 | 158 | 28 | 136 | 68 | 68 | 135 | 41 |
| 90 L | 203 | 259 | 158 | 28 | 136 | 68 | 68 | 135 | 41 |
| 90 LU | 203 | 286 | 158 | 28 | 136 | 68 | 68 | 135 | 41 |
| 90 SL | 203 | 259 | 158 | 28 | 136 | 68 | 68 | 135 | 41 |
| 100 L | 204 | 300 | 158 | 8 | 136 | 68 | 68 | 135 | 41 |
| 100 LG | 235 | 309 | 164 | 10.5 | 136 | 68 | 68 | - | - |
| 100 LR | 204 | 300 | 158 | 8 | 136 | 68 | 68 | 135 | 41 |
| 112 MG | 230 | 309 | 182 | 18 | 136 | 68 | 68 | 148 | 41 |
| 112 MU | 230 | 309 | 182 | 18 | 136 | 68 | 68 | 148 | 41 |
| 132 M | 270 | 385 | 203 | 22 | 136 | 68 | 68 | 165 | 37.5 |
| 132 MR | 270 | 447 | 203 | 22 | 136 | 68 | 68 | 165 | 37.5 |
| 132 MU | 270 | 447 | 203 | 22 | 136 | 68 | 68 | 165 | 37.5 |
| 132 SM | 270 | 385 | 203 | 22 | 136 | 68 | 68 | 165 | 37.5 |
| 160 L | 328 | 495 | 289 | 23.5 | 259 | 115 | 151 | 177 | 45 |
| 160 LUR | 328 | 510 | 289 | 23.5 | 259 | 115 | 151 | 177 | 45 |
| 160 M | 328 | 495 | 289 | 23.5 | 259 | 115 | 151 | 177 | 45 |
| 160 MU | 328 | 510 | 289 | 23.5 | 259 | 115 | 151 | 177 | 45 |
| 180 L | 361 | 552 | 310 | 35.5 | 259 | 115 | 151 | 190 | 45 |
| 180 LUR | 361 | 593 | 310 | 35.5 | 259 | 115 | 151 | 190 | 45 |
| 180 M | 361 | 552 | 310 | 35.5 | 259 | 115 | 151 | 190 | 45 |
| 180 MT | 361 | 537 | 310 | 29.5 | 259 | 115 | 151 | 190 | 45 |
| 180 MUR | 328 | 551 | 289 | 29.5 | 259 | 115 | 151 | 177 | 45 |
| 200 LU | 398 | 671 | 341 | 44 | 259 | 115 | 151 | 243 | 45 |
| 225 M | 487 | 779 | 427 | 69 | 352 | 175 | 212 | 276 | 45 |
| 225 MR | 398 | 675.5 | 341 | 48.5 | 259 | 115 | 151 | 243 | 45 |
| 225 S | 495 | 779 | 432 | 91.5 | 308 | 161 | 208 | 270 | 45 |
| 225 SR | 398 | 678.5 | 341 | 48.5 | 259 | 115 | 151 | 243 | 45 |
| 250 M | 495 | 779 | 432 | 91.5 | 308 | 161 | 208 | 270 | 45 |
| 250 MR | 495 | 859 | 427 | 70.5 | 352 | 175 | 212 | 270 | 45 |
| 280 M | 481 | 959 | 437 | 69 | 352 | 175 | 212 | 303 | 45 |
| 280 S | 481 | 959 | 437 | 69 | 352 | 175 | 212 | 303 | 45 |
| 315 LA | 600 | 1177 | 542 | 119 | 416 | 217 | 264 | 343 | 45 |
| 315 LB | 600 | 1177 | 532 | 101 | 452 | 219 | 269 | 343 | 45 |
| 315 M | 600 | 1177 | 542 | 119 | 416 | 217 | 264 | 343 | 45 |
| 315 S | 600 | 1177 | 542 | 119 | 416 | 217 | 264 | 343 | 45 |
| 355 LA | 688 | 1303 | 570 | 121 | 452 | 219 | 269 | - | - |
| 355 LAL | 688 | 1303 | 570 | 121 | 452 | 219 | 269 | - | - |
| 355 LB | 688 | 1303 | 570 | 121 | 452 | 219 | 269 | - | - |
| 355 LC | 688 | 1303 | 570 | 121 | 452 | 219 | 269 | - | - |
| 355 LD | 688 | 1303 | 570 | 121 | 452 | 219 | 269 | - | - |

* AC: housing diameter without lifting rings

| IEC symbol | Flange dimensions | | | | | | | |
|------------|-------------------|-----|-----|-----|---|----------------|------|----|
| | M | N | D | T | n | α° | S | LA |
| FF165 | 165 | 130 | 200 | 3.5 | 4 | 45 | 12 | 10 |
| FF165 | 165 | 130 | 200 | 3.5 | 4 | 45 | 12 | 10 |
| FF165 | 165 | 130 | 200 | 3.5 | 4 | 45 | 12 | 10 |
| FF165 | 165 | 130 | 200 | 3.5 | 4 | 45 | 12 | 10 |
| FF215 | 215 | 180 | 250 | 4 | 4 | 45 | 14.5 | 12 |
| FF215 | 215 | 180 | 250 | 4 | 4 | 45 | 14.5 | 13 |
| FF215 | 215 | 180 | 250 | 4 | 4 | 45 | 14.5 | 12 |
| FF215 | 215 | 180 | 250 | 4 | 4 | 45 | 14.5 | 13 |
| FF265 | 265 | 230 | 300 | 4 | 4 | 45 | 14.5 | 14 |
| FF265 | 265 | 230 | 300 | 4 | 4 | 45 | 14.5 | 14 |
| FF265 | 265 | 230 | 300 | 4 | 4 | 45 | 14.5 | 14 |
| FF265 | 265 | 230 | 300 | 4 | 4 | 45 | 14.5 | 14 |
| FF300 | 300 | 250 | 350 | 5 | 4 | 45 | 18.5 | 14 |
| FF300 | 300 | 250 | 350 | 5 | 4 | 45 | 18.5 | 14 |
| FF300 | 300 | 250 | 350 | 5 | 4 | 45 | 18.5 | 14 |
| FF300 | 300 | 250 | 350 | 5 | 4 | 45 | 18.5 | 14 |
| FF300 | 300 | 250 | 350 | 5 | 4 | 45 | 18.5 | 15 |
| FF300 | 300 | 250 | 350 | 5 | 4 | 45 | 18.5 | 15 |
| FF300 | 300 | 250 | 350 | 5 | 4 | 45 | 18.5 | 15 |
| FF300 | 300 | 250 | 350 | 5 | 4 | 45 | 18.5 | 14 |
| FF350 | 350 | 300 | 400 | 5 | 4 | 45 | 18.5 | 15 |
| FF400 | 400 | 350 | 450 | 5 | 8 | 22.5 | 18.5 | 16 |
| FF400 | 400 | 350 | 450 | 5 | 8 | 22.5 | 18.5 | 16 |
| FF400 | 400 | 350 | 450 | 5 | 8 | 22.5 | 18.5 | 16 |
| FF400 | 400 | 350 | 450 | 5 | 8 | 22.5 | 18.5 | 16 |
| FF500 | 500 | 450 | 550 | 5 | 8 | 22.5 | 18.5 | 18 |
| FF500 | 500 | 450 | 550 | 5 | 8 | 22.5 | 18.5 | 18 |
| FF500 | 500 | 450 | 550 | 5 | 8 | 22.5 | 18.5 | 18 |
| FF500 | 500 | 450 | 550 | 5 | 8 | 22.5 | 18.5 | 18 |
| FF600 | 600 | 550 | 660 | 6 | 8 | 22.5 | 24 | 22 |
| FF600 | 600 | 550 | 660 | 6 | 8 | 22.5 | 24 | 22 |
| FF600 | 600 | 550 | 660 | 6 | 8 | 22.5 | 24 | 22 |
| FF600 | 600 | 550 | 660 | 6 | 8 | 22.5 | 24 | 22 |
| FF740 | 740 | 680 | 800 | 6 | 8 | 22.5 | 24 | 25 |
| FF740 | 740 | 680 | 800 | 6 | 8 | 22.5 | 24 | 25 |
| FF740 | 740 | 680 | 800 | 6 | 8 | 22.5 | 24 | 25 |
| FF740 | 740 | 680 | 800 | 6 | 8 | 22.5 | 24 | 25 |

ATEX DUST - Zones 21 & 22 - Cast iron

Dimensions in millimetres



| Type | Main dimensions | | | | | | | | | |
|---------|-----------------|-------|-----|------|-----|-----|-----|-----|------|--|
| | AC* | LB | HJ | LJ | J | I | II | AD | AD1 | |
| 80 L | 170 | 212 | 148 | 7 | 136 | 68 | 68 | - | - | |
| 80 LG | 203 | 265 | 158 | 28 | 136 | 68 | 68 | 135 | 41 | |
| 90 L | 203 | 259 | 158 | 28 | 136 | 68 | 68 | 135 | 41 | |
| 90 LU | 203 | 286 | 158 | 28 | 136 | 68 | 68 | 135 | 41 | |
| 90 SL | 203 | 259 | 158 | 28 | 136 | 68 | 68 | 135 | 41 | |
| 100 L | 204 | 300 | 158 | 8 | 136 | 68 | 68 | 135 | 41 | |
| 100 LG | 235 | 309 | 164 | 10.5 | 136 | 68 | 68 | - | - | |
| 100 LR | 204 | 300 | 158 | 8 | 136 | 68 | 68 | 135 | 41 | |
| 112 MG | 230 | 309 | 182 | 18 | 136 | 68 | 68 | 148 | 41 | |
| 112 MU | 230 | 309 | 182 | 18 | 136 | 68 | 68 | 148 | 41 | |
| 132 M | 270 | 385 | 203 | 22 | 136 | 68 | 68 | 165 | 37.5 | |
| 132 MR | 270 | 447 | 203 | 22 | 136 | 68 | 68 | 165 | 37.5 | |
| 132 MU | 270 | 447 | 203 | 22 | 136 | 68 | 68 | 165 | 37.5 | |
| 132 SM | 270 | 385 | 203 | 22 | 136 | 68 | 68 | 165 | 37.5 | |
| 160 L | 328 | 495 | 289 | 23.5 | 259 | 115 | 151 | 177 | 45 | |
| 160 LUR | 328 | 510 | 289 | 23.5 | 259 | 115 | 151 | 177 | 45 | |
| 160 M | 328 | 495 | 289 | 23.5 | 259 | 115 | 151 | 177 | 45 | |
| 160 MU | 328 | 510 | 289 | 23.5 | 259 | 115 | 151 | 177 | 45 | |
| 180 L | 361 | 552 | 310 | 35.5 | 259 | 115 | 151 | 190 | 45 | |
| 180 LUR | 361 | 593 | 310 | 35.5 | 259 | 115 | 151 | 190 | 45 | |
| 180 M | 361 | 552 | 310 | 35.5 | 259 | 115 | 151 | 190 | 45 | |
| 180 MT | 361 | 537 | 310 | 29.5 | 259 | 115 | 151 | 190 | 45 | |
| 180 MUR | 328 | 551 | 289 | 29.5 | 259 | 115 | 151 | 177 | 45 | |
| 200 LU | 398 | 671 | 341 | 44 | 259 | 115 | 151 | 243 | 45 | |
| 225 M | 487 | 779 | 427 | 69 | 352 | 175 | 212 | 276 | 45 | |
| 225 MR | 398 | 675.5 | 341 | 48.5 | 259 | 115 | 151 | 243 | 45 | |
| 225 S | 495 | 779 | 432 | 91.5 | 308 | 161 | 208 | 270 | 45 | |
| 225 SR | 398 | 678.5 | 341 | 48.5 | 259 | 115 | 151 | 243 | 45 | |
| 250 M | 495 | 779 | 432 | 91.5 | 308 | 161 | 208 | 270 | 45 | |
| 250 MR | 495 | 859 | 427 | 70.5 | 352 | 175 | 212 | 270 | 45 | |
| 280 M | 481 | 959 | 437 | 69 | 352 | 175 | 212 | 303 | 45 | |
| 280 S | 481 | 959 | 437 | 69 | 352 | 175 | 212 | 303 | 45 | |
| 315 LA | 600 | 1177 | 542 | 119 | 416 | 217 | 264 | 343 | 45 | |
| 315 LB | 600 | 1177 | 532 | 101 | 452 | 219 | 269 | 343 | 45 | |
| 315 M | 600 | 1177 | 542 | 119 | 416 | 217 | 264 | 343 | 45 | |
| 315 S | 600 | 1177 | 542 | 119 | 416 | 217 | 264 | 343 | 45 | |
| 355 LA | 688 | 1303 | 570 | 121 | 452 | 219 | 269 | - | - | |
| 355 LAL | 688 | 1303 | 570 | 121 | 452 | 219 | 269 | - | - | |
| 355 LB | 688 | 1303 | 570 | 121 | 452 | 219 | 269 | - | - | |
| 355 LC | 688 | 1303 | 570 | 121 | 452 | 219 | 269 | - | - | |
| 355 LD | 688 | 1303 | 570 | 121 | 452 | 219 | 269 | - | - | |


| IEC symbol | Flange dimensions | | | | | | | |
|------------|-------------------|-----|-----|-----|---|------|------|----|
| | M | N | D | T | n | α° | S | LA |
| FF165 | 165 | 130 | 200 | 3.5 | 4 | 45 | 12 | 10 |
| FF165 | 165 | 130 | 200 | 3.5 | 4 | 45 | 12 | 10 |
| FF165 | 165 | 130 | 200 | 3.5 | 4 | 45 | 12 | 10 |
| FF165 | 165 | 130 | 200 | 3.5 | 4 | 45 | 12 | 10 |
| FF165 | 165 | 130 | 200 | 3.5 | 4 | 45 | 12 | 10 |
| FF215 | 215 | 180 | 250 | 4 | 4 | 45 | 14.5 | 12 |
| FF215 | 215 | 180 | 250 | 4 | 4 | 45 | 14.5 | 13 |
| FF215 | 215 | 180 | 250 | 4 | 4 | 45 | 14.5 | 12 |
| FF215 | 215 | 180 | 250 | 4 | 4 | 45 | 14.5 | 13 |
| FF215 | 215 | 180 | 250 | 4 | 4 | 45 | 14.5 | 13 |
| FF265 | 265 | 230 | 300 | 4 | 4 | 45 | 14.5 | 14 |
| FF265 | 265 | 230 | 300 | 4 | 4 | 45 | 14.5 | 14 |
| FF265 | 265 | 230 | 300 | 4 | 4 | 45 | 14.5 | 14 |
| FF265 | 265 | 230 | 300 | 4 | 4 | 45 | 14.5 | 14 |
| FF300 | 300 | 250 | 350 | 5 | 4 | 45 | 18.5 | 14 |
| FF300 | 300 | 250 | 350 | 5 | 4 | 45 | 18.5 | 14 |
| FF300 | 300 | 250 | 350 | 5 | 4 | 45 | 18.5 | 14 |
| FF300 | 300 | 250 | 350 | 5 | 4 | 45 | 18.5 | 14 |
| FF300 | 300 | 250 | 350 | 5 | 4 | 45 | 18.5 | 15 |
| FF300 | 300 | 250 | 350 | 5 | 4 | 45 | 18.5 | 15 |
| FF300 | 300 | 250 | 350 | 5 | 4 | 45 | 18.5 | 14 |
| FF300 | 300 | 250 | 350 | 5 | 4 | 45 | 18.5 | 15 |
| FF350 | 350 | 300 | 400 | 5 | 4 | 45 | 18.5 | 15 |
| FF400 | 400 | 350 | 450 | 5 | 8 | 22.5 | 18.5 | 16 |
| FF400 | 400 | 350 | 450 | 5 | 8 | 22.5 | 18.5 | 16 |
| FF400 | 400 | 350 | 450 | 5 | 8 | 22.5 | 18.5 | 16 |
| FF400 | 400 | 350 | 450 | 5 | 8 | 22.5 | 18.5 | 16 |
| FF500 | 500 | 450 | 550 | 5 | 8 | 22.5 | 18.5 | 18 |
| FF500 | 500 | 450 | 550 | 5 | 8 | 22.5 | 18.5 | 18 |
| FF500 | 500 | 450 | 550 | 5 | 8 | 22.5 | 18.5 | 18 |
| FF500 | 500 | 450 | 550 | 5 | 8 | 22.5 | 18.5 | 18 |
| FF600 | 600 | 550 | 660 | 6 | 8 | 22.5 | 24 | 22 |
| FF600 | 600 | 550 | 660 | 6 | 8 | 22.5 | 24 | 22 |
| FF600 | 600 | 550 | 660 | 6 | 8 | 22.5 | 24 | 22 |
| FF600 | 600 | 550 | 660 | 6 | 8 | 22.5 | 24 | 22 |
| FF740 | 740 | 680 | 800 | 6 | 8 | 22.5 | 24 | 25 |
| FF740 | 740 | 680 | 800 | 6 | 8 | 22.5 | 24 | 25 |
| FF740 | 740 | 680 | 800 | 6 | 8 | 22.5 | 24 | 25 |
| FF740 | 740 | 680 | 800 | 6 | 8 | 22.5 | 24 | 25 |

* AC: housing diameter without lifting rings

ATEX DUST - Zones 21 & 22 - Cast iron

IMfinity® ATEX 3-phase induction motors - IE3 efficiency class
ATEX DUST motors - Zones 21 & 22
FLSPX & FLSES series - Cast iron - Mechanical characteristics
Foot and face mounted IM 2101 (IM B34)

Dimensions in millimetres




| | | Main dimensions | | | | | | | | | | | | | | | | | | | |
|----------------|--------|-----------------|-----|-----|-----|----|----|----|----|----|-----|-----|-----|-----|-----|-----|----|----|-----|------|-------|
| Type | | A | AB | B | BB | C | x | AA | K | HA | H | AC* | HD | LB | LJ | J | I | II | AD | AD1 | Symb |
| FLSPX FLSES | 80 L | 125 | 157 | 100 | 130 | 50 | 18 | 34 | 10 | 10 | 80 | 170 | 228 | 212 | 7 | 136 | 68 | 68 | - | - | FT100 |
| | 80 LG | 125 | 170 | 100 | 138 | 50 | 22 | 39 | 10 | 10 | 80 | 203 | 238 | 245 | 8 | 136 | 68 | 68 | 135 | 41 | FT100 |
| | 90 L | 140 | 170 | 125 | 162 | 56 | 28 | 33 | 10 | 10 | 90 | 203 | 248 | 239 | 8 | 136 | 68 | 68 | 135 | 41 | FT115 |
| | 90 LU | 140 | 170 | 125 | 162 | 56 | 28 | 33 | 10 | 10 | 90 | 203 | 248 | 266 | 8 | 136 | 68 | 68 | 135 | 41 | FT115 |
| | 90 SL | 140 | 170 | 125 | 162 | 56 | 28 | 33 | 10 | 10 | 90 | 203 | 248 | 239 | 8 | 136 | 68 | 68 | 135 | 41 | FT115 |
| | 100 L | 160 | 196 | 140 | 185 | 63 | 29 | 40 | 12 | 13 | 100 | 204 | 258 | 300 | 8 | 136 | 68 | 68 | 135 | 41 | FT130 |
| | 100 LG | 160 | 196 | 140 | 168 | 53 | 13 | 40 | 12 | 14 | 100 | 227 | 266 | 299 | 0.5 | 136 | 68 | 68 | 130 | 45 | FT130 |
| | 100 LR | 160 | 196 | 140 | 185 | 63 | 29 | 40 | 12 | 13 | 100 | 204 | 258 | 300 | 8 | 136 | 68 | 68 | 135 | 41 | FT130 |
| | 112 MG | 190 | 230 | 140 | 186 | 60 | 32 | 48 | 12 | 12 | 112 | 230 | 294 | 299 | 8 | 136 | 68 | 68 | 148 | 41 | FT130 |
| | 112 MU | 190 | 230 | 140 | 186 | 60 | 32 | 48 | 12 | 12 | 112 | 230 | 294 | 299 | 8 | 136 | 68 | 68 | 148 | 41 | FT130 |
| | 132 M | 216 | 255 | 178 | 240 | 89 | 50 | 63 | 12 | 16 | 132 | 270 | 335 | 385 | 22 | 136 | 68 | 68 | 165 | 37.5 | FT165 |
| | 132 MR | 216 | 255 | 178 | 240 | 89 | 50 | 63 | 12 | 16 | 132 | 270 | 335 | 447 | 22 | 136 | 68 | 68 | 165 | 37.5 | FT165 |
| | 132 MU | 216 | 255 | 178 | 240 | 89 | 50 | 63 | 12 | 16 | 132 | 270 | 335 | 447 | 22 | 136 | 68 | 68 | 165 | 37.5 | FT165 |
| | 132 SM | 216 | 255 | 140 | 240 | 89 | 50 | 63 | 12 | 16 | 132 | 270 | 335 | 385 | 22 | 136 | 68 | 68 | 165 | 37.5 | FT165 |

* AC: housing diameter without lifting rings

ATEX DUST - Zones 21 & 22 - Cast iron

IMfinity® ATEX 3-phase induction motors - IE3 efficiency class
ATEX DUST motors - Zones 21 & 22
FLSPX & FLSES series - Cast iron - Mechanical characteristics
Face mounted IM 3601 (IM B14)

Dimensions in millimetres



| Type | Main dimensions | | | | | | | | |
|--------|-----------------|-----|-----|------|-----|----|----|-----|------|
| | AC* | LB | HJ | LJ | J | I | II | AD | AD1 |
| 80 L | 170 | 212 | 148 | 7 | 136 | 68 | 68 | - | - |
| 80 LG | 203 | 245 | 158 | 8 | 136 | 68 | 68 | 135 | 41 |
| 90 L | 203 | 239 | 158 | 8 | 136 | 68 | 68 | 135 | 41 |
| 90 LU | 203 | 266 | 158 | 8 | 136 | 68 | 68 | 135 | 41 |
| 90 SL | 203 | 239 | 158 | 8 | 136 | 68 | 68 | 135 | 41 |
| 100 L | 204 | 300 | 158 | 8 | 136 | 68 | 68 | 135 | 41 |
| 100 LG | 235 | 309 | 164 | 10.5 | 136 | 68 | 68 | - | - |
| 100 LR | 204 | 300 | 158 | 8 | 136 | 68 | 68 | 135 | 41 |
| 112 MG | 230 | 309 | 182 | 18 | 136 | 68 | 68 | 148 | 41 |
| 112 MU | 230 | 309 | 182 | 18 | 136 | 68 | 68 | 148 | 41 |
| 132 M | 270 | 385 | 203 | 22 | 136 | 68 | 68 | 165 | 37.5 |
| 132 MR | 270 | 447 | 203 | 22 | 136 | 68 | 68 | 165 | 37.5 |
| 132 MU | 270 | 447 | 203 | 22 | 136 | 68 | 68 | 165 | 37.5 |
| 132 SM | 270 | 385 | 203 | 22 | 136 | 68 | 68 | 165 | 37.5 |

| IEC symbol | Flange dimensions | | | | | | |
|------------|-------------------|-----|-----|-----|---|----|-----|
| | M | N | D | T | n | α° | S |
| FT100 | 100 | 80 | 120 | 3 | 4 | 45 | M6 |
| FT100 | 100 | 80 | 120 | 3 | 4 | 45 | M6 |
| FT115 | 115 | 95 | 140 | 3 | 4 | 45 | M8 |
| FT115 | 115 | 95 | 140 | 3 | 4 | 45 | M8 |
| FT115 | 115 | 95 | 140 | 3 | 4 | 45 | M8 |
| FT130 | 130 | 110 | 160 | 3.5 | 4 | 45 | M8 |
| FT130 | 130 | 110 | 160 | 3.5 | 4 | 45 | M8 |
| FT130 | 130 | 110 | 160 | 3.5 | 4 | 45 | M8 |
| FT130 | 130 | 110 | 160 | 3.5 | 4 | 45 | M8 |
| FT130 | 130 | 110 | 160 | 3.5 | 4 | 45 | M8 |
| FT165 | 165 | 130 | 200 | 3.5 | 4 | 45 | M10 |
| FT165 | 165 | 130 | 200 | 3.5 | 4 | 45 | M10 |
| FT165 | 165 | 130 | 200 | 3.5 | 4 | 45 | M10 |
| FT165 | 165 | 130 | 200 | 3.5 | 4 | 45 | M10 |

* AC: housing diameter without lifting rings

ATEX DUST - Zones 21 & 22 - Cast iron

PERMANENTLY GREASED BEARINGS

Under normal operating conditions, the service life in hours (L_{10h}) of the lubricant is indicated in the table below for ambient temperatures less than 55°C.

| Series | Type | Polarity | Bearing types Permanently greased | | Bearing service life as a function of rotation speed | | | | | | | | |
|----------------|----------|----------|--------------------------------------|---------|--|---------|---------|------------------------|---------|---------|------------------------|---------|-------|
| | | | | | 3000 min ⁻¹ | | | 1500 min ⁻¹ | | | 1000 min ⁻¹ | | |
| | | | | | 25°C | 40°C | 55°C | 25°C | 40°C | 55°C | 25°C | 40°C | 55°C |
| FLSPX FLSES | 80 L | 2 | 6203 C3 | 6204 C3 | ≥ 40000 | ≥ 40000 | 25000 | - | - | - | - | - | - |
| | 80 LG | 4 | 6204 C3 | 6205 C3 | - | - | - | ≥ 40000 | ≥ 40000 | 31000 | - | - | - |
| | 90 SL/L | 2; 4; 6 | | | ≥ 40000 | ≥ 40000 | 24000 | ≥ 40000 | ≥ 40000 | 31000 | ≥ 40000 | ≥ 40000 | 34000 |
| | 90 LU | 2; 6 | 6205 C3 | 6205 C3 | ≥ 40000 | ≥ 40000 | 24000 | - | - | - | ≥ 40000 | ≥ 40000 | 34000 |
| | 100 L | 2; 4 | 6205 C3 | 6206 C3 | ≥ 40000 | ≥ 40000 | 22000 | ≥ 40000 | ≥ 40000 | 30000 | - | - | - |
| | 100 LG | 4; 6 | | | - | - | - | - | - | - | ≥ 40000 | ≥ 40000 | 33000 |
| | 112 MG | 2; 6 | | | ≥ 40000 | ≥ 40000 | 22000 | - | - | - | ≥ 40000 | ≥ 40000 | 33000 |
| | 112 MU | 4 | 6206 C3 | 6206 C3 | - | - | - | ≥ 40000 | ≥ 40000 | 30000 | - | - | - |
| | 132 SM/M | 2; 4; 6 | 6207 C3 | 6308 C3 | ≥ 40000 | ≥ 40000 | 19000 | ≥ 40000 | ≥ 40000 | 25000 | ≥ 40000 | ≥ 40000 | 30000 |
| | 132 MU | 2; 4 | 6307 C3 | 6308 C3 | ≥ 40000 | ≥ 40000 | 19000 | ≥ 40000 | ≥ 40000 | 25000 | - | - | - |
| | 132 MR | 4; 6 | 6308 C3 | 6308 C3 | - | - | - | ≥ 40000 | ≥ 40000 | 25000 | ≥ 40000 | ≥ 40000 | 30000 |
| | 160 M | 2; 4; 6 | 6210 C3 | 6309 C3 | ≥ 40000 | 37800 | 18900 | ≥ 40000 | ≥ 40000 | 36900 | ≥ 40000 | ≥ 40000 | 20050 |
| | 160 MU | 6 | | | - | - | - | - | - | - | ≥ 40000 | ≥ 40000 | 20050 |
| | 160 LUR | 2; 4; 6 | 6210 C3 | 6310 C3 | ≥ 40000 | 24500 | 12250 | ≥ 40000 | 36400 | 18200 | ≥ 40000 | ≥ 40000 | 22450 |
| | 180 M | 2 | 6212 C3 | 6310 C3 | 34000 | 17000 | 8500 | - | - | - | - | - | - |
| | 180 MT | 4 | 6210 C3 | 6310 C3 | - | - | - | ≥ 40000 | 35500 | 17750 | - | - | - |
| | 180 MUR | 2 | 6312 C3 | 6310 C3 | ≥ 40000 | 22800 | 11400 | - | - | - | - | - | - |
| | 180 L | 4; 6 | 6212 C3 | 6310 C3 | - | - | - | ≥ 40000 | 39500 | 19750 | ≥ 40000 | ≥ 40000 | 29050 |
| | 180 LUR | 4; 6 | 6312 C3 | 6310 C3 | - | - | - | ≥ 40000 | ≥ 40000 | 22900 | ≥ 40000 | ≥ 40000 | 29900 |
| | 200 LU | 2; 4; 6 | 6312 C3 | 6312 C3 | 28600 | 14300 | 7150 | ≥ 40000 | 25400 | 12700 | ≥ 40000 | 33200 | 16600 |
| 225 S | 4 | 6314 C3 | 6314 C3 | - | - | - | ≥ 40000 | 23700 | 11850 | - | - | - | |
| 225 SR | 4 | 6312 C3 | 6313 C3 | - | - | - | ≥ 40000 | ≥ 40000 | 21500 | - | - | - | |
| 225 M | 4; 6 | 6314 C3 | 6314 C3 | - | - | - | ≥ 40000 | 23700 | 11850 | ≥ 40000 | 25600 | 12800 | |
| 225 MR | 2 | 6312 C3 | 6313 C3 | ≥ 40000 | 22800 | 11400 | - | - | - | - | - | - | |

BEARINGS WITH GREASE NIPPLES

For open bearing assemblies of frame size ≥ 160 mm fitted with grease nipples, the table below indicates, depending on the type of motor, the lubrication intervals to be respected at 25°C, 40°C and 55°C for a machine installed with a horizontal shaft.

The table below is valid for FLSPX and FLSES motors lubricated with Polyrex EM103 grease used as standard.

| Series | Type | Polarity | Bearing type for bearing housings with grease nipples | | Quantity of grease g | Lubrication intervals in hours | | | | | | | | |
|----------------|-----------------|----------|---|---------|-------------------------|--------------------------------|-------|------|------------------------|-------|------|------------------------|-------|-------|
| | | | N.D.E. | D.E. | | 3000 min ⁻¹ | | | 1500 min ⁻¹ | | | 1000 min ⁻¹ | | |
| | | | | | | 25°C | 40°C | 55°C | 25°C | 40°C | 55°C | 25°C | 40°C | 55°C |
| FLSPX FLSES | 160 M* | 2; 4; 6 | 6210 C3 | 6309 C3 | 13 | 22200 | 11100 | 5550 | 32400 | 16200 | 8100 | 39800 | 19900 | 9950 |
| | 160 MU | 6 | | | | - | - | - | - | - | - | 23400 | 11700 | 5850 |
| | 160 LUR* | 2; 4; 6 | 6210 C3 | 6310 C3 | 15 | 19600 | 9800 | 4900 | 30400 | 15200 | 7600 | 38200 | 19100 | 6600 |
| | 180 M* | 2 | 6212 C3 | 6310 C3 | 15 | 18000 | 9000 | 4500 | - | - | - | - | - | - |
| | 180 MT* | 4 | 6210 C3 | 6310 C3 | 15 | - | - | - | 30400 | 15200 | 7600 | - | - | - |
| | 180 MUR* | 2 | 6312 C3 | 6310 C3 | 15 | 10600 | 5300 | 2650 | - | - | - | - | - | - |
| | 180 L* | 4; 6 | 6212 C3 | 6310 C3 | 20 | - | - | - | 29200 | 14600 | 7300 | 37200 | 18600 | 9300 |
| | 180 LUR* | 4; 6 | 6312 C3 | 6310 C3 | 20 | - | - | - | 26800 | 13400 | 6700 | 35000 | 17500 | 8750 |
| | 200 LU* | 2; 4; 6 | 6312 C3 | 6312 C3 | 20 | 15200 | 7600 | 3800 | 26800 | 13400 | 6700 | 35000 | 17500 | 8750 |
| | 225 S* | 4 | 6314 C3 | 6314 C3 | 25 | - | - | - | 23600 | 11800 | 5900 | - | - | - |
| | 225 SR* | 4 | 6312 C3 | 6313 C3 | 25 | - | - | - | 25200 | 12600 | 6300 | - | - | - |
| | 225 M* | 4; 6 | 6314 C3 | 6314 C3 | 25 | - | - | - | 23600 | 11800 | 5900 | 32200 | 16100 | 8050 |
| | 225 MR* | 2 | 6312 C3 | 6313 C3 | 25 | 13400 | 6700 | 3350 | - | - | - | - | - | - |
| | 250 M | 2; 6 | 6314 C3 | 6314 C3 | 25 | 10400 | 5200 | 2600 | - | - | - | 32200 | 16100 | 8050 |
| | 250 MR | 4 | | | | - | - | - | 17800 | 8900 | 4450 | - | - | - |
| | 280 S/M | 2; 4; 6 | 6314 C3 | 6316 C3 | 35 | 7200 | 3600 | 1800 | 21000 | 13230 | 6615 | 29000 | 29000 | 18270 |
| | 315 S/M/L | 2 | 6316 C3 | 6218 C3 | 35 | 7400 | 5880 | 2920 | - | - | - | - | - | - |
| | 315 S/M/L | 4; 6 | 6316 C3 | 6320 C3 | 50 | - | - | - | 15600 | 12400 | 6160 | 25000 | 25000 | 12500 |
| | 355 LA/LB/LC/LD | 2 | 6316 C3 | 6218 C3 | 35 | 7400 | 3700 | 1850 | - | - | - | - | - | - |
| | 355 LA/LB/LC/LD | 4; 6 | 6316 C3 | 6322 C3 | 60 | - | - | - | 13200 | 8316 | 4160 | 22000 | 13860 | 6930 |

* bearing housings with grease nipples on request

CONSTRUCTION AND SPECIAL ATMOSPHERES

For a machine installed with a vertical shaft, the lubrication intervals are approximately 80% of the values shown in the tables above.

NB: The quality and quantity of grease along with the lubrication interval are indicated on the machine nameplate.

In the case of special fitting arrangements (motors with roller bearing at the front or other mountings), machines with frame size ≥ 160 mm are fitted with grease nipple bearings.


The instructions required for bearing housing maintenance are shown on the machine nameplate.

BEARING MOUNTING PRINCIPLE

| FLSPX & FLSES series | | Horizontal shaft | Vertical shaft | |
|---|-----------------------|--|--|---|
| | | | Shaft end down | Shaft end up |
| Foot mounted motors | Mounting arrangements | B3 | V5 | V6 |
| | standard fitting | The Front bearing is: - at Front stop for frame size ≤ 132 - locked for frame size ≥ 160 | The Front bearing is locked | The Front bearing is: - at Front stop for frame size ≤ 90 - locked for frame size ≥ 100 |
| | on request | Front bearing locked for frame size < 132 | | Front bearing locked for frame size < 90 |
| Flange mounted motors (or feet and flange) | Mounting arrangements | B5 / B35 / B14 / B34 | V1 / V15 / V18 / V58 | V3 / V36 / V19 / V69 |
| | standard fitting | The Front bearing is locked from 80 to 355 LD | The Front bearing is locked from 80 to 355 LD | The Front bearing is locked from 80 to 355 LD |

Horizontal motor

For a bearing service life L_{10h} of 25,000 hours and 40,000 hours



| Series | Type | Polarity | Permissible axial load (daN) on the main drive shaft for standard fitting of bearings | | | | | | | | | | | | | |
|--------|-----------------|----------|---|--------------|--------------|--------------|--------------|--------------|------------------------|--------------|--------------|--------------|------------------------|--------------|--|--|
| | | | 3000 min ⁻¹ | | | | | | 1500 min ⁻¹ | | | | 1000 min ⁻¹ | | | |
| | | | → | | ← | | → | | ← | | → | | ← | | | |
| | | | 25,000 hours | 40,000 hours | 25,000 hours | 40,000 hours | 25,000 hours | 40,000 hours | 25,000 hours | 40,000 hours | 25,000 hours | 40,000 hours | 25,000 hours | 40,000 hours | | |
| | 80 L | 2 | 30 | 21 | (60) | (51) | - | - | - | - | - | - | - | - | | |
| | 80 LG | 2; 4 | 28 | 19 | (68) | (59) | 48 | 34 | (88) | (74) | - | - | - | - | | |
| | 90 SL/L | 2; 4; 6 | 29 | 23 | (69) | (56) | 45 | 32 | (85) | (72) | 56 | 40 | (96) | (80) | | |
| | 90 LU | 2; 4; 6 | 22 | 13 | (72) | (63) | 38 | 25 | (88) | (75) | 47 | 32 | (97) | (82) | | |
| | 100 L | 2; 4 | 40 | 26 | (90) | (76) | 61 | 43 | (111) | (93) | - | - | - | - | | |
| | 100 LR | 4 | - | - | - | - | 61 | 43 | (111) | (93) | - | - | - | - | | |
| | 100 LG | 4; 6 | - | - | - | - | 55 | 38 | (105) | (88) | 75 | 53 | (125) | (103) | | |
| | 112 MG | 2; 6 | 37 | 24 | (87) | (74) | - | - | - | - | 82 | 61 | (132) | (111) | | |
| | 112 MU | 4; 6 | - | - | - | - | 54 | 36 | (114) | (96) | 66 | 45 | (126) | (105) | | |
| | 132 SM/M | 2; 4; 6 | 101 | 74 | (171) | (144) | 146 | 109 | (216) | (179) | 182 | 138 | (252) | (208) | | |
| | 132 MU | 6 | - | - | - | - | - | - | - | - | 169 | 126 | (249) | (206) | | |
| | 132 MR | 4 | - | - | - | - | 129 | 93 | (219) | (183) | - | - | - | - | | |
| | 160 M | 2; 4 | 129 | 94 | 229 | 194 | 187 | 140 | 287 | 240 | 234 | 177 | 334 | 277 | | |
| | 160 MU | 6 | - | - | - | - | - | - | - | - | 219 | 164 | 319 | 264 | | |
| | 160 L | 2; 4 | 118 | 83 | 218 | 183 | 195 | 148 | 295 | 248 | - | - | - | - | | |
| | 160 LUR | 2; 4; 6 | 158 | 117 | 258 | 217 | 212 | 158 | 312 | 258 | 257 | 193 | 357 | 293 | | |
| | 180 M | 2; 4 | 189 | 148 | 237 | 196 | 228 | 174 | 291 | 237 | - | - | - | - | | |
| | 180 MT | 4 | - | - | - | - | 215 | 161 | 315 | 261 | - | - | - | - | | |
| | 180 MUR | 2 | 178 | 137 | 241 | 200 | - | - | - | - | - | - | - | - | | |
| | 180 L | 4; 6 | - | - | - | - | 240 | 186 | 288 | 234 | 272 | 208 | 320 | 256 | | |
| | 180 LUR | 4; 6 | - | - | - | - | 224 | 170 | 287 | 233 | 224 | 162 | 287 | 225 | | |
| | 200 LU | 2; 4; 6 | 249 | 196 | 312 | 259 | 316 | 245 | 379 | 308 | 327 | 245 | 390 | 308 | | |
| | 225 S | 4 | - | - | - | - | 427 | 336 | 490 | 399 | - | - | - | - | | |
| | 225 SR | 4 | - | - | - | - | 370 | 290 | 433 | 353 | - | - | - | - | | |
| | 225 M | 4; 6 | - | - | - | - | 416 | 325 | 496 | 405 | 511 | 402 | 591 | 482 | | |
| | 225 MR | 2 | 280 | 220 | 343 | 283 | - | - | - | - | - | - | - | - | | |
| | 250 M | 2; 6 | 308 | 240 | 388 | 320 | - | - | - | - | 506 | 400 | 506 | 400 | | |
| | 250 MR | 4 | - | - | - | - | 413 | 322 | 493 | 402 | - | - | - | - | | |
| | 280 S/M | 2; 4; 6 | 342 | 258 | 484 | 400 | 483 | 372 | 625 | 514 | 581 | 445 | 723 | 587 | | |
| | 315 S/M/LA/LB | 2; 6 | 411 | 348 | 165 | 102 | - | - | - | - | 933 | 761 | 687 | 515 | | |
| | 315 S/M/LA/LB | 4 | - | - | - | - | 814 | 670 | 568 | 424 | - | - | - | - | | |
| | 355 LA/LB/LC/LD | 2 | 393 | 333 | 147 | 87 | - | - | - | - | - | - | - | - | | |
| | 355 LAL | 4 | - | - | - | - | 876 | 724 | 630 | 478 | - | - | - | - | | |
| | 355 LA/LB/LC/LD | 4; 6 | - | - | - | - | 876 | 724 | 630 | 478 | 947 | 764 | 701 | 518 | | |

(): permissible axial loads with Front bearing locked

ATEX DUST - Zones 21 & 22 - Cast iron

Vertical motor
Shaft end downwards

For a bearing service life L_{10h}
of 25,000 hours
and 40,000 hours



| | | Permissible axial load (daN) on the main drive shaft for standard fitting of bearings | | | | | | | | | | | | |
|-----------------|-----------------|---|--------------|--------------|--------------|------------------------|--------------|--------------|--------------|------------------------|--------------|--------------|--------------|--------------|
| | | IM V5 IM V1 / V15 IM V18 / V58 | | | | | | | | | | | | |
| | | 3000 min ⁻¹ | | | | 1500 min ⁻¹ | | | | 1000 min ⁻¹ | | | | |
| Series | Type | Polarity | 25,000 hours | 40,000 hours | 25,000 hours | 40,000 hours | 25,000 hours | 40,000 hours | 25,000 hours | 40,000 hours | 25,000 hours | 40,000 hours | 25,000 hours | 40,000 hours |
| FLSPX FLSES | 80 L | 2 | 29 | 20 | (63) | (54) | - | - | - | - | - | - | - | - |
| | 80 LG | 2; 4 | 26 | 16 | (72) | (62) | 45 | 32 | (93) | (78) | - | - | - | - |
| | 90 SL/L | 2; 4; 6 | 26 | 16 | (73) | (63) | 42 | 28 | (91) | (78) | 53 | 37 | (101) | (86) |
| | 90 LU | 2; 4; 6 | 19 | 9 | (77) | (67) | 33 | 20 | (95) | (82) | 43 | 28 | (105) | (89) |
| | 100 L | 2; 4 | 36 | 23 | (96) | (83) | 56 | 38 | (119) | (101) | - | - | - | - |
| | 100 LR | 4 | - | - | - | - | 55 | 37 | (120) | (102) | - | - | - | - |
| | 100 LG | 4; 6 | - | - | - | - | 48 | 31 | (116) | (99) | 68 | 46 | (137) | (115) |
| | 112 MG | 2; 6 | 31 | 18 | (98) | (85) | - | - | - | - | 75 | 53 | (145) | (123) |
| | 112 MU | 4; 6 | - | - | - | - | 45 | 28 | (128) | (110) | 57 | 36 | (140) | (119) |
| | 132 SM/M | 2; 4; 6 | 90 | 62 | (189) | (161) | 135 | 98 | (235) | (198) | 171 | 127 | (271) | (227) |
| | 132 MU | 6 | - | - | - | - | - | - | - | - | 154 | 110 | (275) | (231) |
| | 132 MR | 4 | - | - | - | - | 113 | 77 | (245) | (208) | - | - | - | - |
| | 160 M | 2; 4; 6 | 107 | 72 | 264 | 229 | 164 | 117 | 325 | 277 | 209 | 152 | 374 | 317 |
| | 160 MU | 6 | - | - | - | - | - | - | - | - | 189 | 133 | 375 | 319 |
| | 160 L | 2; 4 | 94 | 59 | 256 | 221 | 174 | 126 | 331 | 284 | - | - | - | - |
| | 160 LUR | 2; 4; 6 | 133 | 92 | 297 | 256 | 185 | 130 | 362 | 308 | 227 | 162 | 417 | 352 |
| | 180 M | 2; 4 | 160 | 119 | 279 | 238 | 187 | 132 | 361 | 306 | - | - | - | - |
| | 180 MT | 4 | - | - | - | - | 190 | 135 | 361 | 306 | - | - | - | - |
| | 180 MUR | 2 | 144 | 102 | 294 | 252 | - | - | - | - | - | - | - | - |
| | 180 L | 4; 6 | - | - | - | - | 206 | 151 | 346 | 291 | 233 | 169 | 391 | 326 |
| | 180 LUR | 4; 6 | - | - | - | - | 187 | 132 | 355 | 300 | 183 | 120 | 377 | 314 |
| | 200 LU | 2; 4; 6 | 207 | 153 | 375 | 320 | 262 | 190 | 471 | 398 | 269 | 186 | 505 | 422 |
| | 225 S | 4 | - | - | - | - | 351 | 260 | 611 | 520 | - | - | - | - |
| | 225 SR | 4 | - | - | - | - | 317 | 236 | 520 | 438 | - | - | - | - |
| | 225 M | 4; 6 | - | - | - | - | 333 | 241 | 627 | 535 | 428 | 319 | 723 | 613 |
| | 225 MR | 2 | 234 | 174 | 413 | 352 | - | - | - | - | - | - | - | - |
| | 250 M | 2; 6 | 247 | 179 | 481 | 413 | - | - | - | - | 423 | 315 | 647 | 539 |
| | 250 MR | 4 | - | - | - | - | 315 | 223 | 639 | 547 | - | - | - | - |
| | 280 S/M | 2; 4; 6 | 396 | 307 | 484 | 395 | 507 | 394 | 670 | 557 | 602 | 461 | 793 | 651 |
| | 315 S/M/LA/LB | 2; 6 | 226 | 156 | 417 | 347 | - | - | - | - | - | - | - | - |
| | 315 S/M/LA/LB | 4 | - | - | - | - | 601 | 449 | 893 | 741 | 683 | 515 | 1042 | 873 |
| | 355 LA/LB/LC/LD | 2 | 135 | 65 | 524 | 454 | - | - | - | - | - | - | - | - |
| 355 LAL | 4 | - | - | - | - | 516 | 350 | 1123 | 957 | - | - | - | - | |
| 355 LA/LB/LC/LD | 4; 6 | - | - | - | - | 516 | 350 | 1123 | 957 | 566 | 364 | 1328 | 1126 | |

(): permissible axial loads with Front bearing locked

Vertical motor
Shaft end upwards

For a bearing service life L_{10h}
of 25,000 hours
and 40,000 hours



| Series | Type | Polarity | Permissible axial load (daN) on the main drive shaft for standard fitting of bearings | | | | | | | | | | | |
|--------------------------------------|-----------|----------|---|--------------|--------------|--------------|------------------------|--------------|--------------|--------------|------------------------|--------------|--------------|--------------|
| | | | 3000 min ⁻¹ | | | | 1500 min ⁻¹ | | | | 1000 min ⁻¹ | | | |
| | | | 25,000 hours | 40,000 hours | 25,000 hours | 40,000 hours | 25,000 hours | 40,000 hours | 25,000 hours | 40,000 hours | 25,000 hours | 40,000 hours | 25,000 hours | 40,000 hours |
| IM V6 IM V3 / V36 IM V19 / V69 | | | | | | | | | | | | | | |
| FLSPX FLSES | 80 L | 2 | (59) | (50) | 33 | 24 | - | - | - | - | - | - | - | - |
| | 80 LG | 2; 4 | (66) | (56) | 32 | 22 | (85) | (71) | 53 | 39 | - | - | - | - |
| | 90 SL/L | 2; 4; 6 | (66) | (56) | 33 | 23 | (82) | (68) | 51 | 38 | (93) | (77) | 61 | 46 |
| | 90 LU | 2; 4; 6 | (69) | (59) | 27 | 18 | (81) | (76) | 43 | 38 | (93) | (82) | 55 | 32 |
| | 100 L | 2 | (86) | (72) | 46 | 33 | (106) | (88) | 69 | 51 | - | - | - | - |
| | 100 LR | 4 | - | - | - | - | (105) | (87) | 70 | 52 | - | - | - | - |
| | 100 LG | 4; 6 | - | - | - | - | (98) | (81) | 67 | 49 | (118) | (96) | 87 | 66 |
| | 112 MG | 2; 6 | (81) | (68) | 48 | 35 | - | - | - | - | (125) | (103) | 95 | 73 |
| | 112 MU | 4; 6 | - | - | - | - | (105) | (88) | 68 | 50 | (117) | (96) | 80 | 60 |
| | 132 SM/M | 2; 4; 6 | (159) | (132) | 120 | 91 | (205) | (168) | 165 | 128 | (249) | (205) | 179 | 135 |
| | 132 MU | 6 | - | - | - | - | - | - | - | - | (234) | (190) | 195 | 151 |
| | 132 MR | 4 | - | - | - | - | (203) | (167) | 155 | 118 | - | - | - | - |
| | 160 M | 2; 4; 6 | 207 | 172 | 164 | 129 | 264 | 217 | 225 | 177 | 309 | 252 | 274 | 217 |
| | 160 MU | 6 | - | - | - | - | - | - | - | - | 289 | 233 | 275 | 219 |
| | 160 L | 2; 4 | 194 | 159 | 156 | 121 | 274 | 226 | 231 | 184 | - | - | - | - |
| | 160 LUR | 2; 4; 6 | 233 | 192 | 197 | 156 | 285 | 230 | 262 | 208 | 327 | 262 | 317 | 252 |
| | 180 M | 2; 4 | 208 | 167 | 231 | 190 | 250 | 195 | 298 | 243 | - | - | - | - |
| | 180 MT | 4 | - | - | - | - | 290 | 235 | 261 | 206 | - | - | - | - |
| | 180 MUR | 2 | 207 | 165 | 231 | 189 | - | - | - | - | - | - | - | - |
| | 180 L | 4; 6 | - | - | - | - | 254 | 199 | 298 | 243 | 281 | 217 | 343 | 278 |
| | 180 LUR | 4; 6 | - | - | - | - | 250 | 195 | 292 | 237 | 246 | 183 | 314 | 251 |
| | 200 LU | 2; 4; 6 | 270 | 216 | 312 | 257 | 325 | 253 | 408 | 335 | 332 | 249 | 442 | 359 |
| | 225 S | 4 | - | - | - | - | 414 | 323 | 548 | 457 | - | - | - | - |
| | 225 SR | 4 | - | - | - | - | 380 | 299 | 457 | 375 | - | - | - | - |
| | 225 M | 4; 6 | - | - | - | - | 413 | 321 | 547 | 455 | 508 | 399 | 643 | 533 |
| | 225 MR | 2 | 297 | 237 | 350 | 289 | - | - | - | - | - | - | - | - |
| | 250 M | 2; 6 | 327 | 259 | 401 | 333 | - | - | - | - | 423 | 315 | 647 | 539 |
| | 250 MR | 4 | - | - | - | - | 395 | 303 | 559 | 467 | - | - | - | - |
| | 280 S/M | 2; 4; 6 | 396 | 307 | 484 | 395 | 507 | 394 | 670 | 557 | 602 | 461 | 793 | 651 |
| | 315 S/M/L | 2 | 226 | 156 | 417 | 347 | - | - | - | - | - | - | - | - |
| 315 S/M/L | 4; 6 | - | - | - | - | 601 | 449 | 893 | 741 | 683 | 515 | 1042 | 873 | |
| 355 LA/LB/LC/LD | 2 | 135 | 65 | 524 | 454 | - | - | - | - | - | - | - | - | |
| 355 LA/LB/LC/LD | 4; 6 | - | - | - | - | 516 | 350 | 1123 | 957 | 566 | 364 | 1328 | 1126 | |










(): permissible axial loads with Front bearing locked

STANDARD FITTING ARRANGEMENT

Permissible radial load on main shaft extension with a bearing life L10h of 25,000 hours.

FR: Radial Force

X: distance with respect to the shaft shoulder












STANDARD FITTING ARRANGEMENT

Permissible radial load on main shaft extension with a bearing life L10h of 25,000 hours.

FR: Radial Force

X: distance with respect to the shaft shoulder









ATEX DUST - Zones 21 & 22 - Cast iron

STANDARD FITTING ARRANGEMENT

Permissible radial load on main shaft extension with a bearing life L10h of 25,000 hours.

FR: Radial Force

X: distance with respect to the shaft shoulder



SPECIAL FITTING ARRANGEMENT







Type of drive end roller bearings

| Series | Type | Polarity | Rear bearing (N.D.E.) | Front Bearing (D.E.) |
|----------------|-----------|----------|-----------------------|----------------------|
| FLSPX FLSES | 160 M/MU | 4; 6 | 6210 C3 | NU 309 |
| | 160 L | 4 | | |
| | 160 LUR | 6 | | |
| | 180 MT | 4 | 6210 C3 | NU 310 |
| | 180 M | 4 | | |
| | 180 L | 4 | 6212 C3 | NU 310 |
| | 180 LUR | 4; 6 | | |
| | 200 LU | 4; 6 | 6312 C3 | NU 312 |
| | 225 S | 4 | 6314 C3 | NU 314 |
| | 225 SR | 4 | 6312 C3 | NU 313 |
| | 225 M | 4; 6 | 6314 C3 | NU 314 |
| | 225 MR | 2 | 6312 C3 | NU 313 |
| | 250 M | 6 | 6314 C3 | NU 314 |
| | 250 MR | 4 | | |
| | 280 S/M | 4; 6 | 6314 C3 | NU 316 |
| | 315 S/M/L | 4; 6 | 6316 C3 | NU 320 |
| | 355 L | 4; 6 | 6316 C3 | NU 322 |

Permissible radial load on main shaft extension with a bearing life L_{10h} of 25,000 hours.

FR: Radial Force

X: distance with respect to the shaft shoulder












SPECIAL FITTING ARRANGEMENT (DRIVE-END ROLLER BEARINGS)

Permissible radial load on main shaft extension with a bearing life L10h of 25,000 hours.

FR: Radial Force

X: distance with respect to the shaft shoulder



INDICATION OF CABLE GLAND SIZE AND TYPE FOR 400 V RATED SUPPLY VOLTAGE IF DRILLINGS REQUIRED WITHOUT DETAILS OF DIAMETERS

| Series | Type | Polarity | Power + auxiliaries | |
|--------|-------------|----------|-------------------------|--|
| | | | Number of holes | Hole diameter |
| FLSPX | 80 | 2; 4; 6 | 1 (2 if auxiliaries) | ISO M20 x 1.5 (1M20 + 1M16) |
| | 90 | 2; 4; 6 | | |
| | 100 | 2; 4; 6 | | |
| | 112 | 2; 4; 6 | | |
| | 132 | 2; 4; 6 | 2 (3 if auxiliaries) | ISO M25 x 1.5 (2M25 + 1M16) |
| | 160 | 2; 4; 6 | | |
| | 180 MUR | 2; 4; 6 | 3 | 2M40 + 1M16 |
| | 180 M/L/LUR | 2; 4; 6 | | |
| | 200 | 2; 4; 6 | | |
| | 225 SR/MR | 2; 4; 6 | | |
| | 225 M | 2; 4; 6 | | |
| | 250 | 2; 4; 6 | | |
| | 280 | 2; 4; 6 | 1 (2 if auxiliaries) | ISO M63 x 1.5 (1M63 + 1M16) ISO M75 x 1.5 (1M75 + 1M16) |
| | 315 | 2; 4; 6 | | |
| 355 | 2; 4; 6 | | | |

| Series | Type | Polarity | Power + auxiliaries | |
|--------|---------|----------|-------------------------|--------------------------------------|
| | | | Number of holes | Hole diameter |
| FLSES | 80 | 2; 4 | 1 (2 if auxiliaries) | ISO M20 x 1.5 (1M20 + 1M16) |
| | 90 | 2; 4; 6 | | |
| | 100 | 2; 4; 6 | | |
| | 112 | 2; 4; 6 | 2 (3 if auxiliaries) | ISO M25 x 1.5 (2M25 + 1M16) |
| | 132 | 2; 4; 6 | | |
| | 160 | 2; 4; 6 | 0 | Removable undrilled support plate |
| | 180 | 2; 4; 6 | | |
| | 200 | 2; 4; 6 | | |
| | 225 | 2; 4; 6 | | |
| | 250 | 2; 4; 6 | | |
| | 280 | 2; 4; 6 | | |
| 315 | 2; 4; 6 | | | |
| 355 | 2; 4; 6 | | | |

**TERMINAL BLOCKS
DIRECTION OF ROTATION**

Standard motors are fitted with a 6-terminal safety block, with the terminal markings complying with or IEC 60034-8. When the motor is running in U1, V1, W1 or 1U, 1V, 1W from a direct mains supply L1, L2, L3, it turns clockwise when seen from the drive shaft end.

If any two of the phases are changed over, the motor will run in the opposite direction (make sure that the motor has been designed to run in both directions).

If the motor is fitted with accessories (thermal protection or space heater), these must be connected on terminal blocks with labelled wires.

Tightening torque for the nuts on the terminal blocks.

| Terminal | M5 | M6 | M8 | M10 | M12 | M14 | M16 |
|------------|-----|----|----|-----|-----|-----|-----|
| Torque N.m | 3.2 | 5 | 10 | 20 | 35 | 50 | 65 |

| Series | Type | 400 V mains supply | | |
|----------------|--------------|---------------------------|-----------|------------------------|
| | | 230/400 V connection | | 400 V drive connection |
| | | Polarity | Terminals | Terminals |
| FLSPX FLSES | 80 to 112 | 2; 4; 6 | M5 | M5 |
| | 132 S to 160 | 2; 4; 6 | M6 | M6 |
| | 180 M | 2 | M6 | M6 |
| | 180 L | 6 | M6 | M6 |
| | 180 LUR | 4 | M8 | M6 |
| | 200 LU | 2 (30 kW); 4; 6 (18.5 kW) | M8 | M6 |
| | 200 LU | 2 (37 kW); 6 (22 kW) | M8 | M8 |
| | 225 M | 6 | M8 | M8 |
| | 225 to 250 | 4 | M10 | M10 |
| | 250 M | 6 | M10 | M10 |
| | 280 to 315 | 2; 4; 6 | M12 | M12 |
| | 355 L | 2; 4; 6 | M12 | M12 |

ATEX DUST - Zones 21 & 22 - Cast iron

| Mechanical adaptations | Frame size |
|--|---------------|
| DE and NDE bearings with 1 machining, for vibration sensor in position 12H, 12H-3H, or 12H-3H-9H | ≥ 132 |
| Different FF flanges from IEC | All |
| Different FT flanges from IEC | ≤ 132 |
| DE roller bearing | ≥ 160: 4p & + |
| Angular contact bearing | All |
| Insulated DE or NDE bearing | ≥ 280 |
| 2 nd standard catalogue NDE shaft end | All |
| 2 nd special NDE shaft end | All |
| Conical shaft | All |
| Smooth shaft without keying | All |
| Shaft with special keying | All |
| Keyed cylindrical NDE shaft (secondary shaft end) as per IEC | All |
| Stainless-steel shaft | All |
| Class B balancing | All |
| F type (full key) or N type (no key) balancing | All |
| Stainless steel fan cover | All |
| Steel fan cover + drip cover | All |
| Steel fan cover + anti-clogging | All |
| Metal fan | All |
| Stainless steel nameplate | All |
| Stainless-steel fastenings | All |
| Three-phase axial forced ventilation - IC 416 A | ≥ 160 |
| Incremental encoder / 1024 or 4096 pts / 5v or 11/30 V | All |
| Positioning holes (jacking screws) | ≥ 250 |
| Radial seal for motor in vertical position with shaft end upwards | All |
| Drain holes for operation in vertical position | All |
| Electrical adaptations | Frame size |
| Terminal board with anti-rotation system as standard | All |
| Special voltages (excluding variable speed) | All |
| Insulation class H | All |
| Main box in position B or D | All |
| Auxiliary boxes | ≥ 160 |
| Plastic PE | All |
| ATEX brass PE for unshielded cable for FLSPX zone 21 | All |
| ATEX brass PE for shielded cable for FLSPX zone 21 | All |
| ATEX brass PE auxiliary for unshielded cable for FLSPX zone 21 | All |
| ATEX brass PE auxiliary for shielded cable for FLSPX zone 21 | All |
| Flying lead via 6 + 1 multicore cable | All |
| Cable entry on the left as seen from the shaft end | All |
| Preparation for NPT cable glands | All |
| Protections | Frame size |
| Standard winding PTC thermistor probe (triple probe) | All |
| Winding PT 100 probe (1 per phase) | All |
| Endshield PTC thermistor probe (triple probe) | ≥ 160 |
| Endshield PT 100 probe (per probe) | ≥ 160 |
| Endshield thermocouple | ≥ 160 |
| Space heaters when stopped (220-230 V) | All |
| Reinforced winding insulation system for variable speed drive power supply | All |
| Finish | Frame size |
| IP 65 for FLSES motors Zone 22 | All |
| IP 56 stopped with fan (IC 411) for FLSES motors Zone 22 | All |
| C3H, C4M, C4H, C5-IL or C5-IM paint | All |
| Other paint shades | All |
| Operating temperature: -55°C < T° < -20°C | All |
| Complete tropicalization (stator + rotor) | All |

NON-STANDARD FLANGES

Optionally, Nidec Leroy-Somer motors can be fitted with flanges and faceplates that are larger or smaller than standard. This means that motors can be adapted to all types of situation without the need for costly and time-consuming modifications.

The tables below give the flange and faceplate dimensions and also indicate flange/motor compatibility.

The bearing and shaft end for each frame size remain standard.


Dimensions in millimetres

(FF) Flange mounted

| Symbol IEC | Flange dimensions | | | | | | |
|---------------|-------------------|------|-----|-----|---|------|------|
| | M | N | D | T | n | S | LA |
| FF 115 | 115 | 95 | 140 | 3 | 4 | 10 | 10 |
| FF 130 | 130 | 110 | 160 | 3.5 | 4 | 10 | 10 |
| FF 165 | 165 | 130 | 200 | 3.5 | 4 | 12 | 10 |
| FF 215 | 215 | 180 | 250 | 4 | 4 | 15 | 12 |
| FF 265 | 265 | 230 | 300 | 4 | 4 | 15 | 14 |
| FF 300 | 300 | 250 | 350 | 5 | 4 | 18.5 | 14 |
| FF 350 | 350 | 300 | 400 | 5 | 4 | 18.5 | 15 |
| FF 400 | 400 | 350 | 450 | 5 | 8 | 18.5 | 16 |
| FF 500 | 500 | 450 | 550 | 5 | 8 | 18.5 | 18** |
| FF 600 | 600 | 550* | 660 | 6 | 8 | 24 | 22 |
| FF 740 | 740 | 680* | 800 | 6 | 8 | 24 | 25 |


* Tolerance N js6

** shaft length = 22 for frame size ≥ 280



(FT) Face mounted

| Symbol IEC | Flange dimensions | | | | | |
|---------------|-------------------|-----|-----|-----|---|-----|
| | M | N | D | T | n | M.S |
| FT 85 | 85 | 70 | 105 | 2.5 | 4 | M6 |
| FT 100 | 100 | 80 | 120 | 3 | 4 | M6 |
| FT 115 | 115 | 95 | 140 | 3 | 4 | M8 |
| FT 130 | 130 | 110 | 160 | 3.5 | 4 | M8 |
| FT 165 | 165 | 130 | 200 | 3.5 | 4 | M10 |
| FT 215 | 215 | 180 | 250 | 4 | 4 | M12 |
| FT 265 | 265 | 230 | 300 | 4 | 4 | M12 |



MODIFIED FLANGES


| Motor type | Forms of fastenings | Flange type | (FF) Flange mounted | | | | | | | | | | (FT) Face mounted | | | | | | | | | | | |
|----------------|---------------------|-----------------------|---------------------|--------|--------|--------|--------|--------|--------|--------|--------|--------|-------------------|--------|-------|-------|-------|--------|--------|--------|--------|--------|--------|---|
| | | | FF 115 | FF 130 | FF 165 | FF 215 | FF 265 | FF 300 | FF 350 | FF 400 | FF 500 | FF 600 | FF 740 | FF 940 | FT 65 | FT 75 | FT 85 | FT 100 | FT 115 | FT 130 | FT 165 | FT 215 | FT 265 | |
| FLSPX FLSES | 80 L/LG | all | ■ | ■ | ● | ◆ | | | | | | | | | | | | ◆ | ● | ◆ | ◆ | ◆ | | |
| | 90 S/L/LU | B5/B35 ⁽¹⁾ | ◆ | ◆ | ● | ◆ | | | | | | | | | | | | | | | | | | |
| | 90 S/L/LU | B3/B14/B34 | | | | | | | | | | | | | | | | ◆ | ● | ◆ | ■ | | | |
| | 100 | all | ■ | ■ | ■ | ● | | | | | | | | | | | | | ◆ | ● | ◆ | ◆ | ◆ | |
| | 112 MG | all | ■ | ■ | ■ | ● | | | | | | | | | | | | | ◆ | ● | ◆ | ◆ | ◆ | |
| | 112 MU | all | | ■ | ■ | ● | ◆ | | | | | | | | | | | | ◆ | ● | ◆ | ◆ | ◆ | |
| | 132 S/M/MR/MU | all | | | ■ | ◆ | ● | | | | | | | | | | | | | | ● | ◆ | ◆ | ◆ |
| | 160 M/L/LU | all | | | | ◆ | ◆ | ● | ◆ | | | | | | | | | | | | | | | |
| | 180 M/MR/L/LUR | all | | | | | ◆ | ● | ◆ | | | | | | | | | | | | | | | |
| | 200 LU | all | | | | | | | ● | ◆ | | | | | | | | | | | | | | |
| | 225 SR/M/MR | all | | | | | | | | ◆ | ● | ◆ | | | | | | | | | | | | |
| | 250 M/MR | all | | | | | | | | ◆ | ● | | | | | | | | | | | | | |
| | 280 S/M | all | | | | | | | | ○ | ● | | | | | | | | | | | | | |
| | 315 S | all | | | | | | | | | ○ | ● | | | | | | | | | | | | |
| | 315 M/ML | all | | | | | | | | | | ● | | | | | | | | | | | | |
| 355 L | all | | | | | | | | | | ○ | ● | | | | | | | | | | | | |

● Standard ■ Modified shaft ◆ Adaptable without shaft modifications ○ Please contact us

DRIP COVER FOR OPERATION IN VERTICAL POSITION, SHAFT END DOWNWARDS

Dimensions in millimetres

| Motor type | LB' | Ø | |
|----------------|-------------|----------|-----|
| FLSPX FLSES | 80 | LB + 20 | 145 |
| | 90 | LB + 20 | 185 |
| | 100 | LB + 20 | 185 |
| | 112 MG | LB + 20 | 185 |
| | 112 MU | LB + 25 | 210 |
| | 132 S | LB + 25 | 210 |
| | 132 MR/MU/M | LB + 30 | 240 |
| | 160 | LB + 60 | 320 |
| | 180 M/MR | LB + 60 | 320 |
| | 180 L/LUR | LB + 60 | 360 |
| | 200 LU | LB + 75 | 400 |
| | 225 SR | LB + 75 | 400 |
| | 225 M/MR | LB + 130 | 420 |
| | 250 M/MR | LB + 130 | 420 |
| | 280 | LB + 130 | 420 |
| 315 | LB + 118 | 620 | |
| 355 L | LB + 112 | 710 | |



SPACE HEATERS

| Series | Type | Power (W) |
|----------------|------------|-----------|
| FLSPX FLSES | 80 L/LG | 10 |
| | 90 to 132 | 25 |
| | 160 to 200 | 52 |
| | 225 SR/MR | 52 |
| | 225 M | 100 |
| | 250 M | 100 |
| | 280 to 315 | 100* |
| | 355 | 150* |

The space heaters use 200/240 V single-phase, 50 or 60 Hz.

* Power increase possible subject to quote.

BRAKE MOTORS, FORCED VENTILATION

The integration of high-efficiency motors within a process often requires accessories to make operation easier:


- forced ventilation for motors used at high or low speeds;
- holding brakes for maintaining the rotor in the stop position without needing to leave the motor switched on;

- emergency stop brakes to immobilise loads in case of failure of the motor torque control or loss of power supply.

Notes:

- Without forced ventilation, there is a possibility of overspeed with optional class B balancing.
- The motor temperature is monitored by sensors built into the winding.

| FLSPX & FLSES | LB dimensions with forced ventilation | |
|---------------------|---------------------------------------|----------------------|
| | Foot or face mounted motor | Flange mounted motor |
| 80 L | | 317 |
| 80 LG | | |
| 90 S | 331 | 353 |
| 90 L | | |
| 90 LU | | |
| 100 L | | 373 |
| 112 MG | | 412 |
| 112 MU | | |
| 132 S | | |
| 132 MR | | 458 |
| 132 M | | |
| 132 MU | | |
| 160 M | | 641 |
| 160 L | | |
| 160 LU | | 702 |
| 180 MR | | 641 |
| 180 M | | |
| 180 L | | 689 |
| 180 LUR | | |
| 200 LU | | 819 |
| 225 SR | | 825.5 |
| 225 MR | | |
| 225 M | | 917 |
| 250 M | | |
| 280 S | | 1167 |
| 280 M | | 1167 |
| 315 S | | |
| 315 M | | 1477 |
| 315 LA/LB | | |
| 355 LA/LB/LC/LD/LAL | | 1668 |



IMfinity® ATEX 3-phase induction motors - IE3 efficiency class

ATEX DUST motors - Zones 21 & 22

FLSPX & FLSES series - Cast iron

Handling - Position of lifting rings


LIFTING THE MOTOR ONLY (not coupled to the machine)

The regulations stipulate that in excess of 25 kg suitable handling equipment must be used.

All our motors are fitted with grab handles, making them easier to handle without risk. A diagram of the sling hoisting method appears below with the required dimensions.


To prevent any damage to the motor during handling (for example: switching the motor from horizontal to vertical), it is essential to follow these instructions.

HORIZONTAL POSITION



| Type | Horizontal position | | | |
|-----------------|---------------------|--------|--------|----|
| | A | min. e | min. h | Øt |
| 100 | 152 | 200 | 150 | 22 |
| 100 | 145 | 200 | 150 | 22 |
| 112 | 145 | 200 | 150 | 22 |
| 132 | 180 | 200 | 150 | 25 |
| 160 | 200 | 260 | 150 | 14 |
| 180 M/MUR/L/LUR | 200 | 260 | 150 | 14 |
| 200 LU | 270 | 260 | 150 | 14 |
| 225 SR/MR | 270 | 260 | 150 | 14 |
| 225 S/M | 360 | 380 | 200 | 30 |
| 250 M/MR | 360 | 380 | 200 | 30 |
| 280 | 360 | 380 | 500 | 30 |
| 315 S/M/LA/LB | 440 | 400 | 500 | 60 |
| 355 | 545 | 500 | 500 | 60 |

VERTICAL POSITION




| Type | Vertical position | | | | | | |
|------------------|-------------------|-----|-----|-----|----|---------|--------|
| | C | E | D | n** | ØS | min. e* | min. h |
| 160 M/MU | 320 | 200 | 230 | 2 | 14 | 320 | 350 |
| 180 M/MUR/L/LUR* | 320 | 200 | 230 | 2 | 14 | 320 | 270 |
| 200 LU | 410 | 300 | 295 | 2 | 14 | 410 | 450 |
| 225 SR/MR | 410 | 300 | 295 | 2 | 14 | 410 | 450 |
| 225 S/M | 480 | 360 | 405 | 4 | 30 | 540 | 350 |
| 250 M/MR | 480 | 360 | 405 | 4 | 30 | 590 | 550 |
| 280 S | 480 | 360 | 585 | 4 | 30 | 590 | 550 |
| 280 M | 480 | 360 | 585 | 4 | 30 | 590 | 550 |
| 315 S/M/LA/LB | 620 | - | 715 | 2 | 35 | 650 | 550 |
| 355 | 760 | - | 750 | 2 | 35 | 800 | 550 |

* if the motor is fitted with a drip cover, allow an additional 50 to 100 mm to avoid damaging it when the load is swung.

** If n = 2, the lifting rings form an angle of 90° with respect to the terminal box. If n = 4, this angle becomes 45°.


Separate ring ≤ 25 kg
Built-in ring > 25 kg

| | |
|---|--|
| ATEX DUST motors - Zone 21 | LSPX series |
|  |  II 2 D Ex tb III C T125°C Db |
| | Premium Efficiency IE3 aluminium on mains IE3 aluminium on drive |
| | |



The complete motor **reference** described below will enable you to **order** the desired equipment.

The selection method consists of following the terms in the designation.




| | |
|---|--|
| ATEX DUST motors - Zone 22 | LSES series |
|  |  II 3 D Ex tc III B T125°C Dc |
| | Premium Efficiency |
| | IE3 aluminium on mains IE3 aluminium on drive |



The complete motor **reference** described below will enable you to **order** the desired equipment.

The selection method consists of following the terms in the designation.



NAMEPLATES

The nameplate identifies the motors, indicates the main performance and shows compatibility of the motor

concerned with the main standards and regulations concerning them.

All motors in this catalogue with power between 0.75 and 200 kW are fitted with

two information plates: one indicating the motor's performance when supplied from the mains, and the other the motor's performance when supplied from a drive.

DEFINITION OF SYMBOLS USED ON NAMEPLATES



Legal mark indicating the conformity of equipment with the requirements of European Directives

SPECIAL MARKING (ATEX)



: protection marking against explosive risks

II 2D or II 3D : ATEX marking

Ex tb or tc : "dust" protection mode

IIIB or IIIC : "dust" equipment group

T125°C : max. surface temperature

Db or Dc : "dust" EPL level

0080 : INERIS Notified Body

INERIS 00ATEX0003X : CE type examination certificate No.

| Zone | Type | ATEX marking | Marking of type of dust protection | Protection rating |
|------|---------------------------------|--|------------------------------------|-------------------|
| 21 | LSPX |  II 2 D | Ex tb IIIC T125°C Db | IP65 |
| 22 | LSES Non-conductive dusts |  II 3 D | Ex tc IIIB T125°C Dc | IP55 |

MAINS SUPPLY PLATE

MOT 3 ~ : three-phase AC motor

LSPX : series

160 : frame size

L : housing symbol

T : impregnation index

Motor no.

0123456 : motor serial number

G : month of production

12 : year of production

001 : batch number

IE3 : efficiency class

92.4% : efficiency at 4/4 load

kg : weight

IP65 : protection rating

IK08 : shock resistance

I cl.F : insulation class F

40°C : max. ambient operating temperature

S1 : duty

V : supply voltage

Hz : supply frequency

min⁻¹ : speed of rotation

kW : rated power

cos φ : power factor

A : rated current

Δ : delta connection

Y : star connection

Bearings

DE : drive end
Drive end bearing

NDE : non drive end
Bearing side opposite the drive

g : amount of grease at each regreasing (in g)

h : regreasing interval (hours)

 : vibration level

 : balancing mode

DRIVE SUPPLY PLATE

Inverter settings : required values for setting the frequency inverter

Motor performance : torque available on the motor shaft in % rated torque at the plate frequencies

Min. Fsw (kHz) : minimum switching frequency acceptable for the motor

Nmax (min⁻¹) : maximum mechanical speed acceptable for the motor

INFORMATION PLATES CAST IRON MOTORS

LSPX Zone 21 and LSES Zone 22

Mains supply plate

Nidec 3~4P LSES80LG CE

LEROY-SOMER
Moteurs Leroy-Somer CS10015
16915 Angoulême cedex 9 - France

IP55 IK08 **IE3**
Ta40°C Ins.Cl.F S1 1000m 82.5%
NEMA Nom. Eff. 83.5%

CCESB CTAUS E68554G NEMA Premium

II 3 D Ex tc IIIB T125°C Dc

DE: 6205 ZZ C3
NDE: G204 ZZ C3

| V | Hz | min-1 | kW | cosφ | A |
|-------|----|-------|------|------|------|
| Δ 380 | 50 | 1440 | 0.75 | 0.83 | 1.65 |
| Δ 230 | 50 | 1450 | 0.75 | 0.81 | 2.75 |
| Δ 400 | 50 | 1450 | 0.75 | 0.81 | 1.60 |
| Δ 415 | 50 | 1452 | 0.75 | 0.78 | 1.60 |
| Δ 460 | 60 | 1758 | 0.75 | 0.77 | 1.45 |

IEC60034-1 H50AL_500

Drive supply plate

Nidec 3~4P LSES80LG CE

LEROY-SOMER
Moteurs Leroy-Somer CS10015
16915 Angoulême cedex 9 - France

IP55 IK08 T
Ta40°C Ins.Cl.F S9 1000m 14kg

CTAUS E68554G

II 3 D Ex tc IIIB T125°C Dc

DE: 6205 ZZ C3
NDE: G204 ZZ C3

| Inverter settings | | | | | |
|-------------------|----|-------|------|------|------|
| V | Hz | min-1 | kW | cosφ | A |
| Δ 400 | 50 | 1440 | 0.75 | 0.83 | 1.70 |
| Δ 400 | 87 | 2550 | 1.31 | 0.83 | 3.00 |

| Motor performance | | | | | | min. Fsw (kHz) |
|-------------------|-----|-----|-----|-----|----|----------------|
| Hz | 10 | 17 | 25 | 50 | 87 | 3 |
| T/Tn% | 100 | 100 | 100 | 100 | 57 | Tn(Nm) 4.95 |

IEC60034-1 H50AL_500

Nidec 3~2P LSPX160L T CE 0080

LEROY-SOMER
Moteurs Leroy-Somer CS10015
16915 Angoulême cedex 9 - France

IP65 IK08 **IE3**
Ta40°C Ins.Cl.F S1 1000m 100kg 92.4%

DE: 6309 ZZ C3
NDE: 6210 ZZ C3

| V | Hz | min-1 | kW | cosφ | A |
|-------|----|-------|------|------|------|
| Δ 400 | 50 | 2950 | 18.5 | 0.88 | 32.8 |
| Δ 690 | 50 | 2950 | 18.5 | 0.88 | 19.0 |
| Δ 415 | 50 | 2954 | 18.5 | 0.86 | 32.3 |
| Δ 460 | 60 | 3558 | 18.5 | 0.87 | 28.7 |

PTC 130°C

INERIS 00ATEX0003X
II 2 D Ex tb III C T125°C Db

H50P_500E

Nidec 3 2P LSPX160L T CE 0080

LEROY-SOMER
Moteurs Leroy-Somer CS10015
16915 Angoulême cedex 9 - France

IP65 IK08
Ta40°C Ins.Cl.F S9 1000m 100kg

DE: 6309 ZZ C3
NDE: 6210 ZZ C3

| Inverter settings | | | | | |
|-------------------|----|-------|------|------|------|
| V | Hz | min-1 | kW | cosφ | A |
| Δ 400 | 50 | 2945 | 18.5 | 0.89 | 35.0 |

min. Fsw (kHz) 3
Nmax(In-1) 5220

| Motor performance | | | | | |
|-------------------|----|-----|-----|-----|----|
| Hz | 10 | 17 | 25 | 50 | 87 |
| T/Tn% | 95 | 100 | 100 | 100 | 57 |

min. Fsw (kHz) 3
Tn(Nm) 60.0

PTC 130°C

INERIS 00ATEX0003X
II 2 D Ex tb III C T125°C Db

H50P_600C

Combustible dust is dangerous because it can form potentially explosive atmospheres when dispersed in the air. Furthermore, a layer of combustible dust can ignite and act as a source of ignition in an explosive atmosphere. Explosive dust atmospheres can be found in many industries, such as agriculture, chemicals, plastics and food and drink related industries.

LSPX and LSES motors with an aluminium casing are designed to prevent any explosion due to dust:

- The ingress of dust into the motor is prevented by the IP protection, either IP55 (dustproof for LSES motors) or IP65 (dustproof for LSPX).
- The maximum surface temperature outside the engine must not exceed the temperature class for which the motor is certified.
- No sparks must reach the outside of the motor enclosure.

These motors are certified to comply with Directive 2014/34/EU.

For zone 22 LSES motors, Nidec Leroy-Somer also provides self-certification with a Declaration of Conformity.

| Designations | Materials | Comments |
|-------------------------------------|---|---|
| Finned housing | Aluminium alloy | <ul style="list-style-type: none"> - with integral or screwed feet, or without feet - 4 or 6 securing holes for housings with feet - lifting rings for frame size ≥ 100 - ground terminal with an optional jumper screw |
| Stator | Insulated low-carbon magnetic steel laminations Electroplated copper | <ul style="list-style-type: none"> - low carbon content guarantees long-term lamination pack stability - semi-enclosed slots - class F insulation - 1 set of PTC sensors in the windings from LSPX 80 to LSPX 315 and from LSES 80 zone 22 to LSES 315 zone 22 |
| Rotor | Insulated low-carbon magnetic steel laminations Aluminium | <ul style="list-style-type: none"> - inclined cage bars - rotor cage pressure die-cast in aluminum (or alloy for special applications) - assembly by hot shrinking on the shaft - rotor balanced dynamically, 1/2 key |
| Shaft | Steel | <ul style="list-style-type: none"> - for frame size ≤ 160 MP - LR: <ul style="list-style-type: none"> • centre hole • closed tapped keyway - for frame size ≥ 160 M - L: <ul style="list-style-type: none"> • tapped centre hole • open keyway |
| End shields | Cast iron | <ul style="list-style-type: none"> - 80 - 90 front and rear bearings - 100 to 315 front and rear bearings |
| Bearings and lubrication | | <ul style="list-style-type: none"> - protected ball bearings, permanently greased for frame size 80 to 225 - protected ball bearings, regreasable for frame size 250 to 315 - bearings preloaded at rear |
| Labyrinth seal Lip seals | Technopolymer or steel Synthetic rubber | <ul style="list-style-type: none"> - gasket or deflector at the front for all face mounted motors - gasket, deflector seal for foot mounted motor |
| Fan | antistatic thermoplastic or aluminium | - bi-directional: straight blades |
| Fan cover | Composite material or steel plate | - fitted, on request, with a drip cover for operation in vertical position, shaft end downwards (steel plate cover) |
| Terminal box | Composite material or aluminium alloy | <ul style="list-style-type: none"> - IP 55 or IP 65 - directional, opposite the feet - fitted with a terminal block with 6 steel terminals as standard (brass as an option) - terminal box fitted with plugs, supplied without cable gland (cable gland as an option) - 1 ground terminal in each terminal box - fastening system consisting of a cover with captive screws |

IMfinity® ATEX 3-phase induction motors - IE3 efficiency class

ATEX DUST motors - Zones 21 & 22

LSPX & LSES series - Aluminium- IE3

Electrical characteristics - Mains supply

| Type | Rated power P _n kW | Rated torque M _n N.m | Starting torque/ Rated torque M _d /M _n | Maximum torque/ Rated torque M _m /M _n | Starting current/ Rated current I _d /I _n | Moment of inertia J kg.m ² | Weight IM B3 kg | Noise LP db(A) | 400V 50Hz | | | | | | | | |
|----------------|-------------------------------------|---------------------------------------|--|---|--|---|-----------------------|----------------------|--|--------------------------------------|-------------------------------------|------|------|------|--------------|------|------|
| | | | | | | | | | Rated speed N _n min ⁻¹ | Rated current I _n A | Efficiency IEC 60034-2-1 2007 | | | | Power factor | | |
| | | | | | | | | | | | 4/4 | 3/4 | 2/4 | 4/4 | 3/4 | 2/4 | |
| 2 poles | | | | | | | | | | | | | | | | | |
| LSPX* LSES | 80 L | 0.75 | 2.5 | 3.44 | 3.44 | 7.75 | 0.00095 | 9.9 | 58 | 2890 | 1.6 | 82.4 | 82.4 | 80.2 | 0.83 | 0.76 | 0.64 |
| | 80 LG | 1.1 | 3.7 | 2.62 | 3.22 | 7 | 0.00223 | 14.1 | 64 | 2885 | 2.2 | 85.6 | 86.9 | 86.7 | 0.85 | 0.80 | 0.69 |
| | 90 SL | 1.5 | 5 | 2.92 | 3.22 | 7.47 | 0.00223 | 15.6 | 64 | 2890 | 3 | 85.3 | 86.3 | 85.5 | 0.84 | 0.78 | 0.67 |
| | 90 L | 1.8 | 6 | 3.08 | 3.37 | 7.42 | 0.00292 | 15.6 | 67 | 2900 | 3.8 | 85.6 | 86.3 | 85.6 | 0.81 | 0.74 | 0.61 |
| | 90 LU | 2.2 | 7.3 | 3.08 | 3.38 | 7.91 | 0.00292 | 20.4 | 67 | 2895 | 4.3 | 86.9 | 88.1 | 87.8 | 0.86 | 0.80 | 0.69 |
| | 100 L | 3 | 10 | 3.53 | 3.43 | 8.34 | 0.00364 | 24.6 | 67 | 2885 | 5.8 | 87.1 | 88.3 | 88.0 | 0.86 | 0.81 | 0.71 |
| | 112 MG | 4 | 13.1 | 2 | 2.9 | 7.1 | 0.00941 | 32.7 | 71 | 2920 | 7.2 | 89.0 | 90.1 | 90.1 | 0.90 | 0.86 | 0.78 |
| | 132 S | 5.5 | 18 | 2.3 | 3.05 | 7.54 | 0.01116 | 39.2 | 63 | 2925 | 10.1 | 89.4 | 90.5 | 90.5 | 0.88 | 0.84 | 0.75 |
| | 132 SM | 7.5 | 24.4 | 2.1 | 2.9 | 6.8 | 0.01102 | 55.7 | 67 | 2935 | 13.8 | 91.2 | 92.1 | 92.1 | 0.86 | 0.83 | 0.74 |
| | 132 M | 9 | 29.2 | 2.15 | 3.25 | 7.65 | 0.01203 | 59.3 | 67 | 2945 | 16.7 | 91.7 | 92.4 | 92.2 | 0.85 | 0.81 | 0.72 |
| | 160 MP | 11 | 35.7 | 1.9 | 2.9 | 6.95 | 0.0139 | 70 | 72 | 2940 | 19.9 | 91.5 | 92.3 | 92.1 | 0.87 | 0.83 | 0.74 |
| | 160 M | 15 | 48.6 | 2.3 | 2.75 | 7.86 | 0.0490 | 95 | 69 | 2945 | 26.5 | 91.9 | 92.6 | 92.6 | 0.89 | 0.87 | 0.81 |
| | 160 L | 18.5 | 59.9 | 2.8 | 3.15 | 7.6 | 0.0551 | 100 | 68 | 2950 | 32.8 | 92.6 | 93.3 | 93.2 | 0.88 | 0.84 | 0.76 |
| | 180 MR | 22 | 71.1 | 3.15 | 3.15 | 8.67 | 0.0628 | 105 | 69 | 2954 | 38.7 | 93.2 | 93.9 | 94.0 | 0.88 | 0.85 | 0.77 |
| | 200 LR | 30 | 97.3 | 2.6 | 3.05 | 7.65 | 0.1106 | 170 | 73 | 2945 | 51.5 | 93.5 | 94.2 | 94.4 | 0.90 | 0.88 | 0.83 |
| | 200 L | 37 | 120 | 2 | 3.05 | 7.08 | 0.2492 | 201 | 73 | 2945 | 63.9 | 93.9 | 94.5 | 94.4 | 0.89 | 0.87 | 0.81 |
| | 225 MR | 45 | 145 | 2.67 | 3.42 | 7.88 | 0.1597 | 227 | 76 | 2962 | 79.7 | 94.8 | 95.1 | 94.7 | 0.86 | 0.82 | 0.73 |
| | 250 MZ | 55 | 178 | 2.45 | 3.45 | 7.9 | 0.1754 | 234 | 72 | 2954 | 97.5 | 94.7 | 95.2 | 95.2 | 0.86 | 0.82 | 0.74 |
| | 280 SC | 75 | 241 | 2.3 | 3.3 | 8.05 | 0.4092 | 350 | 79 | 2970 | 126 | 95.2 | 95.5 | 95.1 | 0.90 | 0.88 | 0.82 |
| | 280 MC | 90 | 289 | 2.5 | 3.6 | 8.5 | 0.4760 | 382 | 80 | 2972 | 151 | 95.5 | 95.8 | 95.5 | 0.90 | 0.87 | 0.82 |
| | 315 SN | 110 | 354 | 2.55 | 3.1 | 8 | 0.5343 | 452 | 79 | 2968 | 185 | 95.5 | 95.9 | 95.8 | 0.90 | 0.88 | 0.84 |
| | 315 MP | 132 | 423 | 2.25 | 3.2 | 7.73 | 0.5784 | 660 | 80 | 2978 | 226 | 96.0 | 96.0 | 95.4 | 0.88 | 0.86 | 0.81 |
| | 315 MP | 160 | 513 | 2.2 | 3.3 | 7.7 | 1.2646 | 705 | 80 | 2978 | 274 | 95.8 | 95.9 | 94.3 | 0.88 | 0.86 | 0.80 |
| | 315 MP | 200 | 642 | 2.15 | 3.5 | 7.8 | 1.3841 | 768 | 80 | 2974 | 342 | 96.0 | 96.2 | 95.9 | 0.88 | 0.86 | 0.80 |

* For power > 200 kW, please contact us.

| | | | | | | | | | | | | | | | | | |
|----------------|---------|------|------|------|------|------|---------|------|----|------|------|------|------|------|------|------|------|
| 4 poles | | | | | | | | | | | | | | | | | |
| LSPX* LSES | 80 LG | 0.75 | 5 | 2.18 | 2.92 | 6.38 | 0.00335 | 13.6 | 48 | 1450 | 1.6 | 83.6 | 84.3 | 83.0 | 0.81 | 0.73 | 0.59 |
| | 90 SL | 1.1 | 7.3 | 2.44 | 3.18 | 6.91 | 0.00418 | 16.2 | 45 | 1450 | 2.3 | 84.8 | 85.7 | 85.0 | 0.81 | 0.74 | 0.61 |
| | 90 LU | 1.5 | 9.9 | 2.89 | 3.69 | 7.66 | 0.00524 | 20.4 | 51 | 1452 | 3.2 | 85.6 | 86.2 | 85.1 | 0.79 | 0.70 | 0.57 |
| | 100 L | 1.8 | 11.8 | 2.41 | 2.73 | 6.42 | 0.00561 | 23.7 | 48 | 1456 | 3.8 | 86.6 | 87.3 | 86.1 | 0.79 | 0.71 | 0.57 |
| | 100 LR | 2.2 | 14.4 | 3.2 | 3.75 | 7.87 | 0.00676 | 25.8 | 47 | 1454 | 4.7 | 87.1 | 87.7 | 86.7 | 0.78 | 0.70 | 0.57 |
| | 100 LG | 3 | 19.6 | 2.45 | 3.25 | 7.22 | 0.01152 | 31 | 55 | 1464 | 6 | 89.2 | 89.9 | 89.9 | 0.81 | 0.74 | 0.61 |
| | 112 MU | 4 | 26.2 | 2.7 | 3.1 | 7.23 | 0.01312 | 34.4 | 54 | 1456 | 7.9 | 88.9 | 89.8 | 89.6 | 0.82 | 0.77 | 0.65 |
| | 132 SM | 5.5 | 35.9 | 2.8 | 3.6 | 8.39 | 0.02286 | 52 | 59 | 1462 | 10.5 | 90.3 | 91.0 | 90.6 | 0.84 | 0.77 | 0.65 |
| | 132 MU | 7.5 | 49.1 | 2.95 | 3.35 | 8.12 | 0.02965 | 62.6 | 61 | 1458 | 13.8 | 90.4 | 91.5 | 91.9 | 0.87 | 0.82 | 0.73 |
| | 160 MR | 9 | 58.7 | 3.1 | 3.65 | 8.69 | 0.03574 | 77.8 | 62 | 1464 | 17 | 91.0 | 91.8 | 91.7 | 0.84 | 0.78 | 0.67 |
| | 160 M | 11 | 71.7 | 2.25 | 3.05 | 7.36 | 0.0712 | 93 | 59 | 1466 | 20.2 | 91.4 | 92.4 | 92.6 | 0.86 | 0.82 | 0.73 |
| | 160 LUR | 15 | 97.6 | 2.55 | 3.45 | 8.47 | 0.0954 | 100 | 58 | 1468 | 27.3 | 92.1 | 92.9 | 93.0 | 0.86 | 0.82 | 0.72 |
| | 180 M | 18.5 | 120 | 2.95 | 2.85 | 7.76 | 0.1333 | 130 | 68 | 1468 | 33.9 | 92.8 | 93.6 | 93.5 | 0.85 | 0.81 | 0.72 |
| | 180 LUR | 22 | 143 | 3.25 | 3.15 | 8.16 | 0.1555 | 155 | 68 | 1470 | 41.1 | 93.0 | 93.4 | 93.3 | 0.83 | 0.79 | 0.69 |
| | 200 LU | 30 | 194 | 3 | 2.8 | 7.31 | 0.2704 | 225 | 63 | 1476 | 55 | 93.7 | 94.3 | 94.1 | 0.84 | 0.79 | 0.70 |
| | 225 SR | 37 | 239 | 3.25 | 3.15 | 7.95 | 0.2897 | 236 | 63 | 1480 | 70.2 | 93.9 | 94.2 | 93.8 | 0.81 | 0.76 | 0.65 |
| | 225 MG | 45 | 289 | 2.31 | 2.86 | 7.25 | 0.6573 | 318 | 70 | 1486 | 83.6 | 94.8 | 95.0 | 94.5 | 0.82 | 0.77 | 0.66 |
| | 250 ME | 55 | 354 | 2.3 | 2.7 | 7.3 | 0.7793 | 350 | 69 | 1484 | 101 | 94.7 | 95.1 | 95.0 | 0.83 | 0.79 | 0.70 |
| | 280 SD | 75 | 482 | 2.45 | 3.2 | 8.08 | 0.9595 | 428 | 69 | 1486 | 139 | 95.0 | 95.2 | 94.9 | 0.82 | 0.78 | 0.69 |
| | 280 MD | 90 | 579 | 2.6 | 3.45 | 8.35 | 1.0799 | 470 | 68 | 1484 | 168 | 95.5 | 95.7 | 95.4 | 0.81 | 0.76 | 0.65 |
| | 315 SP | 110 | 707 | 3.1 | 2.85 | 7.57 | 2.4322 | 690 | 76 | 1486 | 200 | 95.6 | 95.6 | 94.9 | 0.83 | 0.78 | 0.69 |
| | 315 MP | 132 | 847 | 3.05 | 2.75 | 7.24 | 3.2230 | 740 | 76 | 1488 | 237 | 95.9 | 96.0 | 95.5 | 0.84 | 0.80 | 0.70 |
| | 315 MP | 160 | 1030 | 2.55 | 2.8 | 7.2 | 3.2230 | 740 | 76 | 1486 | 291 | 95.8 | 95.7 | 95.2 | 0.83 | 0.78 | 0.67 |
| | 315 MR | 200 | 1290 | 2.95 | 2.9 | 7.38 | 3.2324 | 820 | 76 | 1486 | 362 | 96.0 | 96.0 | 95.5 | 0.83 | 0.79 | 0.68 |

* For power > 200 kW, please contact us.

| | | | | | | | | | | | | | | | | | |
|----------------|---------|------|------|------|------|--------|---------|------|-----|-----|------|------|------|------|------|------|------|
| 6 poles | | | | | | | | | | | | | | | | | |
| LSPX* LSES | 90 SL | 0.75 | 7.5 | 1.87 | 2.32 | 4.25 | 0.00378 | 16 | 56 | 952 | 2 | 79.2 | 80.0 | 79.1 | 0.71 | 0.62 | 0.48 |
| | 90 LU | 1.1 | 11 | 2.35 | 2.7 | 4.75 | 0.00519 | 21.5 | 56 | 956 | 2.8 | 81.9 | 82.3 | 80.3 | 0.70 | 0.61 | 0.47 |
| | 100 LG | 1.5 | 14.8 | 2.35 | 2.8 | 5.64 | 0.01523 | 30 | 43 | 966 | 3.6 | 83.8 | 84.4 | 82.9 | 0.72 | 0.63 | 0.50 |
| | 112 MU | 2.2 | 21.7 | 2.3 | 2.75 | 5.44 | 0.01899 | 37 | 46 | 966 | 5.4 | 84.3 | 84.8 | 83.5 | 0.70 | 0.61 | 0.49 |
| | 132 SM | 3 | 29.5 | 2.75 | 3.15 | 6.6 | 0.02528 | 48 | 50 | 972 | 6.8 | 87.5 | 88.0 | 86.9 | 0.73 | 0.65 | 0.53 |
| | 132 M | 4 | 39.3 | 2.65 | 2.9 | 6.38 | 0.03027 | 54 | 56 | 972 | 9.1 | 87.4 | 88.1 | 87.1 | 0.73 | 0.65 | 0.53 |
| | 132 MU | 5.5 | 54.4 | 2.6 | 2.85 | 6.4 | 0.03699 | 63.1 | 57 | 966 | 11.7 | 88.1 | 89.2 | 89.1 | 0.77 | 0.70 | 0.58 |
| | 160 MU | 7.5 | 73.2 | 2 | 3.05 | 6.93 | 0.1295 | 82 | 58 | 978 | 16.1 | 89.6 | 89.7 | 88.4 | 0.75 | 0.67 | 0.54 |
| | 180 L | 11 | 107 | 3.05 | 3.45 | 8.65 | 0.2048 | 130 | 62 | 982 | 22.6 | 91.1 | 91.3 | 90.3 | 0.77 | 0.70 | 0.57 |
| | 180 LUR | 15 | 146 | 3.05 | 3.15 | 8.42 | 0.2530 | 150 | 63 | 980 | 30.7 | 91.5 | 91.9 | 91.3 | 0.77 | 0.70 | 0.58 |
| | 200 L | 18.5 | 180 | 2.2 | 2.85 | 7.07 | 0.3300 | 200 | 61 | 980 | 36.2 | 92.1 | 92.8 | 92.6 | 0.80 | 0.75 | 0.66 |
| | 200 LU | 22 | 214 | 2.8 | 3.55 | 7.35 | 0.3901 | 236 | 62 | 980 | 44.6 | 92.5 | 93.0 | 92.5 | 0.77 | 0.71 | 0.61 |
| | 225 MG | 30 | 291 | 2.25 | 2.45 | 6.6 | 0.7222 | 284 | 64 | 986 | 55.3 | 93.3 | 93.7 | 93.3 | 0.84 | 0.80 | 0.70 |
| | 250 ME | 37 | 358 | 2.35 | 2.8 | 7.07 | 0.9234 | 310 | 64 | 986 | 66.9 | 93.9 | 94.4 | 94.3 | 0.85 | 0.81 | 0.72 |
| | 280 SC | 45 | 437 | 2.2 | 2.45 | 6.62 | 1.1279 | 377 | 64 | 984 | 80.4 | 93.9 | 94.5 | 94.5 | 0.86 | 0.83 | 0.74 |
| | 280 MD | 55 | 533 | 2.8 | 3 | 7.66 | 1.3995 | 444 | 59 | 986 | 98.6 | 94.7 | 95.2 | 95.0 | 0.85 | 0.81 | 0.72 |
| | 315 SP | 75 | 723 | 2.95 | 2.55 | 7.5 | 2.8937 | 630 | 71 | 990 | 146 | 94.9 | 95.0 | 94.2 | 0.78 | 0.73 | 0.61 |
| | 315 MP | 90 | 868 | 3.05 | 2.65 | 7.8 | 3.4127 | 700 | 75 | 990 | 171 | 95.2 | 95.1 | 94.4 | 0.79 | 0.74 | 0.64 |
| 315 MR | 110 | 1060 | 2.95 | 2.1 | 7.45 | 3.0776 | 770 | 72 | 990 | 208 | 95.4 | 95.6 | 95.1 | 0.80 | 0.76 | 0.66 | |
| 315 MR | 132 | 1270 | 2.7 | 2.15 | 7.16 | 4.6331 | 860 | 76 | 990 | 249 | 95.5 | 95.7 | 95.3 | 0.80 | 0.75 | 0.65 | |

* For power > 132 kW, please contact us.

ATEX DUST - Zones 21 & 22 - Aluminium

ATEX DUST motors - Zones 21 & 22

LSPX & LSES series - Aluminium- IE3

Electrical characteristics - Mains supply

| Type | Rated power | 415V 50Hz | | | | 460V 60Hz | | | | |
|----------------|----------------------|-------------------------------------|---------------------|------------|--------------|-------------------------------------|---------------------|------------|--------------|------|
| | | Rated speed | Rated current | Efficiency | Power factor | Rated speed | Rated current | Efficiency | Power factor | |
| | P _n kW | N _n min ⁻¹ | I _n A | η 4/4 | Cos φ 4/4 | N _n min ⁻¹ | I _n A | η 4/4 | Cos φ 4/4 | |
| 2 poles | | | | | | | | | | |
| LSPX* LSES | 80 L | 0.75 | 2900 | 1.6 | 82.3 | 0.81 | 3505 | 1.4 | 83.3 | 0.80 |
| | 80 LG | 1.1 | 2895 | 2.1 | 86.2 | 0.84 | 3505 | 1.9 | 87.0 | 0.83 |
| | 90 SL | 1.5 | 2900 | 2.9 | 86.1 | 0.83 | 3510 | 2.7 | 86.9 | 0.82 |
| | 90 L | 1.8 | 2910 | 3.8 | 85.7 | 0.78 | 3515 | 3.3 | 86.9 | 0.82 |
| | 90 LU | 2.2 | 2905 | 4.1 | 87.3 | 0.85 | 3505 | 3.7 | 88.2 | 0.85 |
| | 100 L | 3 | 2900 | 5.7 | 87.6 | 0.84 | 3505 | 5.1 | 87.6 | 0.85 |
| | 112 MG | 4 | 2930 | 7 | 89.7 | 0.89 | 3535 | 6.3 | 90.0 | 0.89 |
| | 132 S | 5.5 | 2930 | 9.8 | 89.8 | 0.87 | 3540 | 8.8 | 90.7 | 0.87 |
| | 132 SM | 7.5 | 2945 | 13.4 | 91.5 | 0.85 | 3550 | 12 | 92.1 | 0.85 |
| | 132 M | 9 | 2950 | 16.4 | 91.9 | 0.83 | 3558 | 14.4 | 92.4 | 0.85 |
| | 160 MP | 11 | 2945 | 19.6 | 91.8 | 0.85 | 3552 | 17.4 | 92.2 | 0.86 |
| | 160 M | 15 | 2950 | 25.4 | 92.2 | 0.89 | 3550 | 22.9 | 92.4 | 0.89 |
| | 160 L | 18.5 | 2954 | 32.2 | 92.9 | 0.86 | 3558 | 28.6 | 93.4 | 0.87 |
| | 180 MR | 22 | 2958 | 38.1 | 93.5 | 0.86 | 3564 | 33.8 | 94.0 | 0.87 |
| | 200 LR | 30 | 2954 | 50 | 93.8 | 0.89 | 3556 | 44.5 | 94.0 | 0.90 |
| | 200 L | 37 | 2950 | 62 | 94.2 | 0.88 | 3552 | 56.2 | 93.9 | 0.88 |
| | 225 MR | 45 | 2962 | 80 | 94.9 | 0.83 | 3566 | 69.8 | 95.2 | 0.85 |
| | 250 MZ | 55 | 2958 | 96 | 94.9 | 0.84 | 3564 | 84.2 | 95.3 | 0.86 |
| | 280 SC | 75 | 2974 | 123 | 95.5 | 0.89 | 3574 | 110 | 95.3 | 0.90 |
| | 280 MC | 90 | 2972 | 147 | 95.5 | 0.89 | 3574 | 133 | 95.5 | 0.89 |
| 315 SN | 110 | 2970 | 179 | 95.6 | 0.89 | 3574 | 160 | 95.8 | 0.90 | |
| 315 MP | 132 | 2984 | 220 | 96.0 | 0.87 | 3580 | 197 | 95.9 | 0.88 | |
| 315 MP | 160 | 2978 | 264 | 96.2 | 0.88 | 3580 | 236 | 95.9 | 0.89 | |
| 315 MP | 200 | 2980 | 328 | 96.1 | 0.86 | 3580 | 297 | 96.1 | 0.88 | |

* For power > 200 kW, please contact us.

| 4 poles | | | | | | | | | | |
|----------------|---------|------|------|------|------|------|------|------|------|------|
| LSPX* LSES | 80 LG | 0.75 | 1452 | 1.6 | 83.7 | 0.78 | 1758 | 1.5 | 85.1 | 0.77 |
| | 90 SL | 1.1 | 1454 | 2.3 | 85.4 | 0.79 | 1760 | 2.1 | 86.6 | 0.78 |
| | 90 LU | 1.5 | 1456 | 3.2 | 85.7 | 0.76 | 1760 | 2.9 | 87.2 | 0.76 |
| | 100 L | 1.8 | 1458 | 3.8 | 86.8 | 0.79 | 1762 | 3.4 | 88.2 | 0.76 |
| | 100 LR | 2.2 | 1456 | 4.6 | 87.3 | 0.76 | 1760 | 4.2 | 88.4 | 0.76 |
| | 100 LG | 3 | 1466 | 6 | 89.2 | 0.78 | 1770 | 5.3 | 90.5 | 0.79 |
| | 112 MU | 4 | 1460 | 7.8 | 89.0 | 0.80 | 1764 | 7.1 | 90.3 | 0.79 |
| | 132 SM | 5.5 | 1466 | 10.3 | 90.6 | 0.82 | 1770 | 9.2 | 91.7 | 0.82 |
| | 132 MU | 7.5 | 1462 | 13.5 | 90.9 | 0.85 | 1766 | 12.1 | 91.8 | 0.85 |
| | 160 MR | 9 | 1466 | 16.7 | 91.3 | 0.84 | 1768 | 14.9 | 92.2 | 0.82 |
| | 160 M | 11 | 1470 | 19.6 | 91.7 | 0.85 | 1774 | 17.6 | 92.5 | 0.85 |
| | 160 LUR | 15 | 1472 | 26.6 | 92.4 | 0.85 | 1774 | 24 | 93.2 | 0.84 |
| | 180 M | 18.5 | 1474 | 32.9 | 93.0 | 0.84 | 1774 | 29.5 | 93.6 | 0.84 |
| | 180 LUR | 22 | 1474 | 40.5 | 93.2 | 0.81 | 1770 | 36.3 | 93.8 | 0.81 |
| | 200 LU | 30 | 1478 | 54.1 | 94.1 | 0.82 | 1778 | 48 | 94.5 | 0.83 |
| | 225 SR | 37 | 1482 | 69.4 | 93.9 | 0.79 | 1782 | 61.4 | 94.5 | 0.80 |
| | 225 MG | 45 | 1488 | 82.5 | 94.9 | 0.80 | 1788 | 73.4 | 95.0 | 0.81 |
| | 250 ME | 55 | 1486 | 98.4 | 94.9 | 0.82 | 1786 | 88.1 | 95.4 | 0.82 |
| | 280 SD | 75 | 1486 | 135 | 95.1 | 0.81 | 1788 | 120 | 95.5 | 0.82 |
| | 280 MD | 90 | 1488 | 165 | 95.5 | 0.79 | 1788 | 147 | 95.8 | 0.80 |
| 315 SP | 110 | 1488 | 195 | 95.7 | 0.82 | 1788 | 173 | 95.9 | 0.83 | |
| 315 MP | 132 | 1488 | 233 | 95.9 | 0.82 | 1790 | 207 | 96.2 | 0.83 | |
| 315 MP | 160 | 1488 | 289 | 95.8 | 0.80 | 1790 | 255 | 96.2 | 0.82 | |
| 315 MR | 200 | 1488 | 358 | 96.0 | 0.81 | 1790 | 314 | 96.3 | 0.84 | |

* For power > 200 kW, please contact us.

| 6 poles | | | | | | | | | | |
|----------------|---------|------|-----|------|------|------|------|------|------|------|
| LSPX* LSES | 90 SL | 0.75 | 956 | 2 | 79.7 | 0.68 | 1162 | 1.7 | 82.6 | 0.67 |
| | 90 LU | 1.1 | 960 | 2.8 | 81.9 | 0.67 | - | - | - | - |
| | 100 LG | 1.5 | 970 | 3.7 | 83.7 | 0.68 | - | - | - | - |
| | 112 MU | 2.2 | 970 | 5.4 | 84.3 | 0.67 | - | - | - | - |
| | 132 SM | 3 | 974 | 6.8 | 87.7 | 0.71 | - | - | - | - |
| | 132 M | 4 | 974 | 9.1 | 87.7 | 0.70 | - | - | - | - |
| | 132 MU | 5.5 | 968 | 11.5 | 88.6 | 0.75 | - | - | - | - |
| | 160 MU | 7.5 | 980 | 15.9 | 97.7 | 0.73 | - | - | - | - |
| | 180 L | 11 | 984 | 22.4 | 91.4 | 0.75 | 1182 | 20.1 | 91.7 | 0.75 |
| | 180 LUR | 15 | 982 | 30.8 | 91.6 | 0.74 | 1184 | 27.2 | 92.4 | 0.75 |
| | 200 L | 18.5 | 982 | 35.3 | 92.3 | 0.79 | - | - | - | - |
| | 200 LU | 22 | 984 | 42.2 | 92.7 | 0.74 | - | - | - | - |
| | 225 MG | 30 | 986 | 53.9 | 93.3 | 0.83 | 1186 | 53.9 | 93.4 | 0.85 |
| | 250 ME | 37 | 988 | 65.9 | 94.1 | 0.83 | - | - | - | - |
| | 280 SC | 45 | 986 | 78.4 | 94.0 | 0.85 | 1186 | 78.4 | 94.5 | 0.87 |
| | 280 MD | 55 | 988 | 96.1 | 94.8 | 0.84 | 1190 | 85.3 | 95.2 | 0.85 |
| | 315 SP | 75 | 992 | 144 | 95.1 | 0.76 | 1192 | 131 | 95.2 | 0.79 |
| | 315 MP | 90 | 992 | 169 | 95.1 | 0.78 | 1192 | 150 | 95.0 | 0.78 |
| | 315 MR | 110 | 992 | 205 | 95.7 | 0.78 | 1192 | 182 | 95.8 | 0.79 |
| | 315 MR | 132 | 990 | 247 | 95.5 | 0.78 | 1192 | 219 | 95.8 | 0.79 |

* For power > 132 kW, please contact us.

IMfinity® ATEX 3-phase induction motors - IE3 efficiency class

ATEX DUST motors - Zones 21 & 22

LSPX & LSES series - Aluminium- IE3

Electrical characteristics - Drive-powered

| Type | 400V 50Hz | | | | % Rated torque M_n at | | | | | 400V 87Hz Δ^1 | | | | Maximum mechanical speed ² | |
|----------------|-------------|----------------------------|---------------|-------------------|-------------------------|--------|-------|------|-------|----------------------|----------------------------|---------------|-------------------|---------------------------------------|-------|
| | Rated power | Rated speed | Rated current | Power factor | 10Hz | 17Hz | 25Hz | 50Hz | 87Hz | Rated power | Rated speed | Rated current | Power factor | | |
| | P_n kW | N_n min ⁻¹ | I_n A | Cos ϕ 4/4 | | | | | | P_n kW | N_n min ⁻¹ | I_n A | Cos ϕ 4/4 | | |
| 2 poles | | | | | | | | | | | | | | | |
| LSPX* LSES | 80 L | 0.75 | 2890 | 1.65 | 0.83 | 2.25 | 2.5 | 2.5 | 2.5 | 1.44 | 1.31 | 5006 | 2.88 | 0.85 | 13500 |
| | 80 LG | 1.1 | 2885 | 2.35 | 0.85 | 3.1 | 3.65 | 3.65 | 3.65 | 2.1 | 1.91 | 4997 | 4.06 | 0.87 | 11700 |
| | 90 SL | 1.5 | 2890 | 3.15 | 0.85 | 4.21 | 4.95 | 4.95 | 4.95 | 2.84 | 2.61 | 5006 | 5.5 | 0.86 | 11700 |
| | 90 LU | 2.2 | 2895 | 4.5 | 0.86 | 6.16 | 7.25 | 7.25 | 7.25 | 4.17 | 3.83 | 5014 | 7.87 | 0.88 | 11700 |
| | 100 L | 3 | 2870 | 6.2 | 0.88 | 9.25 | 9.95 | 9.95 | 9.95 | 5.67 | 5.22 | 4997 | 10.67 | 0.86 | 9900 |
| | 112 MG | 4 | 2905 | 7.9 | 0.91 | 12.18 | 13.1 | 13.1 | 13.1 | 7.47 | 6.96 | 5058 | 13.8 | 0.89 | 9900 |
| | 132 S | 5.5 | 2910 | 11 | 0.90 | 16.74 | 18 | 18 | 18 | 10.26 | 9.57 | 5066 | 18.96 | 0.87 | 6700 |
| | 132 SM | 7.5 | 2925 | 15 | 0.88 | 22.7 | 24.4 | 24.4 | 24.4 | 13.91 | 13.05 | 5084 | 25.56 | 0.86 | 6700 |
| | 132 M | 9 | 2935 | 17.8 | 0.87 | 27.16 | 29.2 | 29.2 | 29.2 | 16.64 | 15.66 | 5101 | 30.47 | 0.86 | 6700 |
| | 160 MP | 11 | 2930 | 21.8 | 0.88 | 33.2 | 35.7 | 35.7 | 35.7 | 20.35 | 19.14 | 5092 | 37.08 | 0.86 | 6700 |
| | 160 M | 15 | 2935 | 28.8 | 0.90 | 40.7 | 48.6 | 48.6 | 48.6 | 27.7 | 26.1 | 5101 | 49.94 | 0.88 | 6000 |
| | 160 L | 18.5 | 2945 | 35 | 0.89 | 53 | 60 | 60 | 60 | 34.2 | 32.19 | 5110 | 60.95 | 0.88 | 6000 |
| | 180 MR | 22 | 2940 | 41.5 | 0.90 | 56.3 | 67.64 | 71.2 | 71.2 | 40.6 | 38.28 | 5110 | 72.46 | 0.88 | 5670 |
| | 200 LR | 30 | 2935 | 56.2 | 0.90 | 76.9 | 92.44 | 97.3 | 97.3 | 80.76 | - | - | - | - | 4500 |
| | 200 L | 37 | 2930 | 69.9 | 0.89 | 89.3 | 108 | 120 | 120 | 99.6 | - | - | - | - | 4500 |
| | 225 MR | 45 | 2952 | 86 | 0.87 | 107.9 | 130.5 | 145 | 145 | 120.35 | - | - | - | - | 4320 |
| | 250 MZ | 55 | 2940 | 103 | 0.89 | 132.43 | 160.2 | 178 | 178 | 147.74 | - | - | - | - | 4320 |
| | 280 SC | 75 | 2964 | 136 | 0.90 | 179.3 | 216.9 | 241 | 241 | 200 | - | - | - | - | 4050 |
| | 280 MC | 90 | 2968 | 163 | 0.90 | 241.9 | 289 | 289 | 289 | 239.9 | - | - | - | - | 4050 |
| | 315 SN | 110 | 2962 | 197 | 0.91 | 263.38 | 318.6 | 354 | 354 | 293.8 | - | - | - | - | 3600 |
| 315 MP | 132 | 2974 | 242 | 0.89 | 314.71 | 380.7 | 423 | 423 | 351.1 | - | - | - | - | 3600 | |
| 315 MP | 160 | 2974 | 292 | 0.90 | 381.67 | 461.7 | 513 | 513 | 425.8 | - | - | - | - | 3600 | |
| 315 MP | 200 | 2968 | 320 | 0.89 | 421.85 | 567 | 567 | 567 | 567 | - | - | - | - | 3600 | |


* For power > 200 kW, please contact us.

| | | | | | | | | | | | | | | | |
|----------------|---------|------|------|------|---------|--------|------|------|-------|--------|-------|------|--------|------|-------|
| 4 poles | | | | | | | | | | | | | | | |
| LSPX* LSES | 80 LG | 0.75 | 1450 | 1.7 | 0.80 | 4.46 | 4.95 | 4.95 | 4.95 | 2.84 | 1.31 | 2511 | 2.96 | 0.83 | 11700 |
| | 90 SL | 1.1 | 1450 | 2.43 | 0.81 | 6.53 | 7.25 | 7.25 | 7.25 | 4.17 | 1.91 | 2511 | 4.23 | 0.84 | 11700 |
| | 90 LU | 1.5 | 1452 | 3.31 | 0.79 | 8.87 | 9.85 | 9.85 | 9.85 | 5.66 | 2.61 | 2515 | 5.76 | 0.79 | 11700 |
| | 100 LR | 2.2 | 1445 | 4.9 | 0.81 | 13.39 | 14.4 | 14.4 | 14.4 | 8.21 | 3.83 | 2518 | 8.3 | 0.79 | 9900 |
| | 100 LG | 3 | 1456 | 6.4 | 0.83 | 16.41 | 19.6 | 19.6 | 19.6 | 11.17 | 5.22 | 2529 | 11.09 | 0.81 | 9900 |
| | 112 MU | 4 | 1452 | 8.45 | 0.85 | 21.93 | 26.2 | 26.2 | 26.2 | 14.93 | 6.96 | 2525 | 14.56 | 0.80 | 9900 |
| | 132 SM | 5.5 | 1456 | 11.3 | 0.86 | 33.39 | 35.9 | 35.9 | 35.9 | 20.46 | 9.57 | 2532 | 19.13 | 0.85 | 6700 |
| | 132 MU | 7.5 | 1450 | 15 | 0.88 | 45.66 | 49.1 | 49.1 | 49.1 | 27.99 | 13.05 | 2525 | 25.9 | 0.86 | 6700 |
| | 160 MR | 9 | 1458 | 18.2 | 0.86 | 54.6 | 58.7 | 58.7 | 58.7 | 33.46 | 15.66 | 2536 | 30.98 | 0.85 | 6000 |
| | 160 M | 11 | 1462 | 21.7 | 0.88 | 60 | 71.7 | 71.7 | 71.7 | 40.87 | 19.14 | 2539 | 37.58 | 0.85 | 6000 |
| | 160 LUR | 15 | 1464 | 29.6 | 0.87 | 81.7 | 97.6 | 97.6 | 97.6 | 55.63 | 26.1 | 2543 | 50.79 | 0.85 | 5670 |
| | 180 M | 18.5 | 1466 | 36.4 | 0.87 | 94.86 | 120 | 120 | 120 | 68.4 | 32.19 | 2543 | 63.15 | 0.85 | 5670 |
| | 180 LUR | 22 | 1466 | 44.1 | 0.85 | 113 | 143 | 143 | 143 | 81.51 | 38.28 | 2546 | 75.85 | 0.83 | 4500 |
| | 200 LU | 30 | 1472 | 59.1 | 0.85 | 144.34 | 194 | 194 | 194 | 110.6 | 52.2 | 2557 | 102.93 | 0.84 | 4500 |
| | 225 SR | 37 | 1476 | 74.5 | 0.83 | 177.82 | 239 | 239 | 239 | 136.23 | 64.38 | 2584 | 126.97 | 0.81 | 4320 |
| | 225 MG | 45 | 1480 | 89 | 0.84 | 229.25 | 290 | 290 | 290 | 165.3 | 78.3 | 2570 | 152.88 | 0.83 | 4050 |
| | 250 ME | 55 | 1482 | 107 | 0.85 | 279.84 | 354 | 354 | 354 | 201.78 | 95.7 | 2570 | 187.92 | 0.83 | 4050 |
| | 280 SD | 75 | 1484 | 147 | 0.84 | 381 | 482 | 482 | 482 | 274.74 | - | - | - | - | 3420 |
| | 280 MD | 90 | 1482 | 177 | 0.83 | 457.7 | 579 | 579 | 579 | 330 | - | - | - | - | 3420 |
| | 315 SP | 110 | 1486 | 212 | 0.85 | 624.63 | 707 | 707 | 707 | 403 | - | - | - | - | 2700 |
| 315 MP | 132 | 1486 | 253 | 0.85 | 748.32 | 847 | 847 | 847 | 482.8 | - | - | - | - | 2700 | |
| 315 MP | 160 | 1484 | 309 | 0.85 | 814.22 | 1030 | 1030 | 1030 | 587.1 | - | - | - | - | 2700 | |
| 315 MR | 200 | 1484 | 383 | 0.85 | 1019.75 | 1290 | 1290 | 1290 | 735.3 | - | - | - | - | 2700 | |

* For power > 200 kW, please contact us.

| | | | | | | | | | | | | | | | |
|----------------|---------|------|-----|------|------|---------|------|------|------|--------|-------|------|--------|------|-------|
| 6 poles | | | | | | | | | | | | | | | |
| LSPX* LSES | 90 SL | 0.75 | 950 | 1.9 | 0.72 | 7.55 | 7.55 | 7.55 | 7.55 | 4.34 | 1.31 | 1645 | 3.39 | 0.75 | 11700 |
| | 90 LU | 1.1 | 956 | 2.75 | 0.71 | 11 | 11 | 11 | 11 | 6.32 | 1.91 | 1656 | 4.74 | 0.71 | 11700 |
| | 100 LG | 1.5 | 962 | 3.85 | 0.73 | 13.1 | 14.8 | 14.8 | 14.8 | 8.44 | 2.61 | 1673 | 6.6 | 0.72 | 9900 |
| | 112 MU | 2.2 | 960 | 5.65 | 0.73 | 19.17 | 21.7 | 21.7 | 21.7 | 12.37 | 3.83 | 1673 | 9.57 | 0.70 | 9900 |
| | 132 SM | 3 | 968 | 7.15 | 0.77 | 27.44 | 29.5 | 29.5 | 29.5 | 16.82 | 5.22 | 1684 | 12.02 | 0.73 | 6700 |
| | 132 M | 4 | 968 | 9.55 | 0.76 | 36.55 | 39.3 | 39.3 | 39.3 | 22.4 | 6.96 | 1684 | 16.17 | 0.73 | 6700 |
| | 132 MU | 5.5 | 960 | 12.6 | 0.79 | 50.59 | 54.4 | 54.4 | 54.4 | 31 | 9.57 | 1673 | 21.33 | 0.76 | 6700 |
| | 160 MU | 7.5 | 974 | 18.7 | 0.79 | 68.1 | 73.2 | 73.2 | 73.2 | 41.72 | 13.05 | 1694 | 28.44 | 0.76 | 6700 |
| | 180 L | 11 | 980 | 23.9 | 0.79 | 89.56 | 107 | 107 | 107 | 61 | 19.14 | 1701 | 40.8 | 0.77 | 5670 |
| | 180 LUR | 15 | 976 | 32.4 | 0.79 | 122.2 | 146 | 146 | 146 | 83.22 | 26.1 | 1697 | 55.7 | 0.77 | 4500 |
| | 200 L | 18.5 | 976 | 38.9 | 0.82 | 150.66 | 180 | 180 | 180 | 102.6 | 32.19 | 1697 | 66.53 | 0.80 | 4500 |
| | 200 LU | 22 | 978 | 45 | 0.79 | 179.12 | 214 | 214 | 214 | 186.18 | 38.28 | 1697 | 80.59 | 0.77 | 4500 |
| | 225 MG | 30 | 984 | 58.9 | 0.86 | 243.57 | 291 | 291 | 291 | 165.87 | 52.2 | 1708 | 101.92 | 0.84 | 4050 |
| | 250 ME | 37 | 984 | 71.1 | 0.87 | 299.65 | 358 | 358 | 358 | 204.06 | 64.38 | 1708 | 124.43 | 0.85 | 4050 |
| | 280 SC | 45 | 982 | 86.9 | 0.87 | 365.77 | 437 | 437 | 437 | 249.09 | - | - | - | - | 3420 |
| | 280 MD | 55 | 984 | 105 | 0.87 | 446.12 | 533 | 533 | 533 | 303.81 | - | - | - | - | 3420 |
| | 315 SP | 75 | 990 | 155 | 0.80 | 605.15 | 723 | 723 | 723 | 412.11 | - | - | - | - | 2700 |
| | 315 MP | 90 | 990 | 183 | 0.81 | 726.52 | 868 | 868 | 868 | 494.76 | - | - | - | - | 2700 |
| | 315 MR | 110 | 988 | 221 | 0.82 | 887.22 | 1060 | 1060 | 1060 | 604.2 | - | - | - | - | 2700 |
| | 315 MR | 132 | 990 | 268 | 0.81 | 1062.99 | 1270 | 1270 | 1270 | 723.9 | - | - | - | - | 2700 |

* For power > 132 kW, please contact us.



| Series | Type | Main shaft end | | | | | | | | | | | | | | | | | |
|--------------|----------------------|----------------|----|------|------|-----|-----|----|-----|----|---------|----|------|------|-----|-----|----|-----|----|
| | | 4 and 6 poles | | | | | | | | | 2 poles | | | | | | | | |
| | | F | GD | D | G | E | O | p | L | LO | F | GD | D | G | E | O | p | L | LO |
| LSPX LSES | 80 L/LG | 6 | 6 | 19j6 | 15.5 | 40 | M6 | 16 | 30 | 6 | 6 | 6 | 19j6 | 15.5 | 40 | M6 | 16 | 30 | 6 |
| | 90 L/LU/SL | 8 | 7 | 24j6 | 20 | 50 | M8 | 19 | 40 | 6 | 8 | 7 | 24j6 | 20 | 50 | M8 | 19 | 40 | 6 |
| | 100 L/LG/LR | 8 | 7 | 28j6 | 24 | 60 | M10 | 22 | 50 | 6 | 8 | 7 | 28j6 | 24 | 60 | M10 | 22 | 50 | 6 |
| | 112 M/MG/MU | 8 | 7 | 28j6 | 24 | 60 | M10 | 22 | 50 | 6 | 8 | 7 | 28j6 | 24 | 60 | M10 | 22 | 50 | 6 |
| | 132 M/MU/S/SM/SU | 10 | 8 | 38k6 | 33 | 80 | M12 | 28 | 63 | 10 | 10 | 8 | 38k6 | 33 | 80 | M12 | 28 | 63 | 10 |
| | 160 L/LUR/M/MP/MR/MU | 12 | 8 | 42k6 | 37 | 110 | M16 | 36 | 100 | 6 | 12 | 8 | 42k6 | 37 | 110 | M16 | 36 | 100 | 6 |
| | 180 L/LR/LUR/M/MR/MT | 14 | 9 | 48k6 | 42.5 | 110 | M16 | 36 | 98 | 12 | 14 | 9 | 48k6 | 42.5 | 110 | M16 | 36 | 98 | 12 |
| | 200 L/LR/LU | 16 | 10 | 55m6 | 49 | 110 | M20 | 42 | 97 | 13 | 16 | 10 | 55m6 | 49 | 110 | M20 | 42 | 97 | 13 |
| | 225 MR/MT | - | - | - | - | - | - | - | - | - | 16 | 10 | 55m6 | 49 | 110 | M20 | 42 | 97 | 13 |
| | 225 MG/MR/SR/ST | 18 | 11 | 60m6 | 53 | 140 | M20 | 42 | 126 | 14 | - | - | - | - | - | - | - | - | - |
| | 250 ME | 18 | 11 | 65m6 | 58 | 140 | M20 | 42 | 126 | 14 | 18 | 11 | 60m6 | 53 | 140 | M20 | 42 | 126 | 14 |
| | 250 MZ | - | - | - | - | - | - | - | - | - | 18 | 11 | 60m6 | 53 | 140 | M20 | 42 | 126 | 14 |
| | 280 MC/MD/SC | 20 | 12 | 75m6 | 67.5 | 140 | M20 | 42 | 125 | 15 | 18 | 11 | 65m6 | 58 | 140 | M20 | 42 | 126 | 14 |
| | 280 SD | 20 | 12 | 75m6 | 67.5 | 140 | M20 | 42 | 125 | 15 | - | - | - | - | - | - | - | - | - |
| | 315 MP/MR/SN/SP | 22 | 14 | 80m6 | 71 | 170 | M20 | 42 | 140 | 15 | 18 | 11 | 65m6 | 58 | 140 | M20 | 42 | 126 | 14 |

| Series | Type | Secondary shaft ends | | | | | | | | | | | | | | | | | |
|--------------|----------------------|----------------------|------|------|------|-----|-----|-----|-----|-----|---------|------|------|------|-----|-----|-----|-----|-----|
| | | 4 and 6 poles | | | | | | | | | 2 poles | | | | | | | | |
| | | FA | GF | DA | GB | EA | OA | pA | L' | LO' | FA | GF | DA | GB | EA | OA | Pa | L' | LO' |
| LSPX LSES | 80 L/LG | 5 | 5 | 14j6 | 11 | 30 | M5 | 15 | 25 | 3.5 | 5 | 5 | 14j6 | 11 | 30 | M5 | 15 | 25 | 3.5 |
| | 90 L/LU/SL | 6 | 6 | 19j6 | 15.5 | 40 | M6 | 16 | 30 | 6 | 6 | 6 | 19j6 | 15.5 | 40 | M6 | 16 | 30 | 6 |
| | 100 L/LG/LR | 8 | 7 | 24j6 | 20 | 50 | M8 | 19 | 40 | 6 | 8 | 7 | 24j6 | 20 | 50 | M8 | 19 | 40 | 6 |
| | 112 MG/MU | 8 | 7 | 24j6 | 20 | 50 | M8 | 19 | 40 | 6 | 8 | 7 | 24j6 | 20 | 50 | M8 | 19 | 40 | 6 |
| | 132 M/MU/S/SM/SU | 8 | 7 | 28k6 | 24 | 60 | M10 | 22 | 50 | 6 | 8 | 7 | 28k6 | 24 | 60 | M10 | 22 | 50 | 6 |
| | 160 MP/MR | 10 | 8 | 38k6 | 33 | 80 | M12 | 28 | 63 | 10 | 10 | 8 | 38k6 | 33 | 80 | M12 | 28 | 63 | 10 |
| | 160 L/LUR/M/MU | 12 | 8 | 42k6 | 37 | 110 | M16 | 36 | 100 | 6 | 12 | 8 | 42k6 | 37 | 110 | M16 | 36 | 100 | 6 |
| | 180 L/LR/LUR/M/MR/MT | 14 | 9 | 48k6 | 42.5 | 110 | M16 | 36 | 97 | 13 | 14 | 9 | 48k6 | 42.5 | 110 | M16 | 36 | 97 | 13 |
| | 200 L/LR/LU | 16 | 10 | 55m6 | 49 | 110 | M20 | 42 | 97 | 13 | 16 | 10 | 55m6 | 49 | 110 | M20 | 42 | 97 | 13 |
| | 225 MG/MR | 18 | 11 | 60m6 | 53 | 140 | M20 | 42 | 126 | 14 | 16 | 10 | 55m6 | 49 | 110 | M20 | 42 | 97 | 13 |
| | 225 MT | - | - | - | - | - | - | - | - | - | 16 | 10 | 55m6 | 49 | 110 | M20 | 42 | 97 | 13 |
| | 225 SR/ST | 18 | 11 | 60m6 | 53 | 140 | M20 | 42 | 126 | 14 | - | - | - | - | - | - | - | - | - |
| | 250 ME | 18 | 11 | 60m6 | 53 | 140 | M20 | 42 | 126 | 14 | 18 | 11 | 60m6 | 53 | 140 | M20 | 42 | 126 | 14 |
| | 250 MZ | - | - | - | - | - | - | - | - | - | 18 | 11 | 60m6 | 53 | 140 | M20 | 42 | 126 | 14 |
| | 280 MC/MD/SC | 18 | 11 | 65m6 | 58 | 140 | M20 | 42 | 126 | 14 | 18 | 11 | 65m6 | 58 | 140 | M20 | 42 | 126 | 14 |
| 280 SD | 18 | 11 | 65m6 | 58 | 140 | M20 | 42 | 126 | 14 | - | - | - | - | - | - | - | - | - | |
| 315 SN | 18 | 11 | 75m6 | 58 | 140 | M20 | 42 | 125 | 15 | 18 | 11 | 65m6 | 58 | 140 | M20 | 42 | 125 | 14 | |
| 315 MP/MR/SP | 22 | 14 | 80m6 | 71 | 170 | M20 | 42 | 140 | 30 | 18 | 11 | 65m6 | 58 | 140 | M20 | 42 | 126 | 14 | |

ATEX DUST - Zones 21 & 22 - Aluminium


IMfinity® ATEX 3-phase induction motors - IE3 efficiency class

ATEX DUST motors - Zones 21 & 22

LSPX & LSES series - Mechanical characteristics

Foot mounted IM 1001 (IMB3)

Dimensions in millimetres



| Series | Type | Main dimensions | | | | | | | | | | | | | | | | | | |
|--------------|---------|-----------------|-----|-----|-----|-----|-----|------|------|------|-----|-----|------|-------|------|-----|-----|-----|-----|-----|
| | | A | AB | B | BB | C | x | AA | K | HA | H | AC* | HD | LB | LJ | J | I | II | AD | AD1 |
| LSPX LSES | 80 L | 125 | 157 | 100 | 120 | 50 | 10 | 29 | 9 | 10 | 80 | 170 | 228 | 215 | 5.5 | 126 | 63 | 63 | - | - |
| | 80 LG | 125 | 157 | 100 | 125 | 50 | 14 | 31 | 9 | 10 | 80 | 189 | 238 | 247 | 5.5 | 126 | 63 | 63 | - | - |
| | 90 L | 140 | 172 | 125 | 164 | 56 | 28 | 39 | 10 | 11 | 90 | 189 | 248 | 245 | 5.5 | 126 | 63 | 63 | - | - |
| | 90 LU | 140 | 172 | 125 | 164 | 56 | 28 | 39 | 10 | 11 | 90 | 189 | 248 | 276 | 5.5 | 126 | 63 | 63 | - | - |
| | 90 SL | 140 | 172 | 100 | 164 | 56 | 28 | 39 | 10 | 11 | 90 | 189 | 248 | 245 | 5.5 | 126 | 63 | 63 | - | - |
| | 100 L | 160 | 196 | 140 | 165 | 63 | 12 | 40 | 12 | 13 | 100 | 200 | 263 | 290 | 6.5 | 126 | 63 | 63 | 118 | 45 |
| | 100 LG | 160 | 196 | 140 | 168 | 53 | 13 | 40 | 12 | 14 | 100 | 227 | 272 | 305 | 5.5 | 126 | 63 | 63 | 130 | 45 |
| | 100 LR | 160 | 196 | 140 | 165 | 63 | 12 | 40 | 12 | 13 | 100 | 200 | 263 | 309 | 6.5 | 126 | 63 | 63 | 118 | 45 |
| | 112 M | 190 | 220 | 140 | 165 | 70 | 13 | 44 | 12 | 14 | 112 | 200 | 275 | 290 | 6.5 | 126 | 63 | 63 | 118 | 45 |
| | 112 MG | 190 | 219 | 140 | 168 | 60 | 14 | 52 | 12 | 13.5 | 112 | 231 | 284 | 305 | 5.5 | 126 | 63 | 63 | 130 | 45 |
| | 112 MU | 190 | 219 | 140 | 168 | 60 | 14 | 52 | 12 | 13.5 | 112 | 231 | 284 | 322 | 5.5 | 126 | 63 | 63 | 130 | 45 |
| | 132 M | 216 | 250 | 178 | 208 | 89 | 15 | 50 | 12 | 15 | 132 | 272 | 322 | 385 | 17 | 126 | 63 | 63 | 140 | 45 |
| | 132 MU | 216 | 250 | 178 | 208 | 89 | 15 | 50 | 12 | 15 | 132 | 272 | 322 | 412 | 17 | 126 | 63 | 63 | 140 | 45 |
| | 132 S | 216 | 250 | 140 | 170 | 89 | 15 | 42 | 12 | 16 | 132 | 227 | 304 | 351 | 32.5 | 126 | 63 | 63 | 130 | 45 |
| | 132 SM | 216 | 250 | 140 | 208 | 89 | 15 | 50 | 12 | 15 | 132 | 272 | 323 | 385 | 17 | 126 | 63 | 63 | 140 | 45 |
| | 132 SU | 216 | 250 | 140 | 170 | 89 | 15 | 42 | 12 | 16 | 132 | 227 | 304 | 383 | 32.5 | 126 | 63 | 63 | 130 | 45 |
| | 160 L | 254 | 294 | 254 | 294 | 108 | 20 | 60 | 14.5 | 25 | 160 | 324 | 381 | 495 | 47 | 126 | 63 | 63 | 186 | 45 |
| | 160 LUR | 254 | 294 | 254 | 294 | 108 | 20 | 60 | 14.5 | 25 | 160 | 324 | 381 | 510 | 47 | 126 | 63 | 63 | 186 | 45 |
| | 160 M | 254 | 294 | 210 | 294 | 108 | 20 | 60 | 14.5 | 25 | 160 | 324 | 381 | 495 | 47 | 126 | 63 | 63 | 186 | 45 |
| | 160 MP | 254 | 294 | 210 | 294 | 108 | 20 | 64 | 14 | 25 | 160 | 272 | 350 | 468 | 58.5 | 126 | 63 | 63 | 156 | 45 |
| | 160 MR | 254 | 294 | 210 | 294 | 108 | 20 | 64 | 14 | 25 | 160 | 272 | 350 | 495 | 58.5 | 126 | 63 | 63 | 156 | 45 |
| | 160 MU | 254 | 294 | 210 | 294 | 108 | 20 | 60 | 14.5 | 25 | 160 | 324 | 381 | 510 | 47 | 126 | 63 | 63 | 186 | 45 |
| | 180 L | 279 | 339 | 279 | 329 | 121 | 25 | 86 | 14.5 | 25 | 180 | 350 | 476 | 552 | 27 | 259 | 115 | 151 | 225 | 45 |
| | 180 LR | 279 | 324 | 279 | 321 | 121 | 20 | 79 | 14.5 | 29 | 180 | 317 | 468 | 520 | 17 | 259 | 115 | 151 | 177 | 45 |
| | 180 LUR | 279 | 339 | 279 | 329 | 121 | 25 | 86 | 14.5 | 25 | 180 | 350 | 476 | 614 | 27 | 259 | 115 | 151 | 225 | 45 |
| | 180 M | 279 | 339 | 241 | 291 | 121 | 25 | 86 | 14.5 | 25 | 180 | 350 | 476 | 552 | 27 | 259 | 115 | 151 | 225 | 45 |
| | 180 MR | 279 | 324 | 279 | 321 | 121 | 20 | 79 | 14.5 | 29 | 180 | 317 | 448 | 520 | 17 | 259 | 115 | 151 | 177 | 45 |
| | 180 MT | 279 | 324 | 241 | 321 | 121 | 20 | 79 | 14.5 | 29 | 180 | 317 | 468 | 495 | 17 | 259 | 115 | 151 | 177 | 45 |
| | 200 L | 318 | 391 | 305 | 375 | 133 | 35 | 103 | 18.5 | 33 | 200 | 390 | 516 | 620.5 | 40.5 | 259 | 115 | 151 | - | - |
| | 200 LR | 318 | 378 | 305 | 365 | 133 | 30 | 108 | 18.5 | 30 | 200 | 350 | 496 | 620 | 33 | 259 | 115 | 151 | 225 | 45 |
| | 200 LU | 318 | 391 | 305 | 375 | 133 | 35 | 103 | 18.5 | 33 | 200 | 390 | 516 | 669.5 | 40.5 | 259 | 115 | 151 | - | - |
| | 225 MG | 356 | 420 | 311 | 375 | 149 | 30 | 65 | 18.5 | 33 | 225 | 479 | 626 | 810 | 60 | 308 | 161 | 208 | 283 | 45 |
| | 225 MR | 356 | 434 | 311 | 385 | 149 | 50 | 126 | 18.5 | 32 | 225 | 390 | 541 | 676 | 47 | 259 | 115 | 151 | - | - |
| 225 MT | 356 | 434 | 311 | 385 | 149 | 50 | 126 | 18.5 | 32 | 225 | 390 | 541 | 627 | 47 | 259 | 115 | 151 | - | - | |
| 225 SR | 356 | 434 | 286 | 385 | 149 | 50 | 126 | 18.5 | 32 | 225 | 390 | 541 | 676 | 47 | 259 | 115 | 151 | - | - | |
| 225 ST | 356 | 434 | 286 | 385 | 149 | 50 | 126 | 18.5 | 32 | 225 | 390 | 541 | 627 | 47 | 259 | 115 | 151 | - | - | |
| 250 ME | 406 | 470 | 349 | 420 | 168 | 35 | 90 | 24 | 35 | 250 | 479 | 651 | 810 | 60 | 308 | 161 | 208 | 283 | 45 | |
| 250 MZ | 406 | 475 | 349 | 448 | 168 | 70 | 149 | 24 | 39 | 250 | 390 | 566 | 676 | 47 | 259 | 115 | 151 | - | - | |
| 280 MC | 457 | 520 | 419 | 478 | 190 | 35 | 90 | 24 | 35 | 280 | 479 | 681 | 810 | 60 | 308 | 161 | 208 | 283 | 45 | |
| 280 MD | 457 | 520 | 419 | 478 | 190 | 35 | 90 | 24 | 35 | 280 | 479 | 681 | 870 | 60 | 308 | 161 | 208 | 283 | 45 | |
| 280 SC | 457 | 520 | 368 | 478 | 190 | 35 | 90 | 24 | 35 | 280 | 479 | 681 | 810 | 60 | 308 | 161 | 208 | 283 | 45 | |
| 280 SD | 457 | 520 | 368 | 478 | 190 | 35 | 90 | 24 | 35 | 280 | 479 | 681 | 870 | 60 | 308 | 161 | 208 | 283 | 45 | |
| 315 MP | 508 | 594 | 457 | 537 | 216 | 40 | 114 | 28 | 70 | 315 | 586 | 777 | 947 | 117 | 308 | 161 | 208 | 340 | 45 | |
| 315 MR | 508 | 594 | 457 | 537 | 216 | 40 | 114 | 28 | 70 | 315 | 586 | 777 | 1017 | 117 | 308 | 161 | 208 | 340 | 45 | |
| 315 SN | 508 | 599 | 406 | 537 | 214 | 40 | 140 | 28 | 50 | 315 | 479 | 716 | 868 | 58 | 308 | 161 | 208 | 283 | 45 | |
| 315 SP | 508 | 594 | 406 | 534 | 216 | 38 | 115 | 28 | 71 | 315 | 586 | 777 | 947 | 117 | 308 | 161 | 208 | 335 | 45 | |

* AC: housing diameter without lifting rings

ATEX DUST - Zones 21 & 22 - Aluminium


IMfinity® ATEX 3-phase induction motors - IE3 efficiency class

ATEX DUST motors - Zones 21 & 22

LSPX & LSES series - Mechanical characteristics

Foot and flange mounted IM 2001 (IM B35)

Dimensions in millimetres



| Series | Type | Main dimensions | | | | | | | | | | | | | | | | | | | |
|--------------|---------|-----------------|-----|-----|-----|-----|-----|------|------|------|-----|-----|------|-------|------|-----|-----|-----|-----|-------|-------|
| | | A | AB | B | BB | C | x | AA | K | HA | H | AC* | HD | LB | LJ | J | I | II | AD | AD1 | Symb |
| LSPX LSES | 80 L | 125 | 157 | 100 | 120 | 50 | 10 | 29 | 9 | 10 | 80 | 170 | 228 | 215 | 5.5 | 126 | 63 | 63 | - | - | FF165 |
| | 80 LG | 125 | 157 | 100 | 125 | 50 | 14 | 31 | 9 | 10 | 80 | 189 | 238 | 247 | 5.5 | 126 | 63 | 63 | - | - | FF165 |
| | 90 L | 140 | 172 | 125 | 164 | 56 | 28 | 39 | 10 | 11 | 90 | 189 | 248 | 245 | 5.5 | 126 | 63 | 63 | - | - | FF165 |
| | 90 LU | 140 | 172 | 125 | 164 | 56 | 28 | 39 | 10 | 11 | 90 | 189 | 248 | 276 | 5.5 | 126 | 63 | 63 | - | - | FF165 |
| | 90 SL | 140 | 172 | 100 | 164 | 56 | 28 | 39 | 10 | 11 | 90 | 189 | 248 | 245 | 5.5 | 126 | 63 | 63 | - | - | FF165 |
| | 100 L | 160 | 196 | 140 | 165 | 63 | 12 | 40 | 12 | 13 | 100 | 200 | 263 | 290 | 6.5 | 126 | 63 | 63 | 118 | 45 | FF215 |
| | 100 LG | 160 | 196 | 140 | 168 | 53 | 13 | 40 | 12 | 14 | 100 | 227 | 272 | 305 | 5.5 | 126 | 63 | 63 | 130 | 45 | FF215 |
| | 100 LR | 160 | 196 | 140 | 165 | 63 | 12 | 40 | 12 | 13 | 100 | 200 | 263 | 309 | 6.5 | 126 | 63 | 63 | 118 | 45 | FF215 |
| | 112 M | 190 | 220 | 140 | 165 | 70 | 13 | 44 | 12 | 14 | 112 | 200 | 275 | 290 | 6.5 | 126 | 63 | 63 | 118 | 45 | FF215 |
| | 112 MG | 190 | 219 | 140 | 168 | 60 | 14 | 52 | 12 | 13.5 | 112 | 231 | 284 | 305 | 5.5 | 126 | 63 | 63 | 130 | 45 | FF215 |
| | 112 MU | 190 | 219 | 140 | 168 | 60 | 14 | 52 | 12 | 13.5 | 112 | 231 | 284 | 322 | 5.5 | 126 | 63 | 63 | 130 | 45 | FF215 |
| | 132 M | 216 | 250 | 178 | 208 | 89 | 15 | 50 | 12 | 15 | 132 | 272 | 322 | 385 | 17 | 126 | 63 | 63 | 140 | 45 | FF265 |
| | 132 MU | 216 | 250 | 178 | 208 | 89 | 15 | 50 | 12 | 15 | 132 | 272 | 322 | 412 | 17 | 126 | 63 | 63 | 140 | 45 | FF265 |
| | 132 S | 216 | 250 | 140 | 170 | 89 | 15 | 42 | 12 | 16 | 132 | 227 | 304 | 351 | 32.5 | 126 | 63 | 63 | 130 | 45 | FF265 |
| | 132 SM | 216 | 250 | 140 | 208 | 89 | 15 | 50 | 12 | 15 | 132 | 272 | 323 | 385 | 17 | 126 | 63 | 63 | 140 | 45 | FF265 |
| | 132 SU | 216 | 250 | 140 | 170 | 89 | 15 | 42 | 12 | 16 | 132 | 227 | 304 | 383 | 32.5 | 126 | 63 | 63 | 130 | 45 | FF265 |
| | 160 L | 254 | 294 | 254 | 294 | 108 | 20 | 60 | 14.5 | 25 | 160 | 324 | 381 | 495 | 47 | 126 | 63 | 63 | 186 | 45 | FF300 |
| | 160 LUR | 254 | 294 | 254 | 294 | 108 | 20 | 60 | 14.5 | 25 | 160 | 324 | 381 | 510 | 47 | 126 | 63 | 63 | 186 | 45 | FF300 |
| | 160 M | 254 | 294 | 210 | 294 | 108 | 20 | 60 | 14.5 | 25 | 160 | 324 | 381 | 495 | 47 | 126 | 63 | 63 | 186 | 45 | FF300 |
| | 160 MP | 254 | 294 | 210 | 294 | 108 | 20 | 64 | 14 | 25 | 160 | 272 | 350 | 468 | 58.5 | 126 | 63 | 63 | 156 | 45 | FF300 |
| | 160 MR | 254 | 294 | 210 | 294 | 108 | 20 | 64 | 14 | 25 | 160 | 272 | 350 | 495 | 58.5 | 126 | 63 | 63 | 156 | 45 | FF300 |
| | 160 MU | 254 | 294 | 210 | 294 | 108 | 20 | 60 | 14.5 | 25 | 160 | 324 | 381 | 510 | 47 | 126 | 63 | 63 | 186 | 45 | FF300 |
| | 180 L | 279 | 339 | 279 | 329 | 121 | 25 | 86 | 14.5 | 25 | 180 | 350 | 476 | 552 | 27 | 259 | 115 | 151 | 225 | 45 | FF300 |
| | 180 LR | 279 | 324 | 279 | 321 | 121 | 20 | 79 | 14.5 | 29 | 180 | 317 | 468 | 520 | 17 | 259 | 115 | 151 | 177 | 45 | FF300 |
| | 180 LUR | 279 | 339 | 279 | 329 | 121 | 25 | 86 | 14.5 | 25 | 180 | 350 | 476 | 614 | 27 | 259 | 115 | 151 | 225 | 45 | FF300 |
| | 180 M | 279 | 339 | 241 | 291 | 121 | 25 | 86 | 14.5 | 25 | 180 | 350 | 476 | 552 | 27 | 259 | 115 | 151 | 225 | 45 | FF300 |
| | 180 MR | 279 | 324 | 279 | 321 | 121 | 20 | 79 | 14.5 | 29 | 180 | 317 | 448 | 520 | 17 | 259 | 115 | 151 | 177 | 45 | FF300 |
| | 180 MT | 279 | 324 | 241 | 321 | 121 | 20 | 79 | 14.5 | 29 | 180 | 317 | 468 | 495 | 17 | 259 | 115 | 151 | 177 | 45 | FF300 |
| | 200 L | 318 | 391 | 305 | 375 | 133 | 35 | 103 | 18.5 | 33 | 200 | 390 | 516 | 620.5 | 40.5 | 259 | 115 | 151 | - | - | FF350 |
| | 200 LR | 318 | 378 | 305 | 365 | 133 | 30 | 108 | 18.5 | 30 | 200 | 350 | 496 | 620 | 33 | 259 | 115 | 151 | 225 | 45 | FF350 |
| | 200 LU | 318 | 391 | 305 | 375 | 133 | 35 | 103 | 18.5 | 33 | 200 | 390 | 516 | 669.5 | 40.5 | 259 | 115 | 151 | - | - | FF350 |
| | 225 MG | 356 | 420 | 311 | 375 | 149 | 30 | 65 | 18.5 | 33 | 225 | 479 | 626 | 810 | 60 | 308 | 161 | 208 | 283 | 45 | FF400 |
| 225 MR | 356 | 434 | 311 | 385 | 149 | 50 | 126 | 18.5 | 32 | 225 | 390 | 541 | 676 | 47 | 259 | 115 | 151 | - | - | FF400 | |
| 225 MT | 356 | 434 | 311 | 385 | 149 | 50 | 126 | 18.5 | 32 | 225 | 390 | 541 | 627 | 47 | 259 | 115 | 151 | - | - | FF400 | |
| 225 SR | 356 | 434 | 286 | 385 | 149 | 50 | 126 | 18.5 | 32 | 225 | 390 | 541 | 676 | 47 | 259 | 115 | 151 | - | - | FF400 | |
| 225 ST | 356 | 434 | 286 | 385 | 149 | 50 | 126 | 18.5 | 32 | 225 | 390 | 541 | 627 | 47 | 259 | 115 | 151 | - | - | FF400 | |
| 250 ME | 406 | 470 | 349 | 420 | 168 | 35 | 90 | 24 | 35 | 250 | 479 | 651 | 810 | 60 | 308 | 161 | 208 | 283 | 45 | FF500 | |
| 250 MZ | 406 | 475 | 349 | 448 | 168 | 70 | 149 | 24 | 39 | 250 | 390 | 566 | 676 | 47 | 259 | 115 | 151 | - | - | FF500 | |
| 280 MC | 457 | 520 | 419 | 478 | 190 | 35 | 90 | 24 | 35 | 280 | 479 | 681 | 810 | 60 | 308 | 161 | 208 | 283 | 45 | FF500 | |
| 280 MD | 457 | 520 | 419 | 478 | 190 | 35 | 90 | 24 | 35 | 280 | 479 | 681 | 870 | 60 | 308 | 161 | 208 | 283 | 45 | FF500 | |
| 280 SC | 457 | 520 | 368 | 478 | 190 | 35 | 90 | 24 | 35 | 280 | 479 | 681 | 810 | 60 | 308 | 161 | 208 | 283 | 45 | FF500 | |
| 280 SD | 457 | 520 | 368 | 478 | 190 | 35 | 90 | 24 | 35 | 280 | 479 | 681 | 870 | 60 | 308 | 161 | 208 | 283 | 45 | FF500 | |
| 315 MP | 508 | 594 | 457 | 537 | 216 | 40 | 114 | 28 | 70 | 315 | 586 | 777 | 947 | 117 | 308 | 161 | 208 | 340 | 45 | FF600 | |
| 315 MR | 508 | 594 | 457 | 537 | 216 | 40 | 114 | 28 | 70 | 315 | 586 | 777 | 1017 | 117 | 308 | 161 | 208 | 340 | 45 | FF600 | |
| 315 SN | 508 | 599 | 406 | 537 | 214 | 40 | 140 | 28 | 50 | 315 | 479 | 716 | 868 | 58 | 308 | 161 | 208 | 283 | 45 | FF600 | |
| 315 SP | 508 | 594 | 406 | 534 | 216 | 38 | 115 | 28 | 71 | 315 | 586 | 777 | 947 | 117 | 308 | 161 | 208 | 335 | 45 | FF600 | |

* AC: housing diameter without lifting rings

ATEX DUST - Zones 21 & 22 - Aluminium



IMfinity® ATEX 3-phase induction motors - IE3 efficiency class

ATEX DUST motors - Zones 21 & 22

LSPX & LSES series - Aluminium - Mechanical characteristics

Flange mounted IM 3001 (IM B5) - IM 3011 (IM V1)

Dimensions in millimetres



| Series | Type | Main dimensions | | | | | | | | |
|--------------|---------|-----------------|-------|-----|------|-----|-----|-----|-----|-----|
| | | AC* | LB | HJ | LJ | J | I | II | AD | AD1 |
| LSPX LSES | 80 L | 170 | 215 | 146 | 5.5 | 126 | 63 | 63 | - | - |
| | 80 LG | 189 | 267 | 156 | 25.5 | 126 | 63 | 63 | - | - |
| | 90 L | 189 | 265 | 156 | 25.5 | 126 | 63 | 63 | - | - |
| | 90 LU | 189 | 296 | 156 | 25.5 | 126 | 63 | 63 | - | - |
| | 90 SL | 189 | 265 | 156 | 25.5 | 126 | 63 | 63 | - | - |
| | 100 L | 200 | 290 | 161 | 5.5 | 126 | 63 | 63 | - | - |
| | 100 LG | 235 | 315 | 170 | 15.5 | 126 | 63 | 63 | - | - |
| | 100 LR | 200 | 309 | 161 | 5.5 | 126 | 63 | 63 | - | - |
| | 112 M | 200 | 290 | 161 | 5.5 | 126 | 63 | 63 | - | - |
| | 112 MG | 235 | 315 | 170 | 15.5 | 126 | 63 | 63 | - | - |
| | 112 MU | 235 | 332 | 170 | 15.5 | 126 | 63 | 63 | - | - |
| | 132 M | 272 | 385 | 191 | 17 | 126 | 63 | 63 | 140 | 45 |
| | 132 MU | 272 | 412 | 191 | 17 | 126 | 63 | 63 | 140 | 45 |
| | 132 S | 227 | 351 | 173 | 32.5 | 126 | 63 | 63 | 130 | 45 |
| | 132 SM | 272 | 385 | 191 | 17 | 126 | 63 | 63 | 140 | 45 |
| | 132 SU | 227 | 383 | 173 | 32.5 | 126 | 63 | 63 | 130 | 45 |
| | 160 L | 312 | 495 | 221 | 47 | 126 | 63 | 63 | 186 | 45 |
| | 160 LUR | 312 | 510 | 221 | 47 | 126 | 63 | 63 | 186 | 45 |
| | 160 M | 312 | 495 | 221 | 48 | 126 | 63 | 63 | 186 | 45 |
| | 160 MP | 272 | 468 | 191 | 58 | 126 | 63 | 63 | 156 | 45 |
| | 160 MR | 272 | 495 | 191 | 58 | 126 | 63 | 63 | 156 | 45 |
| | 160 MU | 312 | 510 | 221 | 48 | 126 | 63 | 63 | 186 | 45 |
| | 180 L | 350 | 552 | 296 | 27 | 259 | 115 | 151 | 225 | 45 |
| | 180 LR | 312 | 520 | 288 | 17 | 259 | 115 | 151 | 186 | 45 |
| | 180 LUR | 350 | 614 | 296 | 27 | 259 | 115 | 151 | 225 | 45 |
| | 180 M | 350 | 552 | 296 | 27 | 259 | 115 | 151 | 225 | 45 |
| | 180 MR | 312 | 520 | 268 | 17 | 259 | 115 | 151 | 186 | 45 |
| | 180 MT | 312 | 495 | 288 | 17 | 259 | 115 | 151 | 186 | 45 |
| | 200 L | 390 | 620.5 | 316 | 40.5 | 259 | 115 | 151 | - | - |
| | 200 LR | 350 | 620 | 296 | 33 | 259 | 115 | 151 | 225 | 45 |
| | 200 LU | 390 | 669.5 | 316 | 40.5 | 259 | 115 | 151 | - | - |
| | 225 MG | 479 | 810 | 401 | 60 | 308 | 161 | 208 | 283 | 45 |
| 225 MR | 390 | 676 | 316 | 47 | 259 | 115 | 151 | - | - | |
| 225 MT | 390 | 627 | 316 | 47 | 259 | 115 | 151 | - | - | |
| 225 SR | 390 | 676 | 316 | 47 | 259 | 115 | 151 | - | - | |
| 225 ST | 390 | 627 | 316 | 47 | 259 | 115 | 151 | - | - | |
| 250 ME | 479 | 810 | 401 | 60 | 308 | 161 | 208 | 283 | 45 | |
| 250 MZ | 390 | 676 | 316 | 47 | 259 | 115 | 151 | - | - | |
| 280 MC | 479 | 810 | 401 | 60 | 308 | 161 | 208 | 283 | 45 | |
| 280 MD | 479 | 870 | 401 | 60 | 308 | 161 | 208 | 283 | 45 | |
| 280 SC | 479 | 810 | 401 | 60 | 308 | 161 | 208 | 283 | 45 | |
| 280 SD | 479 | 870 | 401 | 60 | 308 | 161 | 208 | 283 | 45 | |
| 315 MP | 586 | 947 | 462 | 117 | 308 | 161 | 208 | 340 | 45 | |
| 315 MR | 586 | 1017 | 462 | 117 | 308 | 161 | 208 | 340 | 45 | |
| 315 SN | 479 | 870 | 401 | 60 | 308 | 161 | 208 | 283 | 45 | |
| 315 SP | 586 | 947 | 462 | 117 | 308 | 161 | 208 | 340 | 45 | |

* AC: housing diameter without lifting rings


| IEC symbol | Flange dimensions | | | | | | | |
|------------|-------------------|-----|-----|-----|---|------|------|----|
| | M | N | D | T | n | α° | S | LA |
| FF165 | 165 | 130 | 200 | 3.5 | 4 | 45 | 12 | 10 |
| FF165 | 165 | 130 | 200 | 3.5 | 4 | 45 | 12 | 10 |
| FF165 | 165 | 130 | 200 | 3.5 | 4 | 45 | 12 | 10 |
| FF165 | 165 | 130 | 200 | 3.5 | 4 | 45 | 12 | 10 |
| FF165 | 165 | 130 | 200 | 3.5 | 4 | 45 | 12 | 10 |
| FF215 | 215 | 180 | 250 | 4 | 4 | 45 | 14.5 | 12 |
| FF215 | 215 | 180 | 250 | 4 | 4 | 45 | 14.5 | 13 |
| FF215 | 215 | 180 | 250 | 4 | 4 | 45 | 14.5 | 12 |
| FF215 | 215 | 180 | 250 | 4 | 4 | 45 | 14.5 | 12 |
| FF215 | 215 | 180 | 250 | 4 | 4 | 45 | 14.5 | 13 |
| FF215 | 215 | 180 | 250 | 4 | 4 | 45 | 14.5 | 13 |
| FF265 | 265 | 230 | 300 | 4 | 4 | 45 | 14.5 | 14 |
| FF265 | 265 | 230 | 300 | 4 | 4 | 45 | 14.5 | 14 |
| FF265 | 265 | 230 | 300 | 4 | 4 | 45 | 14.5 | 14 |
| FF265 | 265 | 230 | 300 | 4 | 4 | 45 | 14.5 | 14 |
| FF265 | 265 | 230 | 300 | 4 | 4 | 45 | 14.5 | 14 |
| FF300 | 300 | 250 | 350 | 5 | 4 | 45 | 18.5 | 15 |
| FF300 | 300 | 250 | 350 | 5 | 4 | 45 | 18.5 | 15 |
| FF300 | 300 | 250 | 350 | 5 | 4 | 45 | 18.5 | 15 |
| FF300 | 300 | 250 | 350 | 5 | 4 | 45 | 18.5 | 14 |
| FF300 | 300 | 250 | 350 | 5 | 4 | 45 | 18.5 | 14 |
| FF300 | 300 | 250 | 350 | 5 | 4 | 45 | 18.5 | 14 |
| FF300 | 300 | 250 | 350 | 5 | 4 | 45 | 18.5 | 15 |
| FF300 | 300 | 250 | 350 | 5 | 4 | 45 | 18.5 | 15 |
| FF300 | 300 | 250 | 350 | 5 | 4 | 45 | 18.5 | 15 |
| FF300 | 300 | 250 | 350 | 5 | 4 | 45 | 18.5 | 15 |
| FF300 | 300 | 250 | 350 | 5 | 4 | 45 | 18.5 | 15 |
| FF300 | 300 | 250 | 350 | 5 | 4 | 45 | 18.5 | 15 |
| FF300 | 300 | 250 | 350 | 5 | 4 | 45 | 18.5 | 15 |
| FF350 | 350 | 300 | 400 | 5 | 4 | 45 | 18.5 | 15 |
| FF350 | 350 | 300 | 400 | 5 | 4 | 45 | 18.5 | 15 |
| FF350 | 350 | 300 | 400 | 5 | 4 | 45 | 18.5 | 15 |
| FF400 | 400 | 350 | 450 | 5 | 8 | 22.5 | 18.5 | 16 |
| FF400 | 400 | 350 | 450 | 5 | 8 | 22.5 | 18.5 | 16 |
| FF400 | 400 | 350 | 450 | 5 | 8 | 22.5 | 18.5 | 16 |
| FF400 | 400 | 350 | 450 | 5 | 8 | 22.5 | 18.5 | 16 |
| FF400 | 400 | 350 | 450 | 5 | 8 | 22.5 | 18.5 | 16 |
| FF500 | 500 | 450 | 550 | 5 | 8 | 22.5 | 18.5 | 22 |
| FF500 | 500 | 450 | 550 | 5 | 8 | 22.5 | 18.5 | 18 |
| FF500 | 500 | 450 | 550 | 5 | 8 | 22.5 | 18.5 | 22 |
| FF500 | 500 | 450 | 550 | 5 | 8 | 22.5 | 18.5 | 22 |
| FF500 | 500 | 450 | 550 | 5 | 8 | 22.5 | 18.5 | 22 |
| FF500 | 500 | 450 | 550 | 5 | 8 | 22.5 | 18.5 | 22 |
| FF500 | 500 | 450 | 550 | 5 | 8 | 22.5 | 18.5 | 22 |
| FF600 | 600 | 550 | 660 | 6 | 8 | 22.5 | 24 | 22 |
| FF600 | 600 | 550 | 660 | 6 | 8 | 22.5 | 24 | 22 |
| FF600 | 600 | 550 | 660 | 6 | 8 | 22.5 | 24 | 22 |
| FF600 | 600 | 550 | 660 | 6 | 8 | 22.5 | 24 | 22 |
| FF600 | 600 | 550 | 660 | 6 | 8 | 22.5 | 24 | 22 |

For frame sizes ≥ 250 mm for IM 301 use, please contact us.
Dimensions of shaft ends identical to those for foot mounted motors.

ATEX DUST - Zones 21 & 22 - Aluminium

IMfinity® ATEX 3-phase induction motors - IE3 efficiency class
ATEX DUST motors - Zones 21 & 22
LSPX & LSES series - Aluminium - Mechanical characteristics
Foot and face mounted IM 2101 (IM B34)

Dimensions in millimetres




| Series | Type | Main dimensions | | | | | | | | | | | | | | | | | | | |
|--------------|--------|-----------------|-----|-----|-----|----|----|----|----|------|-----|-----|-----|------|------|-----|----|-----|-----|-------|-------|
| | | A | AB | B | BB | C | x | AA | K | HA | H | AC* | HD | LB | LJ | J | I | II | AD | AD1 | Symb |
| LSPX LSES | 80 L | 125 | 157 | 100 | 120 | 50 | 10 | 29 | 9 | 10 | 80 | 170 | 228 | 215 | 5.5 | 126 | 63 | 63 | - | - | FT100 |
| | 80 LG | 125 | 157 | 100 | 125 | 50 | 14 | 31 | 9 | 10 | 80 | 189 | 238 | 247 | 5.5 | 126 | 63 | 63 | - | - | FT100 |
| | 90 L | 140 | 172 | 125 | 164 | 56 | 28 | 39 | 10 | 11 | 90 | 189 | 248 | 245 | 5.5 | 126 | 63 | 63 | - | - | FT115 |
| | 90 LU | 140 | 172 | 125 | 164 | 56 | 28 | 39 | 10 | 11 | 90 | 189 | 248 | 276 | 5.5 | 126 | 63 | 63 | - | - | FT115 |
| | 90 SL | 140 | 172 | 100 | 164 | 56 | 28 | 39 | 10 | 11 | 90 | 189 | 248 | 245 | 5.5 | 126 | 63 | 63 | - | - | FT115 |
| | 100 L | 160 | 196 | 140 | 165 | 63 | 12 | 40 | 12 | 13 | 100 | 200 | 263 | 290 | 6.5 | 126 | 63 | 63 | 118 | 45 | FT130 |
| | 100 LG | 160 | 196 | 140 | 168 | 53 | 13 | 40 | 12 | 14 | 100 | 227 | 272 | 305 | 5.5 | 126 | 63 | 63 | 130 | 45 | FT130 |
| | 100 LR | 160 | 196 | 140 | 165 | 63 | 12 | 40 | 12 | 13 | 100 | 200 | 263 | 309 | 6.5 | 126 | 63 | 63 | 118 | 45 | FT130 |
| | 112 M | 190 | 220 | 140 | 165 | 70 | 13 | 44 | 12 | 14 | 112 | 200 | 275 | 290 | 6.5 | 126 | 63 | 63 | 118 | 45 | FT130 |
| | 112 MG | 190 | 219 | 140 | 168 | 60 | 14 | 52 | 12 | 13.5 | 112 | 231 | 284 | 305 | 5.5 | 126 | 63 | 63 | 130 | 45 | FT130 |
| | 112 MU | 190 | 219 | 140 | 168 | 60 | 14 | 52 | 12 | 13.5 | 112 | 231 | 284 | 322 | 5.5 | 126 | 63 | 63 | 130 | 45 | FT130 |
| | 132 M | 216 | 250 | 178 | 208 | 89 | 15 | 50 | 12 | 15 | 132 | 272 | 322 | 385 | 17 | 126 | 63 | 63 | 140 | 45 | FT165 |
| | 132 MU | 216 | 250 | 178 | 208 | 89 | 15 | 50 | 12 | 15 | 132 | 272 | 322 | 412 | 17 | 126 | 63 | 63 | 140 | 45 | FT165 |
| | 132 S | 216 | 250 | 140 | 170 | 89 | 15 | 42 | 12 | 16 | 132 | 227 | 304 | 351 | 32.5 | 126 | 63 | 63 | 130 | 45 | FT165 |
| | 132 SM | 216 | 250 | 140 | 208 | 89 | 15 | 50 | 12 | 15 | 132 | 272 | 323 | 385 | 17 | 126 | 63 | 63 | 140 | 45 | FT165 |
| | 132 SU | 216 | 250 | 140 | 170 | 89 | 15 | 42 | 12 | 16 | 132 | 227 | 304 | 383 | 32.5 | 126 | 63 | 63 | 130 | 45 | FT165 |
| 160 MP | 254 | 294 | 210 | 294 | 108 | 20 | 64 | 14 | 25 | 160 | 272 | 350 | 468 | 58.5 | 126 | 63 | 63 | 156 | 45 | FT215 | |
| 160 MR | 254 | 294 | 210 | 294 | 108 | 20 | 64 | 14 | 25 | 160 | 272 | 350 | 495 | 58.5 | 126 | 63 | 63 | 156 | 45 | FT215 | |

* AC: housing diameter without lifting rings

IMfinity® ATEX 3-phase induction motors - IE3 efficiency class
ATEX DUST motors - Zones 21 & 22
LSPX & LSES series - Aluminium - Mechanical characteristics
Face mounted IM 3601 (IM B14)

Dimensions in millimetres



| Series | Type | Main dimensions | | | | | | | | |
|--------------|--------|-----------------|-----|-----|------|-----|----|-----|-----|-----|
| | | AC* | LB | HJ | LJ | J | I | II | AD | AD1 |
| LSPX LSES | 80 L | 170 | 215 | 146 | 5.5 | 126 | 63 | 63 | - | - |
| | 80 LG | 189 | 247 | 156 | 5.5 | 126 | 63 | 63 | - | - |
| | 90 L | 189 | 245 | 156 | 5.5 | 126 | 63 | 63 | - | - |
| | 90 LU | 189 | 276 | 156 | 5.5 | 126 | 63 | 63 | - | - |
| | 90 SL | 189 | 245 | 156 | 5.5 | 126 | 63 | 63 | - | - |
| | 100 L | 200 | 290 | 161 | 5.5 | 126 | 63 | 63 | - | - |
| | 100 LG | 235 | 305 | 170 | 5.5 | 126 | 63 | 63 | - | - |
| | 100 LR | 200 | 309 | 161 | 5.5 | 126 | 63 | 63 | - | - |
| | 112 M | 200 | 290 | 161 | 5.5 | 126 | 63 | 63 | - | - |
| | 112 MG | 235 | 315 | 170 | 15.5 | 126 | 63 | 63 | - | - |
| | 112 MU | 235 | 332 | 170 | 15.5 | 126 | 63 | 63 | - | - |
| | 132 M | 272 | 385 | 191 | 17 | 126 | 63 | 63 | 140 | 45 |
| | 132 MU | 272 | 412 | 191 | 17 | 126 | 63 | 63 | 140 | 45 |
| | 132 S | 227 | 351 | 173 | 32.5 | 126 | 63 | 63 | 130 | 45 |
| | 132 SM | 272 | 385 | 191 | 17 | 126 | 63 | 63 | 140 | 45 |
| | 132 SU | 227 | 383 | 173 | 32.5 | 126 | 63 | 63 | 130 | 45 |
| 160 MP | 272 | 468 | 191 | 58 | 126 | 63 | 63 | 156 | 45 | |
| 160 MR | 272 | 495 | 191 | 58 | 126 | 63 | 63 | 156 | 45 | |

*AC: housing diameter without lifting rings

| IEC symbol | Flange dimensions | | | | | | |
|------------|-------------------|-----|-----|-----|---|----|-----|
| | M | N | D | T | n | α° | S |
| FT100 | 100 | 80 | 120 | 3 | 4 | 45 | M6 |
| FT100 | 100 | 80 | 120 | 3 | 4 | 45 | M6 |
| FT115 | 115 | 95 | 140 | 3 | 4 | 45 | M8 |
| FT115 | 115 | 95 | 140 | 3 | 4 | 45 | M8 |
| FT115 | 115 | 95 | 140 | 3 | 4 | 45 | M8 |
| FT130 | 130 | 110 | 160 | 3.5 | 4 | 45 | M8 |
| FT130 | 130 | 110 | 160 | 3.5 | 4 | 45 | M8 |
| FT130 | 130 | 110 | 160 | 3.5 | 4 | 45 | M8 |
| FT130 | 130 | 110 | 160 | 3.5 | 4 | 45 | M8 |
| FT130 | 130 | 110 | 160 | 3.5 | 4 | 45 | M8 |
| FT130 | 130 | 110 | 160 | 3.5 | 4 | 45 | M8 |
| FT165 | 165 | 130 | 200 | 3.5 | 4 | 45 | M10 |
| FT165 | 165 | 130 | 200 | 3.5 | 4 | 45 | M10 |
| FT165 | 165 | 130 | 200 | 3.5 | 4 | 45 | M10 |
| FT165 | 165 | 130 | 200 | 3.5 | 4 | 45 | M10 |
| FT165 | 165 | 130 | 200 | 3.5 | 4 | 45 | M10 |
| FT215 | 215 | 180 | 250 | 4 | 4 | 45 | M12 |
| FT215 | 215 | 180 | 250 | 4 | 4 | 45 | M12 |

ATEX DUST - Zones 21 & 22 - Aluminium

IMfinity® ATEX 3-phase induction motors - IE3 efficiency class
ATEX DUST motors - Zones 21 & 22
LSPX & LSES series - Aluminium - Mechanical characteristics
Bearings and lubrication

PERMANENTLY GREASED BEARINGS

Under normal operating conditions, the service life in hours (L_{10h}) of the lubricant is indicated in the table below for ambient temperatures less than 55°C.

| Series | Type | Polarity | Bearing types Permanently greased | | Bearing service life as a function of rotation speed | | | | | | | | | |
|--------------|----------|----------|--------------------------------------|---------|--|---------|---------|------------------------|---------|---------|------------------------|---------|---------|-------|
| | | | | | 3000 min ⁻¹ | | | 1500 min ⁻¹ | | | 1000 min ⁻¹ | | | |
| | | | | | 25°C | 40°C | 55°C | 25°C | 40°C | 55°C | 25°C | 40°C | 55°C | |
| LSPX LSES | 80 L | 2 | 6203 CN | 6204 C3 | ≥ 40000 | ≥ 40000 | 25000 | - | - | - | - | - | - | |
| | 80 LG | 2; 4 | 6204 C3 | 6205 C3 | ≥ 40000 | ≥ 40000 | 24000 | ≥ 40000 | ≥ 40000 | 31000 | - | - | - | |
| | 90 SL/L | 2; 4; 6 | | | | | | | | | ≥ 40000 | ≥ 40000 | 34000 | |
| | 90 LU | 4 | 6205 C3 | 6205 C3 | - | - | - | ≥ 40000 | ≥ 40000 | 30000 | - | - | - | |
| | 100 L | 2; 4; 6 | 6205 C3 | 6206 C3 | ≥ 40000 | ≥ 40000 | 22000 | ≥ 40000 | ≥ 40000 | 30000 | ≥ 40000 | ≥ 40000 | 33000 | |
| | 100 LR | 4 | | | - | - | - | - | - | - | - | | | |
| | 112 M | 2 | 6205 C3 | 6206 C3 | ≥ 40000 | ≥ 40000 | 22000 | - | - | - | - | - | - | |
| | 112 MG | 2; 6 | | | - | - | - | ≥ 40000 | ≥ 40000 | 33000 | | | | |
| | 112 MU | 4 | 6206 C3 | 6206 C3 | - | - | - | ≥ 40000 | ≥ 40000 | 30000 | - | - | - | |
| | 132 S | 2; 6 | 6206 C3 | 6208 C3 | ≥ 40000 | ≥ 40000 | 19000 | - | - | - | ≥ 40000 | ≥ 40000 | 30000 | |
| | 132 SU | 2; 4 | | | - | - | - | ≥ 40000 | ≥ 40000 | 25000 | - | - | - | |
| | 132 SM/M | 2; 4; 6 | 6207 C3 | 6308 C3 | ≥ 40000 | ≥ 40000 | 19000 | ≥ 40000 | ≥ 40000 | 25000 | ≥ 40000 | ≥ 40000 | 30000 | |
| | 132 MU | 4; 6 | 6307 C3 | 6308 C3 | - | - | - | ≥ 40000 | ≥ 40000 | 25000 | ≥ 40000 | ≥ 40000 | 30000 | |
| | 160 MR | 2; 4 | 6308 C3 | 6309 C3 | ≥ 40000 | 35000 | 15000 | ≥ 40000 | ≥ 40000 | 24000 | - | - | - | |
| | 160 MP | 2; 4 | 6208 C3 | 6309 C3 | ≥ 40000 | 35000 | 18000 | ≥ 40000 | ≥ 40000 | 24000 | - | - | - | |
| | 160 M/MU | 6 | 6210 C3 | 6309 C3 | - | - | - | - | - | - | - | ≥ 40000 | ≥ 40000 | 27000 |
| | 160 L | 2; 4; 6 | | | ≥ 40000 | 30000 | 15000 | ≥ 40000 | ≥ 40000 | 23000 | - | - | - | |
| | 160 LUR | 4; 6 | 6210 C3 | 6310 C3 | - | - | - | ≥ 40000 | ≥ 40000 | 23000 | ≥ 40000 | ≥ 40000 | 27000 | |
| | 180 MT | 2; 4 | | | ≥ 40000 | 30000 | 15000 | - | - | - | - | - | | |
| | 180 M | 4 | 6212 C3 | 6310 C3 | - | - | - | ≥ 40000 | ≥ 40000 | 24900 | - | - | - | |
| | 180 L | 6 | | | - | - | - | - | - | - | ≥ 40000 | ≥ 40000 | 28000 | |
| | 180 LR | 4 | 6210 C3 | 6310 C3 | - | - | - | ≥ 40000 | ≥ 40000 | 23000 | - | - | - | |
| | 180 LUR | 4; 6 | 6312 C3 | 6310 C3 | - | - | - | ≥ 40000 | ≥ 40000 | 22000 | ≥ 40000 | ≥ 40000 | 27000 | |
| | 200 L | 2; 6 | 6214 C3 | 6312 C3 | ≥ 40000 | 25000 | 12500 | - | - | - | ≥ 40000 | ≥ 40000 | 27000 | |
| | 200 LR | 2; 4; 6 | 6312 C3 | 6312 C3 | ≥ 40000 | 25000 | 12500 | ≥ 40000 | ≥ 40000 | 22000 | ≥ 40000 | ≥ 40000 | 27000 | |
| | 200 LU | 4; 6 | | | - | - | - | - | - | - | - | - | | |
| 225 ST | 4 | 6214 C3 | 6313 C3 | - | - | - | ≥ 40000 | ≥ 40000 | 21000 | - | - | - | | |
| 225 MT | 2 | | | ≥ 40000 | 22000 | 11000 | - | - | - | - | - | | | |
| 225 SR | 4 | 6312 C3 | 6313 C3 | - | - | - | ≥ 40000 | ≥ 40000 | 21000 | - | - | - | | |
| 225 MR | 2; 4; 6 | | | ≥ 40000 | 22000 | 11000 | - | - | - | ≥ 40000 | ≥ 40000 | 26000 | | |
| 225 MG | 4; 6 | 6216 C3 | 6314 C3 | - | - | - | ≥ 40000 | ≥ 40000 | 20000 | ≥ 40000 | ≥ 40000 | 25000 | | |

ATEX DUST - Zones 21 & 22 - Aluminium

BEARINGS WITH GREASE NIPPLES

For open bearing assemblies fitted with grease nipples, the table opposite indicates, depending on the type of motor, the lubrication intervals to be respected at 25°C, 40°C and 55°C for a machine installed with a horizontal shaft.

The table below is valid for LSPX and LSES motors lubricated with Polyrex EM103 grease used as standard.

| Series | Type | Polarity | Bearing type for bearing housings with grease nipples | | Quantity of grease g | Lubrication intervals in hours | | | | | | | | |
|--------------|------------|----------|---|---------|-------------------------|--------------------------------|-------|-------|------------------------|-------|------|------------------------|-------|------|
| | | | N.D.E. | D.E. | | 3000 min ⁻¹ | | | 1500 min ⁻¹ | | | 1000 min ⁻¹ | | |
| | | | | | | 25°C | 40°C | 55°C | 25°C | 40°C | 55°C | 25°C | 40°C | 55°C |
| LSPX LSES | 160 M/MU* | 2; 4; 6 | 6210 C3 | 6309 C3 | 13 | 22200 | 11100 | 5550 | 32400 | 16200 | 8100 | 39800 | 19900 | 9950 |
| | 160 L* | | | | | | | | | | | | | |
| | 180 MR* | 2 | 6210 C3 | 6310 C3 | 15 | 19600 | 9800 | 4900 | - | - | - | - | - | - |
| | 180 MT* | 2; 4 | | | | | | | 30400 | 15200 | 7600 | - | - | - |
| | 180 LR* | 4 | - | - | - | - | - | - | - | - | - | - | - | - |
| | 180 LUR* | 4; 6 | 6312 C3 | 6310 C3 | 20 | - | - | - | 26800 | 13400 | 6700 | 35000 | 17500 | 8750 |
| | 180 M* | 4 | 6212 C3 | 6310 C3 | 15 | - | - | - | 29200 | 14600 | 7300 | - | - | - |
| | 180 L* | 6 | | | | | | | - | - | - | 37200 | 18600 | 9300 |
| | 200 LR* | 2; 4; 6 | 6312 C3 | 6312 C3 | 20 | 15200 | 7600 | 3800 | 26800 | 13400 | 6700 | 35000 | 17500 | 8750 |
| | 200 LU* | 4; 6 | | | | - | - | - | | | | | | |
| | 200 L* | 2; 6 | 6214 C3 | 6312 C3 | 20 | 14600 | 7300 | 3650 | - | - | - | 34600 | 17300 | 8650 |
| | 225 ST* | 4 | 6214 C3 | 6313 C3 | 25 | - | - | - | 25200 | 12600 | 6300 | - | - | - |
| | 225 MT* | 2 | | | | 10600 | 5300 | 2650 | - | - | - | | | |
| | 225 SR/MR* | 2; 4; 6 | 6312 C3 | 6313 C3 | 25 | 13400 | 6700 | 3350 | 25200 | 12600 | 6300 | 33600 | 16800 | 8400 |
| | 225 MG* | 4; 6 | 6216 C3 | 6314 C3 | 25 | - | - | - | 23600 | 11800 | 5900 | 32200 | 16100 | 8050 |
| | 250 MZ | 2 | 6312 C3 | 6313 C3 | 25 | 13400 | 6700 | 3350 | - | - | - | - | - | - |
| | 250 ME | 4; 6 | 6216 C3 | 6314 C3 | 25 | - | - | - | 23600 | 11800 | 5900 | 32200 | 16100 | 8050 |
| | 280 SC/MC | 2 | | | | 11800 | 5900 | 2950 | - | - | - | - | - | - |
| | 280 SC | 6 | 6216 C3 | 6316 C3 | 35 | - | - | - | - | - | - | 32200 | 16100 | 8050 |
| | 280 SD/MD | 4; 6 | 6218 C3 | 6316 C3 | 35 | - | - | - | 20800 | 10400 | 5200 | 29600 | 14800 | 7400 |
| 315 SN | 2 | 6216 C3 | 6316 C3 | 35 | 5600 | 2800 | 1400 | - | - | - | - | - | - | |
| 315 MP | 2 | 6317 C3 | 6317 C3 | 40 | 5200 | 2600 | 1300 | - | - | - | - | - | - | |
| 315 SP | 4 | 6317 C3 | 6320 C3 | 50 | - | - | - | 15800 | 7900 | 3950 | - | - | - | |
| 315 MP/MR | 4; 6 | | | | - | - | - | 21200 | 10600 | 5300 | | | | |

* bearing housings with grease nipples on request

CONSTRUCTION AND SPECIAL ATMOSPHERES

For a machine installed with a vertical shaft, the lubrication intervals are approximately 80% of the values shown in the table below.

NB: The quality and quantity of grease along with the lubrication interval are indicated on the machine nameplate.

In the case of special fitting arrangements (motors with roller bearing at the front or other mountings), machines with frame size ≥ 160 mm are fitted with grease nipple bearings.


The instructions required for bearing housing maintenance are shown on the machine nameplate.

BEARING MOUNTING PRINCIPLE

| LSPX / LSES series | | Horizontal shaft | Vertical shaft | |
|---|-----------------------|--|----------------------|----------------------|
| | | | Shaft end down | Shaft end up |
| Foot mounted motors | Mounting arrangements | B3 | V5 | V6 |
| | standard fitting | Front bearing: - Front stop for types ≤ 160 MP/MR/LR - locked for types ≥ 160 M/MU/L/LUR | Front bearing locked | Front bearing locked |
| Flange mounted motors (or feet and flange) | Mounting arrangements | B5 / B35 / B14 / B34 | V1 / V15 / V18 / V58 | V3 / V36 / V19 / V69 |
| | standard fitting | Front bearing locked | Front bearing locked | Front bearing locked |

Horizontal motor

For a bearing service life L_{10h} of 25,000 hours and 40,000 hours




| Series | Type | Polarity | Permissible axial load (daN) on the main drive shaft for standard fitting of bearings | | | | | | | | | | | | | |
|--------------|----------|----------|---|--------------|--------------|--------------|--------------|--------------|------------------------|--------------|--------------|--------------|------------------------|--------------|--|--|
| | | | 3000 min ⁻¹ | | | | | | 1500 min ⁻¹ | | | | 1000 min ⁻¹ | | | |
| | | | → | | ← | | → | | ← | | → | | ← | | | |
| | | | 25,000 hours | 40,000 hours | 25,000 hours | 40,000 hours | 25,000 hours | 40,000 hours | 25,000 hours | 40,000 hours | 25,000 hours | 40,000 hours | 25,000 hours | 40,000 hours | | |
| LSPX LSES | 80 L | 2 | 30 | 21 | (60) | (51) | - | - | - | - | - | - | - | - | | |
| | 80 LG | 2; 4 | 28 | 19 | (68) | (59) | 48 | 34 | (88) | (74) | - | - | - | - | | |
| | 90 SL/L | 2; 4; 6 | 29 | 23 | (69) | (56) | 45 | 32 | (85) | (72) | 56 | 40 | (96) | (80) | | |
| | 90 LU | 2; 4; 6 | 22 | 13 | (72) | (63) | 38 | 25 | (88) | (75) | 47 | 32 | (97) | (82) | | |
| | 100 L | 2; 6 | 42 | 28 | (92) | (78) | - | - | - | - | 78 | 57 | (128) | (107) | | |
| | 100 LR | 4 | - | - | - | - | 58 | 39 | (108) | (90) | - | - | - | - | | |
| | 100 LG | 4; 6 | - | - | - | - | 55 | 38 | (105) | (88) | 75 | 53 | (125) | (103) | | |
| | 112 M | 2 | 38 | 25 | (88) | (75) | - | - | - | - | - | - | - | - | | |
| | 112 MG | 2; 6 | 37 | 24 | (87) | (74) | - | - | - | - | 126 | 104 | (76) | (54) | | |
| | 112 MU | 4; 6 | - | - | - | - | 54 | 36 | (114) | (96) | 66 | 45 | (126) | (105) | | |
| | 132 S | 2; 6 | 69 | 49 | (129) | (109) | - | - | - | - | 124 | 93 | (184) | (153) | | |
| | 132 SU | 2; 4 | 65 | 46 | (125) | (106) | 99 | 73 | (159) | (133) | - | - | - | - | | |
| | 132 SM/M | 2; 4; 6 | 101 | 74 | (171) | (144) | 148 | 111 | (218) | (181) | 178 | 134 | (248) | (204) | | |
| | 132 MU | 4; 6 | - | - | - | - | 139 | 103 | (219) | (183) | 168 | 124 | (248) | (204) | | |
| | 160 MP | 2 | 140 | 104 | (220) | (184) | - | - | - | - | - | - | - | - | | |
| | 160 MR | 2; 4 | 131 | 95 | (221) | (185) | 193 | 145 | (283) | (235) | - | - | - | - | | |
| | 160 M | 2; 4; 6 | 132 | 96 | 232 | 196 | 187 | 140 | 287 | 240 | 235 | 179 | 335 | 279 | | |
| | 160 MU | 6 | - | - | - | - | - | - | - | - | 219 | 164 | 319 | 264 | | |
| | 160 L | 2; 4; 6 | 128 | 96 | 228 | 196 | 183 | 136 | 283 | 236 | 231 | 175 | 331 | 275 | | |
| | 160 LUR | 4; 6 | - | - | - | - | 213 | 159 | 313 | 259 | 257 | 193 | 357 | 293 | | |
| | 180 M | 4 | - | - | - | - | 228 | 174 | 291 | 237 | - | - | - | - | | |
| | 180 MR | 2 | 156 | 115 | 256 | 215 | - | - | - | - | - | - | - | - | | |
| | 180 MT | 2; 4 | 159 | 118 | 259 | 218 | 214 | 160 | 314 | 260 | - | - | - | - | | |
| | 180 L | 6 | - | - | - | - | - | - | - | - | 265 | 201 | 328 | 264 | | |
| | 180 LR | 4 | - | - | - | - | 203 | 150 | 303 | 250 | - | - | - | - | | |
| | 180 LUR | 4; 6 | - | - | - | - | 224 | 170 | 287 | 233 | 224 | 162 | 287 | 225 | | |
| | 200 L | 2; 6 | 244 | 190 | 310 | 256 | - | - | - | - | 362 | 278 | 428 | 344 | | |
| | 200 LR | 2; 4; 6 | 244 | 191 | 307 | 254 | 312 | 241 | 375 | 304 | 341 | 258 | 404 | 321 | | |
| | 200 LU | 4; 6 | - | - | - | - | 316 | 245 | 379 | 308 | 327 | 245 | 390 | 308 | | |
| | 225 SG | 4 | - | - | - | - | 411 | 321 | 481 | 391 | - | - | - | - | | |
| | 225 SR | 4 | - | - | - | - | 350 | 271 | 420 | 341 | - | - | - | - | | |
| | 225 ST | 4 | - | - | - | - | 372 | 292 | 438 | 358 | - | - | - | - | | |
| | 225 MG | 4; 6 | - | - | - | - | 407 | 317 | 477 | 387 | 535 | 426 | 605 | 496 | | |
| | 225 MR | 2; 4; 6 | 280 | 220 | 343 | 283 | 358 | 278 | 421 | 341 | 409 | 315 | 472 | 378 | | |
| | 225 MT | 2 | 281 | 221 | 347 | 287 | - | - | - | - | - | - | - | - | | |
| | 250 ME | 4; 6 | - | - | - | - | 400 | 311 | 470 | 381 | 471 | 365 | 541 | 435 | | |
| | 250 MZ | 2 | 277 | 217 | 340 | 280 | - | - | - | - | - | - | - | - | | |
| | 280 SC | 2; 6 | 303 | 236 | 373 | 306 | - | - | - | - | 461 | 355 | 531 | 425 | | |
| | 280 SD | 4 | - | - | - | - | 454 | 349 | 542 | 437 | - | - | - | - | | |
| | 280 MC | 2 | 300 | 233 | 370 | 303 | - | - | - | - | - | - | - | - | | |
| 280 MD | 4; 6 | - | - | - | - | 446 | 342 | 534 | 430 | 524 | 401 | 612 | 489 | | | |
| 315 SN | 2 | 357 | 279 | 427 | 349 | - | - | - | - | - | - | - | - | | | |
| 315 SP | 4; 6 | - | - | - | - | 814 | 671 | 634 | 491 | 950 | 780 | 770 | 600 | | | |
| 315 MP | 2; 4; 6 | 487 | 405 | 307 | 225 | 768 | 628 | 588 | 448 | 917 | 749 | 737 | 569 | | | |
| 315 MR | 4; 6 | - | - | - | - | 770 | 630 | 590 | 450 | 864 | 699 | 684 | 519 | | | |

(): permissible axial loads with Front bearing locked

Vertical motor
Shaft end downwards

For a bearing service life L_{10h}
of 25,000 hours
and 40,000 hours




| Series | Type | Polarity | Permissible axial load (daN) on the main drive shaft for standard fitting of bearings | | | | | | | | | | | |
|----------|---------|----------|---|--------------|--------------|--------------|------------------------|--------------|--------------|--------------|------------------------|--------------|--------------|--------------|
| | | | 3000 min ⁻¹ | | | | 1500 min ⁻¹ | | | | 1000 min ⁻¹ | | | |
| | | | 25,000 hours | 40,000 hours | 25,000 hours | 40,000 hours | 25,000 hours | 40,000 hours | 25,000 hours | 40,000 hours | 25,000 hours | 40,000 hours | 25,000 hours | 40,000 hours |
| 80 L | 2 | 29 | 20 | (63) | (54) | - | - | - | - | - | - | - | - | |
| 80 LG | 2; 4 | 26 | 16 | (72) | (62) | 45 | 32 | (93) | (78) | - | - | - | - | |
| 90 SL/L | 2; 4; 6 | 26 | 16 | (73) | (63) | 42 | 28 | (91) | (78) | 53 | 37 | (101) | (86) | |
| 90 LU | 2; 4; 6 | 19 | 9 | (77) | (67) | 33 | 20 | (95) | (82) | 43 | 28 | (105) | (89) | |
| 100 L | 2; 6 | 38 | 24 | (98) | (85) | - | - | - | - | 73 | 52 | (137) | (115) | |
| 100 LR | 4 | - | - | - | - | 52 | 34 | (117) | (99) | - | - | - | - | |
| 100 LG | 4; 6 | - | - | - | - | 48 | 31 | (116) | (99) | 68 | 46 | (137) | (115) | |
| 112 M | 2 | 35 | 21 | (95) | (81) | - | - | - | - | - | - | - | - | |
| 112 MG | 2; 6 | 31 | 18 | (98) | (85) | - | - | - | - | 68 | 47 | (138) | (116) | |
| 112 MU | 4; 6 | - | - | - | - | 45 | 28 | (128) | (110) | 57 | 36 | (140) | (119) | |
| 132 S | 2; 6 | 61 | 41 | (142) | (122) | - | - | - | - | 115 | 84 | (200) | (169) | |
| 132 SU | 2; 4 | 57 | 37 | (139) | (120) | 90 | 63 | (176) | (149) | - | - | - | - | |
| 132 SM/M | 2; 4; 6 | 90 | 62 | (189) | (161) | 137 | 100 | (237) | (200) | 165 | 121 | (270) | (226) | |
| 132 MU | 4; 6 | - | - | - | - | 125 | 89 | (242) | (206) | 152 | 108 | (273) | (230) | |
| 160 MP | 2 | 126 | 90 | (243) | (207) | - | - | - | - | - | - | - | - | |
| 160 MR | 2; 4 | 115 | 80 | (246) | (210) | 175 | 127 | (311) | (264) | - | - | - | - | |
| 160 M | 2; 4; 6 | 111 | 75 | 264 | 229 | 164 | 117 | 326 | 278 | 210 | 154 | 375 | 319 | |
| 160 MU | 6 | - | - | - | - | - | - | - | - | 189 | 133 | 375 | 319 | |
| 160 L | 2; 4; 6 | 106 | 70 | 263 | 228 | 160 | 113 | 322 | 274 | 208 | 151 | 371 | 314 | |
| 160 LUR | 4; 6 | - | - | - | - | 186 | 131 | 363 | 309 | 227 | 162 | 417 | 352 | |
| 180 M | 4 | - | - | - | - | 187 | 132 | 361 | 306 | - | - | - | - | |
| 180 MR | 2 | 131 | 90 | 296 | 255 | - | - | - | - | - | - | - | - | |
| 180 MT | 2; 4 | 136 | 95 | 295 | 254 | 189 | 134 | 360 | 305 | - | - | - | - | |
| 180 L | 6 | - | - | - | - | - | - | - | - | 226 | 161 | 398 | 334 | |
| 180 LR | 4 | - | - | - | - | 177 | 122 | 355 | 300 | - | - | - | - | |
| 180 LUR | 4; 6 | - | - | - | - | 187 | 132 | 355 | 300 | 183 | 120 | 377 | 314 | |
| 200 L | 2; 6 | 194 | 139 | 384 | 330 | - | - | - | - | 308 | 223 | 524 | 439 | |
| 200 LR | 2; 4; 6 | 209 | 154 | 360 | 306 | 275 | 203 | 445 | 373 | 299 | 215 | 496 | 412 | |
| 200 LU | 4; 6 | - | - | - | - | 262 | 190 | 471 | 398 | 269 | 186 | 505 | 422 | |
| 225 SG | 4 | - | - | - | - | 335 | 244 | 616 | 524 | - | - | - | - | |
| 225 SR | 4 | - | - | - | - | 294 | 213 | 520 | 439 | - | - | - | - | |
| 225 ST | 4 | - | - | - | - | 322 | 241 | 519 | 438 | - | - | - | - | |
| 225 MG | 4; 6 | - | - | - | - | 324 | 232 | 621 | 530 | 456 | 345 | 749 | 638 | |
| 225 MR | 2; 4; 6 | 234 | 173 | 413 | 352 | 302 | 221 | 520 | 439 | 348 | 253 | 587 | 492 | |
| 225 MT | 2 | 240 | 179 | 410 | 349 | - | - | - | - | - | - | - | - | |
| 250 ME | 4; 6 | - | - | - | - | 305 | 214 | 632 | 541 | 378 | 270 | 712 | 604 | |
| 250 MZ | 2 | 228 | 168 | 417 | 356 | - | - | - | - | - | - | - | - | |
| 280 SC | 2; 6 | 233 | 165 | 488 | 420 | - | - | - | - | 348 | 240 | 728 | 621 | |
| 280 SD | 4 | - | - | - | - | 340 | 233 | 738 | 632 | - | - | - | - | |
| 280 MC | 2 | 221 | 153 | 496 | 428 | - | - | - | - | - | - | - | - | |
| 280 MD | 4; 6 | - | - | - | - | 319 | 213 | 745 | 639 | 391 | 265 | 853 | 728 | |
| 315 SN | 2 | 268 | 188 | 571 | 491 | - | - | - | - | - | - | - | - | |
| 315 SP | 4; 6 | - | - | - | - | 620 | 475 | 923 | 778 | 748 | 575 | 1074 | 901 | |
| 315 MP | 2; 4; 6 | 333 | 249 | 541 | 456 | 541 | 397 | 959 | 815 | 695 | 524 | 1088 | 917 | |
| 315 MR | 4; 6 | - | - | - | - | 537 | 393 | 966 | 822 | 591 | 420 | 1151 | 981 | |

(): permissible axial loads with Front bearing locked

ATEX DUST - Zones 21 & 22 - Aluminium

Horizontal motor

For a bearing service life L_{10h} of 25,000 hours and 40,000 hours



| Series | Type | Polarity | Permissible axial load (daN) on the main drive shaft for standard fitting of bearings | | | | | | | | | | | |
|-----------|----------|----------|---|--------------|--------------|--------------|------------------------|--------------|--------------|--------------|------------------------|--------------|--------------|--------------|
| | | | 3000 min ⁻¹ | | | | 1500 min ⁻¹ | | | | 1000 min ⁻¹ | | | |
| | | | 25,000 hours | 40,000 hours | 25,000 hours | 40,000 hours | 25,000 hours | 40,000 hours | 25,000 hours | 40,000 hours | 25,000 hours | 40,000 hours | 25,000 hours | 40,000 hours |
| | | | IM V6 IM V3 / V36 IM V19 / V69 | | | | | | | | | | | |
| | | | ↓ | ↑ | ↓ | ↑ | ↓ | ↑ | ↓ | ↑ | ↓ | ↑ | ↓ | ↑ |
| | | | 25,000 hours | 40,000 hours | 25,000 hours | 40,000 hours | 25,000 hours | 40,000 hours | 25,000 hours | 40,000 hours | 25,000 hours | 40,000 hours | 25,000 hours | 40,000 hours |
| LS / LSES | 80 L | 2 | (59) | (50) | 33 | 24 | - | - | - | - | - | - | - | - |
| | 80 LG | 2; 4 | (66) | (56) | 32 | 22 | (85) | (71) | 53 | 39 | - | - | - | - |
| | 90 SL/L | 2; 4; 6 | (66) | (56) | 33 | 23 | (82) | (68) | 51 | 38 | (93) | (77) | 61 | 46 |
| | 90 LU | 2; 4; 6 | (69) | (59) | 27 | 18 | (83) | (70) | 45 | 32 | (93) | (77) | 54 | 39 |
| | 100 L | 2; 6 | (88) | (74) | 48 | 35 | - | - | - | - | (123) | (102) | 87 | 65 |
| | 100 LR | 4 | - | - | - | - | (102) | (84) | 67 | 49 | - | - | - | - |
| | 100 LG | 4; 6 | - | - | - | - | (98) | (81) | 67 | 49 | (118) | (96) | 87 | 66 |
| | 112 M | 2 | (84) | (71) | 45 | 31 | - | - | - | - | - | - | - | - |
| | 112 MG | 2; 6 | (81) | (68) | 48 | 35 | - | - | - | - | (118) | (97) | 88 | 66 |
| | 112 MU | 4; 6 | - | - | - | - | (105) | (88) | 68 | 50 | (117) | (96) | 80 | 60 |
| | 132 S | 2; 6 | (121) | (101) | 82 | 62 | - | - | - | - | (175) | (143) | 140 | 109 |
| | 132 SU | 2; 4 | (117) | (97) | 79 | 60 | (150) | (123) | 116 | 89 | - | - | - | - |
| | 132 SM/M | 2; 4; 6 | (160) | (132) | 119 | 91 | (207) | (170) | 167 | 130 | (235) | (191) | 200 | 156 |
| | 132 MU | 4; 6 | - | - | - | - | (206) | (169) | 163 | 126 | (232) | (188) | 193 | 150 |
| | 160 MP | 2 | (206) | (170) | 163 | 127 | - | - | - | - | - | - | - | - |
| | 160 MR | 2; 4 | (205) | (170) | 156 | 120 | (265) | (217) | 222 | 174 | - | - | - | - |
| | 160 M | 2; 4; 6 | 211 | 175 | 164 | 129 | 264 | 217 | 226 | 178 | 310 | 254 | 275 | 219 |
| | 160 MU | 6 | - | - | - | - | - | - | - | - | 289 | 233 | 275 | 219 |
| | 160 L | 2; 4; 6 | 206 | 170 | 163 | 128 | 260 | 213 | 222 | 174 | 308 | 251 | 271 | 214 |
| | 160 LUR | 4; 6 | - | - | - | - | 286 | 231 | 263 | 209 | 327 | 262 | 317 | 252 |
| | 180 M | 4 | - | - | - | - | 250 | 195 | 298 | 243 | - | - | - | - |
| | 180 MR | 2 | 231 | 190 | 196 | 155 | - | - | - | - | - | - | - | - |
| | 180 MT | 2; 4 | 236 | 195 | 195 | 154 | 289 | 234 | 260 | 205 | - | - | - | - |
| | 180 L | 6 | - | - | - | - | - | - | - | - | 289 | 224 | 335 | 271 |
| | 180 LR | 4 | - | - | - | - | 277 | 222 | 255 | 200 | - | - | - | - |
| | 180 LUR | 4; 6 | - | - | - | - | 250 | 195 | 292 | 237 | 246 | 183 | 314 | 251 |
| | 200 L | 2; 6 | 260 | 205 | 318 | 264 | - | - | - | - | 374 | 289 | 458 | 373 |
| | 200 LR | 2; 4; 6 | 272 | 217 | 297 | 243 | 338 | 266 | 382 | 310 | 362 | 278 | 433 | 349 |
| | 200 LU | 4; 6 | - | - | - | - | 325 | 253 | 408 | 335 | 332 | 249 | 442 | 359 |
| | 225 SG | 4 | - | - | - | - | 405 | 314 | 546 | 454 | - | - | - | - |
| | 225 SR | 4 | - | - | - | - | 364 | 283 | 450 | 369 | - | - | - | - |
| | 225 ST | 4 | - | - | - | - | 388 | 307 | 453 | 372 | - | - | - | - |
| | 225 MG | 4; 6 | - | - | - | - | 394 | 302 | 551 | 460 | 526 | 415 | 679 | 568 |
| 225 MR | 2; 4; 6 | 297 | 236 | 350 | 289 | 365 | 284 | 457 | 376 | 411 | 316 | 524 | 429 | |
| 225 MT | 2 | 306 | 245 | 344 | 283 | - | - | - | - | - | - | - | - | |
| 250 ME | 4; 6 | - | - | - | - | 375 | 284 | 562 | 471 | 448 | 340 | 642 | 534 | |
| 250 MZ | 2 | 291 | 231 | 354 | 293 | - | - | - | - | - | - | - | - | |
| 280 SC | 2; 6 | 303 | 235 | 418 | 350 | - | - | - | - | 418 | 310 | 658 | 551 | |
| 280 SD | 4 | - | - | - | - | 428 | 321 | 650 | 544 | - | - | - | - | |
| 280 MC | 2 | 291 | 223 | 426 | 358 | - | - | - | - | - | - | - | - | |
| 280 MD | 4; 6 | - | - | - | - | 407 | 301 | 657 | 551 | 479 | 353 | 765 | 640 | |
| 315 SN | 2 | 338 | 258 | 501 | 421 | - | - | - | - | - | - | - | - | |
| 315 SP | 4; 6 | - | - | - | - | 440 | 295 | 1103 | 958 | 568 | 395 | 1254 | 1081 | |
| 315 MP | 2; 4; 6 | 153 | 69 | 721 | 636 | 361 | 217 | 1139 | 995 | 515 | 344 | 1268 | 1097 | |
| 315 MR | 4; 6 | - | - | - | - | 357 | 213 | 1146 | 1002 | 411 | 240 | 1331 | 1161 | |










(): permissible axial loads with Front bearing locked

STANDARD FITTING ARRANGEMENT

Permissible radial load on main shaft extension with a bearing life L10h of 25,000 hours.

FR: Radial Force

X: distance with respect to the shaft shoulder











ATEX DUST - Zones 21 & 22 - Aluminium

STANDARD FITTING ARRANGEMENT

Permissible radial load on main shaft extension with a bearing life L10h of 25,000 hours.

FR: Radial Force

X: distance with respect to the shaft shoulder












ATEX DUST - Zones 21 & 22 - Aluminium

STANDARD FITTING ARRANGEMENT

Permissible radial load on main shaft extension with a bearing life L10h of 25,000 hours.

FR: Radial Force

X: distance with respect to the shaft shoulder






ATEX DUST - Zones 21 & 22 - Aluminium

STANDARD FITTING ARRANGEMENT

Permissible radial load on main shaft extension with a bearing life L10h of 25,000 hours.

FR: Radial Force

X: distance with respect to the shaft shoulder



SPECIAL FITTING ARRANGEMENT

Type of drive end roller bearings




| Series | Type | Polarity | Rear bearing (N.D.E.) | Front Bearing (D.E.) |
|--------------|-----------|----------|-----------------------|----------------------|
| LSPX LSES | 160 MP/MR | 4;6 | 6210 C3 | NU 309 |
| | 160 L/LUR | | | |
| | 180 MT/MR | 4 | 6210 C3 | NU 310 |
| | 180 LR | | | |
| | 180 LUR | 4;6 | 6312 C3 | NU 310 |
| | 180 M | 4 | 6212 C3 | NU 310 |
| | 180 L | 6 | | |
| | 200 L | 6 | 6214 C3 | NU 312 |
| | 200 LR | 4;6 | 6312 C3 | NU 312 |
| | 200 LU | | | |
| | 225 ST/MT | 4 | 6214 C3 | NU 313 |
| | 225 SR/MR | 4;6 | 6312 C3 | NU 313 |
| | 225 MG | 4;6 | | |
| | 250 ME/MZ | 4;6 | 6216 C3 | NU 314 |
| | 280 SC/MC | 6 | 6216 C3 | NU 316 |
| | 280 SD/MD | 4;6 | 6218 C3 | NU 316 |
| | 315 SP | 4 | | |
| | 315 MP/MR | 4;6 | 6317 C3 | NU 320 |

SPECIAL FITTING ARRANGEMENT

Permissible radial load on main shaft extension with a bearing life L_{10h} of 25,000 hours.

FR: Radial Force

X: distance with respect to the shaft shoulder












SPECIAL FITTING ARRANGEMENT (DRIVE-END ROLLER BEARINGS)

Permissible radial load on main shaft extension with a bearing life L10h of 25,000 hours.

FR: Radial Force

X: distance with respect to the shaft shoulder










ATEX DUST - Zones 21 & 22 - Aluminium

SPECIAL FITTING ARRANGEMENT (DRIVE-END ROLLER BEARINGS)

Permissible radial load on main shaft extension with a bearing life L10h of 25,000 hours.

FR: Radial Force

X: distance with respect to the shaft shoulder



ATEX DUST - Zones 21 & 22 - Aluminium

INDICATION OF CABLE GLAND SIZE AND TYPE FOR 400 V RATED SUPPLY VOLTAGE IF DRILLINGS REQUIRED WITHOUT DETAILS OF DIAMETERS

| Series | Type | Polarity | Terminal box material | Power + auxiliary | | |
|--------|--------------|----------|-----------------------|-------------------------|-----------------------------------|--------------------------------|
| | | | | Number of holes | Hole diameter* | |
| LSPX | 80 | 2; 4; 6 | Aluminium alloy | 2 (3 if auxiliaries) | ISO M20 x 1.5 (1M20 + 1M16) | |
| | 90 | 2; 4; 6 | | | | |
| | 100 | 2; 4; 6 | | | | |
| | 112 | 2; 4; 6 | | | | |
| | 132 | 2; 4; 6 | | | | |
| | 160 | 2; 4; 6 | | | | |
| | 180 | 2; 4; 6 | Cast iron | 3 | 2 x M40 + 1 x M16 | |
| | 200 | 2; 4; 6 | | | 2 x M50 + 1 x M16 | |
| | 225 | 2; 4; 6 | | | 2 x M63 + 1 x M16 | |
| | 250 MZ | 2 | | | | |
| | 250 ME | 4; 6 | | | | |
| 280 | 2; 4; 6 | | | | | |
| LSES | 80 | 2; 4 | Plastic | 2 (3 if auxiliaries) | ISO M20 x 1.5 (1M20 + 1M16) | |
| | 90 | 2; 4; 6 | | | | |
| | 100 | 2; 4; 6 | | | | |
| | 112 | 2; 4; 6 | Aluminium alloy | 3 | 2 (3 if auxiliaries) | ISO M25 x 1.5 (1M25 + 1M16) |
| | 132 | 2; 4; 6 | | | 2 x M25+ 1 x M16 | |
| | 160 MP/MR/LR | 2; 4; 6 | | | 2 x M40 + 1 x M16 | |
| | 160 L/LU/M | 2; 4; 6 | | | 2 x M50 + 1 x M16 | |
| | 180 | 2; 4; 6 | | | 2 x M63 + 1 x M16 | |
| | 200 | 2; 4; 6 | | | | |
| | 225 | 2; 4; 6 | | | | |
| | 250 MZ | 2 | | | | |
| | 250 ME | 4; 6 | | | | |
| | 280 | 2; 4; 6 | | | | |
| | 315 | 2; 4; 6 | | 0 | Removable undrilled support plate | |

* As an option, both ISO M25 holes may be replaced by 1 ISO x M25 and 1 ISO x M32 (to comply with standard DIN 42925).

**TERMINAL BLOCKS
DIRECTION OF ROTATION**

Standard motors are fitted with a block of 6 terminals complying with standard NFC 51 120, with the terminal markings complying with IEC 60034-8 (or NF EN 60034-8).

When the motor is running in U1, V1, W1 or 1U, 1V, 1W from a direct mains supply L1, L2, L3, it turns clockwise when seen from the drive shaft end.

If any two of the phases are changed over, the motor will run in the opposite direction (make sure that the motor has been designed to run in both directions). If the motor is fitted with accessories (thermal protection or space heater), these must be connected on terminal blocks with labelled wires.

Tightening torque for the nuts on the terminal blocks.

| Terminal | M4 | M5 | M6 | M8 | M10 | M12 | M16 |
|------------|----|-----|----|----|-----|-----|-----|
| Torque N.m | 2 | 3.2 | 5 | 10 | 20 | 35 | 65 |

| Series | Type | 400V mains supply | | |
|---------------|-------------|---------------------|-----------|------------------------|
| | | 230/400V connection | | 400 V drive connection |
| | | Polarity | Terminals | Terminals |
| LSPX LSES | 80 to 112 | 2; 4; 6 | M5 | M5 |
| | 132 S/SU | 2; 4; 6 | M5 | M5 |
| | 132 M/MP/MU | 2; 4; 6 | M6 | M6 |
| | 160 | 2; 4; 6 | M6 | M6 |
| | 180 MT/L | 2; 4; 6 | M6 | M6 |
| | 180 LR | 4 | M8 | M6 |
| | 200 LR | 2; 4; 6 | M8 | M6 |
| | 200 L | 2; 6 | M8 | M8 |
| | 225 ST | 4 | M10 | M8 |
| | 225 MR | 4 | M10 | M8 |
| | | 6 | M8 | M8 |
| | 250 ME | 4; 6 | M10 | M8 |
| | 250 MZ | 2 | M10 | M8 |
| | 280 SC | 2 | M12 | M10 |
| | | 4 | M12 | M8 |
| | | 6 | M10 | M8 |
| | | 2 | M12 | M10 |
| | 280 MC | 6 | M10 | M8 |
| | | 4 | M12 | M10 |
| | 280 MD | 4 | M12 | M10 |
| | | 2 | M16 | M12 |
| | 315 SN | 6 | M12 | M10 |
| | | 4 | M16 | M12 |
| | 315 SP | 4 | M16 | M12 |
| | | 2; 4; 6 (110 kW) | M16 | M12 |
| | 315 MP | 6 (90 kW) | M12 | M10 |
| | | 2; 4 (160 kW) | M16 | M12 |
| 2; 4 (200 kW) | | M16 | M16 | |
| 6 | | M16 | M12 | |

| Mechanical adaptations | Frame size |
|--|---------------|
| DE and NDE bearings with 1 machining, for vibration sensor in position 12H, 12H-3H, or 12H-3H-9H | ≥ 132 |
| Different FF flanges from IEC | All |
| Different FT flanges from IEC | ≤ 132 |
| DE roller bearing | ≥ 160: 4p & + |
| Angular contact bearing | All |
| Insulated DE or NDE bearing | ≥ 280 |
| 2 nd standard catalogue NDE shaft end | All |
| 2 nd special NDE shaft end | All |
| Conical shaft | All |
| Smooth shaft without keying | All |
| Shaft with special keying | All |
| Keyed cylindrical NDE shaft (secondary shaft end) as per IEC | All |
| Stainless-steel shaft | All |
| Class B balancing | All |
| F type (full key) or N type (no key) balancing | All |
| Stainless steel fan cover | All |
| Steel fan cover + drip cover | All |
| Steel fan cover + anti-clogging | All |
| Metal fan | All |
| Stainless steel nameplate | All |
| Stainless-steel fastenings | All |
| Incremental encoder / 1024 or 4096 pts / 5v or 11/30 V | All |
| Positioning holes (jacking screws) | ≥ 250 |
| Radial seal for motor in vertical position with shaft end upwards | All |
| Drain holes for operation in vertical position | All |
| Electrical adaptations | Frame size |
| Terminal board with anti-rotation system as standard | All |
| Special voltages (excluding variable speed) | All |
| Insulation class H | All |
| Main box in position B or D | All |
| Auxiliary boxes | ≥ 160 |
| Plastic PE | All |
| ATEX brass PE for unshielded cable for LSPX zone 21 | All |
| ATEX brass PE for shielded cable for LSPX zone 21 | All |
| ATEX brass PE auxiliary for unshielded cable for LSPX zone 21 | All |
| ATEX brass PE auxiliary for shielded cable for LSPX zone 21 | All |
| Flying lead via 6 + 1 multicore cable | All |
| Cable entry on the left as seen from the shaft end | All |
| Preparation for NPT cable glands | All |
| Protections | Frame size |
| Standard winding PTC thermistor probe (triple probe) | All |
| Winding PT 100 probe (1 per phase) | All |
| Endshield PTC thermistor probe (triple probe) | ≥ 160 |
| Endshield PT 100 probe (per probe) | ≥ 160 |
| Endshield thermocouple | ≥ 160 |
| Space heaters when stopped (220-230 V) | All |
| Reinforced winding insulation system for variable speed drive power supply | All |
| Finish | Frame size |
| IP 65 for LSES motors Zone 22 | All |
| IP 56 stopped with fan (IC 411) for LSES motors Zone 22 | All |
| C3H, C4M, C4H, C5-IL or C5-IM paint | All |
| Other paint shades | All |
| Operating temperature: -55°C < T° < -20°C | All |
| Complete tropicalization (stator + rotor) | All |

NON-STANDARD FLANGES

Optionally, Nidec Leroy-Somer motors can be fitted with flanges and faceplates that are larger or smaller than standard. This means that motors can be adapted to all types of situation without the need for costly and time-consuming modifications.

The tables below give the flange and faceplate dimensions and also indicate flange/motor compatibility.

The bearing and shaft end for each frame size remain standard.


Dimensions in millimetres

(FF) Flange mounted

| Symbol IEC | Flange dimensions | | | | | | |
|---------------|-------------------|------|-----|-----|---|------|------|
| | M | N | D | T | n | S | LA |
| FF 115 | 115 | 95 | 140 | 3 | 4 | 10 | 10 |
| FF 130 | 130 | 110 | 160 | 3.5 | 4 | 10 | 10 |
| FF 165 | 165 | 130 | 200 | 3.5 | 4 | 12 | 10 |
| FF 215 | 215 | 180 | 250 | 4 | 4 | 15 | 12 |
| FF 265 | 265 | 230 | 300 | 4 | 4 | 15 | 14 |
| FF 300 | 300 | 250 | 350 | 5 | 4 | 18.5 | 14 |
| FF 350 | 350 | 300 | 400 | 5 | 4 | 18.5 | 15 |
| FF 400 | 400 | 350 | 450 | 5 | 8 | 18.5 | 16 |
| FF 500 | 500 | 450 | 550 | 5 | 8 | 18.5 | 18** |
| FF 600 | 600 | 550* | 660 | 6 | 8 | 24 | 22 |


* Tolerance N js6

** shaft length = 22 for frame size ≥ 280



(FT) Face mounted

| Symbol IEC | Flange dimensions | | | | | |
|---------------|-------------------|-----|-----|-----|---|-----|
| | M | N | D | T | n | M.S |
| FT 85 | 85 | 70 | 105 | 2.5 | 4 | M6 |
| FT 100 | 100 | 80 | 120 | 3 | 4 | M6 |
| FT 115 | 115 | 95 | 140 | 3 | 4 | M8 |
| FT 130 | 130 | 110 | 160 | 3.5 | 4 | M8 |
| FT 165 | 165 | 130 | 200 | 3.5 | 4 | M10 |
| FT 215 | 215 | 180 | 250 | 4 | 4 | M12 |
| FT 265 | 265 | 230 | 300 | 4 | 4 | M12 |



MODIFIED FLANGES

| Motor type | Flange type Forms of fastenings | (FF) Flange mounted | | | | | | | | | | | | | | (FT) Face mounted | | | | | | | | | |
|--------------|------------------------------------|-----------------------|--------|--------|--------|--------|--------|--------|--------|--------|--------|------------------|--------|--------|--------|-------------------|-------|-------|--------|--------|--------|--------|--------|--------|--|
| | | FF 85 | FF 100 | FF 115 | FF 130 | FF 165 | FF 215 | FF 265 | FF 300 | FF 350 | FF 400 | FF 500 | FF 600 | FF 740 | FF 940 | FT 65 | FT 75 | FT 85 | FT 100 | FT 115 | FT 130 | FT 165 | FT 215 | FT 265 | |
| LSPX LSES | 80 L | all | ■ | ■ | ■ | ■ | ● | ◆ | | | | | | | | ◆ | ◆ | ◆ | ● | ◆ | ◆ | | | | |
| | 80 LG / 90 | B5/B35 ⁽¹⁾ | ◆ | ◆ | ◆ | ◆ | ● | ■ | ■ | | | | | | | | | | | | | | | | |
| | 80 LG / 90 | B3/B14/B34 | | | | | | | | | | | | | | | | ◆ | ◆ | ● | ◆ | ◆ | | | |
| | 100 L/LR | all | ■ | ■ | ■ | ■ | ■ | ● | ■ | | | | | | | | | ◆ | ◆ | ◆ | ● | ◆ | | | |
| | 100 LG | all | | | | ■ | ■ | ● | ◆ | | | | | | | | | | | | ◆ | ● | ◆ | ◆ | |
| | 112 MU/MG | all | | | | ■ | ■ | ● | ◆ | | | | | | | | | | | | ◆ | ● | ◆ | ◆ | |
| | 132 S/SU | all | | | | | ■ | ◆ | ● | | | | | | | | | | | | | ◆ | ◆ | ● | |
| | 132 SM/M/MU | all | | | | | ■ | ■ | ● | ◆ | | | | | | | | | | | | ■ | ■ | ● | |
| | 160 MR/LR/MP | all | | | | | | | ■ | ● | ■ | | | | | | | | | | | | | ● | |
| | 160 L/LUR | all | | | | | | ◆ | ◆ | ● | ◆ | | | | | | | | | | | | | | |
| | 180 | all | | | | | | | ● | ● | ◆ | ◆ ⁽¹⁾ | | | | | | | | | | | | | |
| | 200 | all | | | | | | | | ● | ◆ | | | | | | | | | | | | | | |
| | 225 | all | | | | | | | | | ● | ◆ | | | | | | | | | | | | | |
| | 250 | all | | | | | | | | | ◆ | ● | | | | | | | | | | | | | |
| | 280 | all | | | | | | | | | ◆ | ● | ◆ | | | | | | | | | | | | |
| | 315 | all | | | | | | | | | | ◆ ⁽¹⁾ | ● | | | | | | | | | | | | |


● Standard ■ Modified shaft ◆ Adaptable without shaft modifications

(1) Dimension C need not comply with IEC 60072

DRIP COVER FOR OPERATION IN VERTICAL POSITION SHAFT END DOWNWARDS

Dimensions in millimetres

| Series | Motor type | LB' | ∅ |
|--------------|-----------------|-----------|-----|
| LSPX LSES | 80 | LB + 20 | 145 |
| | 90 | LB + 20 | 185 |
| | 100 | LB + 20 | 185 |
| | 112 MR | LB + 20 | 185 |
| | 112 MG/MU | LB + 25 | 210 |
| | 132 S/SU | LB + 25 | 210 |
| | 132 M/MU/SM | LB + 30 | 240 |
| | 160 MP/LR | LB + 30 | 240 |
| | 160 M/L/LU | LB + 36.5 | 265 |
| | 180 MT/LUR/M/MR | LB + 36.5 | 265 |
| | 180 L | LB + 36.5 | 305 |
| | 200 LR | LB + 36.5 | 305 |
| | 200 L/LU | LB + 36.5 | 350 |
| | 225 | LB + 36.5 | 350 |
| | 250 MZ | LB + 36.5 | 350 |
| | 250 ME | LB + 55 | 420 |
| | 280 | LB + 55 | 420 |
| | 315 SN | LB + 55 | 420 |
| | 315 SP/MP/MR | LB + 76.5 | 505 |



SPACE HEATERS

| Series | Type | Power (W) |
|--------------|-----------------|-----------|
| LSPX LSES | 80 L/LG | 10 |
| | 90 to 160 MP/MR | 25 |
| | 160 L to 225 | 52 |
| | 250 MZ | 52 |
| | 250 ME | 84 |
| | 280 SC/SU/MC/MD | 84 |
| | 315 SN | 84 |
| | 315 MP/MR | 108 |


The space heaters use 200/240 V single-phase, 50 or 60 Hz.

FORCED VENTILATION

The integration of high-efficiency motors within a process often requires accessories to make operation easier: forced ventilation for motors used at high or low speeds.

Notes:

- Without forced ventilation, there is a possibility of overspeed with optional class B balancing.
- The motor temperature is monitored by sensors built into the winding.



| Series | Type | LB dimensions with forced ventilation | |
|--------|-------------|---------------------------------------|----------------------|
| | | Foot or face mounted motor | Flange mounted motor |
| LSES | 160 L/LUR | 687 | |
| | 160 MP/MR | | |
| | 180 MT/MR/M | | |
| | 180 LUR | 702 | |
| | 180 L | 741 | |
| | 200 LR/LU | 796 | |
| | 200 L | 802 | |
| | 225 MR/MG | 853.5 | |
| | 225 ST/SR | 808.5 | |
| | 225 MT | | |
| | 250 ME | 1012 | |
| | 250 MZ | 853.5 | |
| | 280 MD | 1072 | |
| | 280 SC | 1012 | |
| | 280 MC | | |
| | 315 SN | 1072 | |
| | 315 SP | 1181 | |
| 315 MP | | | |
| 315 MR | | | |


LIFTING THE MOTOR ONLY
(not coupled to the machine)

The regulations stipulate that in excess of 25 kg suitable handling equipment must be used.

All our motors are fitted with grab handles, making them easier to handle without risk. A diagram of the sling hoisting method appears below with the required dimensions.


To prevent any damage to the motor during handling (for example: switching the motor from horizontal to vertical), it is essential to follow these instructions.

HORIZONTAL POSITION



| Series | Type | Horizontal position | | | |
|--------------|--------------|---------------------|--------|--------|----|
| | | A | min. e | min. h | Øt |
| LSPX LSES | 100 L/LR/LG | 165 | 165 | 150 | 9 |
| | 112 M | 165 | 165 | 150 | 9 |
| | 112 MG/MU | - | - | - | 9 |
| | 132 S/SU | 180 | 180 | 150 | 9 |
| | 132 M/MU/SM | 200 | 180 | 150 | 14 |
| | 160 MP/MR | 200 | 180 | 110 | 14 |
| | 160 L/LUR | 200 | 180 | 110 | 14 |
| | 180 | 200 | 260 | 150 | 14 |
| | 200 L/LR/LU | 270 | 260 | 165 | 14 |
| | 225 | 270 | 260 | 150 | 14 |
| | 250 ME/MZ | 400 | 400 | 500 | 30 |
| | 280 SC/MC/MD | 400 | 400 | 500 | 30 |
| 315 SN | 400 | 400 | 500 | 30 | |
| 315 SP/MP/MR | 360 | 380 | 500 | 17 | |

VERTICAL POSITION



| Series | Type | Vertical position | | | | | | |
|--------------|-----------------|-------------------|-----|-----|-----|----|---------|--------|
| | | C | E | D | n** | ØS | min. e* | min. h |
| LSPX LSES | 160 | 320 | 200 | 230 | 2 | 14 | 320 | 350 |
| | 180 MR/M/T | 320 | 200 | 230 | 2 | 14 | 320 | 270 |
| | 180 L/LUR | 390 | 265 | 290 | 2 | 14 | 390 | 320 |
| | 200 | 410 | 300 | 295 | 2 | 14 | 410 | 450 |
| | 225 | 410 | 300 | 295 | 2 | 14 | 410 | 450 |
| | 250 MZ | 410 | 300 | 295 | 2 | 14 | 410 | 450 |
| | 250 ME | 500 | 400 | 502 | 4 | 30 | 500 | 500 |
| | 280 SC/SD/MC/MD | 500 | 400 | 502 | 4 | 30 | 500 | 500 |
| | 315 SN | 500 | 400 | 502 | 4 | 30 | 500 | 500 |
| | 315 SP/MP/MR | 630 | - | 570 | 2 | 30 | 630 | 550 |

* If the motor is fitted with a drip cover, allow an additional 50 to 100 mm to avoid damaging it when the load is swung.


** If n = 2, the lifting rings form an angle of 90° with respect to the terminal box.
If n = 4, this angle becomes 45°.

Separate ring ≤ 25 kg
Built-in ring > 25 kg

IMfinity® ATEX 3-phase induction motors - IE3 efficiency class

ATEX Gas, Zones 1 and 2 - ATEX Dust, Zones 21 and 22

Appendix Configurator



The Nidec Leroy-Somer Configurator can be used to select motors most suited to your applications, while also providing their technical specifications and corresponding plans.

- Product selection support
- Print-outs of technical specifications
- Print-outs of 2D and 3D CAD files
- The equivalent of 300 catalogues in 15 languages.

Register online at:
<http://configurateurls.leroy-somer.com>



Product availability

Being able both to respond to urgent requests and adhere to promised customer lead times calls for a powerful logistics system.

The availability of motors is ensured by the network of approved partners and Nidec Leroy-Somer central services all working together.

The selection data in the "Express Availability" catalogue specify for each family in the form of a colour code and according to the quantities per order, the product delivery time.

Contact Nidec Leroy-Somer.

Express Availability - Induction motors

FLSD - IFT IE3 Flameproof motors

AVAILABILITY TIMES EX WORKS (FRANCE), IN WORKING DAYS

Orders received, within the maximum quantity limit, by the factory on day D before 12:00 pm Central European Time, will have the following Availability. For products with options, availability will be that of the longest lead-time item, i.e. the product or its options. If the order is received after 12:00 pm, 1 working day will be added to the stated lead time. The maximum quantity is per line of order. Above this maximum quantity, please consult your Sales Office.

| | D | D+1 | D+2 | D+5 | D+10 | D+20 | Please consult |
|--|---|---------------------|---------------------|---------------------|---------------------|---------------------|------------------------|
| 230 V Δ / 400 V Y / 415 V Y - 460 V Y | | | | | | | |
| IE3 | Ex db IIB T4 | | | Ex db IIC T4 | | | Ex db eb IIC T4 |
| | Ex db eb IIC T4 according to IKT | | | | | | |
| | IM 1001 (IM B3) | IM 3001 (IM B5) | IM 3601 (IM B14) | IM 1001 (IM B3) | IM 3001 (IM B5) | IM 3601 (IM B14) | IM 1001 (IM B3) |
| | IM 3001 (IM B5) | IM 3601 (IM B14) | IM 1001 (IM B3) | IM 3001 (IM B5) | IM 3601 (IM B14) | IM 1001 (IM B3) | IM 3001 (IM B5) |
| | IM 3601 (IM B14) | IM 1001 (IM B3) | IM 3001 (IM B5) | IM 3601 (IM B14) | IM 1001 (IM B3) | IM 3001 (IM B5) | IM 3601 (IM B14) |
| Type | P_n kW | Code | Max qV | Code | Max qV | Code | Max qV |
| FLSD 80L | 0.75 | 5129132 | 1 | 5129133 | 1 | 5129134 | 1 |
| FLSD 90SL | 1.1 | 5129157 | 1 | 5129158 | 1 | 5129159 | 1 |
| FLSD 90SL | 1.5 | 5128666 | 1 | 5128667 | 1 | 5128668 | 1 |
| FLSD 90LU | 2.2 | 5128692 | 1 | 5128693 | 1 | 5128694 | 1 |
| FLSD 100L | 3 | 5128718 | 1 | 5128719 | 1 | 5128720 | 1 |
| FLSD 112MG | 4 | 5128744 | 1 | 5128745 | 1 | 5128746 | 1 |
| FLSD 132SM | 5.5 | 5128796 | 1 | 5128797 | 1 | 5128798 | 1 |
| FLSD 132SM | 7.5 | 5128848 | 1 | 5128849 | 1 | 5128850 | 1 |
| FLSD 132M | 9 | 5129223 | 1 | 5129224 | 1 | 5129225 | 1 |
| FLSD 160MA | 11 | 5128920 | 1 | 5128921 | 1 | 5128922 | 1 |
| FLSD 160MB | 15 | 5128928 | 1 | 5128929 | 1 | 5128930 | 1 |
| FLSD 160L | 18.5 | 5128935 | 1 | 5128936 | 1 | 5128937 | 1 |
| FLSD 180M | 22 | 5128942 | 1 | 5128943 | 1 | 5128944 | 1 |
| FLSD 200LA | 30 | 5128949 | 1 | 5128950 | 1 | 5128951 | 1 |
| FLSD 200LB | 37 | 5128956 | 1 | 5128957 | 1 | 5128958 | 1 |
| FLSD 225MR | 45 | 5128963 | 1 | 5128964 | 1 | 5128965 | 1 |
| FLSD 250M | 55 | 5128970 | 1 | 5128971 | 1 | 5128972 | 1 |
| FLSD 280S | 75 | 5128977 | 1 | 5128978 | 1 | 5128979 | 1 |
| FLSD 280M | 90 | 5128984 | 1 | 5128985 | 1 | 5128986 | 1 |

In standard, motors equipped with PTC 150° C sensor for frame size 80 to 132, and with PTC 140° C sensor for frame size 160 to 280.

LEROY-SOMER[™]

www.leroy-somer.com

Connect with us at:

twitter.com/Leroy_Somer_en

facebook.com/leroy-somer.nidec.en

youtube.com/user/LeroySomerOfficiel

linkedin.com/company/leroy-somer



Nidec
All for dreams

© 2021 Moteurs Leroy-Somer SAS. The information contained in this brochure is for guidance only and does not form part of any contract. The accuracy cannot be guaranteed as Moteurs Leroy-Somer have an ongoing development policy. Moteurs Leroy-Somer reserve the right to change the specification of their products without notice.

Moteurs Leroy-Somer SAS. Headquarters: Bd Marcellin Leroy, CS 10015, 16915 Angoulême Cedex 9, France. Share Capital: 38 679 664 €, RCS Angoulême 338 567 258.